

技术要求:

1.材质:双铜128G

2.规格:单页尺寸85x110mm

展开尺寸765x110mm

3.性能要求:风琴折,9P8折,双面印刷

文字色号:PANTONE 431C

85.00 mm

110.00 mm

正

无线充/时钟/夜灯/蓝牙音响

产品使用说明

非常感谢您选择我司产品,在使用产品前请认真阅读产品说明

产品特点

- 造型简易精致。
- 夜灯。
- 蓝牙音响。
- 时钟闹钟。
- 无线快充。
- 充电距离≤6mm。

操作方法

1.将USB数据线的USB端口插入电源适配器,Type-C端口插入无线充电器。

2.将需要的无线充电设备放在本产品充电指示区域,时钟显示区域充电指示灯 $\text{[} \text{]}$ 常亮,进入充电状态充满后指示灯熄灭。

按键功能

向上/屏幕亮度 $\text{[} \text{]}$ 模式 $\text{[} \text{]}$

向下/自然声 $\text{[} \text{]}$ 闹钟 $\text{[} \text{]}$

闹钟如何设置

在正常时钟显示模式下: 闹钟设置方法1

- 短按 $\text{[} \text{]}$ 4次,时钟显示区域,闹钟 $\text{[} \text{]}$ 图标和时钟开始闪烁,进入闹钟1时钟设置状态。
- 短按 $\text{[} \text{]}$ 增加数字,短按 $\text{[} \text{]}$ 减少数字
- 再次短按 $\text{[} \text{]}$ 切换分钟,分钟开始闪烁,进入分钟设置状态,短按 $\text{[} \text{]}$ 增加数字,短按 $\text{[} \text{]}$ 减少数字
- 再次短按 $\text{[} \text{]}$ 时钟显示区域,闹钟 $\text{[} \text{]}$ 图标和时钟开始闪烁,进入闹钟2时钟设置状态,闹钟2设置方法同闹钟1。
- 长按 $\text{[} \text{]}$ 保存当前设置,并返回到时间显示。

在正常时钟显示模式下: 闹钟设置方法2

- 长按 $\text{[} \text{]}$ 时钟显示区域,闹钟 $\text{[} \text{]}$ 图标和时钟开始闪烁,进入闹钟1时钟设置状态。
- 短按 $\text{[} \text{]}$ 增加数字,短按 $\text{[} \text{]}$ 减少数字
- 再次短按 $\text{[} \text{]}$ 切换分钟,分钟开始闪烁,进入分钟设置状态,短按 $\text{[} \text{]}$ 增加数字,短按 $\text{[} \text{]}$ 减少数字
- 再次短按 $\text{[} \text{]}$ 切换分钟,分钟开始闪烁,进入分钟设置状态,短按 $\text{[} \text{]}$ 增加数字,短按 $\text{[} \text{]}$ 减少数字
- 再次长按 $\text{[} \text{]}$ 时钟显示区域,闹钟 $\text{[} \text{]}$ 图标和时钟开始闪烁,进入闹钟2时钟设置状态,闹钟2设置方法同闹钟1。
- 长按 $\text{[} \text{]}$ 保存当前设置,并返回到时间显示。

小夜灯功能

- 触摸开关第一档启动灯光,灯光亮度为30%。
- 触摸开关第二档,灯光亮度为70%。
- 触摸开关第三档,灯光亮度为100%。
- 触摸开关第四档关灯。
- 依次循环开启灯光。

蓝牙音箱的使用方法

接通电源长按蓝牙开关 $\text{[} \text{]}$,有提示音,蓝牙功能打开,时钟显示区域蓝牙图标 $\text{[} \text{]}$ 闪烁,处于准备配对状态,此时打开手机蓝牙功能,在蓝牙设备中,搜索蓝牙音响出现"S05"字样,点击选中"S05"设备名称,自动进入配对状态,连接成功后,会有提示音,再次长按 $\text{[} \text{]}$ 关闭蓝牙。

调整屏幕亮度

短按 $\text{[} \text{]}$ 调整时钟屏幕亮度,高亮—中亮—低亮—关闭依次循环调整屏幕亮度。

注意事项

- 请勿长时间在阳光直射或高温的地方使用,存放该产品。
- 请勿在高磁卡、磁记录媒体和精密的仪器太近的地方充电。
- 请勿分解或者改造本产品。
- 请勿用湿手触摸交流适配器。
- 请将本产品远离水或其他液体。
- 如果您想清洁本产品,请断开电源。
- 产品工作环境温度范围:20—45°C。

WIRELESS CHARGER
CLOCK + LAMP + SPEAKER

PRODUCT INSTRUCTIONS

FEATURES

- Simple and exquisite.
- Nightlight.
- Wireless speaker
- Alarm clock.
- Wireless fast charger.
- Charging distance 6mm.

HOW TO OPERATE

1. Connect the USB port of the USB data cable to the power adapter and the Type-C port to the wireless charger.

2. Place the required wireless charging device in the charging indication area of this product, and the clock will display the regional charging indicator light $\text{[} \text{]}$ is always on, and turns off after it enters the charging state and is fully charged.

BUTTON FUNCTION

Up/Screen Brightness $\text{[} \text{]}$ Mode $\text{[} \text{]}$

Down/natural sound $\text{[} \text{]}$ Alarm clock $\text{[} \text{]}$

HOW TO SET THE ALARM

In normal clock display mode: Alarm setting method 1

- Short press $\text{[} \text{]}$ 4 times, the clock display area, alarm 1 $\text{[} \text{]}$ icon and the clock start to flash, and enter the alarm 1 clock setting state. Short press $\text{[} \text{]}$ to increase the number, short press $\text{[} \text{]}$ to decrease the number.
- Short press $\text{[} \text{]}$ again to switch to minutes, the minutes will start to flash and enter the minute setting state. Short press $\text{[} \text{]}$ to increase the number, short press $\text{[} \text{]}$ to decrease the number.
- Short press $\text{[} \text{]}$ again to switch to the minutes, the minutes will start to flash and enter the minute setting state. Short press $\text{[} \text{]}$ to increase the number, short press $\text{[} \text{]}$ to decrease the number.
- Press and hold $\text{[} \text{]}$ to save the current settings and return to the time display.

In normal clock display mode: Alarm setting method 2

- Long press the $\text{[} \text{]}$ clock display area, the alarm 1 $\text{[} \text{]}$ icon and the clock start to flash, and enter the alarm 1 clock setting state. Short press $\text{[} \text{]}$ to increase the number, short press $\text{[} \text{]}$ to decrease the number.
- Short press $\text{[} \text{]}$ again to switch to minutes, the minutes will start to flash and enter the minute setting state. Short press $\text{[} \text{]}$ to increase the number, short press $\text{[} \text{]}$ to decrease the number.
- Short press the $\text{[} \text{]}$ clock display area again, the alarm 2 $\text{[} \text{]}$ icon and the clock will start to flash, entering the alarm 2 clock setting state. The setting method of alarm 2 is the same as that of alarm 1.
- Long press $\text{[} \text{]}$ to save the current settings and return to the time display.

Alarm 1 sound source and lighting settings

- Short press $\text{[} \text{]}$ to select the sound source, and short touch the night light switch $\text{[} \text{]}$ to select the light.
- Short press the alarm bell $\text{[} \text{]}$ twice. In the clock display area, the alarm icon $\text{[} \text{]}$ flashes 3 times and goes out. The sound source and lighting settings are successful.

Alarm 2 sound source and lighting settings

- Short press $\text{[} \text{]}$ to select the sound source, and short touch the night light switch $\text{[} \text{]}$ to select the light.
- Short press the alarm bell $\text{[} \text{]}$ 3 times in the clock display area, the alarm icon $\text{[} \text{]}$ flashes 3 times and goes out. The sound source and lighting settings are successful.

HOW TO USE WIRELESS SPEAKERS

Connect the power supply (long press the Bluetooth switch $\text{[} \text{]}$), there are prompt sounds, Bluetooth function opening, clock display The area Bluetooth icon $\text{[} \text{]}$ flickered and is preparing to pair. At this time, turn on your phone Bluetooth function, in the Bluetooth device, search for the word "S05" in the Bluetooth audio, click to select the name of the "S05" device; automatically enter the pairing state. After the connection is successful, there will be a prompt sound. Long press $\text{[} \text{]}$ to close the Bluetooth.

ADJUST SCREEN BRIGHTNESS

Short press $\text{[} \text{]}$ to adjust the clock screen brightness. High brightness - medium brightness - low brightness - off to adjust the screen brightness in sequence.

HOW TO USE NATURE SOUNDS

In clock mode:

- Short press $\text{[} \text{]}$ to turn on the natural sound, long press $\text{[} \text{]}$ to turn off the natural sound.
- When natural sound is on:
- Short press $\text{[} \text{]}$ to cycle through the volume adjustment.
- Short press $\text{[} \text{]}$ to cycle through the natural sounds of Sleep fire - Wind chimes - Bell - Birds - Ocean - Stream - Electric fan breeze.
- Double-click $\text{[} \text{]}$ to start flashing in 30 minutes and enter the countdown setting.
- Short press $\text{[} \text{]}$ to cycle through 60-90-30. After 3 seconds without any operation, the countdown begins. The clock display area displays the remaining time of the countdown. After the countdown is over, a natural sound automatically/Automatically closes. If you want to cancel the countdown before the countdown is over, Double-click $\text{[} \text{]}$ to exit the countdown.

APPLICABLE DEVICE

This product supports fast wireless charging, which complies with the Qi wireless charging standard; it realizes short-distance wireless power transmission through magnetic induction. This device supports all wireless charging devices that meet the Qi standard. When using a 5V output adapter, wireless charging supports 5W load. When using an adapter that meets QC2.0 and above standards, the wireless charging supports 10W load. Support overcharge protection (OV) and overcurrent protection (PA).

Thank you so much for choosing our product, please read the manual carefully before using the product.

WIRELESS CHARGING SPECIFICATIONS

ATTENTION POINTS

SPEAKER SPECIFICATIONS

Material: Imported ABS + PP + Hardware
Input: DC 9V/2.1A
Charging efficiency: 75%
Power: 5W/7.5W/10W/15W
Product size: 231x126x216mm
Charging port: Universal Type-C

Bluetooth version: 5.0
Bluetooth distance: 10m
Speaker power: 4Q5Wx1
Speaker specifications: 50mm

RoHS Made in China

FCC Warning

15.19 Labeling requirements.

This device complies with part 15 of the FCC Rules.

Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and

(2) this device must accept any interference received,

including interference that may cause undesired

operation.

15.21 Information to user.

Any Changes or modifications not expressly approved by

the party responsible for compliance could void the user's

authority to operate the equipment.

15.105 Information to the user.

Note: This equipment has been tested and found to

comply with the limits for a Class B digital device, pursuant

to part 15 of the FCC Rules. These limits are designed to

provide reasonable protection against harmful

interference in a residential installation. This equipment

generates uses and can radiate radio frequency energy

and, if not installed and used in accordance with the

instructions, may cause harmful interference to radio

communications. However, there is no

guarantee that interference will not occur in a particular

installation. If this equipment does cause harmful interference to

radio or television reception, which can be determined by

turning the equipment off and on, the user is encouraged to try

to correct the interference by one or more of the following

measures:

-Reorient or relocate the receiving antenna.

-Increase the separation between the equipment and receiver.

-Connect the equipment into an outlet on a circuit different from

that to which the receiver is connected.

-Consult the dealer or an experienced radio/TV technician for

help.

FCC RF Radiation Exposure Statement:

1.This Transmitter must not be co-located or operating in

conjunction with any other antenna or transmitter.

2.This equipment complies with RF radiation exposure limits set

forth for an uncontrolled environment.

This equipment should be installed and operated with minimum

distance **20cm** between the radiator and your body.

IC Warning

This device complies with Industry Canada's licence-exempt

RSSs. Operation is subject to the following two conditions:

(1)This device may not cause interference;

(2)This device must accept any interference, including

interference that may cause undesired operation of the

device.

Le présent appareil est conforme aux CNR d'Industrie

Canada applicables aux appareils radio exempts de licence.

L'exploitation est autorisée aux deux conditions suivantes:

(1)l'appareil ne doit pas produire de brouillage, et

(2)l'utilisateur de l'appareil doit accepter tout brouillage

radioélectrique subi, même si le brouillage est susceptible

d'en compromettre le fonctionnement.

The information listed above provides the user with

information needed to make him or her aware of a RF

exposure, and what to do to assure that this radio operates

within the FCC exposure limits of this radio.

The device complies with RF specifications when the device

used at **20cm** from the body. Third-party belt-clips, holsters,

and similar accessories used by this device should not contain

any metallic components. Body-worn accessories that do not

meet these requirements may not comply with RF exposure

requirements and should be avoided. Use only the supplied

or an approved antenna.