

## GPS L1 Link Budget

### Satellite Transmitter

Transmitter Power (25 Watts)	14 dBW
RF Losses in transmitter path	-1.25 dB
Antenna Gain (with respect to an isotrope)	13.5 dBi
<b>Satellite EIRP</b>	<b>26.25 dBW</b>

### Propagation

Atmospheric and Polarization Losses	-0.5 dB
-------------------------------------	---------

$$Free\ Space\ Path\ Loss = -10 \times \log_{10} \left[ \left( \frac{4\pi d}{\lambda} \right)^2 \right]$$

where d = distance (25236 km)  
 lambda = wavelength = c/f  
 c = speed of light (3x10<sup>8</sup> m/sec)  
 f = frequency (1.57542 GHz)

$$= -10 \log [317.125 \times 10^6 / 190.425 \times 10^{-3}]^2$$

$$= -10 \log [1.665 \times 10^9]^2$$

$$= -184.43\ dB$$

**Received Power on Earth** **-158.68 dBW**  
**-128.68 dBm**

Gain of Receive Antenna	38 dBic
RF losses in LMR400 cabling and connectors from Receive Antenna to Line Amplifier	-6.7 dB
Gain of Line Amplifier	20 dB
Gain of Passive Radiating Antenna	3 dBic

$$Free\ Space\ Path\ Loss = -10 \times \log_{10} \left[ \left( \frac{4\pi d}{\lambda} \right)^2 \right]$$

where d = 100 feet distance (30.48m)  
 lambda = wavelength = c/f  
 c = speed of light (3x10<sup>8</sup> m/sec)  
 f = frequency (1.57542 GHz)

$$= -10 \log [383.023 / 190.425 \times 10^{-3}]^2$$

$$= -10 \log [2011.41]^2$$

$$= -66.07\ dB \quad \text{100 foot distance}$$

**RF power level at 100 ft distance** **-140.45 dBm**