

ERP Calculation

In this calculation, we report ERP relative to a theoretical half-wave dipole. We intend to use approximately 50 ft of Andrew LDF4-50A Helix (http://www.rfparts.com/helix_LDF450A.html) cable which attenuates 0.463 dB per 100 ft at 50 MHz. The system gains and losses are as follows:

- maximum antenna gain: 6.4 dBd
- cable loss: $0.00463 \text{ dB/ft} \cdot 50 \text{ ft} = 0.232 \text{ dB}$
- connector loss: 0.03 dB¹

From the standard definition of decibel

$$\Gamma \text{ dB} = 10 \text{ dB} \log_{10} \left(\frac{P_{ERP}}{P_{TPO}} \right), \quad (1)$$

we obtain the formula² to calculate ERP

$$P_{ERP} = P_{TPO} 10^{\Gamma/10}. \quad (2)$$

The net gain is $\Gamma = 6.4 - 0.232 - 0.03 = 6.14 \text{ dB}$. With $P_{TPO} = 2000 \text{ W}$ the ERP is 8200 W.

¹We conservatively estimate 0.03 dB for our system. Various amateur radio forums and tutorials discuss RF connector losses ranging from 0.01 dB to 0.09 dB.

² P_{ERP} and P_{TPO} are Effective Radiated Power and Transmitter Power Output, respectively.