

Exhibit C

Radiation Hazard Analysis

1. Analysis of Non-Ionizing Radiation for a Sage Millimeter, model SAC-1533-250-S2 Ka Band Conical Horn Antenna Earth Station Antenna System

This report analyzes the non-ionizing radiations levels for a Sage Millimeter, model SAC-1533-250-S2 Ka band conical horn antenna earth station antenna system.

The FCC's Office of Engineering Technology's Bulletin No. 65 specifies that there are two separate tiers of exposure limits that are dependent upon the situation in which the exposure takes place and/or the status of the individuals who are subject to the exposure. The two tiers are General Population / Uncontrolled environment, and an Occupational / Controlled environment.

The applicable exposure limit for the General Population / Uncontrolled environment, i.e., areas that people may enter freely, at an operational frequency between 33000 and 36000 MHz is 1 mW/cm² average power density over a 30 minute period.

The applicable exposure limit for the Occupational / Controlled environment, i.e., areas that only authorized / trained personnel have access to, at an operational frequency between 33000 and 36000 MHz is 5 mW/cm² average power density over a 6 minute period.

The antenna will not be operated in an uncontrolled environment so only the controlled environment values are summarized

2. Summary of expected radiations levels at 36 GHz for a Controlled Environment

<u>Region</u>	<u>Maximum Power Density</u>	<u>Hazard Assessment</u>
Far field (R_{ff}) = 0.026 m	1.489 mW/cm ²	Satisfies FCC MPE
Near field (R_{nf}) = 0.0108 m	2.737 mW/cm ²	Satisfies FCC MPE
Transition region (R_t) = 0.0108 m (R_t) = $R_{nf} < R_t < R_{ff}$	2.737 mW/cm ²	Satisfies FCC MPE
Main Reflector Surface ($S_{surface}$)	5.634 mW/cm ²	Exceeds FCC MPE, however recommendations to address this are in the conclusion.

Analysis

The analysis and calculations that follow in this report are performed in compliance with the methods described in the OET Bulletin No. 65.

Conclusion

Although the FCC limits are exceeded at the surface of the antenna, the limits quickly fall under the FCC occupational limits once personnel is 0.0108 m, or just over 1 cm away from the antenna. The proposed earth station system is located in an environment with controlled access and will be serviced by trained personnel. Only trained personnel will operate the transmitting system during testing. No access to the reflector/feed area will be permitted when the transmitter is turned on. Based on the above analysis it is concluded that no hazard exists for the public.

Definition of terms

The terms are used in the formulas here are defined as follows:

S_{surface} = maximum power density at the antenna surface

S_{nf} = maximum near-field power density

S_t = power density in the transition region

S_{ff} = power density (on axis)

R_{nf} = extent of near-field

R_{ff} = distance to the beginning of the far-field

R = distance to point of interest

$P = 4.0 \times 10^{-3} \text{ W}$

power fed to the antenna in Watts

$A = 2.84 \times 10^{-4} \text{ m}^2$

physical area of the aperture antenna

$G = 31.623$

power gain relative to an isotropic radiator

$D = 0.019 \text{ m}$

diameter of antenna in meters

$F = 36,000$

frequency in MHz

$\lambda = 8.328 \times 10^{-3} \text{ m}$

wavelength in meters

$\eta = 0.485$

aperture efficiency

Antenna Surface. The maximum power density directly in front of an antenna (e.g., at the antenna surface) can be approximated by the following equation:

$$\begin{aligned} S_{\text{surface}} &= (4 * P) / A \\ &= (4 * 4.0 \times 10^{-3} \text{ W}) / 2.84 \times 10^{-4} \text{ m}^2 \\ &= 5.634 \text{ mW/cm}^2 \end{aligned}$$

Near Field Region. In the near-field or Fresnel region, of the main beam, the power density can reach a maximum before it begins to decrease with distance. The extent of the near field can be described by the following equation (**D** and λ in same units):

$$\begin{aligned} R_{\text{nf}} &= D^2 / (4 * \lambda) \\ &= (0.019 \text{ m})^2 / (4 * 8.328 \times 10^{-3} \text{ m}) \\ &= 0.0108 \text{ m} \end{aligned}$$

The magnitude of the on-axis (main beam) power density varies according to location in the near field. However, the maximum value of the near-field, on-axis, power density can be expressed by the following equation:

$$\begin{aligned} S_{\text{nf}} &= (16 * \eta * P) / (\pi * D^2) \\ &= (16 * 0.485 * 4 \times 10^{-3} \text{ W}) / (\pi * (0.019 \text{ m})^2) \\ &= 2.737 \text{ mW/cm}^2 \end{aligned}$$

Transition Region. Power density in the transition region decreased inversely with distance from the antenna, while power density in the far field (Fraunhofer region) of the antenna decreased inversely with the square of the distance. The transition region will then be the region extending from R_{nf} to R_{ff} . If the location of interest falls within this transition region, the on-axis power density can be determined from the following equation:

$$\begin{aligned} S_t &= (S_{\text{nf}} * R_{\text{nf}}) / R \\ &= (27.369 * 0.011 \text{ m}) / R \\ &= (0.301 \text{ m} * \text{mW/cm}^2) / R \end{aligned} \quad \text{where } R \text{ is the location of interest in meters}$$

Far-Field Region. The power density in the far-field or Fraunhofer region of the antenna pattern decreased inversely as the square of the distance. The distance to the start of the far field can be calculated by the following equation:

$$\begin{aligned} R_{ff} &= (0.6 * D^2) / \lambda \\ &= (0.6 * (0.019 \text{ m})^2) / 8.328 \times 10^{-3} \text{ m} \\ &= 0.026 \text{ m} \end{aligned}$$

The power density at the start of the far-field region of the radiation pattern can be estimated by the equation:

$$\begin{aligned} S_{ff} &= (P * G) / (4 * \pi * R_{ff}^2) \\ &= (4.0 \times 10^{-3} \text{ W} * 31.623) / (4 * \pi * (0.026 \text{ m})^2) \\ &= 1.489 \text{ mW/cm}^2 \end{aligned}$$