



Your source for quality GNSS Networking Solutions and Design Services, Now!

Change the values in the yellow boxes to calculate required readings

Receive Ant Gain	Ant Cable Insertion Loss	Repeater Amp Gain	Splitter Loss/Gain	Repeater Ant Gain	Range in Feet	EIRP @ Range In dBm	ERP
40	-26.97	30	11	3	100	-139.29	-141.44

Total Signal Power @ Range in Watts
11.8E-18

GPS Carrier Frequency MHz : 1575 MHz

Range in Meters
31.17
Radiated Power dBm
-72.97

Avg Receive Power L1 dBm N. America : -130 dBm

Transmitted Power (W)
25.3E-12

Free Space loss with Isotropic Antennas : -66.32 dB

TX Pwr (dBm) to antenna = -130 dBm + 57.03 - 3 dB (Repeater Ant Gain) = -75.97

Effective Isotropic Radiated Power (W)
50.5E-12 30.77 pW ERP

Effective Radiated Power (dBW)
-102.97

	EiRP	ERP	
TX Pwr (dBm) to antenna	-75.97	-75.97	dBm
Repeater Ant Gain	3	0.85	dBi/dBd
Total Power radiated	-72.97	-75.12	dBm
FSPL (100 ft)	-66.32	-66.32	dB
EiRP/ERP @ 100 ft	-139.29	-141.44	dBm

Effective Radiated Power -102.97 -105.12 dBW

Effective Radiated Power 50.5 30.8 pW

EiRP

ERP