

GPS L1 Link Budget

Satellite Transmitter

Transmitter Power (25 Watts)	14.25 dBW	
RF Losses in trasmitter path	-1.25 dB	
Antenna Gain (with respect to an isotrope)	13.5 dBi	
Satellite EIRP (wrt isotropic radiator)	26.50 dBW	446.68 Watts

Propagation

Atmospheric and Polarization Losses	-0.5 dB
-------------------------------------	---------

$\text{Free Space Path Loss} = -10 \times \log_{10} \left[\left(\frac{4\pi d}{\lambda} \right)^2 \right]$ where d = distance from antenna = 2.52E+07 meters c = speed of light = 3.00E+08 m/sec f = frequency = 1.58E+09 Hz lambda = wavelength = c/f = 1.90E-01 meters $= -10 \log_{10} \left[3.17E+08 / 1.90E-01 \right]^2$ $= -10 \log_{10} \left[1.67E+09 \right]^2$ Free Space Path Loss over Distance -184.43 dB

Received Power on Earth

-158.43 dBW	
-128.43 dBm	1.44E-04 pW

Gain of Receive Antenna	38 dBic
-------------------------	---------

RF losses in 300 feet of LMR400UF cabling and connectors from Receive Antenna to Line Amplifier	-6.7 dB
Gain of Line Amplifier	20 dB

RF Power at Input to Re-Radiating Antenna	-77.13 dBm	19.36 pW
Gain of Passive Re-Radiating Antenna	3 dBic	

Re-Radiated EIRP (wrt isotropic radiator)	-74.13 dBm	38.64 pW
Re-Radiated ERP (wrt dipole radiator)	-76.28 dBm	23.55 pW

$$Free\ Space\ Path\ Loss = -10 \times \log_{10} \left[\left(\frac{4\pi d}{\lambda} \right)^2 \right]$$

where d = distance from antenna = 100 feet

$$= -10 \log_{10} \left[383.023 / 1.90E-01 \right]^2$$

$$= -10 \log_{10} \left[2.01E+03 \right]^2$$

Free Space Path Loss over Distance -66.07 dB

RF power level at 100 ft distance =

-140.20 dBm	wrt isotropic antenna
-142.35 dBm	wrt dipole antenna