

GPS L1 Link Budget

Satellite Transmitter

Transmitter Power (25 Watts)	14 dBW
RF Losses in trasmitter path	-1.25 dB
Antenna Gain (with respect to an isotrope)	13.5 dBi
Satellite EIRP	26.25 dBW

Propagation

Atmospheric and Polarization Losses	-0.5 dB
-------------------------------------	---------

$$Free Space Path Loss = -10 \times \log_{10} \left[\left(\frac{4\pi d}{\lambda} \right)^2 \right]$$

where d = distance (25236 km)
lambda = wavelength = c/f
c = speed of light (3x10⁸ m/sec)
f = frequency (1.57542 GHz)

$$\begin{aligned} &= -10 \log [317.125 \times 10^6 / 190.425 \times 10^{-3}]^2 \\ &= -10 \log [1.665 \times 10^9]^2 \\ &= -184.43 \text{ dB} \end{aligned}$$

Received Power on Earth

-158.68 dBW
-128.68 dBm

Gain of Receive Antenna	38 dBic
RF losses in LMR400 cabling and connectors from Receive Antenna to Line Amplifier	-6.7 dB
Gain of Line Amplifier	20 dB
Gain of Passive Radiating Antenna	3 dBic

$$Free Space Path Loss = -10 \times \log_{10} \left[\left(\frac{4\pi d}{\lambda} \right)^2 \right]$$

where d = 100 feet distance (30.48m)
lambda = wavelength = c/f
c = speed of light (3x10⁸ m/sec)
f = frequency (1.57542 GHz)

$$\begin{aligned} &= -10 \log [383.023 / 190.425 \times 10^{-3}]^2 \\ &= -10 \log [2011.41]^2 \\ &= -66.07 \text{ dB} \end{aligned}$$

100 foot di

RF power level at 100 ft distance

-140.45 dBm

istance