倍思包装设计稿件信息 Baseus

基本信息	产品型号	BPE45A		
	产品名称	倍思 优塔ioTa随行电户外移动电源 420W（美日规110V）冷松绿		
	产品方案编码			
	物料编码	1000056278	包装编码+版本号	PB3813Z-P0A0
	物料规格描述	说明书\悦声高自80G，单色印刷，骑马钉，160*190MM，8页16P		
	包装平面设计	Andy 李运成	包装结构设计	易婷

版本历史

版本	变更日期	变更描述
P0A0	2022.12.08	初始版本

包装审核区域责任划分 Baseus

产品相关	产品外观/参数/瑞雕	产品经理/项目主管请在此处签名
	彩盒/说明书文案	
	执行标准/生产商信息	
认证相关	认证相关文案	认证工程师请在此处签名
	认证相关图标	
品质相关	法律法规相关文案	品质工程师请在此处签名
	警示语	
定制需求	定制渠道需求	定制代表请在此处签名
品类相关	外功能/图标表达	品类策划/文案策划请在此处签名
	文案部分/翻译	
包装设计相关	产品条形码	包装设计师/组长/主管请在此处签名
	公司地址信息	
	文件基于最新量产版	
	包装设计规范	

温馨提示：请印刷供应商严格按照倍思的图纸印刷生产。如贵司有生产上的原因需要调整倍思图纸的字体、图形、颜色、刀模尺寸等，请必须通知倍思相关负责的包装设计师，并在征得包装设计师同意的情况下修改文档并发回存档。

切线 ——
折线 - - - -
刀线图例

K

Baseus

User Manual
取扱説明書

Baseus IoTa Series Portable Power Station 420W (US/JP 110V)
倍思 優格IoTaエネルギーステップ携带式デジタルエネルギー的電電源420W（110V US/JP）

Thank you for purchasing Baseus IoTa Series Portable Power Station. (hereinafter referred to as Baseus Digital Portable Power Station). The information contained herein affects your safety and your legal rights and responsibilities. Read this manual carefully before using the product and follow the instructions. Failure to follow the instructions and warnings herein may result in serious injury to you or bystanders, or damage to your device or property. Shenzhen Baseus Technology Co. Ltd. reserves the right of final explanation for this document and all relevant documents relating to Baseus Digital Portable Power Station. Please visit the official website for the latest version.

信思、優格のエネルギーステップ携带式デジタルエネルギー的電電源をご購入いただきまして、誠にありがとうございます。本取扱説明書に記載されている内容は、お客様の安全と法的権利および責任に関係しています。製品を使用する前に本説明書をよくお読みください。説明書の指示および警告に従わない場合、お客様ご自身や第三者に怪我を負わせたり、機器に損傷を与えたりする恐れがあります。本取扱説明書と信思デジタルエネルギー携带式デジタル電源の関連する解釈権は深圳市信思科技有限公司に帰属します。最新の情報については、公式サイトをご参照ください。

By using this product, you hereby signify that you have read this document carefully and that you understand and agree to abide by the terms and conditions herein. You agree that you are solely responsible for your own conduct while using this product and for any consequences thereof. You agree to use this product only for purposes that are in accordance with all terms, precautions, practices, policies and guidelines Shenzhen Baseus Technology Co. Ltd. (Baseus Digital Portable Power Station) intends to provide and generally accepted in relevant fields. You agree that you are solely responsible for your own conduct while using this product, and therefore agree that Shenzhen Baseus Technology Co. Ltd. (Baseus Digital Portable Power Station) and its affiliates, officers, agents, or employees are not liable for any damage or injury to third parties resulting from your improper use of this product. You further agree to indemnify Shenzhen Baseus Technology Co. Ltd. (Baseus Digital Portable Power Station) and its affiliates, officers, agents, or employees for any such claim or demand, including but not limited to, those set forth herein.

本製品を使用する前に、取扱説明書をよく読んでください。ドイツの弁護士事務所を通じて法的責任が明確にされるために、法的に拘束力があります。本取扱説明書は、本製品に関する法的権利および義務を定めています。本製品をご使用になる前にこの説明書をよくお読みください。説明書の指示および警告に従わない場合、お客様ご自身や第三者に怪我を負わせたり、機器に損傷を与えたりする恐れがあります。本取扱説明書と信思デジタルエネルギー携帯式デジタル電源の解釈権は深圳市信思科技有限公司に帰属します。最新の情報については、公式サイトをご参照ください。

Shenzhen Baseus Technology Co. Ltd. (Baseus Digital Portable Power Station) accepts no liability for damage, injury or any legal responsibility incurred directly or indirectly from the use of this product. Users shall observe safe operation guidelines including, but not limited to, those set forth herein.

深セン市信思科技有限公司(信思デジタルエネルギー携帯式)は、本製品の使用または以接続的な使用によって生じた損害、負傷、または法的責任について一切責任を負わない。本取扱説明書に記載されているものを含むがこれに限定されない。すべての関連ガイドラインに従う義務があります。

EN

1. Function Description

1 This product is developed based on industry-leading digital power technology. It supports PD3.1 240W fast charging, fully meeting your power needs.

2 This product uses a LCD screen to display real-time operation status (battery level, operating temperature, current input/output power, remaining charging time), charge and discharge reminder, and status alert.

3 This product is equipped with 4 AC outlets, which can simultaneously supply power to a maximum of lower than 420W, such as non-mounted mini fridges, non-mounted rice machines, desk lamps, small rice cookers, etc.

4 It supports simultaneous power output of up to 8 products, with a maximum of 1400W PD fast charging via a single Type-C port. The product automatically optimizes multiple protocols for USB Type-C based fast power output to meet the charging needs of digital products.

5 Supports no more than 2 methods of input for charging: Type-C PD3.1 fast charging (240W Max.), DC port charging (500W Max.). The product automatically prioritizes the input of the first connected product, supporting direct power supply via non-mounted chargers and direct charging via solar panels with MC4 interface.

6 The built-in LED lighting provides three lighting modes: long light, SOS and strobe. You can switch the mode by pressing the button or adjust the brightness of the long light on the app.

2. Product Specification

Name: Digital Power Bank 420W
Model No.: BPE45B
Battery Capacity: 1000W(115.200Wh)
Solar DC Input: 12V~24V 1200W Max.
Type-C Input: 5V~9V, 9A; 12V~14V, 15V~16A; 20V~24V, 28V~30A 1400W Max.
AC Output: 100V-120V ~ 50/60Hz 420W (Pure Sine Wave; Peak Power 840W)
USB1/USB2 Output: 5V~9V, 9A; 12V~20V, 12V~12A
Type-C1/Type-C2 Output: 5V~9V, 9A; 12V~20V, 15V~5A; 20V~24V, 28V~5A 1400W Max.
Type-C3 Output: 5V~9V, 9A; 12V~20V, 12V~5A
Type-C4/Type-C5 Output: 100W-20V
USB1+USB2 Output: 5V~5A
USB3 Output: 5V~5A
Type-C1+Type-C2+USB1+USB2 Output: 100W+25W
DC+Car Charger Output: 13.5V~7.4A 100W Max.
Total Output: 420W
Product Size: 280×175×120mm
Product Weight: 3.9kg
Execution Standard: Q/BHSD3.047
List of Accessories: Solar Charger Cable (MC4 to DC Input), Superior Series Fast Charging Data Cable Type-C to Type-C (240W), User Guide, Warranty Card

---

3. Package Including

Main Unit (Baseus IoTa Portable Power Station 420W) (US/JP 110V) ×1
Solar Charger Cable (MC4 to DC Input) ×1
Superior Series Fast Charging Data Cable Type-C to Type-C (240W) ×1
User Manual ×1
Warranty Card ×1

4. Schematic Display of Product



Download the Baseus App and User Manual:

1 Visit the QR code on the right for the download address with your mobile device, or https://u.baseus.com/download (in other languages in the search bar to download the app.

2 Open the app and follow the prompts to register if you have registered, please login directly, login, add equipment, and then connect and operate.

---

5. Instructions

Note: The following instructions assume that the APP has been connected to the product. If the connection is broken or the distance between them is too far (over 10 meters), the APP may not be able to instantly respond or issue reminders. This will affect your user experience. It is recommended to use the product while keeping the APP on and keep them close for smoother use.

1. Start/Shutdown

1 Press the power button for 3s to turn on the product, the power indicator lights up, screen prompts to enter standby mode.
2 In the power on state, press and hold the power button for 2 seconds to turn it off with the power indicator off.



* The default standby time of this product is 15 minutes. If the inverter switch/LED light switch is off and the product has no load accessed, the product will automatically turn off in 15 minutes.

2. How to charge a device

1 Charge a device via a USB/Type-C/DC port
2 When the product is in the standby state, the USB/Type-C/DC port will enter the standby mode and can be used to charge cell phones or other digital products with compatible data cables.
* Meanwhile, the main screen will display all parameters for reference, including the current total output power, current temperature, remaining battery level, and remaining discharge time under the current output power.

2) Charge a device via the AC port

1 After the product is turned on, press and hold the AC output button for 2 seconds to enable AC inversion output, with the AC output indicator on. Now you can plug in and charge an AC device.
2 If the AC output is not needed, you can turn off the AC output button for 2 seconds to disable AC inversion output, with the AC output indicator off.
⚠ **Warning: There is a high-voltage output after the AC inversion output is enabled. Please do not plug metal or conductive objects into the AC main socket to avoid electric shock!**

---

3) How to charge the product

This product supports up to 140W PD fast charging, and accommodates all adapters and car-mounted chargers that are compatible with the PD protocol.

DC charging
* The DC port supports the MPPT protocol, and can be charged with car-mounted chargers or solar panels.
* When the product is in the standby state, press the power on-state automatically in order to monitor all modules and provide feedback on operation status in real time.

Note:
* The product will not enter automatic shutdown when it is charged with a device through USB Type-C/DC/AC ports.
* **The value of each parameter on the main screen is measured by a built-in program, which may be subject to errors and changes in real time. The parameter information is for reference only.**
* **Do not stop the charging and discharging chart of the ports in the APP for more details about the charging and discharging of the ports.**

4) LED Lighting

* This product comes with a LED flashlight for emergency lighting needs.
1 Press and hold the LED switch/mode switch button for 2 seconds to turn on the LED light. The light has a default state of staying on and can be adjusted in brightness in the app. It also supports other modes with an SOS and strobe.
2 Press and hold the button under the app on mode in the app.
* Under the LED lighting state, press and hold the LED switch/mode switch button for 2 seconds to turn it off.

Note: If the LED lighting is on, the default standby time of this product will be adjusted to 6 hours for any need of emergency lighting at night.



---

5) Advanced use of the APP

1 You can contact Baseus for 1on 1 customer service via the app to solve problems you may have.
2 The device name can be edited in the app.

6) FAQ

1 What type of battery is used in the product?
This product uses high-quality automotive-grade lithium iron phosphate battery.
2 What equipment can be charged via the AC output port of the product?
The AC output of the product is rated at 420W with a peak power of 840W, being able to supply power to most consumer electronic devices. Please check the rated power of the equipment and make sure that the total power of all load equipment is lower than the rated power before using it.
3 How do I know how long the product can supply power?
The LCD display will show the remaining battery life and calculate a remaining discharge time based on the current power, for reference only.
4 How can I tell the product is charging?
When charging, the LCD display will show the remaining charging time and input power.
5 Does the product support simultaneous charging and discharging?
The Type-C port and USB port support simultaneous charging and discharging; when using the DC port to charge the product, it does not support output charging.
6 Can I use it in the rain?
Please use a dry, soft and clean cloth or paper towel to wipe this product.
7 Can I carry this product on the plane?
Equipment no larger than 100Wh is allowed on planes. This product is 1080Wh, so it is not allowed on planes.
8 How do I store and maintain the product?
* It is recommended to use or store the product with a temperature of 20-30°C, and keep it away from water, heat source and metal objects.
* Avoid deep storage, please charge and discharge the product once every 3 months (discharge it to 30% and then charge it to 50%).
* For safety reasons, do not store the product when the temperature is higher than 45°C or lower than -10°C for a long time. Long-term storage at high temperatures will accelerate the aging of the battery and affect its service life. If the storage time is less than a full battery, its battery core will suffer irreversible damage and the service life of the product will shorten.
* If the product has low remaining power and has been idle for too long (not in one discharge/charge state), it will enter deep sleep mode and need to be charged before being used again.

---

6. Common Problems & Troubleshooting

Details of Error Icons	Error Type	Recovery Methods
Icon flashes	USB overload protection	Remove the abnormal load and normal operation will resume automatically once the load is normal.
Icon flashes	Type-C overload protection	Remove the abnormal load and normal operation will resume automatically once the load is normal.
Icon flashes	Type-C high temperature protection	Normal operation will resume automatically after the temperature returns to normal.
Icon flashes	Battery charging high temperature protection	Normal operation will resume automatically after you stop the charging and place it in a cool and ventilated place.
Icon flashes	Battery discharge high temperature protection	Normal operation will resume automatically after the battery cools down.
Icon flashes	Battery charging low temperature protection	Normal operation will resume automatically after the battery temperature is restored to above 5°C (41°F).
Icon flashes	Charging overload protection	Normal operation will resume automatically after the overload is removed.
Icon flashes	AC output overload protection	Normal operation will resume after removing the over-powered device and reserving the product. (Vertical appliances must be placed in a ventilated place.)
Icon flashes	AC over-temperature protection	Please remove the abnormal load, and put the product in a cool and ventilated place, and it will resume normal automatically.
Icon flashes	AC over-discharge protection	Normal operation will resume automatically after the battery is restored to normal.
Icon flashes	Fan blocking	Please check whether the fan is blocked by foreign objects and remove them if so.
Icon flashes	DC overload protection	Normal operation will resume automatically once the load is normal.
Icon flashes	DC high temperature protection	Normal operation will resume automatically after the product cools down.
Icon flashes	Battery discharge low temperature protection	Normal operation will resume automatically after the battery temperature is restored to above 5°C (41°F).
Icon flashes	Battery discharge underv oltage protection	Please charge the product immediately.
Icon flashes	Failure of communication with BMS	Normal operation will resume automatically after being restored.

If any alert occurs during the use of this product and the alert icon does not disappear after the product is restarted, please stop using the product immediately (do not attempt to charge or discharge). If the above information fails to resolve your problem, please contact customer service for further support.

JP

一、 製品規格について

* 本製品は最新の最新のデジタル電源技術の研究開発に基づき、PD3.1 240W急速充電に対応。
1 本製品はLCDスクリーンを搭載しており、リアルタイムの動作ステータス（バッテリーレベル、動作温度、入力/出力電力、残充電時間）、充電/放電通知、ステータスアラートを表示します。
2 本製品は4個のACポートを搭載しており、最大420W（ピーク840W）の電力を同時に供給します。例えば、冷蔵庫、炊飯器、デスクランプ、小型炊飯器などです。
3 最大8台の製品を同時に給電することができます。1ポートあたり1台のUSB-C/USB-A/DCポートの最大600W可能な充電を対応し、USB-C/Type-C ポートでは、デジタル製品の急速充電のニーズを満たすために最適な電力プロトコルを自動的に調整します。
4 Type-C PD3.1充電電力（240W Max.）、DCポート充電（500W Max.）の最大2種類の入力充電に対応。
5 内蔵のLED照明は、ロングライト、SOS、ストロボの3つのモードを提供しています。ボタンを押してモードを切り替えたり、アプリで長時間照明の明るさを調整することもできます。

二、 製品仕様

製品名：デジタルパワーバンク420W
型番：BPE45B
バッテリー容量：1000W(115.200Wh)
ソーラー充電入力：12.0V-24.0V 1200W Max.
Type-C入力：5V~9V,9A;12V~20V,15A;20V~24V,28V~5A 1400W Max.
AC出力：100V-120V ~50/60Hz 420W（正弦波、ピーク840W）
USB1/USB2出力：5V~9V,9A;12V~20V,12A~12A
Type-C1/Type-C2出力：5V~9V,9A;12V~20V,15V~5A;20V~24V,28V~5A 1400W Max.
Type-C3出力：5V~9V,9A;12V~20V,12A
Type-C4/Type-C5出力：100W-20V
USB1+USB2出力：5V~5A
USB3出力：5V~5A
USB1+Type-C1出力：100W-20V
USB2+Type-C2出力：100W-20V
USB1+Type-C1+Type-C2+USB1+USB2出力：100W+25W
DC+車載充電器出力：13.5V~7.4A 100W Max.
総出力：420W
製品サイズ：280×175×120mm
本体重量：約3.9kg
実行基準：Q/BHSD3.047
付属品一覧：ソーラー充電ケーブル（MC4～DC入力）、優勝シリーズ高速充電ケーブル Type-C to Type-C（240W）、取扱説明書、保証書

三、 包括的な明細書

優格のエネルギーステップ携帯デジタルエネルギー的電電源420W（110V US/JP）×1
ソーラー充電ケーブル（MC4～DC入力）×1
優勝シリーズ高速充電ケーブル Type-C to Type-C（240W）×1
取扱説明書×1
保証カード×1

四、 製品概略図について（説明とインターフェースの説明）

BaseusAPPおよびユーザーガイドのダウンロード

1 スマートフォンを使用して、以下のQRコードをスキャンし、ダウンロードアドレスを取得します。または、ブラウザに入力します。https://u.baseus.com/download（その他言語）
2 アプリをダウンロードします。
3 APPのサインインまたは登録が完了した場合はログインしてログインを続行します。登録されていない場合は、アカウントを作成し、デバイスを追加して接続して操作します。

五、 製品の使用

ご注意：ご使用の前に、デフォルトのAPPはすでに製品と相互接続されています。接続が切れた、距離が遠いはるかかなりの場合、APPはすぐに応答できないか、問題をタイムリーに発行します。ご使用の経験に影響を与えます。APPをオンにしてデバイスの近くに保ちながらご使用ください。スムーズにご使用いただけます。

1. 電源のオン/オフ

1 電源キーを約3秒押しして電源を起動すると、電源キーのライトが点灯し、画面が待機モードに入ります。
2 電源オン状態で電源ボタンを2秒間押し続けると、製品の電源がオフになり、電源ボタンのライトがオフになります。

2. 充電機器を使用

1) USB Type/Type-C/DCポートを使用して機器を充電する。
* 製品が電源オフ状態または、USB Type/C/DCポートがオン状態になった、対応するポートをデータケーブルをインターフェイスに接続した後、製品は自動的にポートの電力を調整します。
* メインの画面にはパラメータ一覧が表示され、製品の現在の入力/出力電力、残りの充電時間、バッテリーの容量などが表示されます。このパラメータ情報は参考のみです。**数値は実時間で変動します。**
* **あなたの製品がポートの充電を停止するまで、APPを閉じないでください。**数値は実時間で変動します。

4) LED照明

* 本製品には緊急照明用の内蔵LEDフラッシュライトが搭載されています。
1 LEDライトをプッシュ可能な状態になるまで約2秒間長押しします。LEDライトは、デフォルトでは「オン」状態であり、アプリで明るさを調整することもできます。
2 アプリの下の長押しボタンを押します。
* LEDライト使用時に、長押しまたはスイッチを約2秒間長押しして、LEDライトを消します。

ご注意：LED照明がオンになっている場合、本製品のデフォルトの待機時間は、睡眠の安全を保持するために6時間に調整されます。

---

3) 充電方法

本製品は、最大140WのPD急速充電をサポートし、PDプロトコルをサポートするすべてのアダプター、自動車充電器、およびその他の機器を使用して製品を充電できます。

DC充電

* 本製品のDCポートは、MPPTプロトコルをサポートしており、本製品の充電方式の自動車充電器およびソーラーパネルの充電をサポートします。
* 電源オフ状態で、ディスプレイ画面がオンになり、本製品の電力をリアルタイムの調整をなくてはならずにメインインターフェイスをオフ状態に調整はスクリーンがなくなり調整です。

ご注意：
USB/Type-C/DC/ACは充電のインターフェースはPD急速プロ、対象の電子インターフェースPD製品を充電している場合、製品は自動ポートオプティマイザ調整に取りかかる。
メインの画面のパラメータープロンプトは、製品の現在のみプロトコルによって測定された値であり、特定のエラーが、リアルタイムで変更されが発生の参考です。このパラメーター情報は参考のみです。数値は実時間で変動します。
あなたの製品がポートの充電を停止するまで、APPを閉じないでください。数値は実時間で変動します。

4) LED照明

* 本製品には緊急照明用の内蔵LEDフラッシュライトが搭載されています。
1 LEDライトをプッシュ可能な状態になるまで約2秒間長押しします。LEDライトは、デフォルトでは「オン」状態であり、アプリで明るさを調整することもできます。
2 アプリの下の長押しボタンを押します。
* LEDライト使用時に、長押しまたはスイッチを約2秒間長押しして、LEDライトを消します。

ご注意：LED照明がオンになっている場合、本製品のデフォルトの待機時間は、睡眠の安全を保持するために6時間に調整されます。

---

5) APPのトラブルプッシュ通知

1 APPをクリックして設定のお客様サービスに1on1サービスを問い合わせをして、お客様の問題を解決いたします。
2 APPでの製品のデバイスの名前を変更することができます。

6) よくある質問

1 製品はどのタイプのバッテリーを使用していますか？
この製品は、高品質の自動車用グレードのリン酸鉄リチウム電池を使用しています。
2 製品のACポートから何を充電できますか？
本製品のACポートの定格電力は420W、ピーク電力は840Wです。ほとんどの消費者電子製品の電力を供給できます。使用前に電子機器の電力定格をご確認ください。すべての電子ツールが合計の定格電力よりも小さくなければなりません。
3 どのくらい製品がどのくらい電力を供給できるか知っていますか？
本製品の残量をLCDディスプレイに表示し、参考のみの残り充電時間を計算します。
4 製品が充電されていることをどうやって知ることができますか？
充電中、LCDディスプレイは残り充電時間と入力電力を表示します。
5 製品は同時に充電と放電をサポートしていますか？
USB-A、USB-C、DCポートは同時充電と放電をサポートしています。
6 雨の中でも使えますか？
本製品のクリーニングには、柔らかい乾いた清潔な布またはペーパータオルを使用してください。
7 この製品を飛行機に持ち込むことはできますか？
100Whを超えない機器は飛行機に持ち込むことができます。製品は1080Whであるため、飛行機に搭載することはできません。
8 本製品の保管、保管方法、および使用方法はどのようにしますか？
* 本製品は、高、低、その他の温度条件から離れた25°Cの室温で使用または保管することを推奨します。
* 長期保管の場合は、3ヶ月に1回の充電と放電を行ってください（3ヶ月ごとに30%まで放電し、次に50%まで充電します）。
* 安全上の理由から、本製品を45°C以上または-10°C以下の環境で長期保管しないでください。
* 本製品の保管温度が高すぎる場合、バッテリーコアは不可逆的な損傷を受けます。バッテリーが完全に充電されていない状態（バッテリーが完全に放電されていない状態）で、バッテリーに不可逆的な損傷を与え、製品の寿命を短くします。
* 本製品の残り電力が少なく、アイドル時間が長すぎる（放電状態や充電状態ではない）場合、製品はディープスリープモードに入ります。製品を再使用する前に充電する必要があります。

七、 本製品の使用に関するメッセージ説明書、および関連する法的要件

Statement on Toxic and Hazardous Substances in Electronic Information Products：

Part Name	Toxic or Hazardous substances and elements					
	Lead (Pb)	Mercury (Hg)	Cadmium (Cd)	Hexavalent Chromium (Cr6+)	Polybrominated biphenyls (PBB)	Polybrominated diphenyl ether (PBDE)
PCB	Nor	Nor	Nor	Nor	Nor	Nor
Metal Part	Nor	Nor	Nor	Nor	Nor	Nor
Plastic	Nor	Nor	Nor	Nor	Nor	Nor
Rechargeable Battery	Nor	Nor	Nor	Nor	Nor	Nor

This form is prepared in accordance with SJ/T 11364 regulations.
Nor means that the content of the toxic and hazardous substances in all homogeneous materials are below the limit requirements specified by GB/T 26572 standard.
X indicates that contents of the toxic and hazardous substances exceed the limit requirements specified by GB/T 26572 standard in at least one of the homogeneous materials of the parts.
This product complies with EU RoHS 2 Directive(2011/65/EU).
The 5-year icon refers to the "effective life of environmental protection", <nil> the product quality assurance period. Environmental protection use period refers to the electronic products sold in the specified conditions, not to be dismantled, discard, and not substantial damage to the environment, or cause serious damage to people and property. The term of "environmental protection use" means that all electronic products will be required to ensure that the environment will not be damaged or cause harm to people or property. The quality of the products due to the safety risks that arise after the safe use period.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.
If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

Warning:
Operation of this equipment in a residential environment could cause radio interference.

八、 機器の使用と関連する法的要件

異常アイコン説明		問題タイプ	異常の回復方法
アイコンが点滅	USB過負荷保護	USB過負荷保護	異常負荷を取り外し、正常になったら自動回復します
アイコンが点滅	Type-C過負荷保護	Type-C過負荷保護	異常負荷を取り外し、正常になったら自動回復します
アイコンが点滅	Type-C高温保護	製品の冷却後に、自動回復します	
アイコンが点滅	ファンの閉塞の保護	異物がないかチェックしてください	
アイコンが点滅	バッテリ充電時の高温保護	バッテリの温度回下降に自動回復します	
アイコンが点滅	バッテリ充電時の低温保護	バッテリ温度が5℃以上に戻ると自動回復します	
アイコンが点滅	充電過負荷保護	異常負荷の自動回復	
アイコンが点滅	AC過負荷保護	「オーバーパワーデバイス」を取り外し、使用を保護中の状態に戻ります。（垂直方向の電子機器は、通風の良い場所に置いてください）	
アイコンが点滅	AC高温保護	異常負荷を取り外し、自動冷却用の場所に置いた後に、自動回復します	
アイコンが点滅	AC低電圧保護	弾性温度が回復すると自動回復します	
アイコンが点滅	ファン閉塞保護	ファンに異物が詰まっていないかどうかを確認し、異物を取り除きます	
アイコンが点滅	DC過負荷保護	負荷が正常になったら、自動回復します	
アイコンが点滅	DC高温保護	製品が冷却後に自動回復します	
アイコンが点滅	バッテリ放電低温保護	バッテリ温度が5℃以上に戻ると自動回復します	
アイコンが点滅	コア放電不足電圧保護	できるだけ早く充電してください	
アイコンが点滅	BMS通信に異常しました	異常回復後に自動回復します	

本製品の使用中に異常メッセージが表示され、異常回復も異常アイコンが消えない場合は、すぐに使用を中止してください！
充電（放電）をしないでください！

FCC ID:2AHGJ-BPE45B

警告：LED光源はLED光源（ランプ）のみ。
交換不可能。LED光源、光電池の交換は、
製品メーカーまたはその代理店にご連絡ください。

Warning: Please follow the above safety instructions. LED light source (lamp) only. Non-replaceable. Contact the manufacturer or its agent for any changes of LED light source, photovoltaic cell.

Manufacturer: Shenzhen Baseus Technology Co., Ltd.
Add: 2nd Floor, Building B, Baseus Intelligence Park, No.2006, Xuegang Road,
Longgang Community, Bantian Street, Longgang District, Shenzhen
Postcode: Shenzhen 518129 P.R.C
Hotline: +86 0755-33171102 Website: www.baseus.com

倍思 由Designed by Baseus
中国制造 Made in China

PB3813Z-P0A0
XXXXXXXX