

深圳市拓一科技有限公司

Common push-pull cover remote control related parameters:

(fixed code, learning code, rolling code, dial code at each frequency, copy)

1. Working voltage: DC12V (one 23A battery)
2. Working current: $\leq 8\text{mA}$
3. Working frequency: 315 (330 350 390 430 418 433 and other special can be customized)
4. Modulation method: ASK (amplitude modulation)
5. Transmitting power: $\leq 100\text{mW}$
6. Launch distance: 50 ~ 150m (open space)
7. Encoding type: 2262 (learning code EV1527 rolling code HCS301 dial code copy type)
8. Dimensions: $62 \times 39 \times 12\text{mm}$
9. Working temperature: $-10^{\circ}\text{C} \sim +50^{\circ}\text{C}$
10. Self-test: with low-voltage detection function, when the battery supply voltage is low, the indicator light will not light, which proves that the battery needs to be replaced
11. Appearance color: red mahogany, golden mahogany, pearl white, emerald, blue, matte black, glossy black.
12. Product use: remote control of rolling shutter doors of garages, retractable gates, LED lamps, LED special flashing lights, various alarm devices, switch signals, remote control audio and other remote control fields

★Note: special frequencies, special symbols, need to be customized.



深圳市拓一科技有限公司

FCC STATEMENT :

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

This device may not cause harmful interference, and

This device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

RF warning statement:

The device has been evaluated to meet general RF exposure requirement.

The device can be used in portable exposure condition without restriction.