



Quick Installation Guide

WiFi to Ethernet Adapter | Wireless Access Point | WiFi Extender

Installation Video Guide
<https://mywifiassist.com/pages/video>

24/7 Technical Support Email
support@mywifiassist.com

Model: ACB/ABE8

LED Descriptions

Signal LED	Solid blue	Connected to your existing WiFi router and is in a usable location. Or set up as Wireless Access Point Mode successfully.
	Blinking blue	Pairing with your existing WiFi router.
	Solid orange	Connected to your existing WiFi router while restoring a wireless signal.
	Blinking orange	Restoring to factory default settings.
WiFi LED	OFF	Failed to connect to your existing WiFi router and all LED indicators light off. The device is returned to its factory default setting. Please do not power off this device during the reset process, otherwise you may damage it.
	ON	No device is connected to the Ethernet port.
Ethernet LED	Solid blue	Successfully connected to the Internet.
	Blinking blue	Not connected to the Internet.

Button and Port Introduction

WPS/Reset Button	<p>Used to reset the device, or start WPS connection.</p> <p>• WPS: Press the button on your WiFi router, then press and hold the button on the device for 1 second within 2 minutes. The Signal LED of the device should change from blinking blue to solid blue, which indicates a successful connection between your router and this adapter.</p> <p>• Reset: Press and hold the button for 7 seconds then release it. The Signal LED should start blinking orange and all LED indicators light off. The device is returned to its factory default setting. Please do not power off this device during the reset process, otherwise you may damage it.</p>
Ethernet Port	Connect to a wired device when set up as WiFi to Ethernet Adapter Mode, or connect to an Internet-enabled port when set up as Wireless Access Point Mode.

WiFi to Ethernet Adapter or Extender Mode

There are two ways to set up the adapter: via a web browser, or via the WPS button. Please choose either Method 1 or Method 2 to set up as WiFi to Ethernet Adapter or WiFi Extender.

Method 1: Via a Web Browser

1. Power on your adapter

Plug the adapter in the same room as your WiFi router.

2.1 Launch a web browser, enter setupwifi.net in the address bar. Default login password is: admin.

2.2 Enter the correct password of the network you selected and customize the name of your extended networks.

2.3 Create your new login password for future logins (recommended). Select WiFi to Ethernet Adapter and Extender Mode. Click Next.

2.4 Select the existing network that you want to extend.

3.1 Work as WiFi to Ethernet Adapter

Connect your WiFi router to the Ethernet port of this adapter for Internet connection with an Ethernet cable. The location where you install this adapter should be within the WiFi coverage of your existing router. The Signal LED of this adapter should be in solid blue or orange color for a successful Internet connection. Otherwise, you should move your adapter closer to your existing WiFi router for better signal.

3.2 Work as WiFi Extender

Connect your Wireless Devices to the extended WiFi network created by this adapter.

3.2.1 Relocate your Adapter

For general WiFi coverage and performance, please plug the adapter about halfway between your WiFi router and the WiFi devices. The location you choose must be within the range of your existing network. Wait until the Signal LED turns solid blue or orange.

3.1.1 For optimal connection for your wired device, we do not recommend connecting other WiFi devices to the extended network created by this adapter, which may limit the speed of your wired device. You can log back into the web management page of this adapter to turn off the extended network.

3.1.2 In most cases, you need to configure the IP address and DNS server address of your wired device as AUTO OBTAIN.

Method 2: Via the WPS Button

You can use this method if your router has a WPS button (the button may look like one of these). Otherwise, use Method 1. By pressing the WPS button on both of your existing router and this adapter, you can connect this adapter to your router.

1. Power on

Plug the adapter in the same room as your WiFi router.

2.1 Wait until the Signal LED changes from blinking blue to solid blue, which indicates a successful connection between your router and this adapter.

2.2 Wait until the Signal LED changes from blinking blue to solid blue, which indicates a successful connection between your router and this adapter.

3. Connect your devices to this adapter

Please refer to Step 3 in Method 1.

Wireless Access Point Mode

1. Power on

Plug the access point into an electrical outlet.

2.1 Create your new network

Select **WiFi to Ethernet Adapter and Extender Mode**.
WiFi to Ethernet Adapter and Extender Mode
Wireless Access Point Mode

2.2 Launch a web browser, enter setupwifi.net in the address bar. Default login password is: admin.

2.3 Create your new login password for future logins (recommended). Select **Wireless Access Point Mode**. Click Next.

2.4 Customize your new WiFi network name and password. Click Next.

2.5 Confirm the setup information. Take a screenshot for future usage. Then click Apply.

3. Connect to the Internet

Connect the access point to your router or an Internet-enabled Ethernet port with an Ethernet cable. Setup Completed! You can now connect to your new dual-band WiFi network for fast Internet connection!

FAQ

- Q1: How to reset the device back to its factory default settings?**
- When the device is powered on, press and hold the WPS/Reset button for 7 seconds and then release it. The Signal LED should firstly start blinking orange and then all the LED indicators will light off. Then the device is restored back to its factory default setting. Please do not power off the device during this reset process, otherwise, you may damage the device.
- Q2: What should I do if I forget my login password?**
- Please refer to Q1 to reset the device, then reconnect to the default network mywifi_xxxx and visit setupwifi.net to create a new login password.
- Note: Default WiFi key for the default network is: 12345678. Default login password for setupwifi.net is: admin. After you reset this device, you need to reconfigure it to have access to the Internet again. Please write down your login password on a piece of paper for future logins.
- Q3: What should I do if I cannot access the Web management page?**
- Make sure that your wireless device has connected to the adapter's network. Or you can also use an Ethernet cable to connect the Ethernet port of the adapter to your computer directly.
 - Verify that setupwifi.net is correctly entered in the Web browser.
 - Make sure the IP address and DNS server address of your configured as AUTO OBTAIN.
 - In case you are setting up as Wireless Access Point Mode, please do not connect the Ethernet port of this adapter to your uplinked router before you finish the initial web page setup.
- Q4: What should I do if the adapter cannot find the WiFi network of my router?**
- Your router may be encrypted with WEP or WPA/WPA (Enterprise) algorithm. Please change the encryption type to **WPA-PSK**, **WPA2-PSK** or **WPA-PSK/WPA2-PSK**, and try scanning again.
 - Please change the WiFi channel of your router and try again.

Manufacturer: Early Sail Technology Co., Limited
 Address: Flat 38, 3/F, Bank Tower, Nos.35-18,353 King's Road, North Point, HongKong
 Website: <https://mywifiassist.com>
 Telephone: +86-13207655053
 Technical Support Email: support@mywifiassist.com

Authorized U.K. Representative Information:
 Name: APEX GC SPECIALISTS LIMITED
 Address: 80 Princess Street, Manchester, M1 4HT, UK
 Contact: Wails
 Telephone No.: 00441616371080
 E-Mail: info@apex-gc.com

For EU/EEFTA, this product can be used in the following countries:

CE
 CE Marking: This is a certified environmental product that has been tested and approved for use in the European Union. It is designed to be safe for the environment and to meet the requirements of the EU Directive 2012/19/EU and 2006/66/EC. It is designed to be safe for the environment and to meet the requirements of the EU Directive 2012/19/EU and 2006/66/EC. It is designed to be safe for the environment and to meet the requirements of the EU Directive 2012/19/EU and 2006/66/EC.

IC
 IC Marking: This is a certified environmental product that has been tested and approved for use in the European Union. It is designed to be safe for the environment and to meet the requirements of the EU Directive 2012/19/EU and 2006/66/EC. It is designed to be safe for the environment and to meet the requirements of the EU Directive 2012/19/EU and 2006/66/EC. It is designed to be safe for the environment and to meet the requirements of the EU Directive 2012/19/EU and 2006/66/EC.

FCC
 FCC Marking: This is a certified environmental product that has been tested and approved for use in the European Union. It is designed to be safe for the environment and to meet the requirements of the EU Directive 2012/19/EU and 2006/66/EC. It is designed to be safe for the environment and to meet the requirements of the EU Directive 2012/19/EU and 2006/66/EC. It is designed to be safe for the environment and to meet the requirements of the EU Directive 2012/19/EU and 2006/66/EC.

70g书写纸 双面单黑 315*630mm 折成品105*90mm