

## BLOCK

小方98三模机械键盘  
Triple Mode Connection Mechanical Keyboard

### 产品规格

按键: 98键, 可插拔机械轴  
多媒体组合键: 13个  
材质: 主体ABS, PC, 键帽PBT  
接口: Type-C  
模式: 2.4G/蓝牙/有线模式  
蓝牙名称: Block98@Lofree  
尺寸: 387x165x40.5mm

### 产品图解

### ① 电量指示灯

充电状态为对应的电量指示灯轮点亮  
75%电量为三颗电量指示灯常亮  
50%电量为两颗电量指示灯常亮  
25%电量为最后一颗电量指示灯常亮  
电量低于20%, 最后一颗电量指示灯闪烁  
电量低于5%, 最后一颗电量指示灯快闪至关机

### ② 蓝牙指示灯

启动蓝牙配对时, 对应的BT1/2/3指示灯进入慢闪, 连接成功后常亮  
切换设备时对应的BT1/2/3指示灯快闪3s, 连接成功后常亮

### ③ 2.4G指示灯

启动2.4G配对时, 对应的2.4G灯慢闪, 连接成功后常亮

### ④ 大小写锁定指示灯

指示灯常亮表示大写模式开启  
指示灯熄灭表示大写模式关闭

### ⑤ Num Lock 数字键区指示灯

指示灯常亮表示数字键区开启  
指示灯熄灭表示数字键区关闭

### ⑥ 模式旋钮开关

OFF: 关闭 CAB: 有线模式 WLS: 无线2.4G及蓝牙模式

### ⑦ 音量旋钮开关

顺时针方向音量小; 逆时针方向音量大  
正面按压静音及非静音切换

### ⑧ 系统切换开关

Windows, Android/Mac, iOS系统 (左右拨档互切)

### ⑨ Type-C接口

充电和有丝连接接口

### ⑩ 键盘脚架支架

调节键盘使用角度 (默认4°, 支架撑起后8°)

### ⑪ 2.4G接收器

### 有线连接模式:

① 将模式切换开关拨动到 CAB 档位

② 取出本产品附赠 Type-C 数据线将键盘与设备进行连接, 即可完成有线连接操作

### 蓝牙连接模式:

① 将模式旋钮开关切换到 WLS 无线档位

② 长按 Fn+1/Fn2/Fn+3 直至对应的 BT 指示灯慢闪

③ 打开设备蓝牙功能, 在蓝牙设备列表中查找并点击连接 "Block98@Lofree"

④ 对应的 BT 指示灯常亮后表示蓝牙模式连接成功

### 2.4G 连接模式:

① 键盘侧面取出 2.4G 接收器

② 将模式旋钮开关切换到 WLS 无线档位

③ 长按 Fn+4 启动 2.4G 连接模式, 对应的 2.4G 灯进入慢闪

④ 将 2.4G 接收器插入设备 USB 接口中, 配对成功后对应的 2.4G 灯常亮

注: Mac 系统设备在 2.4G, USB 连接下不支持多媒体功能。

### 系统切换开关:

① Windows-Android/Mac, iOS 系统互切 (左右拨档)

### 多媒体组合功能键

Fn 右下角 Fn + F1 ..... 为触发多功能键

功能标示	Mac	Windows
Fn+F1	亮度减小	亮度减小
Fn+F2	亮度增加	亮度增加
Fn+F3	多屏显示	多屏显示
Fn+F4	搜索	搜索
Fn+F5	/	截屏
Fn+F6	/	启动计算器
Fn+F7	上一曲	上一曲
Fn+F8	播放/暂停	播放/暂停
Fn+F9	下一曲	下一曲
Fn+F10	静音	静音
Fn+F11	音量减小	音量减小
Fn+F12	音量增加	音量增加
Fn+Opt/Ctrl	/	菜单键

### 背景灯效使用方法 (14 种灯效可切换):

① LFn + ←/→: 切换背景灯效

② 2Fn + ↑/↓: 背景灯光明暗调节

### 产品中有害物质的名称及含量

有害物质	零部件					
	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr(VI))	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
塑胶零件	0	0	0	0	0	0
电路板零件	0	0	0	0	0	0
硅胶零件	0	0	0	0	0	0
金属零件	0	0	0	0	0	0

**EN SPECIFICATIONS:**

Number of keys: 98 (hot-swappable Mechanical Switch)  
Number of Multimedia Keys: 13  
Materials: ABS + PC Body, PBT Keycaps  
Interface: Type-C  
Mode: 2.4G / Bluetooth / Wired  
Bluetooth Name: Block98@Lofree  
Dimensions: 387mm X 165mm X 40.5mm

**Diagram:**

## Lofree

深圳市洛斐客文化有限公司  
Shenzhen Lofree Culture Co., Ltd.  
深圳市宝安区西乡街道宝源路1065号F518时尚创意园F8栋202-F8, F518 Idea Land, 1065 Bao Yuan Road, Shenzhen  
Service Hotline/服务热线: 400602083  
www.lofree.com.cn www.lofree.co  
lofree.co lofreeco lofreeco

### ① Power Indicator

The charging status shows that corresponding indicator lights are on in turn, and 4 indicator lights are always on when fully charged.  
75% power, three indicator lights are always on.  
50% power, two indicator lights are always on.  
25% power, the last indicator light is always on.  
When the power is lower than 5%, the last power indicator flashes quickly to shutdown.

### ② Bluetooth Pairing Indicator

When Bluetooth pairing is started, the corresponding BT1/2/3 indicators will flash slowly, then always on after successful connection.

### ③ 2.4G Wireless Pairing Indicator

When 2.4G pairing is started, the 2.4G indicators will flash slowly, then always on after successful connection.

### ④ Caps Lock Indicator

Solid LED light = The uppercase mode is turned on;  
LED light off = The uppercase mode is turned off.

### ⑤ Num Lock Indicator

Light on means the numeric keypad area is open;  
Light off means the numeric keypad area is off.

### ⑥ Mode Rotary Switch

OFF: Off CAB: Wired mode WLS: Bluetooth and wireless 2.4G mode

### ⑦ Volume Rotary Switch

The volume in the counterclockwise direction is small; The volume in the clockwise direction is large; Press to switch between mute and non-mute.

### ⑧ System Switch

Windows, Android/Mac, iOS system

### ⑨ Type-C Interface

Wired Mode/Charging Mode Interface.

### ⑩ Keyboard Feet

Adjust the keyboard use angle.  
(4° by default, 8° after the keyboard feet are opened)

### ⑪ 2.4G Receiver

### Detailed Operation: Wired Mode:

① Switch to the "CAB" position.

② Take out the Type-C cable that comes with this product, connect the keyboard with device to complete the wired connection.

### Bluetooth Connection Mode:

① Switch to the "WLS" position.

② Long press Fn+1/Fn+2/Fn+3 until the BT indicator light flashes slowly.

③ Turn on the Bluetooth function of your device, search for "Block98@Lofree" and connect.

④ The BT indicator light is always on means successful connection.

### 2.4G Wireless Mode:

① Take out the 2.4G receiver from the side of the keyboard.

② Switch to the "WLS" position.

③ Long press Fn+4 to start the 2.4G connection mode, the corresponding 2.4G light flashes slowly.

④ Insert the 2.4G receiver into the USB port of the device, and the corresponding 2.4G light will always be on after successful connection.

**Note:** MAC/iOS system devices do not support multimedia functions under 2.4G USB connection.

### System Switch:

① Windows, Android/Mac, iOS system.

### Multimedia And Function Keys:

Fn+F1 in the lower right corner...= the multimedia keys.

Function Sign	Mac	Windows
Fn+F1	Screen BR-	Screen BR-
Fn+F2	Screen Screen	Screen BR+
Fn+F3	Multi-Screen	Multi-Screen
Fn+F4	Search	Search
Fn+F5	/	Screenshot
Fn+F6	/	Calculator
Fn+F7	Prev Song	Prev Song
Fn+F8	Play/Pause	Play/Pause
Fn+F9	Next Song	Next Song
Fn+F10	Mute	Mute
Fn+F11	VOL-	VOL-
Fn+F12	VOL+	VOL+
Fn+Opt/Ctrl	/	Menu

### Backlight Usage (14 kinds of lighting effects):

① LFn + ←/→: Switch the backlight effect.

② 2Fn + ↑/↓: Adjustment of backlight brightness.

### NAME AND CONTENT OF HAZARDOUS SUBSTANCES IN PRODUCT:

Hazardous Elements	Hazardous substances					
	Lead (Pb)	Mercury (Hg)	Cadmium (Cd)	Hexavalent Chromium (Cr(VI))	Polybrominated Biphenyls (PBB)	Polybrominated Diphenyl Ethers (PBDE)
Plastic Components	0	0	0	0	0	0
Circuit Board Assembly	0	0	0	0	0	0
Silicone Components	0	0	0	0	0	0
Silicone Parts	0	0	0	0	0	0

This table is prepared in accordance with the provisions of SJ/T 11364. The classification and marking of this product was performed in accordance with the EU directive 2011/65/EU and the revised directive 2015/863/EU.  
0: Indicates that the said hazardous substance contained in all the homogeneous materials for this component is below the limit requirement in GB/T 26572.  
X: Indicates that this hazardous substance contained in at least one of the homogeneous materials used for this part is above the limit requirement in GB/T 26572.

**FCC RF Radiation Exposure Statement:**  
1. This Transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.  
2. This equipment complies with RF radiation exposure limits set forth for an uncontrolled environment.  
This equipment should be installed and operated with minimum distance 5mm between the radiator and your body.

### ENVIRONMENTAL PROTECTION INSTRUCTIONS:

The hazardous substances contained in the electronic parts of this product will not leak or change under normal use conditions for a period of ten years. During this period, the electronic components of this product will not cause serious environmental pollution or serious damage to human health or property while the products are being used by the consumer. According to the Chinese electronic industry standard SJ/T 11364-2014 and related Chinese government regulations, this product and some of its internal or external components may have an environmentally friendly use period mark, depending on the component and component manufacturer, the mark lifespan on the product and its components may vary. The expiration date on the component takes precedence over any conflicted or different UL/FUP (label on the product).

**Warning**  
- If the battery is not replaced properly, there may be leakage or explosion and personal injury hazards. Do not use the battery when there is leakage, discoloration, deformation, or any other abnormality.  
- Do not leave the battery in a discharged or unused state for a long time.  
- Do not short-circuit the product.  
- Battery life varies with usage. Used batteries should be disposed of in accordance with local laws or thrown away in trash cans for recycling electronic devices.  
- If any liquid accidentally enters the product, please immediately disconnect the power supply and remove the product. Continue to use the product may cause fire or electric shock. Please contact the agent or the nearest customer service center for inspection and maintenance.

### FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.  
If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:  
- Reorient or relocate the receiving antenna.  
- Increase the separation between the equipment and receiver.  
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.  
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:  
(1) This device may not cause harmful interference, and (2) This device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.