Product Overview

Product appearance



1. Reserver
2. Light/Distance Sensor
3. LED Indicator
4. Volume
5. Speaker
6. Secondary Microphone
7. Touch display
8. SIM Card Tray
9. Power Button
10. Type C Port
11. Detection Contact
12. Microphone

(LED Indicator:Red - Low Battery; Yellow - Normal; Green - High Battery)

Chargers with an Input: DC 5V ⎓2A are recommended

User Interface

01. Device info
02. Accumulated flow
03. Number of device connections
04. Battery level
05. SIM card signal strength
06. QR code
07. More info

Product Introduction

Brand : GlocalMe

Box Content: Device, User Manual, Micro USB cable

Note: Adaptors (Charging) 100-240V~50/60Hz 0.15A are recommended

Technical Specification :

- LTE FDD: Band 1/2/3/4/5/7/8/9/12/13/17/18/19/20/24/28
- LTE TDD: Band 38/39/40/41
- WCDMA: Band 1/2/4/5/8
- Max Upload Speed: 50Mbps
- Max Download Speed: 150Mbps
- Wi-Fi: IEEE802.11b/g/n
- Screen Size: 0.3 inch
- Number of external SIM cards: one nano SIM card
- Micro USB
- Battery Capacity: 3900mAh (3.85V/15.02Wh)
- Input: DC 5V ⎓2A
- Size: 138*72.2*12 mm
- Weight: 150g (net)

Quick Start Guide

Step 1.Turn on G3

Press the power button for 3 seconds, once it's on, the homepage of G3 is shown as below:

Step 2.

Switch on Wi-Fi on smartphone, connect to the Wi-Fi network of G3 (Wi-Fi name is shown on the homepage), input the Wi-Fi password and enjoy the internet once it's connected.

Quick Start Guide

Powerbank Function

Connect the OTG cable to the USB port (output) of device, and connect the other end to the asset phone, the powerbank will work automatically (the battery level should be above 30%) no matter the device is on or off.

If G3 works properly, while the powerbank does not work, the reasons may be:

1. The OTG cable is not recognized by device. Please try with the original charging cable of device.
2. The OTG cable is not working. Please try with a new charging cable if it still does not work, please contact customer service for warranty.

Local SIM Guide

1. Local SIM is supported by device, which has two SIM slots (both are Nano SIM Slots).
2. Open the SIM card tray with a needle, and insert the SIM card as shown in the picture below. Please contact customer service if any issue encountered.
3. Please remove the PIN of the SIM before you insert the SIM, as the SIMs with PIN are not supported by device.

Quick Start Guide

Tips :

Different SIM Cards: SIM、Micro SIM、Nano SIM, as shown below:

APN Setting

Follow the steps below to set APN for local SIMs on device:

1. Insert the local SIM, and select it in SIM Manager page;
2. Click Local SIM on the homepage;
3. Click "Data Connection" on the top;
4. Click "Access Point Name (APN)" to finish the settings.

FAQ

1. How long does it take to fully charge the Device?
It depends on the electronic current. If you use the charger 2A to charge the phone, it will take four hours to get the phone full charged.

2. How long can it work continuously?
Approximately 20 hours once fully charged.

3. How can I change my Wi-Fi name and password?
Go to "My Hotspot", make changes and save.

4. What should I do if my device is lost or stolen?
Deactivate the device through GlocalMe APP to prevent non-permitted use of your account balance and report the loss to our Customer Service team.

5. How many connections can it support at the same time?
G3 can support up to 5 connections at the same time.

6. How long does it take to connect to the internet once switched on?
It depends on the local network condition, normally it will take 1-2 minutes. If it is used for the first time in a country, it may take up to 10 minutes.

7. Why the signal icon shows 3G even if the device supports 4G?
The GlocalMe service depends on the local operators' network, the 4G network is prioritized. When the 4G signal is weak, the signal will be transferred to 3G.

8. What should I do if it stops responding?
Press the power button for 14 seconds.

9. What should I do if the local SIM doesn't work?
Manually enter the APN of the SIM card ("Sim Manger" -> "APN settings", manually enter the APN info of your SIM card and save.)

For more info, please visit www.glocalme.com

Warning

Specific Absorption Rate (SAR) information. SAR tests are conducted using standard operating positions accepted by the FCC with the device transmitting at its highest certified power level in all tested frequency bands, although the SAR is determined at the highest certified power level, the actual SAR level of the device while operating can be well below the maximum value, in general, the closer you are to a wireless base station antenna, the lower the power output.

Before a new device can be made available for sale to the public, it must be tested and certified by the FCC that it does not exceed the exposure limit established by the FCC. Tests for each device are performed in positions and locations as required by the FCC. For body worn operation, this device has been tested and meets the FCC RF exposure guidelines when used with an accessory designated for this product or when used with an accessory that contains no metal and that positions the device a minimum of 1 cm from the body.

This device complies with part 15 of the FCC Rules. Operation is subjcct to the following two conditions: (1) This device may not cause harmful interference and (2) this device must accept any interference received, including interference that may cause.

Unintered operation Any Changes or modifications not expressly approved by the party responsible for compliance could vcid the user's authority to operate the equipment.

Note: This equipment has been tested and complies with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur during installation. If the device does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is suggested to try to correct the interference by the following measures:

Warning

-Reorient or relocate the receiving antenna.
-Increase the distance between the equipment and receiver.
-Connect the equipment to an outlet on a different circuit to the receiver.
-Consult the manufacturer or an experienced radio/TV technician for help.

Information on the disposal and recycling of the device

This symbol (with or without a solid bar) on the device, batteries (if included), and/or the packaging, indicates that the device and its electrical accessories (forexample, a headset, adapter, or cable) and batteries should not be disposed of as household garbage. These items should not be disposed of as unsorted municipal waste and should be taken to a certified collection point for recycling or proper disposal. For detailed information about device or battery recycling, contact your local city office, household waste disposal service, or retail store. Disposal of the device and batteries (if included) is subject to WEEE Directive Recast (Directive 2012/19/EU) and Battery Directive (Directive 2006/66/EC). The purpose of separating WEEE and batteries from other waste is to minimize the potential environmental impacts and human health risk of any hazardous substances that may be present.

WeChat

SHENZHEN JIYUGUOJIBA NETWORK TECHNOLOGY LIMITED
Room 1-2, 2/F, Block A, Hongwei Ind. Park, Liuxian 1 Road, Bao'an District, Shenzhen, China

Website:www.glocalme.com
Phone Number:+852 3193 2992
E-mail:service@yiguoji8ba.com
Facebook:GlocalMe HK - GlocalMe International
Twitter:@GlocalMeOnline