

版本记录

V1.2,2016-08-10
原始版本







V1.4,2019-06-11
设计, 谢亮亮
1.更新公司LOGO,更新字体为Arial
2.更新待机功耗
3.更新售后电话

V1.5,2021-03-15
设计, 李哲
1.更新公司LOGO样式及版式

V1.5,2021-11-22
1.设计, 黄竹
修改
Power supply:100-240V AC
Rated power consumption:1.5w

正面

← 210.00 mm →

<p>linptech</p> <p>Self-powered Wireless Doorbell User Manual v1.5 Model Number: G4</p> 	<p style="text-align: center;">Quick and Easy Setup</p> <p>STEP 1: Plug the receiver into the socket The receiver will ring and the instruction lights will flash.</p>  <p>Attention: Please place the receiver at least 20 in. above the ground to maximize signal strength.</p> <p>STEP 2: Enjoy it</p>  <p>Press the transmitter and the music will ring and light will flash with the music.</p>	<p style="text-align: center;">Install the transmitter</p> <p>Install the transmitter</p> <p>Option 1 If the wall is clean and flat enough, tape is enough for installation.</p>  <p>①.Paste the 3M double-sided tape on the back of the transmitter. ②.Paste the other side of the double-sided tape on the wall.</p> <p>Option 2 If the surface of the wall is not good enough, use way 2 for installation.</p>  <p>①.Remove the mounting panel from the transmitter using screwdriver. ②.Fix the mounting panel to the wall. ③.Fix the transmitter to the panel.</p> <p>Remove the transmitter</p> <p>You can remove the transmitter from the panel when necessary plug the straight screwdriver into the mouth of the transmitter then turn it 90°, and the transmitter will be separated from the mounting panel on the wall.</p> 
--	--	---

↑ 70.00 mm ↓

反面

<p style="text-align: center;">Adding code/Deleting code</p> <p>The coding has been done before the doorbell out of the factory. You can use it directly without coding. Coding is needed only when you add transmitter or change transmitter. Through coding, one transmitter can match with several receivers or several transmitters can match one receiver.</p> <p style="text-align: center;">Adding code</p> <p>The 1st step: Choose the music. Repeat pressing the music key to choose music until you find your favorite music.</p> <p>The 2nd step: Enter coding model Press the volume key or the music key constantly for at least 3 seconds, the light will flash. (It shows that the receiver has entered into the coding mode and it is waiting for your pressing the transmitter.) Till now, you can release the key of the receiver. At this time: if you still need to change music, you can press the music key to change music. If you want to quit the coding course, you can press the volume key. If no action is done within 30 seconds, the receiver will quit the mode of coding.</p> <p>The 3rd step: Just press the transmitter. At this time, the music that has been chosen by you will ring, it means successful coding. After this, when you press the transmitter, the music that has been chosen by you will ring. Every time you press the transmitter, the music will be the same one, even after sudden power-off.</p> <p style="text-align: center;">Deleting code</p> <p>Press the music key or the volume key constantly at least 10 seconds, until the light flashes 4 times. All the transmitters connected with the receiver will be removed. At this time, if you press the transmitter, the receiver will not react.</p>	<p style="text-align: center;">Product presentation</p> <table style="width: 100%;"> <tr> <td style="width: 50%;"> Dimension : 83mm×46mm×20mm Weight : 45g Frequency : 433.92MHz Distance : outdoors~80m;inside~30m Output power : 10dBm Standby power consumption : 0w Operating pressure : 350g </td> <td style="width: 50%; text-align: center;">Transmitter</td> </tr> <tr> <td> Dimension : 83mm×48mm×23.5mm Weight : 59g Power supply : 100-240V AC Plug : international standard 2 feet Standby power consumption : 0.5w Rated power consumption : 1.5w </td> <td style="text-align: center;">Receiver</td> </tr> </table> <p style="text-align: center;">NO Battery Eco-Friendly</p> <p>wuhan linptech Co.Ltd. is a high-tech company which is supported by Huazhong University of Science and Technology.It looks more like a lab than a company. Our engineers like technology and try their best to develop new,interesting,environmental-friendly and useful products.If you have any suggestion,you are free to contact us.</p> <p style="text-align: center;">PRODUCT OF WUHAN LINPTech</p>	Dimension : 83mm×46mm×20mm Weight : 45g Frequency : 433.92MHz Distance : outdoors~80m;inside~30m Output power : 10dBm Standby power consumption : 0w Operating pressure : 350g	Transmitter	Dimension : 83mm×48mm×23.5mm Weight : 59g Power supply : 100-240V AC Plug : international standard 2 feet Standby power consumption : 0.5w Rated power consumption : 1.5w	Receiver	<p style="text-align: center;">Warranty Card</p> <table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td rowspan="2" style="width: 15%;">Customer information</td> <td style="width: 15%;">Name</td> <td style="width: 15%;"></td> <td style="width: 15%;">Tel</td> <td style="width: 40%;"></td> </tr> <tr> <td>Add</td> <td colspan="4"></td> </tr> <tr> <td>Product type</td> <td colspan="2"></td> <td>Warranty terms</td> <td>1 year</td> </tr> <tr> <td>Fault reason</td> <td colspan="4"></td> </tr> <tr> <td>Purchase time</td> <td colspan="4"></td> </tr> </table> <ol style="list-style-type: none"> 1. The free warranty time of the product is 1year, and you can get maintenance upon your own payment after 1 year. 2. If maintenance is needed, please supply us with effective selling list and complete warranty-card. 3. If the faulty is caused by wrong operation or other wrong maintenance,the warranty is not supplied. 4. The product is out warranty range if it is opened, reinstalled or maintained without our authority. 	Customer information	Name		Tel		Add					Product type			Warranty terms	1 year	Fault reason					Purchase time				
Dimension : 83mm×46mm×20mm Weight : 45g Frequency : 433.92MHz Distance : outdoors~80m;inside~30m Output power : 10dBm Standby power consumption : 0w Operating pressure : 350g	Transmitter																														
Dimension : 83mm×48mm×23.5mm Weight : 59g Power supply : 100-240V AC Plug : international standard 2 feet Standby power consumption : 0.5w Rated power consumption : 1.5w	Receiver																														
Customer information	Name		Tel																												
	Add																														
Product type			Warranty terms	1 year																											
Fault reason																															
Purchase time																															

图纸审核

项目名 ▶ G4门铃说明书英文

印刷工艺 ▶ 四色胶印

物料材质 ▶ 157g铜版纸

料号 ▶ L5-0057

成品尺寸 ▶ 70x70(MM)

成型形式 ▶ 3折页

Caution:

This device complies with Part 15 of the FCC rules and Industry Canada license-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications or change to this equipment. Such modifications or change could void the user's authority to operate the equipment.

This radio transmitter (identify the device by certification number or model number if Category II) has been approved by Industry Canada to operate with the antenna types listed below with the maximum permissible gain indicated. Antenna types not included in this list, having a gain greater than the maximum gain indicated for that type, are strictly prohibited for use with this device.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement.