



Antenna Gain Measurement Report

Project: Nokia G6

- Summary of requirements
 - To provide appropriate antenna gain measurement results to demonstrate compliance
- Test steps:
 - Antenna System Description
 - 6 x dipole type internal antennas and don't have beam steering
 - 2 x 2.4GHz band antennas
 - 2 x dual band(2.4GHz+5GHz) antennas
 - 2 x 5GHz band antennas
 - Measurement Quantity
 - Correlated and uncorrelated directional gain is calculated using the methods shown in slides 5 and 6
 - Measurement Method
 - Use Gain-transfer method
 - Measurement Method
 - CATR (compact antenna test range)
- Antenna Gain Measurement results:
 - Correlated Directional Gain

- 6 x dipole type internal antennas and don't have beam steering
 - 2 x 2.4GHz band antennas
 - 2 x dual band(2.4GHz+5GHz) antennas
 - 2 x 5GHz band antennas

- Antenna system description:
 - A1,A2 - 2.4G band antennas
 - A3,A4 - dual band antennas (2.4GHz+5GHz)
 - A5,A6 - 5G band antennas

Measurement Quantity

- The composite gain is based on FCC document 662911. Part e (ii)

$$DirectionalGain = 10 \cdot \log \left[\frac{\sum_{j=1}^{N_{SS}} \left\{ \sum_{k=1}^{N_{ANT}} g_{j,k} \right\}^2}{N_{ANT}} \right]$$

where

Each antenna is driven by no more than one spatial stream;

N_{SS} = the number of independent spatial streams of data;

N_{ANT} = the total number of antennas

$g_{j,k} = 10^{G_k / 20}$ if the k th antenna is being fed by spatial stream j , or zero if it is not;

G_k is the gain in dBi of the k th antenna.

Reference: FCC document, “Emissions Testing of Transmitters with Multiple Outputs in the Same Band”, 662911 D01 Multiple Transmitter Output v02r01

- The composite gain is based on FCC document 662911. Part d (ii)

d) *Unequal antenna gains, with equal transmit powers.* For antenna gains given by G_1, G_2, \dots, G_N dBi

(ii) If all transmit signals are *completely uncorrelated*, then

$$\text{Directional gain} = 10 \log[(10^{G_1/10} + 10^{G_2/10} + \dots + 10^{G_N/10})/N_{\text{ANT}}] \text{ dBi}$$

Reference: FCC document, “Emissions Testing of Transmitters with Multiple Outputs in the Same Band”, 662911 D01 Multiple Transmitter Output v02r01

Measurement Method

- Use Gain-transfer method to perform directional gain measurement.

Measurement Environment

- CATR (Compact antenna test range)
 - MVG Satimo SG24 chamber
 - LxWxH : 5mx5mx5m
 - Measurement Frequency Range: 600MHz-6000MHz



Beamforming Gain

2.4G Non-Beamforming

Antenna Gain/ dBi	2400 GHz				2450 GHz				2490 GHz			
	A1	A2	A3	A4	A1	A2	A3	A4	A1	A2	A3	A4
	2.75	3.04	2.24	3.78	2.92	2.41	2.07	3.32	3.56	2.49	2.09	3.28
Power Direction Gain (the maximum individual antenna gain)	3.78				3.32				3.56			
PSD Direction Gain (direction gain)	5.90				5.80				5.80			

5G Non-Beamforming

Antenna Gain/ dBi	5200 GHz				5500 GHz				5800 GHz			
	A3	A4	A5	A6	A3	A4	A5	A6	A3	A4	A5	A6
	3.37	4.54	3.24	3.97	3.71	3.24	3.25	4.08	3.61	2.89	4.37	4.69
Power Direction Gain (the maximum individual antenna gain)	4.54				4.08				4.69			
PSD Direction Gain (direction gain)	5.90				5.90				5.90			

2.4G Beamforming

	2400 GHz	2450 GHz	2490 GHz
Power Direction Gain (the maximum individual antenna gain)	3.78	3.32	3.56
PSD Direction Gain (direction gain)	5.90	5.80	5.80

5G Beamforming

	5200 GHz	5500 GHz	5800 GHz
Power Direction Gain (the maximum individual antenna gain)	4.54	4.08	4.69
PSD Direction Gain (direction gain)	5.90	5.90	5.90