

Bluetooth keyboard Manual


Package Contents

- 1.Ultra-slim Bluetooth keyboard
- 2.Micro-USB charging cable
- 3.User manual













Specifications
















| | |
|--------------------------|-------------------|
| Bluetooth Specification | Broadcom 3.0 chip |
| Dimensions | 247x150x6.5mm |
| Operating Range | Up to 10 meters |
| Modulation System | GFSK |
| Stand-by time | 60 days |
| Charge time | 4 hours |
| Uninterrupted Work Time | 44 hours |
| Lithium Battery Capacity | 110 mAh |
| Lithium Battery Life | 3 years |
| Key Life | 3 million clicks |

Led Display

| | |
|--|---|
| CAPS | Lights blue when CAPS-lock is active |
|  | Will flash blue (3min. long) after pressing the "Connect" button until a BT connection is established. It disappears when connected. |
| Charge | Lights red when the keyboard is charging. Turns off when the battery is fully charged. Flashes red, when the battery is weak and should be charged. |
| Power | Lights up blue for about 4 sec when being turned on. |

Function Keys

| | | | | | |
|--|------------|---|------------|---|----------------|
|  | Back |  | Home |  | Lock |
|  | Copy |  | Paste |  | Cut |
|  | Select All |  | Mute |  | Volume down |
|  | Volume up |  | Play/pause |  | Previous track |

| | | | | | |
|--|------------------|---|-----------------|---|------------------|
|  | Next track |  | Menu |  | Web browser |
|  | Decrease |  | Increase |  | Virtual keyboard |
|  | Calculator |  | Desktop |  | Taskbar |
|  | Application Menu | lang | switch Language |  | map |
|  | voice search |  | Play |  | Settings |
|  | Email | | | | |

SPECIAL NOTE:

- 1.This keyboard doesn't support the Nokia Mobile.**
- 2. For Android users: The Caps Lock indicator may not light, but will still function normally.**

Pairing keyboard method

Pairing with Tablets ,Laptops,Cellphones

- Step 1: Turn on the keyboard’s power button .The blue status light will light for 4 seconds and then shut off.
- Step 2: Press the connect button, the Bluetooth indicator light will be blinking blue.
- Step 3: Go to your “SETTINGS”screen on your tablets with Bluetooth –enabled device, activate its Bluetooth function and search for the keyboard device.
- Step 4: Once the “Bluetooth 3.0 keyboard” has been found, select its name to connect.
- Step 5: Enter the password code as displayed on the screen.
- Step 6: Once the Bluetooth keyboard has successfully connected to your device, the Bluetooth indicator will turn off.

SPECIAL NOTE:

- 1. Only one device can be actively paired at one time.**
- 2. For other Bluetooth enabled device, please verify the Bluetooth Standard&compatibility before attempting to connect to the keyboard.**
- 3. After pairing for the first time, your device will connect to the keyboard automatically when opening the keyboard.**
- 4. In case of connect failure, delete the pairing record from your device, and try the above procedures again.**

Power Saving Mode

The keyboard will enter sleep mode after being idle for 15 minutes.To active it, press any key and wait for 3 seconds.

Charging

When the battery is low, the battery indicator will turn red. If there is no light displayed at all, the battery is completely drained. For both situations, it is time to charge the keyboard.

To charge the keyboard, plug the USB charging cable (Micro-USB) into the keyboard charging port. Plug the USB end of the charging cable into either a USB AC adapter or USB port on your computer.

The keyboard will be fully charged in approximately 4 hours. The battery indicator will turn off when the keyboard is fully charged.

NOTE: You can use the keyboard while charging.

Caution

When not in use for a prolonged period of time, it is recommended that you turn off the keyboard to lengthen the battery life.

FCC Warning:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.

- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

RF Exposure Statement

This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment.