





材质: 157G双铜, 规格: 单页尺寸, 90*150 双面彩色印刷, 折页

<p>ARTECK™</p> <p>User Manual</p> <p>Arteck K730 Wireless Keyboard</p>  <p>ROHS CE FCC 2014-420181</p> <p>2 Years Warranty Claim Email: support@arteck.com</p>	<p>Welcome</p> <p>Thank you for choosing this Arteck K730 wireless keyboard. To ensure optimum performance and safety, please read these instructions carefully before operating this product. It is strongly recommended you keep the manual for future reference.</p> <p>Product Specifications</p> <table border="1"> <tr><td>Wireless Specification</td><td>2.4G USB Wireless</td></tr> <tr><td>Operating Range</td><td>Up to 10 Meters</td></tr> <tr><td>Modulating System</td><td>GFSK</td></tr> <tr><td>Operating Voltage</td><td>3.0-4.2V</td></tr> <tr><td>Operating Current</td><td><2.0mA</td></tr> <tr><td>Standby Current</td><td>0.2mA</td></tr> <tr><td>Sleeping Current</td><td><10uA</td></tr> <tr><td>Standby Time</td><td>>200 days</td></tr> <tr><td>Uninterrupted Working Time</td><td>>250 hours</td></tr> <tr><td>Battery Type</td><td>AAA batteries</td></tr> <tr><td>Key Strength</td><td>50-80g</td></tr> <tr><td>Key Life</td><td>3 million strokes</td></tr> <tr><td>Operating Temperature</td><td>-10 ~ 50°C</td></tr> </table> <p>Package Contents:</p> <ul style="list-style-type: none"> Arteck K730 Wireless Keyboard *1 USB nano 2.4G receiver *1 AAA Battery (installed at the battery holder at the back of keyboard) *1 User manual *1 	Wireless Specification	2.4G USB Wireless	Operating Range	Up to 10 Meters	Modulating System	GFSK	Operating Voltage	3.0-4.2V	Operating Current	<2.0mA	Standby Current	0.2mA	Sleeping Current	<10uA	Standby Time	>200 days	Uninterrupted Working Time	>250 hours	Battery Type	AAA batteries	Key Strength	50-80g	Key Life	3 million strokes	Operating Temperature	-10 ~ 50°C	<p>Getting Started Guide</p> <p>1. Product Overview</p>   <ol style="list-style-type: none"> ① Power Indicator: Lights up green for about 3 sec when being power on ② Low Battery Warning: Red light will be flashing when the battery is running out. ③ CAPS Lock Indicator: Green light on when CAPS lock is on. ④ Number Lock Indicator: Green light on when number lock is on. ⑤ Nano 2.4G USB Receiver Storage Box ⑥ Foldable raised stand legs 	<p>2. Function Keys</p>  <p>Fn Lock Key</p> <p>The default function of the F1-F12 will be above media functions. If you like to have the F1-F12 as default function, you can press Fn+Esc to turn on the Fn lock function. Press Fn+Esc again to turn off the function.</p> <p>Steps of Pairing the Keyboard with Your Computer</p> <p>Step 1: Peel off the plastic sheet isolator from the battery if there is.</p> <p>Step 2: Insert the USB receiver to the port of your computer. It will pair to the keyboard automatically. You are able to type the keyboard right now.</p> <p>Notice: If you are not able to connect the keyboard to your computer, please kindly change to another USB port and make sure that the USB receiver plug to the end of the USB port. If above doesn't solve, please kindly contact with support@arteck.com for assistance. We will solve your issue with 100% satisfactory solution.</p> <p>Troubleshooting</p> <ol style="list-style-type: none"> 1. Make sure the keyboard is in operating distance (within 10 meters). 2. Ensure the battery storage has power. 3. Make sure the USB receiver is plugged to the end of USB port. 	<p>⚠Caution:</p> <ol style="list-style-type: none"> 1. When not in use for a prolonged period, it is recommended that you take off the battery to lengthen the battery life. 2. When the power status light flash, it is recommended that changing the battery in 2 hours. <p>Energy-saving Sleep Mode</p> <p>Keyboard's long life battery lasts for several months of normal use. The keyboard will go into sleep mode not being used in several minutes, press any key and wait a second or two to bring it out of sleep mode.</p> <p>⚠ Safety Caution</p> <ol style="list-style-type: none"> 1. Keep the item away from sharp objects. 2. Do not place heavy object on the keyboard. 3. Away from microwave items. 4. Do not force or distorted the keyboard. 5. Keep away from oil, chemical or other organic liquid. <p>♻️ Disposal of Waste Batteries</p> <p>Insert screwdriver between plastic top and metal case at keyboard top or bottom and Pry up plastic top and remove it completely. This action destroys keyboard separate battery from circuit board, it is your responsible to hand this over to an applicable collection and recycling will help to conserve natural resources and prevent potential negative consequences for human health and the environment due to the possible presence of hazardous in batteries and electrical and electronic equipment.</p> <p>Warranty</p> <p>Our company provides customers with a warranty of 24 months from the date of purchase.</p> <p>Contact Us</p> <p>For any inquires or comments concerning our products, please send an email to support@arteck.com, and we will respond to you as soon as possible. If there is any quality-related issue with the product, you may request a replacement or refund by submitting a request to support@arteck.com.</p>
Wireless Specification	2.4G USB Wireless																													
Operating Range	Up to 10 Meters																													
Modulating System	GFSK																													
Operating Voltage	3.0-4.2V																													
Operating Current	<2.0mA																													
Standby Current	0.2mA																													
Sleeping Current	<10uA																													
Standby Time	>200 days																													
Uninterrupted Working Time	>250 hours																													
Battery Type	AAA batteries																													
Key Strength	50-80g																													
Key Life	3 million strokes																													
Operating Temperature	-10 ~ 50°C																													

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in residential installation. This equipment generates uses and can radiate radiofrequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:- Reorient or relocate the receiving antenna.- Increase the separation between the equipment and receiver.-Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.-Consult the dealer or an experienced radio/TV technician for help. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:(1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.