

## RF EXPOSURE EVALUATION METHOD

### SAR Test Exclusion Thresholds for 100 MHz – 6 GHz and $\leq 50$ mm

Approximate SAR Test Exclusion Power Thresholds at Selected Frequencies and Test Separation Distances are illustrated in the following Table.

| MHz  | 5  | 10 | 15  | 20  | 25  | mm                                      |
|------|----|----|-----|-----|-----|---|
| 150  | 39 | 77 | 116 | 155 | 194 | SAR Test<br>Exclusion<br>Threshold (mW) |
| 300  | 27 | 55 | 82  | 110 | 137 |   |
| 450  | 22 | 45 | 67  | 89  | 112 |   |
| 835  | 16 | 33 | 49  | 66  | 82  |   |
| 900  | 16 | 32 | 47  | 63  | 79  |   |
| 1500 | 12 | 24 | 37  | 49  | 61  |   |
| 1900 | 11 | 22 | 33  | 44  | 54  |   |
| 2450 | 10 | 19 | 29  | 38  | 48  |   |
| 3600 | 8  | 16 | 24  | 32  | 40  |   |
| 5200 | 7  | 13 | 20  | 26  | 33  |   |
| 5400 | 6  | 13 | 19  | 26  | 32  |   |
| 5800 | 6  | 12 | 19  | 25  | 31  |   |

The 1-g and 10-g SAR test exclusion thresholds for 100 MHz to 6 GHz at test separation distances  $\leq 50$  mm are determined by:

$[(\text{max. power of channel, including tune-up tolerance, mW}) / (\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] \leq 3.0$  for 1-g SAR and  $\leq 7.5$  for 10-g extremity SAR, where  $f(\text{GHz})$  is the RF channel transmit frequency in GHz

Power and distance are rounded to the nearest mW and mm before calculation

The result is rounded to one decimal place for comparison

The test exclusions are applicable only when the minimum test separation distance is  $\leq 50$  mm and for transmission frequencies between 100 MHz and 6 GHz. When the minimum test separation distance is  $< 5$  mm, a distance of 5 mm is applied to determine SAR test exclusion.

Maximum measured transmitter power.

BT The Worst Case

| Mode           | frequency | Maximum Peak<br>Conducted Output Power | Tune up tolerance |
|----------------|-----------|--|-------------------|
|                | GHz       | dBm                                    | dBm               |
| GFSK           | 2.480     | 5.12                                   | 5±1               |
| $\pi/4$ -DQPSK | 2.480     | 4.52                                   | 4±1               |
| 8DPSK          | 2.441     | 4.48                                   | 4±1               |

Remark: The worst case gain of the antenna is 0dBi.

0dBi logarithmic terms convert to numeric result is nearly 1

Tune up Power<sub>(2480)</sub> = 3.981mW

Tune up Power<sub>(2480)</sub> = 3.162mW

Tune up Power<sub>(2441)</sub> = 3.162mW

$[(\text{GFSK power of channel, including tune-up tolerance, mW})/(\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] = 3.981/5 \cdot \sqrt{2.480} = 1.254 \leq 3.0$

$[(\pi/4\text{-DQPSK power of channel, including tune-up tolerance, mW})/(\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] = 3.162/5 \cdot \sqrt{2.480} = 0.996 \leq 3.0$

$[(8\text{DPSK power of channel, including tune-up tolerance, mW})/(\text{min. test separation distance, mm})] \cdot [\sqrt{f(\text{GHz})}] = 3.162/5 \cdot \sqrt{2.441} = 0.988 \leq 3.0$

Threshold at which no SAR required is  $1.254 \leq 3.0$  for 1-g SAR, Separation distance is 5mm.

Threshold at which no SAR required is  $0.996 \leq 3.0$  for 1-g SAR, Separation distance is 5mm.

Threshold at which no SAR required is  $0.988 \leq 3.0$  for 1-g SAR, Separation distance is 5mm.