

**Appendix A:Maximum Transmitter Power**

Operation Mode	Modulation Type	Test Channel	Measured Power(dBm)	Measured Power(W)	Rated Power(W)	Percentage (%)	Limit (%)	Result
TX-DNH	4FSK	CH _L	37.7	5.91	5.00	18.2	±20	PASS
TX-DNH	4FSK	CH _{M1}	37.5	5.62	5.00	12.5	±20	PASS
TX-DNH	4FSK	CH _{M2}	36.3	4.28	5.00	-14.3	±20	PASS
TX-DNH	4FSK	CH _{M3}	37.6	5.75	5.00	15.1	±20	PASS
TX-DNH	4FSK	CH _H	37.1	5.09	5.00	1.8	±20	PASS
TX-DNL	4FSK	CH _L	31.8	1.53	1.50	1.9	±20	PASS
TX-DNL	4FSK	CH _{M1}	32.3	1.71	1.50	13.7	±20	PASS
TX-DNL	4FSK	CH _{M2}	32.3	1.70	1.50	13.5	±20	PASS
TX-DNL	4FSK	CH _{M3}	32.3	1.70	1.50	13.2	±20	PASS
TX-DNL	4FSK	CH _H	32.1	1.62	1.50	8.3	±20	PASS
TX-ANH	FM	CH _L	37.0	5.00	5.00	0.0	±20	PASS
TX-ANH	FM	CH _{M1}	37.1	5.15	5.00	3.0	±20	PASS
TX-ANH	FM	CH _{M2}	37.1	5.14	5.00	2.9	±20	PASS
TX-ANH	FM	CH _{M3}	37.1	5.18	5.00	3.6	±20	PASS
TX-ANH	FM	CH _H	37.0	5.06	5.00	1.3	±20	PASS
TX-ANL	FM	CH _L	31.7	1.49	1.50	-0.4	±20	PASS
TX-ANL	FM	CH _{M1}	32.2	1.68	1.50	11.8	±20	PASS
TX-ANL	FM	CH _{M2}	32.3	1.68	1.50	12.3	±20	PASS
TX-ANL	FM	CH _{M3}	31.9	1.55	1.50	3.1	±20	PASS
TX-ANL	FM	CH _H	32.5	1.79	1.50	19.7	±20	PASS

**Appendix B:Occupied Bandwidth**

Operation Mode	Modulation Type	Test Channel	Occupied Bandwidth		99% Limit(kHz)	Result
			99%(kHz)	26dB(kHz)		
TX-DNH	4FSK	CH _L	7.680	9.734	≤11.25	PASS
TX-DNH	4FSK	CH _{M1}	7.766	9.568	≤11.25	PASS
TX-DNH	4FSK	CH _{M2}	7.729	9.999	≤11.25	PASS
TX-DNH	4FSK	CH _{M3}	7.748	10.310	≤11.25	PASS
TX-DNH	4FSK	CH _H	7.528	9.823	≤11.25	PASS
TX-DNL	4FSK	CH _L	7.764	9.761	≤11.25	PASS
TX-DNL	4FSK	CH _{M1}	7.691	10.060	≤11.25	PASS
TX-DNL	4FSK	CH _{M2}	7.793	10.060	≤11.25	PASS
TX-DNL	4FSK	CH _{M3}	7.759	9.886	≤11.25	PASS
TX-DNL	4FSK	CH _H	7.617	9.897	≤11.25	PASS
TX-ANH	FM	CH _L	5.288	10.120	≤11.25	PASS
TX-ANH	FM	CH _{M1}	5.288	10.120	≤11.25	PASS
TX-ANH	FM	CH _{M2}	5.287	10.120	≤11.25	PASS
TX-ANH	FM	CH _{M3}	5.221	10.110	≤11.25	PASS
TX-ANH	FM	CH _H	5.186	10.090	≤11.25	PASS
TX-ANL	FM	CH _L	5.263	10.130	≤11.25	PASS
TX-ANL	FM	CH _{M1}	2.288	10.120	≤11.25	PASS
TX-ANL	FM	CH _{M2}	5.283	10.120	≤11.25	PASS
TX-ANL	FM	CH _{M3}	5.204	10.110	≤11.25	PASS
TX-ANL	FM	CH _H	5.181	10.080	≤11.25	PASS



Appendix B:Occupied Bandwidth

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT
TX-DNH	4FSK	CH _L	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 400.012500 MHz Center Freq: 400.012500 MHz #Res BW 100 Hz #VBW 300 Hz Span 50 kHz Sweep FFT Occupied Bandwidth 7.680 kHz Total Power 43.8 dBm Transmit Freq Error 31 Hz OBW Power 99.00 % x dB Bandwidth 9.734 kHz x dB -26.00 dB</p>
TX-DNH	4FSK	CH _{M1}	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 405.987500 MHz Center Freq: 405.987500 MHz #Res BW 100 Hz #VBW 300 Hz Span 50 kHz Sweep FFT Occupied Bandwidth 7.769 kHz Total Power 43.9 dBm Transmit Freq Error -20 Hz OBW Power 99.00 % x dB Bandwidth 9.568 kHz x dB -26.00 dB</p>
TX-DNH	4FSK	CH _{M2}	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 406.112500 MHz Center Freq: 406.112500 MHz #Res BW 100 Hz #VBW 300 Hz Span 50 kHz Sweep FFT Occupied Bandwidth 7.729 kHz Total Power 43.9 dBm Transmit Freq Error -65 Hz OBW Power 99.00 % x dB Bandwidth 9.999 kHz x dB -26.00 dB</p>



Appendix B:Occupied Bandwidth

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT
TX-DNH	4FSK	CH _{M3}	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 438.012500 MHz Center Freq: 438.012500 MHz Trig: Free Run #Atten: 24 dB #Gain: Low #Res BW: 100 Hz #VBW: 300 Hz Span: 50 kHz Sweep: FFT Ref: 40.76 dBm Occupied Bandwidth: 7.748 kHz Total Power: 43.8 dBm Transmit Freq Error: 34 Hz OBW Power: 99.00 % x dB Bandwidth: 10.31 kHz x dB: -26.00 dB Status: DC Coupled</p>
TX-DNH	4FSK	CH _H	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 469.987500 MHz Center Freq: 469.987500 MHz Trig: Free Run #Atten: 24 dB #Gain: Low #Res BW: 100 Hz #VBW: 300 Hz Span: 50 kHz Sweep: FFT Ref: 40.93 dBm Occupied Bandwidth: 7.528 kHz Total Power: 43.7 dBm Transmit Freq Error: -36 Hz OBW Power: 99.00 % x dB Bandwidth: 9.823 kHz x dB: -26.00 dB Status: DC Coupled</p>
TX-DNL	4FSK	CH _L	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 400.012500 MHz Center Freq: 400.012500 MHz Trig: Free Run #Atten: 20 dB #Gain: Low #Res BW: 100 Hz #VBW: 300 Hz Span: 50 kHz Sweep: FFT Ref: 36.23 dBm Occupied Bandwidth: 7.764 kHz Total Power: 37.6 dBm Transmit Freq Error: 49 Hz OBW Power: 99.00 % x dB Bandwidth: 9.761 kHz x dB: -26.00 dB Status: DC Coupled</p>



Appendix B:Occupied Bandwidth

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT
TX-DNL	4FSK	CH _{M1}	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 405.987500 MHz Center Freq: 405.987500 MHz Span 50 kHz #Res BW 100 Hz #VBW 300 Hz Occupied Bandwidth 7.691 kHz Total Power 38.2 dBm Transmit Freq Error -2 Hz x dB Bandwidth 10.06 kHz OBW Power 99.00 % x dB -26.00 dB</p>
TX-DNL	4FSK	CH _{M2}	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 406.112500 MHz Center Freq: 406.112500 MHz Span 50 kHz #Res BW 100 Hz #VBW 300 Hz Occupied Bandwidth 7.793 kHz Total Power 38.0 dBm Transmit Freq Error -14 Hz x dB Bandwidth 10.16 kHz OBW Power 99.00 % x dB -26.00 dB</p>
TX-DNL	4FSK	CH _{M3}	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 438.012500 MHz Center Freq: 438.012500 MHz Span 50 kHz #Res BW 100 Hz #VBW 300 Hz Occupied Bandwidth 7.759 kHz Total Power 38.4 dBm Transmit Freq Error -30 Hz x dB Bandwidth 9.886 kHz OBW Power 99.00 % x dB -26.00 dB</p>



Appendix B:Occupied Bandwidth

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT
TX-DNL	4FSK	CH _H	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 469.987500 MHz Center Freq: 469.987500 MHz Trig: Free Run #Att: 20 dB Avg/Hold: >10/10 Radio Std: None Radio Device: BTS</p> <p>10 dB/div Ref 36.76 dBm Log 30.1 16.8 3.24 -9.2 -32.2 -43.2 -53.2</p> <p>Center 470 MHz #Res BW 100 Hz #VBW 300 Hz Span 50 kHz Sweep FFT</p> <p>Occupied Bandwidth 7.617 kHz Total Power 39.4 dBm</p> <p>Transmit Freq Error -9 Hz x dB Bandwidth 9.897 kHz OBW Power 99.00 % x dB -26.00 dB</p> <p>MISC STATUS DC Coupled</p>
TX-ANH	FM	CH _L	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 400.012500 MHz Center Freq: 400.012500 MHz Trig: Free Run #Att: 24 dB Avg/Hold: >10/10 Radio Std: None Radio Device: BTS</p> <p>10 dB/div Ref 40.05 dBm Log 30.1 10.1 0.050 -30.0 -40.0 -60.0</p> <p>Center 400 MHz #Res BW 100 Hz #VBW 300 Hz Span 50 kHz Sweep FFT</p> <p>Occupied Bandwidth 5.288 kHz Total Power 36.1 dBm</p> <p>Transmit Freq Error -228 Hz x dB Bandwidth 10.12 kHz OBW Power 99.00 % x dB -26.00 dB</p> <p>MISC STATUS DC Coupled</p>
TX-ANH	FM	CH _{M1}	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 405.987500 MHz Center Freq: 405.987500 MHz Trig: Free Run #Att: 24 dB Avg/Hold: >10/10 Radio Std: None Radio Device: BTS</p> <p>10 dB/div Ref 40.20 dBm Log 30.2 10.2 0.200 -39.8 -49.8</p> <p>Center 406 MHz #Res BW 100 Hz #VBW 300 Hz Span 50 kHz Sweep FFT</p> <p>Occupied Bandwidth 5.288 kHz Total Power 36.3 dBm</p> <p>Transmit Freq Error -227 Hz x dB Bandwidth 10.12 kHz OBW Power 99.00 % x dB -26.00 dB</p> <p>MISC STATUS DC Coupled</p>



Appendix B:Occupied Bandwidth

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT
TX-ANH	FM	CH _{M2}	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 406.112500 MHz Center Freq: 406.112500 MHz Trig: Free Run #Att: 24 dB Avg/Hold: >10/10 Radio Device: BTS Frequency: 406.112500 MHz Center Freq: 406.112500 MHz Ref: 40.20 dBm Span: 50 kHz Sweep: FFT #Res BW: 100 Hz #VBW: 300 Hz Occupied Bandwidth: 5.287 kHz Total Power: 36.3 dBm Transmit Freq Error: -228 Hz OBW Power: 99.00 % x dB Bandwidth: 10.12 kHz x dB: -26.00 dB Status: DC Coupled</p>
TX-ANH	FM	CH _{M3}	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 438.012500 MHz Center Freq: 438.012500 MHz Trig: Free Run #Att: 24 dB Avg/Hold: >10/10 Radio Device: BTS Frequency: 438.012500 MHz Center Freq: 438.012500 MHz Ref: 39.93 dBm Span: 50 kHz Sweep: FFT #Res BW: 100 Hz #VBW: 300 Hz Occupied Bandwidth: 5.221 kHz Total Power: 35.9 dBm Transmit Freq Error: -250 Hz OBW Power: 99.00 % x dB Bandwidth: 10.11 kHz x dB: -26.00 dB Status: DC Coupled</p>
TX-ANH	FM	CH _H	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 469.987500 MHz Center Freq: 469.987500 MHz Trig: Free Run #Att: 24 dB Avg/Hold: >10/10 Radio Device: BTS Frequency: 469.987500 MHz Center Freq: 469.987500 MHz Ref: 39.85 dBm Span: 50 kHz Sweep: FFT #Res BW: 100 Hz #VBW: 300 Hz Occupied Bandwidth: 5.186 kHz Total Power: 36.0 dBm Transmit Freq Error: -221 Hz OBW Power: 99.00 % x dB Bandwidth: 10.09 kHz x dB: -26.00 dB Status: DC Coupled</p>



Appendix B:Occupied Bandwidth

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT
TX-ANL	FM	CH _L	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 400.012500 MHz Center Freq: 400.012500 MHz #Res BW 100 Hz #VBW 300 Hz Span 50 kHz Sweep FFT Occupied Bandwidth 5.263 kHz Total Power 30.7 dBm Transmit Freq Error -243 Hz OBW Power 99.00 % x dB Bandwidth 10.13 kHz x dB -26.00 dB</p>
TX-ANL	FM	CH _{M1}	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 405.987500 MHz Center Freq: 405.987500 MHz #Res BW 100 Hz #VBW 300 Hz Span 50 kHz Sweep FFT Occupied Bandwidth 5.288 kHz Total Power 31.3 dBm Transmit Freq Error -228 Hz OBW Power 99.00 % x dB Bandwidth 10.12 kHz x dB -26.00 dB</p>
TX-ANL	FM	CH _{M2}	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 406.112500 MHz Center Freq: 406.112500 MHz #Res BW 100 Hz #VBW 300 Hz Span 50 kHz Sweep FFT Occupied Bandwidth 5.283 kHz Total Power 31.3 dBm Transmit Freq Error -232 Hz OBW Power 99.00 % x dB Bandwidth 10.12 kHz x dB -26.00 dB</p>



Appendix B:Occupied Bandwidth

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT
TX-ANL	FM	CH _{M3}	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 438.012500 MHz Center Freq: 438.012500 MHz Trig: Free Run #Att: 18 dB Ref 34.87 dBm 10 dB/div Log Center 438 MHz #Res BW 100 Hz #VBW 300 Hz Span 50 kHz Sweep FFT Occupied Bandwidth 5.204 kHz Total Power 30.9 dBm Transmit Freq Error -282 Hz OBW Power 99.00 % x dB Bandwidth 10.11 kHz x dB -26.00 dB STATUS DC Coupled</p>
TX-ANL	FM	CH _H	<p>Agilent Spectrum Analyzer - Occupied BW Center Freq 469.987500 MHz Center Freq: 469.987500 MHz Trig: Free Run #Att: 18 dB Ref 35.19 dBm 10 dB/div Log Center 470 MHz #Res BW 100 Hz #VBW 300 Hz Span 50 kHz Sweep FFT Occupied Bandwidth 5.181 kHz Total Power 31.1 dBm Transmit Freq Error -266 Hz OBW Power 99.00 % x dB Bandwidth 10.08 kHz x dB -26.00 dB STATUS DC Coupled</p>



Appendix C:Emission Mask

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT
TX-DNH	4FSK	CH _L	
TX-DNH	4FSK	CH _{M1}	
TX-DNH	4FSK	CH _{M2}	



Appendix C:Emission Mask

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT
TX-DNH	4FSK	CH _{M3}	
TX-DNH	4FSK	CH _H	
TX-DNL	4FSK	CH _L	



Appendix C:Emission Mask

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT
TX-DNL	4FSK	CH _{M1}	
TX-DNL	4FSK	CH _{M2}	
TX-DNL	4FSK	CH _{M3}	



Appendix C:Emission Mask

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT																																																															
TX-DNL	4FSK	CH _H																																																																
TX-ANH	FM	CH _L	<table border="1" data-bbox="596 1232 1117 1388"> <thead> <tr> <th>Start Freq</th> <th>Stop Freq</th> <th>Integ BW</th> <th>dBm</th> <th>Lower ΔLim(dB)</th> <th>Freq (Hz)</th> <th>Peak dBm</th> <th>Upper ΔLim(dB)</th> <th>Freq (Hz)</th> </tr> </thead> <tbody> <tr> <td>0.0 Hz</td> <td>5.625 kHz</td> <td>100.0 Hz</td> <td>35.41</td> <td>(-2.18)</td> <td>-250.0</td> <td>27.71</td> <td>(-9.68)</td> <td>2.250 k</td> </tr> <tr> <td>5.625 kHz</td> <td>12.50 kHz</td> <td>100.0 Hz</td> <td>-34.99</td> <td>(-1.07)</td> <td>-12.40 k</td> <td>-35.29</td> <td>(-2.89)</td> <td>12.30 k</td> </tr> <tr> <td>12.50 kHz</td> <td>60.00 kHz</td> <td>100.0 Hz</td> <td>-34.77</td> <td>(-14.77)</td> <td>-12.70 k</td> <td>-33.86</td> <td>(-13.86)</td> <td>15.00 k</td> </tr> <tr> <td>4.000 MHz</td> <td>8.000 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> <tr> <td>8.000 MHz</td> <td>12.50 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> <tr> <td>12.50 MHz</td> <td>15.00 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> </tbody> </table>	Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Freq (Hz)	Peak dBm	Upper ΔLim(dB)	Freq (Hz)	0.0 Hz	5.625 kHz	100.0 Hz	35.41	(-2.18)	-250.0	27.71	(-9.68)	2.250 k	5.625 kHz	12.50 kHz	100.0 Hz	-34.99	(-1.07)	-12.40 k	-35.29	(-2.89)	12.30 k	12.50 kHz	60.00 kHz	100.0 Hz	-34.77	(-14.77)	-12.70 k	-33.86	(-13.86)	15.00 k	4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	—	(—)	—	8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	—	(—)	—	12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	—	(—)	—
Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Freq (Hz)	Peak dBm	Upper ΔLim(dB)	Freq (Hz)																																																										
0.0 Hz	5.625 kHz	100.0 Hz	35.41	(-2.18)	-250.0	27.71	(-9.68)	2.250 k																																																										
5.625 kHz	12.50 kHz	100.0 Hz	-34.99	(-1.07)	-12.40 k	-35.29	(-2.89)	12.30 k																																																										
12.50 kHz	60.00 kHz	100.0 Hz	-34.77	(-14.77)	-12.70 k	-33.86	(-13.86)	15.00 k																																																										
4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
TX-ANH	FM	CH _L	<table border="1" data-bbox="596 1814 1117 1971"> <thead> <tr> <th>Start Freq</th> <th>Stop Freq</th> <th>Integ BW</th> <th>dBm</th> <th>Lower ΔLim(dB)</th> <th>Freq (Hz)</th> <th>Peak dBm</th> <th>Upper ΔLim(dB)</th> <th>Freq (Hz)</th> </tr> </thead> <tbody> <tr> <td>0.0 Hz</td> <td>5.625 kHz</td> <td>100.0 Hz</td> <td>36.70</td> <td>(-0.89)</td> <td>-200.0</td> <td>-20.98</td> <td>(-58.57)</td> <td>150.0</td> </tr> <tr> <td>5.625 kHz</td> <td>12.50 kHz</td> <td>100.0 Hz</td> <td>-32.45</td> <td>(-3.69)</td> <td>-11.80 k</td> <td>-37.78</td> <td>(-5.74)</td> <td>12.25 k</td> </tr> <tr> <td>12.50 kHz</td> <td>60.00 kHz</td> <td>1.000 MHz</td> <td>-36.15</td> <td>(-16.15)</td> <td>-16.65 k</td> <td>-36.08</td> <td>(-16.08)</td> <td>16.20 k</td> </tr> <tr> <td>4.000 MHz</td> <td>8.000 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> <tr> <td>8.000 MHz</td> <td>12.50 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> <tr> <td>12.50 MHz</td> <td>15.00 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> </tbody> </table>	Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Freq (Hz)	Peak dBm	Upper ΔLim(dB)	Freq (Hz)	0.0 Hz	5.625 kHz	100.0 Hz	36.70	(-0.89)	-200.0	-20.98	(-58.57)	150.0	5.625 kHz	12.50 kHz	100.0 Hz	-32.45	(-3.69)	-11.80 k	-37.78	(-5.74)	12.25 k	12.50 kHz	60.00 kHz	1.000 MHz	-36.15	(-16.15)	-16.65 k	-36.08	(-16.08)	16.20 k	4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	—	(—)	—	8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	—	(—)	—	12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	—	(—)	—
Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Freq (Hz)	Peak dBm	Upper ΔLim(dB)	Freq (Hz)																																																										
0.0 Hz	5.625 kHz	100.0 Hz	36.70	(-0.89)	-200.0	-20.98	(-58.57)	150.0																																																										
5.625 kHz	12.50 kHz	100.0 Hz	-32.45	(-3.69)	-11.80 k	-37.78	(-5.74)	12.25 k																																																										
12.50 kHz	60.00 kHz	1.000 MHz	-36.15	(-16.15)	-16.65 k	-36.08	(-16.08)	16.20 k																																																										
4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										



Appendix C:Emission Mask

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT																																																															
TX-ANH	FM	CH _{M1}	<p>Agilent Spectrum Analyzer - Spectrum Emission Mask Center Freq 405.987500 MHz Ref Offset 28 dB Ref 42.0 dBm Total Power Ref 36.92 dBm/0.0125 MHz</p> <table border="1"> <thead> <tr> <th>Start Freq</th> <th>Stop Freq</th> <th>Integ BW</th> <th>dBm</th> <th>Lower ΔLim(dB)</th> <th>Freq (Hz)</th> <th>Peak dBm</th> <th>Upper ΔLim(dB)</th> <th>Freq (Hz)</th> </tr> </thead> <tbody> <tr> <td>0.0 Hz</td> <td>5.625 kHz</td> <td>100.0 Hz</td> <td>35.55</td> <td>(-2.14)</td> <td>-200.0</td> <td>27.85</td> <td>(-9.84)</td> <td>2.300 k</td> </tr> <tr> <td>5.625 kHz</td> <td>12.50 kHz</td> <td>100.0 Hz</td> <td>-34.75</td> <td>(-2.09)</td> <td>-12.35 k</td> <td>-37.42</td> <td>(-4.76)</td> <td>12.35 k</td> </tr> <tr> <td>12.50 kHz</td> <td>60.00 kHz</td> <td>100.0 Hz</td> <td>-35.58</td> <td>(-15.58)</td> <td>-14.55 k</td> <td>-35.10</td> <td>(-15.10)</td> <td>12.85 k</td> </tr> <tr> <td>4.000 MHz</td> <td>8.000 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> <tr> <td>8.000 MHz</td> <td>12.50 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> <tr> <td>12.50 MHz</td> <td>15.00 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> </tbody> </table>	Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Freq (Hz)	Peak dBm	Upper ΔLim(dB)	Freq (Hz)	0.0 Hz	5.625 kHz	100.0 Hz	35.55	(-2.14)	-200.0	27.85	(-9.84)	2.300 k	5.625 kHz	12.50 kHz	100.0 Hz	-34.75	(-2.09)	-12.35 k	-37.42	(-4.76)	12.35 k	12.50 kHz	60.00 kHz	100.0 Hz	-35.58	(-15.58)	-14.55 k	-35.10	(-15.10)	12.85 k	4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	—	(—)	—	8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	—	(—)	—	12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	—	(—)	—
Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Freq (Hz)	Peak dBm	Upper ΔLim(dB)	Freq (Hz)																																																										
0.0 Hz	5.625 kHz	100.0 Hz	35.55	(-2.14)	-200.0	27.85	(-9.84)	2.300 k																																																										
5.625 kHz	12.50 kHz	100.0 Hz	-34.75	(-2.09)	-12.35 k	-37.42	(-4.76)	12.35 k																																																										
12.50 kHz	60.00 kHz	100.0 Hz	-35.58	(-15.58)	-14.55 k	-35.10	(-15.10)	12.85 k																																																										
4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
TX-ANH	FM	CH _{M1}	<p>Agilent Spectrum Analyzer - Spectrum Emission Mask Center Freq 405.987500 MHz Ref Offset 28 dB Ref 42.0 dBm Total Power Ref 36.89 dBm/0.0125 MHz</p> <table border="1"> <thead> <tr> <th>Start Freq</th> <th>Stop Freq</th> <th>Integ BW</th> <th>dBm</th> <th>Lower ΔLim(dB)</th> <th>Freq (Hz)</th> <th>Peak dBm</th> <th>Upper ΔLim(dB)</th> <th>Freq (Hz)</th> </tr> </thead> <tbody> <tr> <td>0.0 Hz</td> <td>5.625 kHz</td> <td>100.0 Hz</td> <td>36.87</td> <td>(0.82)</td> <td>-200.0</td> <td>-17.38</td> <td>(-55.07)</td> <td>150.0</td> </tr> <tr> <td>5.625 kHz</td> <td>12.50 kHz</td> <td>100.0 Hz</td> <td>-35.89</td> <td>(-2.50)</td> <td>-12.45 k</td> <td>-37.20</td> <td>(-4.55)</td> <td>12.35 k</td> </tr> <tr> <td>12.50 kHz</td> <td>60.00 kHz</td> <td>100.0 Hz</td> <td>-37.73</td> <td>(-17.73)</td> <td>-14.50 k</td> <td>-37.87</td> <td>(-17.87)</td> <td>16.80 k</td> </tr> <tr> <td>4.000 MHz</td> <td>8.000 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> <tr> <td>8.000 MHz</td> <td>12.50 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> <tr> <td>12.50 MHz</td> <td>15.00 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> </tbody> </table>	Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Freq (Hz)	Peak dBm	Upper ΔLim(dB)	Freq (Hz)	0.0 Hz	5.625 kHz	100.0 Hz	36.87	(0.82)	-200.0	-17.38	(-55.07)	150.0	5.625 kHz	12.50 kHz	100.0 Hz	-35.89	(-2.50)	-12.45 k	-37.20	(-4.55)	12.35 k	12.50 kHz	60.00 kHz	100.0 Hz	-37.73	(-17.73)	-14.50 k	-37.87	(-17.87)	16.80 k	4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	—	(—)	—	8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	—	(—)	—	12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	—	(—)	—
Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Freq (Hz)	Peak dBm	Upper ΔLim(dB)	Freq (Hz)																																																										
0.0 Hz	5.625 kHz	100.0 Hz	36.87	(0.82)	-200.0	-17.38	(-55.07)	150.0																																																										
5.625 kHz	12.50 kHz	100.0 Hz	-35.89	(-2.50)	-12.45 k	-37.20	(-4.55)	12.35 k																																																										
12.50 kHz	60.00 kHz	100.0 Hz	-37.73	(-17.73)	-14.50 k	-37.87	(-17.87)	16.80 k																																																										
4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
TX-ANH	FM	CH _{M2}	<p>Agilent Spectrum Analyzer - Spectrum Emission Mask Center Freq 406.112500 MHz Ref Offset 28 dB Ref 42.0 dBm Total Power Ref 36.89 dBm/0.0125 MHz</p> <table border="1"> <thead> <tr> <th>Start Freq</th> <th>Stop Freq</th> <th>Integ BW</th> <th>dBm</th> <th>Lower ΔLim(dB)</th> <th>Freq (Hz)</th> <th>Peak dBm</th> <th>Upper ΔLim(dB)</th> <th>Freq (Hz)</th> </tr> </thead> <tbody> <tr> <td>0.0 Hz</td> <td>5.625 kHz</td> <td>100.0 Hz</td> <td>35.53</td> <td>(-2.14)</td> <td>-200.0</td> <td>27.83</td> <td>(-9.85)</td> <td>2.300 k</td> </tr> <tr> <td>5.625 kHz</td> <td>12.50 kHz</td> <td>100.0 Hz</td> <td>-36.36</td> <td>(-2.97)</td> <td>-12.45 k</td> <td>-34.49</td> <td>(-2.19)</td> <td>12.30 k</td> </tr> <tr> <td>12.50 kHz</td> <td>60.00 kHz</td> <td>100.0 Hz</td> <td>-32.85</td> <td>(-12.85)</td> <td>-13.40 k</td> <td>-34.13</td> <td>(-14.13)</td> <td>13.05 k</td> </tr> <tr> <td>4.000 MHz</td> <td>8.000 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> <tr> <td>8.000 MHz</td> <td>12.50 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> <tr> <td>12.50 MHz</td> <td>15.00 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>—</td> <td>(—)</td> <td>—</td> </tr> </tbody> </table>	Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Freq (Hz)	Peak dBm	Upper ΔLim(dB)	Freq (Hz)	0.0 Hz	5.625 kHz	100.0 Hz	35.53	(-2.14)	-200.0	27.83	(-9.85)	2.300 k	5.625 kHz	12.50 kHz	100.0 Hz	-36.36	(-2.97)	-12.45 k	-34.49	(-2.19)	12.30 k	12.50 kHz	60.00 kHz	100.0 Hz	-32.85	(-12.85)	-13.40 k	-34.13	(-14.13)	13.05 k	4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	—	(—)	—	8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	—	(—)	—	12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	—	(—)	—
Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Freq (Hz)	Peak dBm	Upper ΔLim(dB)	Freq (Hz)																																																										
0.0 Hz	5.625 kHz	100.0 Hz	35.53	(-2.14)	-200.0	27.83	(-9.85)	2.300 k																																																										
5.625 kHz	12.50 kHz	100.0 Hz	-36.36	(-2.97)	-12.45 k	-34.49	(-2.19)	12.30 k																																																										
12.50 kHz	60.00 kHz	100.0 Hz	-32.85	(-12.85)	-13.40 k	-34.13	(-14.13)	13.05 k																																																										
4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										
12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	—	(—)	—																																																										



Appendix C:Emission Mask

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT																																																																						
TX-ANH	FM	CH _{M2}	<p>Agilent Spectrum Analyzer - Spectrum Emission Mask</p> <p>Center Freq 406.112500 MHz Center Freq: 406.112500 MHz Radio Std: None</p> <p>Ref Offset 28 dB Ref 42.0 dBm</p> <p>Center 406.1 MHz Span 120 kHz</p> <table border="1"> <thead> <tr> <th>Start Freq</th> <th>Stop Freq</th> <th>Integ BW</th> <th>dBm</th> <th>Lower ΔLim(dB)</th> <th>Upper ΔLim(dB)</th> <th>Peak</th> <th>Upper ΔLim(dB)</th> <th>Lower ΔLim(dB)</th> <th>Freq (Hz)</th> </tr> </thead> <tbody> <tr> <td>0.0 Hz</td> <td>5.625 kHz</td> <td>100.0 Hz</td> <td>-36.85</td> <td>(-0.82)</td> <td>-200.0</td> <td>-17.26</td> <td>(-54.94)</td> <td>-36.85</td> <td>200.0</td> </tr> <tr> <td>5.625 kHz</td> <td>12.50 kHz</td> <td>100.0 Hz</td> <td>-36.60</td> <td>(-3.56)</td> <td>-12.40 k</td> <td>-36.28</td> <td>(-6.52)</td> <td>-36.60</td> <td>11.95 k</td> </tr> <tr> <td>12.50 kHz</td> <td>60.00 kHz</td> <td>100.0 Hz</td> <td>-36.63</td> <td>(-16.63)</td> <td>-13.80 k</td> <td>-36.07</td> <td>(-16.07)</td> <td>-36.63</td> <td>15.80 k</td> </tr> <tr> <td>4.000 MHz</td> <td>8.000 MHz</td> <td>1.000 MHz</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> </tr> <tr> <td>8.000 MHz</td> <td>12.50 MHz</td> <td>1.000 MHz</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> </tr> <tr> <td>12.50 MHz</td> <td>15.00 MHz</td> <td>1.000 MHz</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> </tr> </tbody> </table>	Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Upper ΔLim(dB)	Peak	Upper ΔLim(dB)	Lower ΔLim(dB)	Freq (Hz)	0.0 Hz	5.625 kHz	100.0 Hz	-36.85	(-0.82)	-200.0	-17.26	(-54.94)	-36.85	200.0	5.625 kHz	12.50 kHz	100.0 Hz	-36.60	(-3.56)	-12.40 k	-36.28	(-6.52)	-36.60	11.95 k	12.50 kHz	60.00 kHz	100.0 Hz	-36.63	(-16.63)	-13.80 k	-36.07	(-16.07)	-36.63	15.80 k	4.000 MHz	8.000 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-	8.000 MHz	12.50 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-	12.50 MHz	15.00 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-
Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Upper ΔLim(dB)	Peak	Upper ΔLim(dB)	Lower ΔLim(dB)	Freq (Hz)																																																																
0.0 Hz	5.625 kHz	100.0 Hz	-36.85	(-0.82)	-200.0	-17.26	(-54.94)	-36.85	200.0																																																																
5.625 kHz	12.50 kHz	100.0 Hz	-36.60	(-3.56)	-12.40 k	-36.28	(-6.52)	-36.60	11.95 k																																																																
12.50 kHz	60.00 kHz	100.0 Hz	-36.63	(-16.63)	-13.80 k	-36.07	(-16.07)	-36.63	15.80 k																																																																
4.000 MHz	8.000 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-																																																																
8.000 MHz	12.50 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-																																																																
12.50 MHz	15.00 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-																																																																
TX-ANH	FM	CH _{M3}	<p>Agilent Spectrum Analyzer - Spectrum Emission Mask</p> <p>Center Freq 438.012500 MHz Center Freq: 438.012500 MHz Radio Std: None</p> <p>Ref Offset 28 dB Ref 41.0 dBm</p> <p>Center 438 MHz Span 120 kHz</p> <table border="1"> <thead> <tr> <th>Start Freq</th> <th>Stop Freq</th> <th>Integ BW</th> <th>dBm</th> <th>Lower ΔLim(dB)</th> <th>Upper ΔLim(dB)</th> <th>Peak</th> <th>Upper ΔLim(dB)</th> <th>Lower ΔLim(dB)</th> <th>Freq (Hz)</th> </tr> </thead> <tbody> <tr> <td>0.0 Hz</td> <td>5.625 kHz</td> <td>100.0 Hz</td> <td>35.10</td> <td>(2.30)</td> <td>-250.0</td> <td>26.92</td> <td>(-10.49)</td> <td>35.10</td> <td>2.250 k</td> </tr> <tr> <td>5.625 kHz</td> <td>12.50 kHz</td> <td>100.0 Hz</td> <td>-34.50</td> <td>(1.19)</td> <td>-12.40 k</td> <td>-36.78</td> <td>(3.11)</td> <td>-34.50</td> <td>12.45 k</td> </tr> <tr> <td>12.50 kHz</td> <td>60.00 kHz</td> <td>100.0 Hz</td> <td>-35.87</td> <td>(-15.87)</td> <td>-14.25 k</td> <td>-34.11</td> <td>(-14.11)</td> <td>-35.87</td> <td>13.90 k</td> </tr> <tr> <td>4.000 MHz</td> <td>8.000 MHz</td> <td>1.000 MHz</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> </tr> <tr> <td>8.000 MHz</td> <td>12.50 MHz</td> <td>1.000 MHz</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> </tr> <tr> <td>12.50 MHz</td> <td>15.00 MHz</td> <td>1.000 MHz</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> </tr> </tbody> </table>	Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Upper ΔLim(dB)	Peak	Upper ΔLim(dB)	Lower ΔLim(dB)	Freq (Hz)	0.0 Hz	5.625 kHz	100.0 Hz	35.10	(2.30)	-250.0	26.92	(-10.49)	35.10	2.250 k	5.625 kHz	12.50 kHz	100.0 Hz	-34.50	(1.19)	-12.40 k	-36.78	(3.11)	-34.50	12.45 k	12.50 kHz	60.00 kHz	100.0 Hz	-35.87	(-15.87)	-14.25 k	-34.11	(-14.11)	-35.87	13.90 k	4.000 MHz	8.000 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-	8.000 MHz	12.50 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-	12.50 MHz	15.00 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-
Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Upper ΔLim(dB)	Peak	Upper ΔLim(dB)	Lower ΔLim(dB)	Freq (Hz)																																																																
0.0 Hz	5.625 kHz	100.0 Hz	35.10	(2.30)	-250.0	26.92	(-10.49)	35.10	2.250 k																																																																
5.625 kHz	12.50 kHz	100.0 Hz	-34.50	(1.19)	-12.40 k	-36.78	(3.11)	-34.50	12.45 k																																																																
12.50 kHz	60.00 kHz	100.0 Hz	-35.87	(-15.87)	-14.25 k	-34.11	(-14.11)	-35.87	13.90 k																																																																
4.000 MHz	8.000 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-																																																																
8.000 MHz	12.50 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-																																																																
12.50 MHz	15.00 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-																																																																
TX-ANH	FM	CH _{M3}	<p>Agilent Spectrum Analyzer - Spectrum Emission Mask</p> <p>Center Freq 438.012500 MHz Center Freq: 438.012500 MHz Radio Std: None</p> <p>Ref Offset 28 dB Ref 41.0 dBm</p> <p>Center 438 MHz Span 120 kHz</p> <table border="1"> <thead> <tr> <th>Start Freq</th> <th>Stop Freq</th> <th>Integ BW</th> <th>dBm</th> <th>Lower ΔLim(dB)</th> <th>Upper ΔLim(dB)</th> <th>Peak</th> <th>Upper ΔLim(dB)</th> <th>Lower ΔLim(dB)</th> <th>Freq (Hz)</th> </tr> </thead> <tbody> <tr> <td>0.0 Hz</td> <td>5.625 kHz</td> <td>100.0 Hz</td> <td>36.33</td> <td>(-1.07)</td> <td>-250.0</td> <td>-18.07</td> <td>(-55.47)</td> <td>36.33</td> <td>450.0</td> </tr> <tr> <td>5.625 kHz</td> <td>12.50 kHz</td> <td>100.0 Hz</td> <td>-36.66</td> <td>(-3.35)</td> <td>-12.40 k</td> <td>-37.63</td> <td>(-4.69)</td> <td>-36.66</td> <td>12.35 k</td> </tr> <tr> <td>12.50 kHz</td> <td>60.00 kHz</td> <td>100.0 Hz</td> <td>-35.86</td> <td>(-15.86)</td> <td>-14.60 k</td> <td>-35.99</td> <td>(-15.99)</td> <td>-35.86</td> <td>14.05 k</td> </tr> <tr> <td>4.000 MHz</td> <td>8.000 MHz</td> <td>1.000 MHz</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> </tr> <tr> <td>8.000 MHz</td> <td>12.50 MHz</td> <td>1.000 MHz</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> </tr> <tr> <td>12.50 MHz</td> <td>15.00 MHz</td> <td>1.000 MHz</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> <td>(-)</td> <td>-</td> <td>-</td> </tr> </tbody> </table>	Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Upper ΔLim(dB)	Peak	Upper ΔLim(dB)	Lower ΔLim(dB)	Freq (Hz)	0.0 Hz	5.625 kHz	100.0 Hz	36.33	(-1.07)	-250.0	-18.07	(-55.47)	36.33	450.0	5.625 kHz	12.50 kHz	100.0 Hz	-36.66	(-3.35)	-12.40 k	-37.63	(-4.69)	-36.66	12.35 k	12.50 kHz	60.00 kHz	100.0 Hz	-35.86	(-15.86)	-14.60 k	-35.99	(-15.99)	-35.86	14.05 k	4.000 MHz	8.000 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-	8.000 MHz	12.50 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-	12.50 MHz	15.00 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-
Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Upper ΔLim(dB)	Peak	Upper ΔLim(dB)	Lower ΔLim(dB)	Freq (Hz)																																																																
0.0 Hz	5.625 kHz	100.0 Hz	36.33	(-1.07)	-250.0	-18.07	(-55.47)	36.33	450.0																																																																
5.625 kHz	12.50 kHz	100.0 Hz	-36.66	(-3.35)	-12.40 k	-37.63	(-4.69)	-36.66	12.35 k																																																																
12.50 kHz	60.00 kHz	100.0 Hz	-35.86	(-15.86)	-14.60 k	-35.99	(-15.99)	-35.86	14.05 k																																																																
4.000 MHz	8.000 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-																																																																
8.000 MHz	12.50 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-																																																																
12.50 MHz	15.00 MHz	1.000 MHz	-	(-)	-	-	(-)	-	-																																																																



Appendix C:Emission Mask

Operation Mode	Modulation Type	Test Channel	TEST PLOT RESULT																																																	
TX-ANH	FM	CH _H	<p>Agilent Spectrum Analyzer - Spectrum Emission Mask</p> <p>Center Freq: 469.987500 MHz</p> <p>Ref Offset: 28 dB, Ref: 41.0 dBm</p> <p>Total Power Ref: 36.30 dBm @ 0.0125 MHz</p> <table border="1"> <thead> <tr> <th>Start Freq</th> <th>Stop Freq</th> <th>Integ BW</th> <th>dBm</th> <th>Lower ΔLim(dB)</th> <th>Upper ΔLim(dB)</th> <th>Peak Freq (Hz)</th> </tr> </thead> <tbody> <tr> <td>0.0 Hz</td> <td>5.625 kHz</td> <td>100.0 Hz</td> <td>35.30</td> <td>(-1.90)</td> <td>26.51</td> <td>(-10.69)</td> </tr> <tr> <td>5.625 kHz</td> <td>12.50 kHz</td> <td>100.0 Hz</td> <td>-36.04</td> <td>(-1.80)</td> <td>-12.50 k</td> <td>-36.74</td> </tr> <tr> <td>12.50 kHz</td> <td>60.00 kHz</td> <td>100.0 Hz</td> <td>-35.88</td> <td>(-15.88)</td> <td>-12.65 k</td> <td>-36.70</td> </tr> <tr> <td>4.000 MHz</td> <td>8.000 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>(—)</td> </tr> <tr> <td>8.000 MHz</td> <td>12.50 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>(—)</td> </tr> <tr> <td>12.50 MHz</td> <td>15.00 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>(—)</td> </tr> </tbody> </table>	Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Upper ΔLim(dB)	Peak Freq (Hz)	0.0 Hz	5.625 kHz	100.0 Hz	35.30	(-1.90)	26.51	(-10.69)	5.625 kHz	12.50 kHz	100.0 Hz	-36.04	(-1.80)	-12.50 k	-36.74	12.50 kHz	60.00 kHz	100.0 Hz	-35.88	(-15.88)	-12.65 k	-36.70	4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	(—)	8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	(—)	12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	(—)
Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Upper ΔLim(dB)	Peak Freq (Hz)																																														
0.0 Hz	5.625 kHz	100.0 Hz	35.30	(-1.90)	26.51	(-10.69)																																														
5.625 kHz	12.50 kHz	100.0 Hz	-36.04	(-1.80)	-12.50 k	-36.74																																														
12.50 kHz	60.00 kHz	100.0 Hz	-35.88	(-15.88)	-12.65 k	-36.70																																														
4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	(—)																																														
8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	(—)																																														
12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	(—)																																														
TX-ANH	FM	CH _H	<p>Agilent Spectrum Analyzer - Spectrum Emission Mask</p> <p>Center Freq: 469.987500 MHz</p> <p>Ref Offset: 28 dB, Ref: 41.0 dBm</p> <p>Total Power Ref: 36.22 dBm @ 0.0125 MHz</p> <table border="1"> <thead> <tr> <th>Start Freq</th> <th>Stop Freq</th> <th>Integ BW</th> <th>dBm</th> <th>Lower ΔLim(dB)</th> <th>Upper ΔLim(dB)</th> <th>Peak Freq (Hz)</th> </tr> </thead> <tbody> <tr> <td>0.0 Hz</td> <td>5.625 kHz</td> <td>100.0 Hz</td> <td>36.28</td> <td>(0.92)</td> <td>-18.69</td> <td>(-55.69)</td> </tr> <tr> <td>5.625 kHz</td> <td>12.50 kHz</td> <td>100.0 Hz</td> <td>-36.83</td> <td>(-5.88)</td> <td>-12.05 k</td> <td>-38.82</td> </tr> <tr> <td>12.50 kHz</td> <td>60.00 kHz</td> <td>100.0 Hz</td> <td>-35.25</td> <td>(-15.25)</td> <td>-13.05 k</td> <td>-35.31</td> </tr> <tr> <td>4.000 MHz</td> <td>8.000 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>(—)</td> </tr> <tr> <td>8.000 MHz</td> <td>12.50 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>(—)</td> </tr> <tr> <td>12.50 MHz</td> <td>15.00 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>(—)</td> </tr> </tbody> </table>	Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Upper ΔLim(dB)	Peak Freq (Hz)	0.0 Hz	5.625 kHz	100.0 Hz	36.28	(0.92)	-18.69	(-55.69)	5.625 kHz	12.50 kHz	100.0 Hz	-36.83	(-5.88)	-12.05 k	-38.82	12.50 kHz	60.00 kHz	100.0 Hz	-35.25	(-15.25)	-13.05 k	-35.31	4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	(—)	8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	(—)	12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	(—)
Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Upper ΔLim(dB)	Peak Freq (Hz)																																														
0.0 Hz	5.625 kHz	100.0 Hz	36.28	(0.92)	-18.69	(-55.69)																																														
5.625 kHz	12.50 kHz	100.0 Hz	-36.83	(-5.88)	-12.05 k	-38.82																																														
12.50 kHz	60.00 kHz	100.0 Hz	-35.25	(-15.25)	-13.05 k	-35.31																																														
4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	(—)																																														
8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	(—)																																														
12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	(—)																																														
TX-ANL	FM	CH _L	<p>Agilent Spectrum Analyzer - Spectrum Emission Mask</p> <p>Center Freq: 400.012500 MHz</p> <p>Ref Offset: 28 dB, Ref: 36.0 dBm</p> <p>Total Power Ref: 31.36 dBm @ 0.0125 MHz</p> <table border="1"> <thead> <tr> <th>Start Freq</th> <th>Stop Freq</th> <th>Integ BW</th> <th>dBm</th> <th>Lower ΔLim(dB)</th> <th>Upper ΔLim(dB)</th> <th>Peak Freq (Hz)</th> </tr> </thead> <tbody> <tr> <td>0.0 Hz</td> <td>5.625 kHz</td> <td>100.0 Hz</td> <td>30.09</td> <td>(-2.21)</td> <td>22.40</td> <td>(-9.90)</td> </tr> <tr> <td>5.625 kHz</td> <td>12.50 kHz</td> <td>100.0 Hz</td> <td>-39.61</td> <td>(-1.20)</td> <td>-12.40 k</td> <td>-42.86</td> </tr> <tr> <td>12.50 kHz</td> <td>60.00 kHz</td> <td>100.0 Hz</td> <td>-38.93</td> <td>(-18.93)</td> <td>-14.50 k</td> <td>-40.14</td> </tr> <tr> <td>4.000 MHz</td> <td>8.000 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>(—)</td> </tr> <tr> <td>8.000 MHz</td> <td>12.50 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>(—)</td> </tr> <tr> <td>12.50 MHz</td> <td>15.00 MHz</td> <td>1.000 MHz</td> <td>—</td> <td>(—)</td> <td>—</td> <td>(—)</td> </tr> </tbody> </table>	Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Upper ΔLim(dB)	Peak Freq (Hz)	0.0 Hz	5.625 kHz	100.0 Hz	30.09	(-2.21)	22.40	(-9.90)	5.625 kHz	12.50 kHz	100.0 Hz	-39.61	(-1.20)	-12.40 k	-42.86	12.50 kHz	60.00 kHz	100.0 Hz	-38.93	(-18.93)	-14.50 k	-40.14	4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	(—)	8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	(—)	12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	(—)
Start Freq	Stop Freq	Integ BW	dBm	Lower ΔLim(dB)	Upper ΔLim(dB)	Peak Freq (Hz)																																														
0.0 Hz	5.625 kHz	100.0 Hz	30.09	(-2.21)	22.40	(-9.90)																																														
5.625 kHz	12.50 kHz	100.0 Hz	-39.61	(-1.20)	-12.40 k	-42.86																																														
12.50 kHz	60.00 kHz	100.0 Hz	-38.93	(-18.93)	-14.50 k	-40.14																																														
4.000 MHz	8.000 MHz	1.000 MHz	—	(—)	—	(—)																																														
8.000 MHz	12.50 MHz	1.000 MHz	—	(—)	—	(—)																																														
12.50 MHz	15.00 MHz	1.000 MHz	—	(—)	—	(—)																																														