


<p>We Provide The Best Service User Guide</p> <p>Model 1</p>	<p>Quick Start Guide for Watch (Safekeeper) Model 1</p> <p>Please read this instruction carefully before starting to use the device in order to install and use quickly. Pictures are only for information, take practicality as standard.</p> <p>1. Prepare</p> <p>Confirm the device type, check the accessories.</p> <p>Choose GSM network's SIM card, Reference business operator' suggestion. Please turn off the device before install the card.</p> <p>The watch SIM card need to have GPRS and caller ID function (It must be compatible with 2g of data traffic).</p> <p>Install client APP on the phone, which can</p>	<p>Inquiry your agency.</p> <p>Bar-code or two-dimension code for user to register.</p> <p>2. Products function</p> <ul style="list-style-type: none"> • GPS+base station+wifi, Three mode to location • Mobile phone or Computer GPRS service platform, double control model • GPRS real-time location, trace, monitor • Talkback • Intercom • Health • Trace • Watch alarm • Safety area • SOS emergency alert 	<p>Watch introduce</p>  <ul style="list-style-type: none"> • Watch remove alert • Low power alarm • Remote turn off • Bumper Dating 	<p>3. Part description and screen</p>  <p>3.1 Home page: The first line of small icons were gam signal, ringing mode, networking flag, location icon, symbol voice(not shown), light per caption flag, flag battery, below the time, date, Love.</p> <p>3.2 The phone book: Click to go to see the 15 numbers app settings, click to dial Pick.</p> <p>3.3 Micro chat: Point into the micro-chat app that send voice phone.</p> <p>3.4 Press intercom: Press recording, release sent.</p>	<p>3.5 Bumper Dating: In the interface, not to pay off a friend's watch nudged cross friends, dating success, the interface will remind each watch can only cross a friend.</p> <p>Replace Friends: After the friend handed over the watch only app which deletes the current friends, and then with other friends watch bumper post.</p> <p>3.6 Pedometer: Pedometer off by default, need to open the app inside, after pedometer pedometer will automatically turn on the watch, the data interface can be seen after clicking the number of steps.</p> <p>3.7 Unopened pedometer interface: app pedometer pedometer data will be displayed after opening.</p> <p>3.8 Download the app: The interface of the two-dimensional code is a two-dimensional code to download the app, click on the icon to zoom</p>	<p>into the two-dimensional code, id as shown below watch id number, automatic identification.</p> <p>4. Clients(safe keeper)operate instructio</p> <p>4.1 APP register</p> <p>Before logging in need to manually register the account, registration code scanner 15 or manually enter the registration code registration, registration code is unique and can not re-registered, if registered agent is required to restore the corresponding ID number; account must be unique, and others can not repeat, repeat if the user needs to replace the account re-registration; additional information customers can enter their own password can be modified, retrieve password required registration code, login account and fill in the registration phone number, the registration interface as shown</p>	<p>below:</p>  <p>4.2 Login</p> <p>4.2.1 APP function menu</p> <p>After finish register, input the correct account number and password, click login, enter the main menu. The main menu show as below:</p>	 <p>Partial function instruction:</p> <p>(1) Inter phone: Watch talk to mobile phone</p> <p>App sent voice: After turn on record function, App start to record and sent to watch. The longest voice can be 15s. Micro-end watches into the chat interface short press to play the voice box. Watch for sending recording app: Enter the micro-chat screen, press the intercom icon</p>	<p>recording(The longest record time is 15s), release the recording sent to app; Watch recordings Sent to a friend; Press the record button a friend, watches after sending recordings to a friend watches release, the maximum recording 15 seconds.</p> <p>(2) Map: Real-time check the watch's location</p> <p>The map menu display the watch and APP mobile phone position. Watch start to count for 3 minutes by Click "location". The interval time for upload is 20s. After 3 minutes it will back to the default work style. We can know the pattern of the watch location in real-time on the map menu. When location icon is red it is GPS location, Yellow is LBS location, Green is WIFI location, That green wifi positioning network targeting.</p>	<p>(3) Setting: Parameters setting for watch</p>  <p>a. Set SOS phone number: 3 phone numbers can be set. It will alert after 3S if press SOS key when in emergency situation. Call the 3 phone number periodic. If nobody answer it will be over after two turns.</p> <p>b. Monitor: Usually parents' phone number are set as monitor number. When confirmed the watch dial the monitor number initiatively, But the</p>	<p>watch can not hear any sound from phone. In that way the phone can monitor watch.</p> <p>c. No disturbing time: The three time shield all calls(Saturday, excluding weekends).</p> <p>d. Message prompt setting: Low voltage, SOS, three kinds of alert message switch when turn off the watch, That number is set wristwatch alarm messages sent to that number, alarm messages according to the normal SMS charges, after the number is set to open by default will monitor inside.</p> <p>e. Phone book: 15 phone book numbers can be set in the watch. These 15 numbers can dial to watch in two-way.</p> <p>f. Recover default work model: Default work model: open APP for 24 hours, the upload interval time is 60s.</p>
--	--	---	---	---	---	---	---	---	--	---	--

<p>g. Turn off: It can not press "OFF" key to turn off the watch once it start work normal. Only Through APP to remote turn off.</p> <p>h. Bumper Dating: Watches will show your friends add friends after the id, and can delete the add friends, watch re-cross a friend, a friend can only be submitted for each watch.</p> <p>(4) Safety area: The smallest radius of the fence is 200m. Alert will happen when for inside of the fence to outside. NOTE: fence alarm only when the watch gps positioning will trigger an alarm message, the base station location is not traveling fence alarm information.</p> <p>(5) Watch alarm: 3 watch alarm is available and also you can select the model of the watch to meet your needs.</p> <p>(6) Award for warm heart: Choose the number of the red hearts, click to send to watch, it will</p>	<p>display the warm heart and the numbers</p> <p>(7) Seek the watch: Send command while the watch is not at hand, the watch will ring for 1 minutes so that you can find out it. Press any key Client can stop it.</p> <p>Clients can know other function will be introduced in "MINE" and "HELP" menu.</p> <p>4.2.2 "Mine" men</p> 	<p>Note: The list of devices which can check customer registration id number, this id and watches posted id inconsistent watches can not connect app.</p> <p>"HELP" document describe details of all function. Client can go through that.</p> <p>4.3 Watch alert instruction</p> <p>Client will get alert push when it happens from watch. Phone client click the alert and enter APP main menu to check the details in information center.</p> <p>5. Watch work model</p> <p>Three base work models: Normal model, Power saving model, Real-time location model. Different models have different interval upload time. Client can set work model based one needs.</p>	<p>Normal model: 600s upload time interval; Power saving model: 3600s upload time interval; Real-time model: 60s upload time interval.</p> <p>6. Watch relative instructions</p> <p>6.1 Watch SOS emergency alert</p> <p>Long press SOS key for 3s. It will display SOS on screen. Watch will be on alert state. Circular dial 3 SOS numbers for two turns. It will stop when call answered. If not, it will continue until the two turns over. Watch can send message to monitor number(default "off" state). Also, send alert notification to APP.</p> <p>6.2 Remove wrist alert</p> <p>There is sensor switch on watchband. It will alert unless you wear the watch for at least 3 minutes. The watch send alert message to monitor number</p>	<p>(default "off" state) At the same time sent alert notification to APP. The watch then have remove symbol.</p> <p>6.3 Low power alert</p> <p>The watch battery appear in percentage. When lower than 20% the alert will happen. The watch send alert message to monitor number(default "off" state) At the same time sent alert notification to APP.</p> <p>6.4 Micro chat</p> <p>Watch enter the micro chat interface, and optional micro-chat app. Press and friends watch the recording button to start recording, release the button after sending recordings to watch Friends. Watch received a voice, a voice will mark the screen, press the record button to play all voice finished playing flag disappeared while being removed.</p>	<p>6.5 Voice Care</p> <p>Watch care need to set the number, the default display settings inside guardianship SMS alert number. After the app delivers turn on voice care instructions, dial the number to care for single talk.</p> <p>6.6 Shutdown</p> <p>Watches can be no card keys off, APP remote shutdown, power off.</p> <p>6.7 family number</p> <p>Only one family watch dial keys, press "Mom" corresponding to the number dialed sos1.</p> <p>6.8 The phone book</p> <p>Watch app can set up 10 phone book numbers, press watch "Mom" to enter the phone book, and then a short press to select the number, and finally press the dial.</p>	<p>6.9 Answer and end calls</p> <p>The number of calls related to watch, touch screen virtual buttons can answer the phone, hang up the power button.</p> <p>7. Trouble shoot</p> <p>1) The SIM inside watch is GSM networks or not, such as telecommunications does not support .</p> <p>2) The SIM card is opened the data traffic, data traffic must be compatible with 2g of watches currently only 2g of data traffic.</p> <p>3) Server parameters namely IP and port, ID is correct, we must ensure consistent and watches factory barcode id id watches posted writes, customers can edit their own mobile phone text messages pw, 123456, ts * sent to watch (wristwatch card must be installed</p>	<p>power, SMS must be in English input method], if agents do not understand can ask.</p> <p>4) Not registered in two situations: a prompt device number does not exist or the device number has been registered, must find agents processing; b Tip account that is already registered the account has been registered, the customer can simply change an account.</p>	<p>8. Entrance to scan bar-code</p>  <p>Download Android and IOS for mobile phone client by scan bar-code</p>	<p>This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.</p> <p>Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.</p> <p>NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following</p>	<p>measures:</p> <ul style="list-style-type: none"> --- Reorient or relocate the receiving antenna. --- Increase the separation between the equipment and receiver. --- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. --- Consult the dealer or an experienced radio/TV technician for help. <p>This device and its antenna(s) must not be co-located or operation in conjunction with any other antenna or transmitter.</p>	
---	--	---	--	--	--	---	--	---	--	--	--

Size: 770x63mm 折页印刷

FCC Warning

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Specific Absorption Rate (SAR) information:

This Pet Caller Tracker meets the government's requirements for exposure to radio waves. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The standards include a substantial safety margin designed to assure the safety of all persons regardless of age or health.

FCC RF Exposure Information and Statement

The SAR limit of USA (FCC) is 1.6 W/kg averaged over one gram of tissue. Device types: Pet Caller Tracker (FCC ID: 2ASXEMODEL1) has also been tested against this SAR limit. The highest SAR value reported under this standard during product certification for use when properly worn on the body is 0.062W/kg. the simultaneous transmission SAR value is 0.096W/ kg on the body. This device was tested for typical body-worn operations with the back of the handset kept 0mm from the body. To maintain compliance with FCC RF exposure requirements, use accessories that maintain a 0mm separation distance between the user's body and the back of the handset. The use of belt clips, holsters and similar accessories should not contain metallic components in its assembly. The use of accessories that do not satisfy these requirements may not comply with FCC RF exposure requirements, and should be avoided.

Body-worn Operation

This device was tested for typical body-worn operations. To comply with RF exposure requirements, a minimum separation distance of 0mm must be maintained between the user's body and the handset, including the antenna. Third-party belt-clips, holsters, and similar accessories used by this device should not contain any metallic components. Body-worn accessories that do not meet these requirements may not comply with RF exposure requirements and should be avoided. Use only the supplied or an approved antenna.