




800LR Z-WAVE STICK ZST39 LR



www.getzooz.com



FEATURES

- Z-Wave Plus Static USB Controller
- Latest S2 security protocol for a truly private network
- 800 Series Long Range Z-Wave for fast, low-power direct communication
- Extended range up to a mile in open space when using Long Range
- LED indicator for troubleshooting
- No drivers needed: works out of the box on Windows, Linux, and MAC OS

SPECIFICATIONS

- Model Number: ZST39 LR
- Power: 4.75-5.25 VDC
- SDK: 7.18.01
- Operating Temperature: 14-104° F
- Operating Humidity: Up to 85%
- Installation and Use: Indoor only
- Dimensions: 2" x 0.8" x 0.3"

a Z-Wave radio for your DIY smart home system. Simply connect it to a USB port on your PC, laptop, or Raspberry Pi and match it with home automation software (host software) of your choice to enjoy a fully secure, private Z-Wave Plus mesh network. If the software supports Z-Wave Long Range, enable direct communication between your devices and the controller for supreme range up to 1 mile and a larger network size up to 4000 nodes.

Questions? ask@getzooz.com

WINDOWS SET-UP

Windows 2000, XP, Vista, 7, 8 (32 / 64 bit)

The device will display in **Device Manager** under **Ports**. You can access it through the Windows CreateFile API using “`\\\\.\\COMxxx`” where xxx stands for the COM port number assigned by Windows.

UZH.INF and UZH.CAT are listed in the Z-Wave SDK which uses the standard `usbser.sys` or `usbser64.sys` Windows driver.

LINUX SET-UP

Linux

The device will display as “`/dev/ttyUSB0`”, you can discover it with the “`dmesg | grep tty`” command.


MAC OS SET-UP

MAC OS

The device will display as “`/dev/cu.usbmodem`” under Apple: System preferences: Network.

SerialAPI Mode:

Once the S2 stick is plugged into the USB port of the host computer, it automatically enrolls in the SerialAPI mode and remains active (awake), always listening for commands sent from the host software and relaying them to the Z-Wave devices in the network. It acts as a Z-Wave signal adapter for your smart home system, translating any Z-Wave reports and notifications sent by devices in your network to your smart home interface.



Scan to register your product for extended warranty, priority customer service, and more perks.

www.getzooz.com/register

Z-WAVE STICK AS SECONDARY CONTROLLER

You can use the S2 stick as a secondary controller with your existing Z-Wave system if it accepts additional controllers. To enroll the S2 stick in your current system, send the inclusion command and put the S2 stick into learning mode, using the SerialAPI mode.

FACTORY RESET

The 800 Series Stick can only be reset by the host software while it's in SerialAPI mode. The device is reset once an appropriate command from the host software is sent to reset the Z-Wave network.

There is no way to manually reset the S2 stick if it's not controlled by host software.

⚠ WARNING

- This product should be installed **indoors** upon completion of any building renovations.
- Do not install the S2 Stick in a place with direct sun exposure, high temperature, or humidity.
- Keep away from chemicals, water, and dust.
- Ensure the device is never close to any heat source or open flame to prevent fire.
- Ensure the device is connected to an electric power source that does not exceed the maximum load power.
- No part of the device may be replaced or repaired by the user.



This product can be included and operated in any Z-Wave network with other Z-Wave certified devices from other manufacturers and/or other applications. All non-battery operated nodes within the network will act as repeaters regardless of vendor to increase reliability of the network.

This product features the latest Security 2 (S2) framework to remove smart home network hacking risks. This device is equipped with a unique authentication code for trusted wireless communication.

WARRANTY

This product is covered under a standard 12-month warranty and an extended 5-year limited warranty once registered. To read the full warranty policy or file a warranty claim, please go to:

www.getzooz.com/warranty

FCC NOTE

THE MANUFACTURER IS NOT RESPONSIBLE FOR ANY RADIO OR TV INTERFERENCE CAUSED BY UNAUTHORIZED MODIFICATIONS TO THIS EQUIPMENT. SUCH MODIFICATIONS COULD VOID THE USER'S AUTHORITY TO OPERATE THE EQUIPMENT. STORE INDOORS WHEN NOT IN USE. SUITABLE FOR DRY LOCATIONS ONLY. DO NOT IMMERSE IN WATER. NOT FOR USE WHERE DIRECTLY EXPOSED TO WATER.

This device complies with Part 15 of the FCC Rules.

Operation is subject to the following conditions:

1. This device may not cause harmful interference,
2. This device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used according to instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in any given installation.

If this equipment causes harmful interference to radio or television reception, the user may try to correct the interference by taking one or more of the following measures:

- Reorient or relocate receiving antenna
- Increase the separation between equipment and receiver
- Connect equipment into a separate outlet or circuit from receiver
- Consult the dealer or an experienced radio/TV technician for additional assistance

FCC/IC Radiation Exposure Statement

- The equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.

All brand names displayed are trademarks of their respective holders.