Zwide®

说 明 书
USER MANUAL
取扱説明書

无线领夹麦克风
Wireless Lavalier Microphone
ワイヤレスピンマイク

M3-V23.01

产品介绍

感谢您选择智纬科技Zwide的无线领夹麦克风。为了能更进一步了解产品，请仔细阅读本说明书。祝您体验愉快。

本产品为智能降噪无线麦克风，三档降噪，可提供专业级的录音输出，即插即用，无需复杂的APP操作。

多种用途：网络直播、视频vlog拍摄、节目访谈、采访录音、视频教学等场景使用。

无线领夹麦克风由两部分构成:发射器和接收器。

产品型号

M3



USB-C 接收器

Lightning 接收器



发射器

背夹磁铁

收纳盒

充电仓

充电仓充电线

USB-C充电线
（一拖二）

监听耳机

发射器



① 内置麦克风
② 电量灯
③ 禁音键
④ 增益+键
⑤ 增益-键
⑥ 电源指示灯
⑦ 配对指示灯
⑧ 降噪指示灯
⑨ 电源键
⑩ 降噪键
⑪ 充屏键
⑫ 麦克风关子
⑬ 充电触点
⑭ USB-C接口

接收器



① USB-C 音频输出接口
② USB-C 充电接口
③ 监听耳机接口
④ 声音外放键
⑤ Lightning 音频输出接口
⑥ Lightning 充电接口
⑦ TX 配对指示灯
⑧ 电源指示灯
⑨ TX2配对指示灯

操作说明

发射器 TX

功能模式	按键	操作说明	指示灯状态
开 机		关机状态下长按三秒开机	蓝灯常亮
		开机后电量展示态	红灯 电量展示常亮
配对模式		接收器未开机	蓝灯闪烁
		接收器开机，配对成功	蓝灯常亮
禁麦键		按一下，开启禁麦功能	蓝灯常亮
		再按一下，关闭禁麦功能	蓝灯常亮
增益+		短按，增益+	
增益-		短按，增益-	
ENC键		按一下，开启一档降噪	绿灯常亮
		再按一下，开启二档降噪	蓝灯常亮
		再按一下，开启三档降噪	红灯常亮
		再按一下，关闭降噪功能	红灯熄灭
亮屏键		按一下，屏幕点亮	蓝灯常亮
		再按一下，屏幕灭	蓝灯熄灭
电池电量		电量充足	蓝灯常亮
		电池电量低于20%	红灯闪烁
		开关机状态下充电	红灯常亮
		充满电量	红灯熄灭
电量屏		开机亮屏显示实时电量。	

操作说明

接收器 RX

功能模式	按键	操作说明	指示灯状态
开 机		插入手机接收器自动开机	蓝灯闪烁
配对模式 ★		与发射器配对成功	蓝灯常亮
		发射器未开机，配对未成功	蓝灯闪烁
手机声音外放模式		短按外音键打开手机声音外放	蓝灯常亮
		短按外放键关闭声音外放	蓝灯熄灭

★ 无线领夹麦克风开机自动配对；如无法配对，请快速按发射器TX的电源键3次即可开始配对。

使用场景

发射器 TX

背夹磁铁

发射器可直接夹在衣领、帽子边沿上使用。
用背夹磁铁，可吸附到衣服上，防止衣服变形影响视频效果。

在户外或有风的环境中，推荐使用防风罩。

接收器 RX



USB-C 接收器　　Lightning 接收器

⚠ OPPO/vivo/iQOO/真我/一加品牌的手机每次连接使用需要"设置"里搜索"OTG"→"打开"OTG连接"或"OTG供电"才能正常使用；部分型号需要搜索"默认录音设备"→"选择"外接设备"。

⚠ 无线麦克风与设备连接成功后，打开相机录制视频。录制视频完成后，如需在录音播放视频需断开连接线，设备才会有声音输出。
另一种方式是按一下接收器的外放键，手机也可直接外放声音。

外放键如下图所示：

基本参数

麦克风

频率范围	2.4GHz	音频采样频率	48KHz	传输距离	~50m ★
传输延迟	20ms	音频范围	100Hz-8000Hz	电池	140mAh
充电电压	DC 5V	充电时间	~1.5h	工作时长	TX：~4.5h

★ FCC标准，在室外空旷无干扰环境下测得。

充电仓

型号	C3	输入	5V⎓1A	输出	5V⎓0.2A
充电时间	~2.5h	工作时间	~7h	电池	7.6Wh 3.8V 2000mAh

⚠ 发射器置入充电仓将自动关机。

包装清单

- (1) 发射器 x2
- (2) USB-C 接收器 x1
- (3) Lightning 接收器 x1
- (4) 充电仓 x1
- (5) 防风罩 x2
- (6) 背夹磁铁 x2
- (7) 充电仓充电线 x1
- (8) USB-C充电线（一拖二） x1
- (9) 3.5mm TRRS监听耳机 x2
- ★(10) 收纳盒 x1
  - (11) 说明书 x1
  - (12) 感谢信 x1

⚠ 不同套装内所含物品不同，请以实际购买套装为准。
本说明书所描述均为通用功能。

⚠ 本公司产品不断创新，如有更改恕不另行通知。

Product Introduction

Thank you for choosing Zwide Wireless Lavalier Microphone.
In order to know more about our products, please read this USER MANUAL carefully before using. Have a good using experience.
This product is an intelligent noise reduction wireless microphone, which can provide professional recording ouput. Plug and play, no APP required. It support 3 levels ENC and recharging as use also. It's the best choice for live-broadcasting.
Multiple uses: network broadcast, Vlog shooting, interview recording, video teaching and other scenarios.
Zwide Wireless Lavalier Microphone consists of two parts, TX and RX.

Model No.

M3

USB-C RX　　Lightning RX



TX

Magnetic Clip

Storage Box

Charging Case

Charging Case Cable

Charging Cable(1 to 2)

Monitor Earphone

TX



① Built-in Mic
② Power Screen
③ Mute Key
④ Gain + Key
⑤ Gain - Key
⑥ Power Indicator
⑦ Connect Indicator
⑧ ENC Indicator
⑨ Power Key
⑩ ENC Key
⑪ Screen Key
⑫ Mic Clip
⑬ Charging Pad
⑭ USB-C Port

RX



① USB-C Audio Output Port
② USB-C Charging Port
③ Monitor Earphone Port
④ Play By Phone Key
⑤ Lightning Audio Output Port
⑥ Lightning Charging Port
⑦ TX1 Connect Indicator
⑧ Power Indicator
⑨ TX2 Connect Indicator

Operating Instruction

TX

Function Mode	Key	Operation	Indicators State
Power ON		Hold the key 3s in Powered OFF state.	Blue light keeps ON
		The default state of the Power Screen.	Power Screen keeps ON
Connect Mode ★		RX haven't Power ON.	Blue light blink
		RX Powered ON, connect with RX automatically.	Blue light keeps ON
Mute		Press one time to mute.	Light goes out
		Press one more time to unmute, default is unmute.	Blue light keeps ON
Gain Adjustment		Press one time to increase the gain. Total are 5 levels. Default is L3.	
		Press one time to decrease the gain. Total are 5 levels. Default is L3.	
ENC		Press one time to enable L1 noise reduction.	Green light keeps ON
		Press again to enable L2 noise reduction , default is L2.	Blue light keeps ON
		Press one more time to enable L3 noise reduction.	Red light keeps ON
		Press again to disable noise reduction function.	Light goes out
Screen Key		Press one time to switch the screen ON.	Blue light keeps ON
		Press one more time to switch the screen OFF.	Light goes out

Operating Instruction

TX

Function Mode	Key	Operation	Indicators State
Battery Capacity		Power >20%	Blue light keeps ON
		Power <20%	Red light blink
		Charging	Red light keeps ON
		Full charging	Light goes out
Power Screen		It will display the power volume	

★ TX will connected RX automaticly if they Powered ON.
If not, please rapidly press Power Key of TX 3 times.

Operating Instruction

RX

Function Mode	Key	Operation	Indicators State
Power ON		RX will ON automatically when it connected with the phone.	Blue light blink
Connect Mode ★		TX Powered ON, RX connect with TX automatically.	Blue light keeps ON
		TX haven't Power ON.	Blue light blink
Play by Phone Mode		Press one time to enable poly the sound by phone.	Blue light keeps ON
		Press one more time to disable poly the sound by phone, sound played by mobile earphone, default is disable.	Light goes out

Using

TX

Magnetic Clip

TX can be clamped to clothes or hat.
Also can be attached using the Magnetic Clip to either clothes or a stable surface.

It is recommended to use the Windscreen when using the TX outdoors or in a windy environment.

RX



USB-C RX　　Lightning RX

⚠ OPPO/vivo/iQOO/realme/OnePlus brand phones can be used normally only search "OTG" in "Settings" -> turn ON "OTG connection" or "OTG power supply".
Servernal models need to search "Default recorder" in "Settings" -> select "Add-on".

⚠ Take video on the device after the RX connected with the device successfully.
Please disconnect the RX from the device if you want to play the video with audio in the device directly.
Or press the Play By Phone Key(if have), the sound will play by phone directly.

Play By Phone Key like below:

Basic Parameters

Mic

Working Frequency	2.4GHz	Recording Sampling Frequency	48KHz	Transmission Distance	~50m ★
Transmission Delay	20ms	Frequency Response Range	100Hz-8000Hz	Battery	140mAh
Charging Voltage	DC 5V	Charging Time	~1.5h	Working Time	TX：~4.5h

★ Tested in an obstruction-free outdoor environment.

Charging Case

Model No.	C3	Input	5V⎓1A	Output	5V⎓0.2A
Charging Time	~2.5h	Working Time	~7h	Battery	7.6Wh 3.8V 2000mAh

⚠ TX will OFF automatically when place in the Charging Case.

Packing List

- (1) TX x2
- (2) USB-C RX x1
- (3) Lightning RX x1
- (4) Charging Case x1
- (5) Windscreen x2
- (6) Magnetic Clip x2
- (7) Charging Case Cable x1
- (8) Charging Cable(1 to 2) x1
- (9) 3.5mm TRRS Monitor Earphone x2
- (10) Storage Box x1
  - (11) USER MANUAL x1
  - (12) Thanks Note x1

★ Different combos include different items. Please refer to the actual combo purchased. The features described in this USER MANUAL are general and apply to all combos.

⚠ Our products are constantly innovative and subject to change without prior notice.

製品紹介

このたびは、Zwideのワイヤレスピンマイクをお買い上げいただき、誠にありがとうございます。正しくご使用いただくために、必ずこの取扱説明書をお読みになり、末長くご愛用くださいますようお願い申し上げます。
弊社のワイヤレスピンマイクは、ノイズリダクション機能を搭載しております。強度は段階の調節が可能です。プロ級レベルの録音出力が可能で、ステレオ、モノラル、モノラルセーフタイトラックが簡単に切り替え可能です。機器はapp操作は不要です。
様々な使用シーン：屋外における映画、youtuber、Vlogger、ドラマのカラ取材や監急録音などの制作現場における音声の収音に最適です。
本機は送信機、受信機などと組み合わせて使用するワイヤレスピンマイクです。

製品型番

M3

USB-C受信機　　Lightning受信機



送信機

マグネットクリップ

収納ケース

充電ケース

充電ケースケーブル

USB-C充電ケーブル
(2in1)

監視イヤホン

送信機



① 内蔵マイク
② バッテリー残量表示
③ 消音ボタン
④ ゲイン+ボタン
⑤ ゲイン-ボタン
⑥ 電源指示ランプ
⑦ ペアリング指示ランプ
⑧ ノイズリダクション指示ランプ
⑨ 電源ボタン
⑩ ノイズリダクションボタン
⑪ LED ON
⑫ 充電用接点端子
⑬ USB-C接続口
⑭

受信機



① USB-C オーディオ出力接続口
② USB-C 充電接続口
③ 監視イヤホン接続口
④ 音声がスピーカーにするボタン
⑤ Lightning オーディオ出力接続口
⑥ Lightning 充電接続口
⑦ TX1ペアリング指示ランプ
⑧ 電源指示ランプ
⑨ TX2ペアリング指示ランプ

使用操作

送信機

機能モード	ボタン	操作説明	指示ランプの状態
電源ON		電源を切った状態で 1 秒間長押すと電源が入れる	ランプが青く点灯
		電源を入れたバッテリー表示状態	バッテリー残 点灯
ペアリングモード ★		受信機の電源が入っていない	ランプが青く点滅
		受信機とペアリングに成功する場合	ランプが青く点灯
消音		1回を短押すと、消音機能がON	青ランプが点灯しない
		再び1回を短押すと、消音機能がOFF	青ランプが点灯
ゲイン調節+		短押すとゲインを上げる	
ゲイン調節-		短押すとゲインを下げる	
ENC ボタン		1回を押すと、レベル1設定	緑ランプが点灯
		再び押すと、レベル2設定	青ランプが点灯
		もう 1 回押すと、レベル3設定	赤いランプが点灯
		再び 1 回を短押すと、ノイズリダクション機能がOFF	赤いランプが点灯しない
LED ON ボタン		ボタンを 1 回押すと、LED ON	青ランプが点灯
		再び押すと、LED OFF	青ランプが点灯しない

送信機

機能モード	ボタン	操作説明	指示ランプの状態
電源ON		スマホを差し込むと、自動的に電源が入ります	青ランプが点滅
ペアリングモード ★		送信機とペアリングに成功する	青ランプが点灯
		送信機の電源がついていない、ペアリングに失敗した	青ランプが点滅
スマホモードによる再生		スマホモードによる再生ボタンを短押しし、音声をスマホから再生します。	青ランプが点灯
		スマホモードによる再生ボタンを短押しで、音声をスマホから再生しません。	青ランプが点灯しない

使用場合

送信機

マグネットクリップ

クリップを使用して、直接に服や帽子の縁に装着できます。
或いは、マグネットクリップを利用して、服に貼り付け可能なので、簡単に装着します。

屋外または風の強い環境で使用する場合は、ファーウインドシールドをお勧めします。

受信機



USB-C受信機　　Lightning受信機

⚠ OPPO/vivo/iQOO/realme/OnePlusブランドのスマホは、「設定」の「OTG」を検索→「OTG接続」または「OTG電源」をONにするだけで正常に使用できます。一部の機種は「デフォルトレコーダー」を検索→「アドオン」を選択する必要があります。

⚠ ワイヤレスピンマイクが正常に接続された後、ビデオを録画します。ビデオを録画した後、このデバイスでビデオを再生したい場合は、ケーブルを使用機器から取り外してください。
もう一つの場合は、受信機のスマホモードによる再生ボタンを押さないと、本機から音声がでたりきません。

スマホモードによる再生ボタン

製品仕様

ワイヤレスピンマイク

送受信周波数	2.4GHz帯	録音用周波数	48KHz	転送距離	~50m ★
伝送遅延	20ms	周波数特性	100Hz-8000Hz	バッテリー容量	140mAh
充電電圧	DC 5V	充電時間	~1.5h	バッテリー稼動時間	TX：~4.5h

★ FCCに準拠し、障害物のない、屋外環境で測定。

充電ケース

型番	C3	入力	5V⎓1A	出力	5V⎓0.2A
充電時間	~2.5h	持続使用可能時間	~7h	バッテリー容量	7.6Wh 3.8V 2000mAh

⚠ 送信機を充電ケースに入れると、自動的に電源が切れます。

セット内容

- (1) 送信機 x2
- (2) USB-C 受信機 x1
- (3) Lightning 受信機 x1
- (4) 充電ケース x1
- (5) アテーウインドシールド x2
- (6) マグネットクリップ x2
- (7) 充電ケース充電ケーブル x1
- (8) USB-C充電ケーブル(2in1) x1
- (9) 3.5mm TRRS監視イヤホン x2
- (10) 収納ケース x1
  - (11) 説明書 x1
  - (12) サンクスレター x1

★ セットによって含まれる部品が異なりますので、実際に購入されたセットでご確認ください。

⚠ 当社の製品は常に革新的であり、予告なく変更される場合があります。

Zwide®

深圳市智纬科技有限公司
SHENZHEN ZHIWEI TECHNOLOGY CO., LTD

Zwide is a trademark of SHENZHEN ZHIWEI TECHNOLOGY CO., LTD
Copyright ©2023 Zwide Inc. All Rights Reserved.
Zwide 是深圳市智纬科技有限公司的商标
Copyright ©2023 智纬科技 版权所有
Made in China 中国制造

The Apple logo, iPhone, iPad and Lightning are trademarks of Apple Inc., registered in the U.S. and other countries.
The trademark of 'iPhone' is used in Japan with a license from Alphone KK
Android is trademark of Google LLC, registered in the U.S. and other countries.

USB-C and USB Type-C are registered trademarks of USB Implementers Forum.

Bluetooth logo and bluetooth are trademarks of Bluetooth SIG, Inc., registered in the U.S. and other countries.

All other company names, product names and logos are the trademarks or registered trademarks of their respective owners.

Compliance Information

FCC Compliance Notice

Supplier's Declaration of Conformity
Product Name: wireless lavalier microphone
Model Number: M3
FCC ID: 2BB3W-M3
Responsible Party: Zwide Inc.

We, Zwide Inc., being the responsible party, declares that the above mentioned model was tested to demonstrate complying with all applicable FCC rules and regulations.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more

of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and
(2) This device must accept any interference received, including interference that may cause undesired operation.
Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

RF Exposure Information

The device has been evaluated to meet general RF exposure requirement.
The device can be used in portable exposure condition without restriction.

IC Statement

This device complies with Industry Canada's licence-exempt RSSs. Operation is subject to the following two conditions:
(1) This device may not cause interference; and
(2) This device must accept any interference, including interference that may cause undesired operation of the device.
Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :
(1) l'appareil ne doit pas produire de brouillage, et
(2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

合格证 Qualified Certificate

合格证
经检验为合格产品
特此证明
深圳市智纬科技有限公司

QUALIFIED CERTIFICATE
Upon inspection and test this product is qualified
Shenzhen Zhiwei Technology Co., Ltd

保修卡

保修范围：如有产品故障，凭厂商授权服务中心的检测证明，享受15日包换，365日免费维修服务!

Warranty Card

Warranty scope:In case of product failure, you can get a replacement within 15 days and free repair service for 365 days, with inspection report issued by authorized service center.

保証書

【1年日本国内保証付き】保証期間に正常な使用状態でご使用の場合に限り品質を保証しております。万一保証期間で故障がありました場合は、お買い上げの販売店へお問い合わせください。
保証書は再発行いたしませんので、大切に保管してください。

Zwide®

产品型号 Model No. 型 番	M3
购买日期 Date of Purchase お買い上げ日	
订单号 Order No. ご注文番号	
经销商 Dealer 販売店名	
客户姓名 Customer Name お名前	
联系电话 Contact No. 電 話	
联系地址 Contact Address ご住所	
维修记录 Maintenance Record 修理記録	

SUBSCRIBE FOR MORE INFO
关注Zwide智纬及时获取最新资讯
http://www.zwide.com

RoHS　PSE　FC　CE　RECYCLABLE

地址：深圳市龙华区龙华街道油松社区利金城工业园8号厂房6层，6号厂房4层、5层
Address: 4th~5th Floor, Bld 6 and 6th Floor, Bld 8, Lijincheng Industrial Park, Yousong Community, Longhua Street, Longhua District, Shenzhen, China 518109

臻享纯净 以声相许
ENJOY THE PURITY PROMISE THE VOICE