www.waizowl.com

公众号

X:waizowl japan

WAIZOWL
WISER THAN OWLS

OGM CLOUD

OGM CLOUD



❶ 左键 L
❷ 右键 R
❸ 中键 M
❹ 前侧键
❺ 后侧键
❻ PR/MODE键
❼ DPI/POWER键
❽ Type-C接口

规格

鼠标尺寸	126x57x38mm
重量	55±2g
传感器	PAW3395
主控芯片	nRF52840
按键寿命(左/右)	8000W次
发射角度	360°
2.4G模式连续使用时长	135h (125Hz) 80h (1kHz) 20h(4kHz)
最大移动速度	26000DPI
扫描频率	650IPS
加速度	50G
工作距离	≤ 9 m
电池规格	300mA/h
回报率	125-4000Hz
充电时长	约2.5小时
进入睡眠时间	约10分钟

关于功能

1. 开/关机
长按DPI/POWER键2S

2. 电量状态

低电量警报	DPI/POWER键红色呼吸
充电状态	DPI/POWER键绿色呼吸
电量充满	DPI/POWER键绿色常亮

3. DPI切换
单击DPI键依次切换，DPI灯常亮提示档位，
分别为：400(红) - 800(绿) - 1600(蓝) - 3200(紫) - 6400(青)

4. 回报率调节
有线/2.4G无线模式下，单击PR/MOD键依次切换，PR键灯提示档位，
分别为: 125(红) - 250(绿) - 500(蓝) - 1000(紫) - 2000(青) - 4000(黄)
注：2000(青)/4000(黄)属于4K接收器模式下

5. 接收器切换
长按L/R/前侧键3S进行切换，PR/MODE键指示灯为绿色闪烁，绿色常亮为连接成功。
注：鼠标可分别记忆1K/4K接收器各一个，两个接收器同时处于工作状态时鼠标开机优先连接4K接收器。

关于连接

1. 模式切换
长按PR/MODE键
2.4G模式：PR/MODE键亮绿灯2s
蓝牙模式：PR/MODE键亮蓝灯2S

2. 2.4G无线模式
开机状态下，将鼠标发射器插入设备端USB接口内，即可使用。
注：首次连接需等待几秒到十几秒时间

3. 蓝牙模式
开机状态下，长按PR/MODE键2S，从设备中寻找设备“OGM 05”进行连接即可。
注：首次连接需等待几秒到十几秒时间

4. 有线模式
将附件中的Type-C充电线连接鼠标接口，连接电脑即可实现充电并正常使用。

5. 2.4G无线模式重新配对
开机后，同时长按L/M/R键3S，即可重新与发射器进行配对，PR/MODE键指示灯为绿色闪烁，绿色常亮为配对成功。

6. 蓝牙模式重新配对
长按L/M/R键3S，即可进入搜索状态，PR/MODE键指示灯为蓝色闪烁，蓝灯常亮为配对成功。

驱动安装

请您前往WAIZOWL官网下载驱动安装包
官网地址：http://waizowl.com

*产品介绍中的数据源于WAIZOWL实验室，由于使用环境和设备不同会存在一定差异，仅供参考。

◆ 购买WAIZOWL产品在7天内出现质量问题，且无法根据包装内信息卡上提示解决的
用户可以选择：
(a) 前往购买产品的旗舰店，申请退货退款
(b) 前往购买产品的旗舰店更换同型号产品
(c) 前往WAIZOWL旗舰店进行维修或更换

◆ 购买WAIZOWL产品在15天内出现质量问题，且无法根据包装内信息卡上提示解决的
前往购买产品的旗舰店更换同型号产品

◆ 购买WAIZOWL产品超过15天但仍在保质期内出现质量问题，且无法根据包装内信息卡上提示解决的
用户可以选择：
前往WAIZOWL旗舰店进行维修或更换。
处理流程为：在我们工作人员的指导下填写用户信息注册单，寄往工作人员提供的地址，等待我们的工程师为您检测，维修或更换产品。

◆ 有限质保申明
WAIZOWL公司对其产品包装内所有的硬件产品，在符合WAIZOWL公司三包条件下予以三包服务。此服务仅限于出现质量问题的产品，而不包括因使用实者利益损失及其他意外情况造成的任何直接或间接损失。

◆ 属于以下情况之一的WAIZOWL产品，WAIZOWL不提供三包服务
(a) 不能出示产品有效三包凭证和有效原始购物发票或收据，同时产品原序列号标签有涂改、替换、撕毁的现象。
(b) 产品超出WAIZOWL公司所规定的三包期限。
(c) 未依据产品使用说明书或未依据说明书所指示的电脑工作环境使用，维护、保管所导致的故障和损坏，以及由非WAIZOWL公司授权机构的维修人员安装、修理、更改或拆卸(撤销元保护标签破损)而造成的故障或损坏。

本卡内容不得擅自涂改，并请保存产品包装盒，以维护您的合法权益。

OGM CLOUD



❶ Left Click L
❷ Right Click R
❸ Middle key M
❹ Front side key
❺ Back side key
❻ PR/MODE
❼ DPI/POWER
❽ Type-C port

Product specification

Mouse size	126x57x38mm
Weight	55 ± 2g
Sensor	PAW3395
Main control chip	nRF52840
Key life (left/right)	8000W
Emission Angle	360°
2.4G continuous usage duration	135h（125Hz） 80h（1kHz）20h(4kHz)
Maximum moving speed	26000DPI
Scanning frequency	650IPS
Acceleration	50G
Working distance	≤ 9 m
Battery specification	300mA/h
Rate of return	125-4000Hz
Charging time	about 2.5 hours
Time to sleep	About 10 minutes

About Product Features

1. On/off
Hold down the DPI/POWER key for 2S

2. Charge state

Low battery Alert	DPI/POWER key red breath
Charging status	DPI/POWER key green breathing
Full charge	The DPI/POWER button is steady green

3. DPI switching
Click the DPI key to switch successively, and the DPI indicator is steady on. They are 400 (red) -800 (green) -1600 (blue) -3200 (purple) -6400 (cyan)

4. Rate of return adjustment
In wired /2.4G wireless mode, click the PR/MOD key to switch successively, and the PR key light indication gear is 125 (red) - 250 (green) - 500 (blue) - 1000 (purple) -2000 (cyan) -4000 (yellow) respectively.
Note: 2000 (blue) / 4000 (yellow) is in 4K receiver mode

5. Receiver switching
Hold down the L/R/ front key for 3S to switch. If the PR/MODE indicator blinks green and is steady green, the connection is successful.
Note: The mouse can separately remember a 1K/4K receiver, two receivers at the same time in the working state of the mouseConnect the 4K receiver at boot priority.

About connection mode

1. Mode switching
Hold down the PR/MODE key
2.4G MODE: The PR/MODE key is green for 2 seconds
Bluetooth MODE: PR/MODE button on the blue light 2S

2. 2.4G wireless mode
When the device is powered on, insert the mouse transmitter into the USB port of the device, and you can use it.
Note: The first connection takes a few seconds to ten seconds

3. Bluetooth mode
When the device is powered on, hold down the PR/MODE key for 2S, and find the device "OGM 05" from the device to connect.

4. Wired mode
Connect the Type-C charging cable in the attachment to the mouse interface, and connect the computer to realize charging and normal use.

5. 2.4G wireless mode repair
After starting up, long press the L/M/R key for 3S at the same time.
You can pair with the transmitter again. The PR/MODE key indicator blinks green, and the green indicator is steady on， indicating successful pairing.

6. Bluetooth mode repair
Press and hold L/M/R for 3S to enter the search state. The PR/MODE indicator blinks blue, and the blue indicator is steady on, indicating successful pairing.

◆ Limited warranty statement
WAIZOWL Company shall provide three-package service for all hardware products in its product packaging, subject to the three-package conditions of WAIZOWL Company. This service is limited to products with quality problems, and does not include compensation for any direct or indirect losses caused by loss of interests of buyers and other unexpected circumstances

◆ WAIZOWL does not provide three-pack service for WAIZOWL products under one of the following conditions
(a) Cannot produce valid three package voucher and valid original purchase invoice or receipt
(b) The product is beyond the three warranty period stipulated by WAIZOWL Company
(c) Failure and damage caused by not using, maintaining or keeping the computer in accordance with the product instruction manual or the computer working environment specified in the instruction manual; And failure or damage caused by installation, repair, alteration or removal (screw hole protection tag broken) by repairmen not authorized by WAIZOWL

The contents of this card shall not be altered without authorization, and please keep the product packaging box to protect your legitimate rights and interests.

OGM CLOUD



❶ 左ボタン L
❷ 右ボタン R
❸ ホイール M
❹ サイドボタン1(進む)
❺ サイドボタン2(戻る)
❻ DPI/POWERボタン
❼ PR/MORDボタン
❽ Type-Cコネクタ

製品規格

寸法	126x57x38mm
重量	55±2g
センサー	PAW3395
MCU	nRF52840
メインボタン(左/右ボタン)寿命	約8000万回
ワイヤレス発信角度	360°
2.4Gモード連続動作時間	135h (125Hz) 80h (1kHz) 20h(4kHz)
最大解像度	26000DPI
最大速度	650IPS
最大加速度	50G
通信距離	≤ 9 m
バッテリー容量	300mA/h
ポーリングレート	125-4000Hz
フル充電	約2.5h
自動睡眠モード	10分

使用

1. ON/OFF
DPI/POWERボタンを2秒長押しすると、電源ON/電源OFF

2. バッテリー状態

低電力警告	DPI/POWERボタンLEDライトが赤く点滅
充電中	DPI/POWERボタンLEDライトが緑色で点滅
充電完了	DPI/POWERボタンLEDライトが緑色で点灯

3. 感度(DPI)切り替え方
「DPI/POWERボタン」ボタンをワンクリックし、LEDライトが5色点灯します。順番に400(赤)、800(緑)、1600(青)、3200(紫)、6400(水色)の5段階に切り替えることが可能（ソフトウェアでより細かい調節ことが可能）

4. ポーリングレート切り替え
マウス本体を有線/2.4Ghzワイヤレスモードにし、「PR/MOD」ボタンをワンクリックし、ボタン指示ライトが125Hz(赤)-250Hz(緑)-500Hz(青)-1000Hz(紫)2000Hz(水色)-4000Hz(黄色)を順次に切り替えます。
注意：2000Hz及び4000Hzは4Kドングル（別売り）接続状態モードでしか対応していません。

5. ドングル切り替え方
切り替えしたい方のドングルを設備に接続させ、マウス本体の左ボタン/ホイル/サイドボタン1(L/M/進む)を同時に3秒ほど長押し、PR/MODEボタン指示が緑色で点滅し、ドングルペアリングモードに入り、緑色でしばらく点灯したらペアリング成功となります。
注意：マウス本体は同時に2個までドングルと4Khzドングルを記憶することが可能ですが、両方のドングルを同時に設備に接続させた場合、4Khzドングルの方が優先的に接続します。

接続

1. モード切り替え
PR/MODEボタンを長押し。
2.4Gモード：PR/MODEボタンを3秒程長押し、緑色で点灯すると切り替えが完了し利用可能になります。
BTモード：PR/MODEボタンを3秒程長押し、青く点灯すると切り替えが完了し利用可能になります。

2. 2.4Ghzワイヤレスモード
マウス本体がPC電源ONの状態で、ドングルを設備に接続させ、緑色で点滅し、消灯になったらご使用になられます。
注意：初回接続で数秒の間、ペアリングモードに入ることがあります。

3. BTモード
マウス本体が電源ONの状態で、PR/MODEボタンを3秒程長押し、指示ライトが青く点滅し始めるとペアリングモードに入り、接続から「OGM 05」を選択し、接続させたらご使用になられます。

4. 2.4Gワイヤレスモードでの再ペアリング
2.4Ghzモードで起動後、左ボタン/ホイル/右ボタン(L/M/R)を同時に5秒程長押し、PR/MODEボタン指示ライトが緑色で点滅したら、2.4Gワイヤレスペアリングモードに入り、指示ライトがしばらく緑色で点灯したらペアリング成功となります。

5. BTモードの初回及び再ペアリング
BTモードで起動後、左ボタン/ホイル/右ボタン(L/M/R)を同時に5秒程長押し、PR/MODEボタン指示ライトが青く点滅したら、BTペアリングモードに入り、指示ライトがしばらく青く点灯したらペアリング成功となります。

ダウンロード

ソフトウェアのダウンロードは正規代理販売店DeviceArmoury公式サイトにて
ダウンロード：www.ka-ei.co.jp

注意：製品紹介中のデータは全てWAIZOWL実験室の実験結果に基づいて書いたものです。使用環境や設備より違いが生じることがあります。ご参考のほどでよろしくお願いいたします。

製品保証について

購入して頂いたWAIZOWL商品が初期不良や、通常に使用している時に故障が発生した場合、保証規定に従い保証いたします。製品付属の保証書とお買い上げした際のレシートか証明書をご用意した上で、公式サイトのお問い合わせページまでご連絡頂きますようお願い致します。

FCC Certification

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

◆ Reorient or relocate the receiving antenna.
◆ Increase the separation between the equipment and receiver.
◆ Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
◆ Consult the dealer or an experienced radio/TV technician for help

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

说明书品号：751-832918-000
128克双胶/四色印刷/装订成册
成品尺寸：80*100mm
注意边距要一样