

Specifications

Battery Type	Lithium-Ion rechargeable
Battery Duration	60 - 72 hours when fully charged
Charge Time	24 hours from 0-100%
Operating Temperature Range	-4 F° to 140 F°
Operating Humidity Range	0 to 95% (relative humidity)
Temperature Accuracy	±0.5 F° typical, ±2 F° maximum
Humidity Accuracy	±2% typical, ±5% maximum
Cellular Technology	4G NB-IoT: Band2/4/5/12/66
Cellular Network Compatibility	AT&T, T-Mobile, Cellular One
Data Upload Frequency	Every 10 minutes
Check-in Frequency	Every 10 seconds

Warranty

The Necto Cellular Multisensor comes with a 1-Year Limited Warranty from the date of shipment.

FCC Compliance

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Caution: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital Device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with radio frequency (RF) exposure limits adopted by the Federal Communications Commission for an uncontrolled environment. This device should be installed and operated with minimum distance 20 CM between the radiator & your body.

necto

4G Cellular Multisensor QUICK START GUIDE

3-STEP EASY SET UP

1. Create an Account

Go to app.getnecto.com or scan the QR code on the right to create an account.



<https://app.getnecto.com>

2. Register the Device

Enter the Device ID located on the back of the device. To access the Device ID, remove the wall mount on the device by gently sliding it downwards. Then set the desired alert settings.

3. Power Up

Plug in the device using the supplied cable. Then press the power button on the side of the device for 3 seconds to turn it on. Once the device successfully connects to the cellular network, the bottom LED indicator will turn solid green (this can take up to 3 minutes).

Please Note: After the device is first plugged in or moved to a new location, it can take up to 30 minutes for the sensors to adjust to their new environment, and show accurate readings.

Device Placement

The device can be placed on a flat surface or mounted on the wall. To ensure accurate readings: (1) Place the device out of direct sunlight, and away from any heat source or vents. (2) Make sure the small holes on the bottom of the device are kept clear of any obstructions to allow proper airflow.

How to Attach the Wall Mount

- Peel off the sticker from the back of the wall mount, and attach it to the desired location on the wall. If attaching to a rough surface use the included screws.
- Align the slots on the back of the device with the pegs on the wall mount. Then, gently slide the device downwards to secure it.

Important Battery Information

- In order to maintain good battery health: (1) If your device is in use, let the battery drain for 24 hours at least once every 3 months. (2) If your device is not in use, charge it at least once every 3 months.
- The device can take up to 24 hours to fully charge. The slow charge rate minimizes the heating of the battery, ensuring no impact on the accuracy of the temperature readings.

LED Indicator Guide

Power LED	Meaning
Solid Green	Connected to power outlet
Flashing Green (every 3 seconds)	No power at outlet, running on battery
Flashing Red (every 3 seconds)	No power at outlet, battery below 10%
Cellular LED	Meaning
Solid Green	Connected to cellular network
Red/Green Alternating Flash	Searching for network connection
Solid Red	No network connection

Need Help?

For troubleshooting and FAQs visit getnecto.com/support



<https://getnecto.com/support>

The Necto Support team is here to help! Please email us at support@getnecto.com if we can be of any assistance.