

CLR903

LTE USB Dongle



This product uses the ASR1803S chip platform, high speed! stable! Plug and Play! Compatible and adapted to various operating systems, to meet the long-term Internet needs of individual users and also meet the needs of police and corporate VPDN private networks.

ASR
1803S

CAT4
High speed

WebUI
support

CLR903

LTE USB Dongle

Product Features		
Size	89.6mm*28.6mm*13mm	
Weight	50g	
Power Supply	5~18V/0.5~1A	
Antenna	Built-in antenna	
LED	Power indicator/4G signal light	
Band	AU European version	LTE-FDD:B1/B3/B5/B7/B8/B28
		LTE-TDD:B38/B40/B41
		WCDMA:B1/B5/B8
LTE Rate	FDD-LTE 150Mbps DL / 50Mbps UL @20M BW Cat4	
	TDD-LTE 130Mbps DL / 35Mbps UL @20M BW Cat4	
USB Driver	Windows series/Linux/WinCE/Android etc.	
Interface	USB 2.0	
	Micro-SIM card×1+eSIM card or eSIM card×3 (QFN5*6)	
Dialing Method	RNDIS	
Operating Temperature	-20℃ - 60℃	
Web	Support web background management, address 192.168.1.1, default login account admin:admin	
Maximum Connectable Users	Less than 10 people+1 USB	

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harm full interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Specific Absorption Rate (SAR) information:

This Device meets the government's requirements for exposure to radio waves. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The standards include a substantial safety margin designed to assure the safety of all persons regardless of age or health. FCC RF Exposure Information and Statement the SAR limit of USA (FCC) is 1.6 W/kg averaged over one gram of tissue. Device types: Device has also been tested against this SAR limit. This device was tested for typical body-worn operations with the back of the device kept 5mm from the body. To maintain compliance with FCC RF exposure requirements, use accessories that maintain an 5mm separation distance between the user's body and the back of the device. The use of belt clips, holsters and similar accessories should not contain metallic components in its assembly. The use of accessories that do not satisfy these requirements may not comply with FCC RF exposure requirements, and should be avoided.