

Mini Wireless Keyboard Touchpad Combo Installation & User Manual Ver: 3.6

New product With

MULTI TOUCH

IN LINE WITH THE POLICY OF CONTINUED DEVELOPMENT THE MANUFACTURER RESERVES THE RIGHT TO AMEND THE SPECIFICATIONS WITHOUT PRIOR NOTIFICATION, THE PICTURES AND DATE IN THE STYLEBOOK ARE CONSULT ONLY, IF THERE IS FLUCTUATION, ACCORDING TO THE REAL OBJECT PLEASE.



Overview

Thank you for purchasing the Wireless Mini QWERTY Keyboard & TouchPad Combo. You can use it for email, chat, remote, type and games. It is compatible with PC, Laptop, Raspberry Pi 2, Mac IOS, Linux, HTPC, IPTV, Google Android Smart TV Box ,XBMC, Windows 2000 XP Vista 7 8 10. Use it with your android box or smart tv on your sofa or browse the internet in the most comfortable fashion.

Package Contents

- Keyboard touch pad Combo
- USB Wireless Receiver
- User Manual
- USB Charging Cable

System Requirements

- HID compatible device
- Terminal with USB port
- Windows 2000
- Windows XP
- Windows Vista, Windows CE, Windows 7, Windows 8, Windows 10
- Linux (Debian-3.1, Redhat-9.0, Ubuntu-8.10, Fedora-7.0 tested)

- Android OS (With standard USB interface)

Please note:

1. It can work on Amazon Fire TV as follows: use an app called app2 fire on android. You can send any app to fire tv. Then run it so for example google chrome. The keyboard works as mouse and keyboard. Just note that it only works on sideloaded application's. for example google chrome, firefox,showbox. KODI is a native app on fire.
2. Not suitable for all smart tv. Some smart tv do no support external input device. Before you place the order, Please use a wired keyboard to check if it can work.

Specifications

Receiver(dongle): Nano style

Connection port : With USB2.0 above

Transmission mode: GFSK 2.4GHz wireless, up to 10 meters

Transmission Power: Less than +4db

Power supply: Rechargeable polymer Lithium-ion battery

Charging voltage: 4.4V ~ 5.25V

Charging current: 300mA

Sleeping current class1: 30uA

Operation voltage: 3.7V

Operating current: <15mA

Product weight: 110g

Product size: 146.8*97.5*19mm

Installation

1. Take off the USB receiver from back cover of the keyboard.
2. Plug the USB Receiver into your device's USB port.Such as android tv box, smart TV.
3. Turn on the keyboard.

The yellow light will not flash. That means the keyboard has paired with your device.

You can enjoy the keyboard now!

Note:

- 1.If the yellow light stay flashing, It means the keyboard need to be paired with your device handy. As for how to pair, Please try following steps:

Step1.Make sure the keyboard can be turned on normally. The blue light is always on, which means that the battery is fully charged. If the blue light is flashing or not, please charge the keyboard.

Step2.Keep your PC or Android power on, When the keyboard is turned off, press and hold the F1 key, and then turn on keyboard switch, the yellow light will flash quickly.

At this time, insert the receiver into the computer or Android box. If the yellow light out, the pairing is successful.

2. About the meaning of the three leds(Blue, Red and Yellow)

Blue: Means power status. When it is on, It means powerful. If it is flashing,

It means low power, Please charge the keyboard.

Red: Means charge status. When start to charge, It will be on. When it is powerful,

It will be off automatically.

Yellow: Means sync. After turning on the keyboard, When yellow light doesn't flash,

It means the keyboard is connected to your device successfully. When press any key or touchpad, Yellow light will flash quickly.

If the yellow light stay on flashing without any press, You need to do the above 2 steps to pair it.

3. Shortcut Keys:

FN+Esc: 3minutes/2hours sleep time

FN+F7: Print screen

FN+F8: Disable/Enable touchpad mouse function

FN+F9: F11

FN+F10: F12

FN+PgUp: Home

FN+PgDn: End

FN+Enter: CTRL+ALT+DEL

FN+Space: Touch speed adjustment

4. Special keys used in special layout. such as @ in UK layout

This keyboard has different layouts. Please know exactly which layout do you want.

For example. If you want and buy UK layout. And you want to use @.You need to first change your device's system language to british English.Then it can work by shift+ @.

5. Auto Sleep/Wake Up Function

This keyboard has 2 models auto sleep/wake up function(Model 1 is 3 minis,

Model 2 is 2 hours). When you do not press any button or touch pad mouse in 3 minis or 2 Hours, It will enter into sleep automatically, You can press any button it up. You can also press Fn + Esc to convert the two models.

Switching Off The Keyboard After Use

After use, push the switch to the "OFF" position to turn it off. The USB receiver does not need to be pulled out from the terminal. You can use it next time directly.

Charging The Battery

The device uses built-in lithium-ion battery. Please use only approved data cables.

Note: Fully charge the unit before initial operation. This device can be used when charging, But charging time will be extended.

When the battery is low, The blue light will blink to warn the user.

The unit will be automatically turned off if the battery has been depleted.

Power Button To Make Your Device Standby(Only for power key versions)

Please press the Power button without release for 3s to make your device standby.

Turn ON/OFF The Backlit LED (Only for backlight versions)

While turn on the keyboard, you can press the light control key to turn on the backlight.

The backlit will automatically turn off after it enter into auto sleep function.

Audio Feature (Only for Audio versions)

Audio feature configuration is available for this device, This device includes a MIC.

Under some systems, the audio feature requires manual configuration.

Multi-finger Functions Touchpad

This touchpad supports multi-finger functions.

(1) Single finger clicks on behalf of left mouse

(2) Two-finger click on behalf of right mouse

(3) Double finger drag up and down on behalf of Rolling screen

(4) When a single finger sliding pointer can be controlled

Disable/Enable Touchpad Mouse Function

The touchPad is activated while turning on the keyboard and can be worked as mouse.

Press FN+F8 can Disable/Enable touchpad mouse function.

Warning

- When charging finishes, Pull out the charging cable.
- Never try to open or repair this product yourself.
- Keep this device away from fluids, Such as water.

Maintenance

- Do not attempt to disassemble the device or replace the rechargeable battery. Doing so will void the warranty.
- The battery will discharge when it is stored for a long time without operation.
- Disconnect the device when the battery is fully charged.Over charging will shorten the battery life.
- Do not expose the device in extreme heat or cold environment, Which will shorten the battery life.

Disposal



Always dispose the used appliance at a recycling centre. Do not dispose the used appliance together with the household waste.

Note:

Due to 2.4G wave technology adoption, The connection can be subject to interference from obstacles, Like walls, metals, Or other electronic devices. Please keep the space between the keyboard and USB receiver free of obstacle.

In line with the policy of continued development, The manufacturer reserves the right to amend. The specifications without prior notification. The illustrations in the user manual are for reference only. Please operate according to the real design.

FCC WARNING

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Note: The Grantee is not responsible for any changes or modifications not expressly approved by the party responsible for compliance. such modifications could void the user's authority to operate the equipment.

The device has been evaluated to meet general RF exposure requirement. This equipment complies with FCC's RF radiation exposure limits set forth for an uncontrolled environment. This device and its antenna(s) must not be co-located or conjunction with any other antenna or transmitter.