

# AZDEN CORPORATION

---

147 New Hyde Park Road ~ PO Box 10 ~ Franklin Square, NY 11010  
Phone 516-328-7500 ~ Fax 516-328-7506 ~ Website: [www.azdencorp.com](http://www.azdencorp.com) ~ E-mail: [walonso@azdencorp.com](mailto:walonso@azdencorp.com)

## 30BT Operating Instructions

### TRANSMITTER (30BT)

(1) Remove the battery compartment lid by sliding it down.

(2) Insert two fresh alkaline AA batteries into the compartment. Make sure the battery polarity is correct as marked inside the battery compartment.

In addition to the battery, inside the battery compartment you will find:

#### (3) Audio Input Level Control

Using the supplied screwdriver, turn the dial clockwise to increase input level. Turn the dial counterclockwise to decrease input level.

(4) Before the 30BT can be used, it and the associated receiver have to be set to the same frequency. Next, using the tip of the tool provided press the UP or DOWN button to the desired frequency, numbered from 1 to 240. Once the desired frequency number has been selected on the transmitter, set the receiver to the same frequency number.

#### (5) Power

Switches the Transmitter "On" or "Off".

#### (6) Mic Input Jack

The mic Input Jack accepts a 3.5mm jack from a microphone such as the supplied EX-503. Other lavalier and/or headset microphones can also be used.

#### (7) LCD Display

This display shows the frequency number from 1 to 240 and battery condition.