

Model: A03302		Test Number: 210505a	
MPE Calculator	RF Exposure uses EIRP for calculation. EIRP is based on TX power added to the antenna gain in dBi. dBi = dB gain compared to an isotropic radiator. S = power density in mW/cm ²		
	Transmitter Output power (dBm)	31.55	
	Transmitter Output power (mW)	1430.01	
Duty Cycle: 50	Output power (W)	1.4300	Antenna Gain (dBi)
	Output Power corrected for Duty Cycle (Watts)	0.715	Antenna Gain (Numeric)
			2.00
Tx Frequency (MHz)	1621	Calculation power (Watts)	0.72
		dBd + 2.17 = dBi	dBi to dBd
			2.2
			Antenna Gain (dBd)
			0.83
Cable Loss (dB)	0.0	Adjusted Power (dBm)	28.54
			Antenna minus cable (dBi)
			3.00
		Calculated ERP (mw) 865.586	EIRP = Po(dBm) + Gain (dB)
		Calculated ERP (W) 0.87	Radiated (EIRP) dBm
		Calculated EIRP (mw) 1,426.626	ERP = EIRP - 2.17 dB
		Calculated EIRP (W) 1.43	Radiated (ERP) dBm
			31.543
			29.373

Power density (S) mW/cm² = $\frac{EIRP}{4 \pi r^2}$

r (cm) EIRP (mW)

FCC radio frequency radiation exposure limits per 1.1310			
	Frequency (MHz)	Occupational Limit (mW/cm ²)	Public Limit (mW/cm ²)
5	30-300	1	0.2
50	300-1,500	ƒ/300	ƒ/1500
1	1,500-10,000	5	1
10			

IC radio frequency radiation exposure limits per RSS-102			
	Frequency (MHz)	Occupational Limit (W/m ²)	Public Limit (W/m ²)
0.6455 f ^{0.5}	100-6,000	0.6455 f ^{0.5}	
32.3	6,000-15,000	50	
	48-300		1.291
0.02619 f ^{0.6834}	300-6,000		0.02619 f ^{0.6834}
4.1	6,000-15,000	50	10

f = Transmit Frequency (MHz)	f (MHz) =	1621 MHz
P _T = Power Input to Antenna (mW)	P _T (mW) =	1,430.0130 mW
Duty cycle (percentage of operation)	% =	50 %
P _A = Adjusted Power due to Duty cycle or Cable Loss (mW)	P _A (mW) =	715.01 mW
G _N = Numeric Gain of the Antenna	G _N (numeric) =	2.00 numeric
S ₂₀ = Power Density of device at 20cm (mW/m ²)	S ₂₀ (mW/m ²) =	0.28 mW/m ²
S ₂₀ = Power Density of device at 20cm (W/m ²)	S ₂₀ (W/m ²) =	2.84 W/m ²
S _L = Power Density Limit (W/m ²)	S _L (W/m ²) =	4.090 W/m ²
R _C = Minimum distance to the Radiating Element for Compliance (cm)	R _C (cm) =	16.7 cm
S _C = Power Density of the device at the Compliance Distance R _C (W/m ²)	S _C (W/m ²) =	4.09 W/m ²
R ₂₀ = 20cm	R ₂₀ =	20 cm
		6.6 inches
		7.9 inches

Summary: Standalone MPE Calculations and Summary								
Band (MHz)	Tx Duty Cycle (%)	Tx Frequency (MHz)	Power Total (mW)	Antenna Gain (dBi)	S _L (W/m ²)	S ₂₀ (W/m ²)	R _C (cm)	S _C (W/m ²)
1616-1626	50	1621	715	3	4.090	2.84	16.7	4.09
Band (MHz)	Tx Duty Cycle (%)	Tx Frequency (MHz)	Power Total (mW)	Antenna Gain (dBi)	SL (W/m2)	S20 (W/m2)	RC (cm)	SC (W/m2)
2412-2462	100	2437	15.52	6.00	5.404	0.12	3.0	5.40

For Compliance with Canada General Population Limits, User Manual must indicate a minimum separation distance of 16.7 cm
Or in Meters for Compliance with Canada General Population Limits, a minimum separation distance of 0.17 Meters

Rogers Labs, Inc.
4405 West 259th Terrace
Louisburg, KS 66053
Phone/Fax: (913) 837-3214
Revision 1

Garmin International, Inc.
Model: AA3851
Test: 210505
Test to: CFR47 15C, RSS-210
File: AA3851 RFExp

SN's: 3367328349 / 3367328315
FCC ID: IPH-A3851
IC: 1792A-A3851
Date: March 14, 2022
Page 1 of 2

Model: AA3851		Test Number: 210505	
MPE Calculator	RF Exposure uses EIRP for calculation. EIRP is based on TX power added to the antenna gain in dBi. dBi = dB gain compared to an isotropic radiator. S = power density in mW/cm ²		
	Transmitter Output power (dBm)	11.91	
	Transmitter Output power (mW)	15.52	
Duty Cycle	100	Output power (W)	0.0155
		Output Power corrected for Duty Cycle (Watts)	0.016
		Antenna Gain (dB)	6
		Antenna Gain (Numeric)	3.98
Tx Frequency (MHz)	2437	Calculation power (Watts)	0.02
		dBd + 2.17 = dBi	dBi to dBd
			2.2
			Antenna Gain (dBd)
			3.83
Cable Loss (dB)	0.0	Adjusted Power (dBm)	11.91
			Antenna minus cable (dBi)
			6.00
		Calculated ERP (mw) 37.497	EIRP = Po(dBm) + Gain (dB)
		Calculated ERP (W) 0.037	Radiated (EIRP) dBm
		Calculated EIRP (mw) 61.802	ERP = EIRP - 2.17 dB
		Calculated EIRP (W) 0.062	Radiated (ERP) dBm
			15.740
<div style="border: 1px solid black; padding: 5px; width: fit-content;"> Power density (S) mW/cm² = $\frac{\text{EIRP}}{4 \pi r^2}$ r (cm) EIRP (mW) </div>			
Occupational Limit			
FCC radio frequency radiation exposure limits per 1.1310			
	5	mW/cm ²	Frequency (MHz)
	50	W/m ²	Occupational Limit (mW/cm ²)
			Public Limit (mW/cm ²)
			30-300
			1
			0.2
			300-1,500
			f/300
			f/1500
	1	mW/cm ²	1,500-10,000
	10	W/m ²	5
			1
Occupational Limit			
IC radio frequency radiation exposure limits per RSS-102			
	0.6455 f ^{0.5}	W/m ²	Frequency (MHz)
	39.7	W/m ²	Occupational Limit (W/m ²)
			Public Limit (W/m ²)
			100-6,000
			0.6455 f ^{0.5}
			6,000-15,000
			50
			48-300
			1.291
			300-6,000
			0.02619 f ^{0.6834}
			6,000-15,000
			50
			10
f = Transmitt Frequency (MHz)			f (MHz) =
P _T = Power Input to Antenna (mW)			P _T (mW) =
Duty cycle (percentage of operation)			% =
P _A = Adjusted Power due to Duty cycle or Cable Loss (mW)			P _A (mW) =
G _N = Numeric Gain of the Antenna			G _N (numeric) =
S ₂₀ = Power Density of device at 20cm (mW/m ²)		S ₂₀ =(P _A G _N)/(4πR ₂₀) ²	S ₂₀ (mW/m ²) =
S ₃₀ = Power Density of device at 20cm (W/m ²)		S ₂₀ =(P _A G _N)/(4πR ₂₀) ²	S ₂₀ (W/m ²) =
S _L = Power Density Limit (W/m ²)			S _L (W/m ²) =
R _C = Minimum distance to the Radiating Element for Compliance (cm)		R _C =√(P _A G _N /4πS _L)	R _C (cm) =
S _C = Power Density of the device at the Compliance Distance R _C (W/m ²)		S _C =(P _A G _N)/(4πR _C) ²	S _C (W/m ²) =
R ₂₀ = 20cm			R ₂₀ =
			2437 MHz
			15.5239 mW
			100 %
			15.52 mW
			3.98 numeric
			0.01 mW/m ²
			0.12 W/m ²
			5.404 W/m ²
			3.0 cm
			1.2 inches
			5.40 W/m ²
			20 cm
			7.9 inches
Summary: Standalone MPE Calculations and Summary			
Band (MHz)	Tx Duty Cycle (%)	Tx Frequency (MHz)	Power Total (mW)
2412-2462	100	2437	15.52
			Antenna Gain (dBi)
			6
			S _L (W/m ²)
			5.404
			S ₂₀ (W/m ²)
			0.12
			R _C (cm)
			3.0
			S _C (W/m ²)
			5.40

Rogers Labs, Inc.
 4405 West 259th Terrace
 Louisburg, KS 66053
 Phone/Fax: (913) 837-3214
 Revision 1

Garmin International, Inc.
 Model: AA3851
 Test: 210505
 Test to: CFR47 15C, RSS-210
 File: AA3851 RFExp

SN's: 3367328349 / 3367328315
 FCC ID: IPH-A3851
 IC: 1792A-A3851
 Date: March 14, 2022
 Page 2 of 2