

(10) THE ADJUSTMENT OF MODULATION LEVEL:

THE FIRST PIN OF MEASURING IC101 IS $400\text{mV}\pm 30\text{mV}$.

ADJUST VR101 TO MAKE THE MODULATION METER APPEAR
TO $18\pm 1\text{KHz}$.

(11) THE ADJUSTMENT OF TONE LEVEL:

CHANGE THE AF FILTERS OF MODULATION METER TO 60
KHz, AND ADJUST VR102 TO MAKE THE MODULATION METER
APPEAR TO $10\pm 2\text{KHz}$. (OR ADJUST SPAN=100KHz FROM
SPECTRUM ANALYZER TO MAKE THE DIFFERENCE
BETWEEN LEVEL AND MAIN FREQUENCY BE $16\text{dB}\pm 2$.