

**TEST REPORT
FROM
RFI GLOBAL SERVICES LTD**

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and
FCC Part 24: 2005 (Subpart E)

Test Report Serial No:
RFI/RPTE2/RP72183JD09A

Supersedes Test Report Serial No:
RFI/RPTE1/RP72183JD09A

This Test Report Is Issued Under The Authority Of Andrew Brown, Operations Manager:	
pp. 	
Tested By: Richelieu Quoi 	Checked By: Michael Derby 
Report Copy No: PDF01	
Issue Date: 07 February 2007	Test Dates: 26 September 2006

This report is issued in Adobe Acrobat portable document format (PDF). It is only a valid copy of the report if it is being viewed in PDF format with the following security options not allowed: Changing the document, Selecting text and graphics, Adding or changing notes and form fields.

This report may be copied in full. The results in this report apply only to the sample(s) tested.

RFI Global Services Ltd

Pavilion A, Ashwood Park, Ashwood Way, Basingstoke, Hampshire RG23 8BG

Telephone: +44 (0)1256 312000 Facsimile: +44 (0)1256 312001

Email: info@rfi-global.com Website: www.rfi-global.com

Registered in England and Wales. Company number:2117901

RFI GLOBAL SERVICES LTD

TEST REPORT

S.No. RFI/RPTE2/RP72183JD09A

Page: 2 of 20

Issue Date: 07 February 2007

**Partial Test of: Enfora L.P
GSM3408**

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

This page has been left intentionally blank.

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

Table of Contents

1. Client Information..... 4
2. Equipment Under Test (EUT) 5
3. Test Specification, Methods and Procedures..... 8
4. Deviations from the Test Specification 9
5. Operation of the EUT during Testing 10
6. Summary of Test Results 11
7. Measurements, Examinations and Derived Results 12
8. Measurement Uncertainty 15
9. Measurement Methods 16
Appendix 1. Test Equipment Used 20

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

1. Client Information

Company Name:	Enfora L.P
Address:	661 E 18th Street Plano US TX 75074
Contact Name:	Mr R Holden

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

2. Equipment Under Test (EUT)

The following information (with the exception of the Date of Receipt) has been supplied by the client:

2.1. Identification of Equipment Under Test (EUT)

Description:	Handheld Cradle for palm Tx and E2
Brand Name:	Enfora
Model Name or Number:	GSM3408
Unique Type Identification:	None Stated By Client
Serial Number:	3408390600004
IMEI Number:	011069000050049
Hardware Version Number:	A
Software Version Number:	0.7.6
FCC Identification:	MIVGSM3408
Country of Manufacture:	USA
Date of Receipt:	26 September 2006

2.2. Accessories

No accessories were supplied with the EUT:

2.3. Description of EUT

The equipment under test is a GSM3408 Quad-band wireless sled for a family of Palms PDAs that is capable of operating in GSM and GPRS technologies bands.

2.4. Modifications Incorporated in the EUT

During the course of testing the EUT was not modified.

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

2.5. Additional Information Related to Testing

Power Supply Requirement:	3.7V / 870 mAh
Intended Operating Environment:	Within GSM coverage
Equipment Category:	Portable (Standalone battery powered device)
Type of Unit:	GSM(850/1900) and GPRS(850/1900)

FCC Part 22

Transmit Frequency Range:	824.0 to 849.0 MHz		
Transmit Channels Tested:	Channel ID	Channel Number	Channel Frequency (MHz)
	Bottom	128	824.2
	Middle	189	836.4
	Top	251	848.8
Receive Frequency Range:	869.0 MHz to 894.0 MHz		
Receive Channels Tested:	Channel ID	Channel Number	Channel Frequency (MHz)
	Bottom	128	869.2
	Middle	189	881.4
	Top	251	893.8
Maximum Power Output (ERP):	25.3 dBm		

FCC Part 24

Transmit Frequency Range:	1850.0 to 1910.0 MHz		
Transmit Channels Tested:	Channel ID	Channel Number	Channel Frequency (MHz)
	Bottom	512	1850.2
	Middle	189	1879.8
	Top	251	1909.8
Receive Frequency Range:	1930.0 MHz to 1990.0 MHz		
Receive Channels Tested:	Channel ID	Channel Number	Channel Frequency (MHz)
	Bottom	512	1930.2
	Middle	189	1959.8
	Top	251	1989.8
Maximum Power Output (EIRP):	32.8 dBm		

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

2.6. Support Equipment

The following support equipment was used to exercise the EUT during testing:

Description:	PalmOne
Brand Name:	Tungsten
Model Name or Number:	Logpad E2
Unique Type Identification:	PN20UCP5V141
IC:	3905A-LEO
PHT Number:	T11901
Software Version Number:	V.45.2P
FCC ID:	08FLEO
Connected to Port:	Data Port Unique to Manufacturer
Country of Manufacturer:	China
Date of Receipt:	26 September 2006

Description:	Radio Communication Analyser
Brand Name:	Anritsu
Model Name or Number:	MT8820A
Serial Number:	6K00000647
Cable Length and Type:	1.5m Utiflex Cable
Connected to Port:	RF (Input/Output) Air Link

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

3. Test Specification, Methods and Procedures

Reference:	FCC Part 22: 2005 Subpart H (Cellular Radiotelephone Service)
Title:	Code of Federal Regulations, Part 22 (47CFR22) Personal Communication Services.

Reference:	FCC Part 24: 2005 Subpart E (Broadband PCS)
Title:	Code of Federal Regulations, Part 24 (47CFR24) Personal Communication Services.

3.1. Methods and Procedures

The methods and procedures used were as detailed in:

ANSI/TIA-603-B-2003

Land Mobile Communications Equipment, Measurements and performance Standards

ANSI C63.2 (1987)

Title: American National Standard for Instrumentation - Electromagnetic noise and field strength.

ANSI C63.4 (2003)

Title: American National Standard Methods of Measurement of Electromagnetic Emissions from Low Voltage Electrical and Electronic Equipment in the Range of 9 kHz to 40 GHz.

ANSI C63.5 (1988)

Title: American National Standard for the Calibration of antennas used for Radiated Emission measurements in Electromagnetic Interference (EMI) control.

ANSI C63.7 (1988)

Title: American National Standard Guide for Construction of Open Area Test Sites for performing Radiated Emission Measurements.

CISPR 16-1: (1999)

Title: Specification For Radio Disturbance and Immunity Measuring Apparatus and Methods. Part 1: Radio Disturbance and Immunity Measuring Apparatus.

3.2. Definition of Measurement Equipment

The measurement equipment used complied with the requirements of the standards referenced in the methods & procedures Section above. Appendix 1 contains a list of the test equipment used.

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

4. Deviations from the Test Specification

Only ERP and EIRP measurements were performed.

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

5. Operation of the EUT during Testing

5.1. Operating Modes

At the client's request the EUT was tested in the following operating mode(s):

GSM850 Call allocated.
PCS1900 Call allocated.

The reason for choosing this mode was that it has been defined by the client as being typical of normal use and likely to be a worst case.

5.2. Configuration and Peripherals

The EUT was tested in the following configuration(s):

Tested as a stand alone device.

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

6. Summary of Test Results

FCC Part 22

Range of Measurements	Specification Reference	Port Type	Compliance Status
Transmitter Effective Radiated Power (ERP)	C.F.R. 47 FCC Part 22: 2004 Section 22.913(a)	Antenna	Complied

FCC Part 24

Range of Measurements	Specification Reference	Port Type	Compliance Status
Transmitter Effective Isotropic Radiated Power (EIRP)	C.F.R. 47 FCC Part 24: 2004 Section 24.232	Antenna	Complied

6.1. Location of Tests

All the measurements described in this report were performed at the premises of RFI Global Services Ltd, Ewhurst Park, Ramsdell, Basingstoke, Hampshire, RG26 5RQ

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

7. Measurements, Examinations and Derived Results

7.1. General Comments

This Section contains test results only.

Measurement uncertainties are evaluated in accordance with current best practice. Our reported expanded uncertainties are based on standard uncertainties, which are multiplied by an appropriate coverage factor to provide a statistical confidence level of approximately 95%. Please refer to Section 8 for details of measurement uncertainties.

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

7.2. Test Results – FCC Part 22 (Subpart H)

7.2.1. Transmitter Effective Radiated Power (ERP): Section 22.913(a)

The EUT was configured as for effective radiated power as described in Section 9 of this report.

Tests were performed to identify the maximum effective radiated power (ERP).

Results:

Channel	Frequency (MHz)	Level (dBm)	Limit (dBm)	Margin (dB)	Result
Bottom	824.2	25.3	38.4	13.1	Complied
Middle	836.4	24.9	38.4	13.5	Complied
Top	848.8	22.7	38.4	15.7	Complied

Note(s):

1. ERP measurements are performed before testing only.

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

7.2.2. Transmitter Effective Isotropic Radiated Power (EIRP): Section 24.232

The EUT was configured as for effective isotropic radiated power as described in Section 9 of this report.

Tests were performed to identify the maximum effective isotropic radiated power (EIRP).

Results:

Channel	Measured Frequency (MHz)	Antenna Polarity	Maximum Transmitter EIRP (dBm)	Limit EIRP (dBm)	Margin (dB)	Result
Bottom	1850.2	Vertical	32.8	33.0	0.2	Complied
Middle	1879.8	Vertical	30.8	33.0	2.2	Complied
Top	1909.8	Vertical	30.6	33.0	2.4	Complied

Note(s):

1. EIRP measurements are performed before testing only.

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

8. Measurement Uncertainty

No measurement or test can ever be perfect and the imperfections give rise to error of measurement in the results. Consequently, the result of a measurement is only an approximation to the value of the measurand (the specific quantity subject to measurement) and is only complete when accompanied by a statement of the uncertainty of the approximation.

The expression of uncertainty of a measurement result allows realistic comparison of results with reference values and limits given in specifications and standards.

The uncertainty of the result may need to be taken into account when interpreting the measurement results.

The reported expanded uncertainties below are based on a standard uncertainty multiplied by an appropriate coverage factor, such that a confidence level of approximately 95% is maintained. For the purposes of this document “approximately” is interpreted as meaning “effectively” or “for most practical purposes”.

Measurement Type	Range	Confidence Level (%)	Calculated Uncertainty
Equivalent Isotropic Radiated Power (EIRP) and Effective Radiated Power (ERP)	GSM Bands	95%	±2.54 dB

The methods used to calculate the above uncertainties are in line with those recommended within the various measurement specifications. Where measurement specifications do not include guidelines for the evaluation of measurement uncertainty, the published guidance of the appropriate accreditation body is followed.

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

9. Measurement Methods

9.1. Effective Radiated Power (ERP) – FCC Part 22

ERP measurements were performed in accordance with the standard, against appropriate limits.

The ERP was measured with the EUT arranged on a non-conducting turntable on a standard test site compliant with ANSI C63.4 – 2003 Clause 5.4. The transmitter was fitted with an integral antenna; as such all radiated tests were performed with the unit operating into the integral antenna.

The level of the ERP was measured using a spectrum analyser.

The test antenna was positioned in the horizontal plane. The EUT was oriented in the X plane. The test antenna was then raised and lowered until a maximum peak was observed. The turntable was then rotated through 360 degrees and the maximum peak reading obtained. The height search was then repeated to take into consideration the new angular position of the turntable. The maximum reading observed was then recorded. This procedure was then repeated with the EUT oriented in the Y and Z planes. The highest reading taken in all 3 planes was recorded. The entire procedure was then repeated with the test antenna set in the vertical polarity.

Once the final amplitude (maximised) had been obtained, the EUT was substituted with a substitution antenna. For ERP measurements a dipole antenna was used. The centre of the substitution antenna was set to approximately the same centre location as the EUT. The substitution antenna was set to the horizontal polarity. The substitution antenna was matched into a signal generator using a 6 dB or greater attenuator. The signal generator was tuned to the EUT's frequency under test.

The test antenna was then raised and lowered to obtain a maximum reading on the spectrum analyser. The level of the signal generator output was then adjusted until the maximum recorded EUT level was observed. The signal generator level was noted. This procedure was repeated with both test antenna and substitution antenna vertically polarised. The ERP was calculated as:-

$$\text{ERP} = \text{Signal Generator Level} - \text{Cable Loss} + \text{Antenna Gain}$$

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

Effective Radiated Power (ERP) (Continued)

Circumstances where the signal generator could not produce the desired power, substitutions were performed with the signal generator set to 0 dBm. The radiated signal was maximised as previously described. The level indicated on the measuring receiver was noted. The delta between this level and the maximum level for the EUT was calculated and also noted. The ERP of the signal generator was calculated using the above formulae. The recorded delta was added to the calculated ERP to obtain the substituted EUT ERP.

$$\text{Delta (dB)} = \text{EUT} - \text{SG}$$

Where:

EUT = spectrum analyser indicated EUT raw level

SG = spectrum analyser indicated signal generator raw level

The signal generator actual ERP is calculated as:

$$\text{ERP SG} = \text{Signal Generator Level} - \text{Cable Loss} + \text{Antenna Gain}$$

The EUT ERP is calculated as:

$$\text{ERP EUT} = \text{ERP SG} + \text{Delta.}$$

The test equipment settings for ERP measurements were as follows:

Receiver Function	Setting
Detector Type:	Peak
Mode:	Not applicable
Bandwidth:	≥ Emission Bandwidth
Amplitude Range:	100 dB
Sweep Time:	Coupled

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

9.2. Effective Isotropic Radiated Power (EIRP) – FCC Part 24

EIRP measurements were performed in accordance with the standard, against appropriate limits.

The EIRP was measured with the EUT arranged on a non-conducting turn table on a standard test site compliant with ANSI C63.4 – 2003 Clause 5.4. The transmitter was fitted with an integral antenna; therefore all radiated tests were performed with the unit operating into the integral antenna.

The level of the EIRP was measured using a spectrum analyser.

The test antenna was positioned in the horizontal plane. The EUT was oriented in the X plane. The test antenna was then raised and lowered until a maximum peak was observed. The turntable was then rotated through 360 degrees and the maximum peak reading obtained. The height search was then repeated to take into consideration the new angular position of the turntable. The maximum reading observed was then recorded. This procedure was then repeated with the EUT oriented in the Y and Z planes. The highest reading taken in all 3 planes was recorded. The entire procedure was then repeated with the test antenna set in the vertical polarity.

Once the final amplitude (maximised) had been obtained, the EUT was substituted with a substitution antenna. For EIRP measurements a Horn antenna whose gain was based on an isotropic antenna was used, ERP measurements were done using a dipole. The centre of the substitution antenna was set to approximately the same centre location as the EUT. The substitution antenna was set to the horizontal polarity. The substitution antenna was matched into a signal generator using a 6 dB or greater attenuator. The signal generator was tuned to the EUT's frequency under test.

The test antenna was then raised and lowered to obtain a maximum reading on the spectrum analyser. The level of the signal generator output was then adjusted until the maximum recorded EUT level was observed. The signal generator level was noted. This procedure was repeated with both test antenna and substitution antenna vertically polarised. The EIRP was calculated as:-

$$\text{EIRP} = \text{Signal Generator Level} - \text{Cable Loss} + \text{Antenna Gain}$$

All measurements were performed using broadband Horn antennas.

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

Effective Isotropic Radiated Power (EIRP) (Continued)

Circumstances where the signal generator could not produce the desired power, substitutions were performed with the signal generator set to 0 dBm. The radiated signal was maximised as previously described. The level indicated on the measuring receiver was noted. The delta between this level and the maximum level for the EUT was calculated and also noted. The EIRP of the signal generator was calculated using the above formulae. The recorded delta was added to the calculated EIRP to obtain the substituted EUT EIRP.

$$\text{Delta (dB)} = \text{EUT} - \text{SG}$$

Where:

EUT = spectrum analyser indicated EUT raw level

SG = spectrum analyser indicated signal generator raw level

The signal generator actual EIRP is calculated as:

$$\text{EIRP SG} = \text{Signal Generator Level} - \text{Cable Loss} + \text{Antenna Gain}$$

The EUT EIRP is calculated as:

$$\text{EIRP EUT} = \text{EIRP SG} + \text{Delta.}$$

The test equipment settings for EIRP measurements were as follows:

Receiver Function	Setting
Detector Type:	Peak
Mode:	Not applicable
Bandwidth:	1 MHz
Amplitude Range:	100 dB
Sweep Time:	Coupled

Partial Test of: Enfora L.P
GSM3408

To: FCC Part 22: 2005 (Subpart H) and FCC Part 24: 2005 (Subpart E)

Appendix 1. Test Equipment Used

RFI No.	Instrument	Manufacturer	Type No.	Serial No.	Date Last Calibrated	Cal. Interval
A027	1-2 GHz Horn Antenna	Eaton	9188-2	301	8 June 06	36
A059	3146 Log Periodic Antenna	EMCO	3146	8902-2378	9 May 06	12
A020	Tripod	Thurley	TRI-74-S	N/A	N/A	-
C1065	20m cable	Rosenberger	UFA210-1-7872	0985	6 Oct 06	12
M1140	Radio Communications Analyser	Anritsu	MT8820A	6K0000647	N/A	-
M028	Spectrum Analyser	Rohde & Schwarz, Inc.	FSB	860 001/009 (RF), 860 161/007	18 August 2006	12
M1264	Thermo Hygrometer	RS	212-124	0	18 Feb 06	12
S202	Test Site 2	RFI	2	S202-15011990	Cal before use	-

NB In accordance with UKAS requirements, all the measurement equipment is on a calibration schedule.