

EMC TEST REPORT

Report No. : TS08120011-EME

Model No. : SDW3100

Issued Date : Feb. 09, 2009

Applicant: AboCom System, Inc
77, Yu-Yih Rd., Chu-Nan Chen, Miao-Lih Hsuan, Taiwan

Test Method/ Standard: FCC Part 15 Subpart E Section §15.207、§15.209、§15.407 and ANSI C63.4/2003.

Test By: Intertek Testing Services Taiwan Ltd.
No. 11, Lane 275, Ko-Nan 1 Street, Chia-Tung Li,
Shiang-Shan District, Hsinchu City, Taiwan

It may be duplicated completely for legal use with the allowance of the applicant. It shall not be reproduced except in full, without the written approval of Intertek Laboratory. The test result(s) in this report only applies to the tested sample(s).

The test report was prepared by: Sign on File
Sammi Liu/ Assistant

These measurements were taken by: Sign on File
Jacky Chen/ Engineer

The test report was reviewed by:

Name Kevin Chen
Title Chief Engineer

Table of Contents

- Summary of Tests3
- 1. Dynamic Frequency Selection (DFS) test4
 - 1.1 Operating environment4
 - 1.2 UNII Device Description4
 - 1.2.1 Operating mode5
 - 1.3 Test Protocol and Requirements6
 - 1.4 DFS Detection Thresholds and Limitations of each Parameter8
 - 1.5 Radar Test Waveforms9
 - 1.6 Radar Waveform Calibration.....12
 - 1.6.1 Radar Waveform Calibration Plots13
 - 1.7 Test instruments and setup19
 - 1.7.1 Test instruments19
 - 1.7.1.1 Deviation about the radar waveform.....19
 - 1.7.2 Test setup19
 - 1.8 DFS test results20
 - 1.8.1 Test summary20
 - 1.8.2 DFS test result21
 - 1.8.2.1 Channel Move time.....21
 - 1.8.2.2 Channel Closing Transmission Time27
 - 1.8.2.3 Non-Occupancy Period34



Summary of Tests

**802.11a/b/g wireless SD card
FCC ID: MQ4SDW3100**

Test	Reference	Results
Dynamic Frequency Selection (DFS) test	15.407(h), FCC 06-96	Pass

1. Dynamic Frequency Selection (DFS) test

1.1 Operating environment

Temperature:	23	°C
Relative Humidity:	58	%
Atmospheric Pressure	1023	hPa

1.2 UNII Device Description

1. The SDW3100 operates in the following UNII bands:

a. 5150-5350 MHz

2. Operating mode: (client)

- Client (Slave) EUT: (without radar detection)

The EUT was defined as the client without radar detection function.

There are no an “ad-hoc” or peer-to-peer mode for this device (please refer the declaration letter).

Associating peripheral:

The device was set up to associate with the master device (AIR-AP1242AG-A-K9).

3. The maximum EIRP of this device is 20.04 dBm from UNII band. This device doesn't exceed 27dBm EIRP, so no transmit power control is implemented.

4. Below are the available 50 ohm antenna assemblies and their corresponding gains. 0dBi gain was used to set the -63dBm threshold level (-64dBm+1dB) during calibration of the conducted test setup.

Antenna type: PCB printed

Antenna gain: 2.09 dBi

5. Information regarding the parameters of the detected Radar Waveforms is not available to the end user.

1.2.1 Operating mode

Performance was measured at an active frequency of 5300 MHz, and the radar signal was centered at 5300 MHz.

One laptop PC is connected to the AP via a wire Ethernet connection. A separate laptop PC is used as a host computer for the Station. The AP and the Station transmit output levels are set to normal operating condition during DFS testing.

System architectures were used under IP based mode.

1.3 Test Protocol and Requirements

For a Master Device, the DFS conformance requirements will be verified utilizing one short pulse radar type. Additionally, the Channel Move Time and Channel Closing Transmission Time requirements will be verified utilizing the long pulse radar type. The statistical performance check will be verified utilizing all radar type.

For a Client Device without DFS, the channel move time and channel closing transmission time requirements will be verified with one short pulse radar type.

For testing a Client Device with In-Service Monitoring, two configurations must be tested.

a. The Client Device detects the radar waveform:

The channel move time and channel closing transmission time requirements will be verified utilizing short pulse radar type and the long pulse radar type. The statistical performance check will be verified utilizing all radar types.

b. The Master Device detects the radar waveform:

The channel move time and channel closing transmission time requirements will be verified utilizing short pulse radar type.

A UNII network will employ a DFS function to:

- detect signals from radar systems and to avoid co-channel operation with these systems
- provide on aggregate a Uniform Spreading of the Operating Channels across the entire band. This applies to the 5250-5350 MHz and/ or 5470-5725 MHz bands.

Within the context of the operation of the DFS function, a UNII device will operate in either Master Mode or Client Mode. UNII devices operating in Client Mode can only operate in a network controlled by a UNII device operating in Master Mode.

The tables as below summarize the information contained.

Applicability of DFS Requirements Prior to Use of a Channel

Requirement	Operational Mode		
	Master	Client Without Radar Detection	Client With Radar Detection
Non-Occupancy Period	Yes	Not required	Yes
DFS Detection Threshold	Yes	Not required	Yes
Channel Availability Check Time	Yes	Not required	Not required
Uniform Spreading	Yes	Not required	Not required
UNII Detection Bandwidth	Yes	Not required	Yes

Applicability of DFS requirements during normal operation

Requirement	Operational Mode		
	Master	Client Without Radar Detection	Client With Radar Detection
DFS Detection Threshold	Yes	Not required	Yes
Channel Closing Transmission Time	Yes	Yes	Yes
Channel Move Time	Yes	Yes	Yes
UNII Detection Bandwidth	Yes	Not required	Yes

1.4 DFS Detection Thresholds and Limitations of each Parameter

Maximum Transmit Power	Value (See Notes 1 and 2)
≥ 200 mW	-64 dBm
≤ 200 mW	-62 dBm

Note 1: This is the level at the input of the receiver assuming a 0 dBi receive antenna.
 Note 2: Throughout these test procedures an additional 1 dB has been added to the amplitude of the test transmission waveforms to account for variations in measurement equipment. This will ensure that the test signal is at or above the detection threshold level to trigger a DFS response.

Parameter	Value
Non-occupancy Period	Minimum 30 minutes
Channel Availability Check Time	60 seconds
Channel Move Time	10 seconds (See Note 1)
Channel Closing Transmission Time	200 milliseconds + an aggregate of 60 milliseconds over remaining 10 second period (See Note 1 and 2)
UNII Detection Bandwidth	Minimum 80% of the UNII 99% transmission power bandwidth. (See Note 3)

Note 1: The instant that the Channel Move Time and the Channel Closing Transmission Time begins is as follows:

- For the Short Pulse Radar Test Signals this instant is the end of the Burst.
- For the Frequency Hopping radar Test Signal, this instant is the end of the last radar Burst generated.
- For the Long Pulse Radar Test Signal this instant is the end of the 12 second period defining the Radar Waveform.

Note 2: The Channel Closing Transmission Time is comprised of 200 milliseconds starting at the beginning of the Channel Move Time plus any additional intermittent control signals required to facilitate a Channel move (an aggregate of 60 milliseconds) during the remainder of the 10 second period. The aggregate duration of control signals will not count quiet periods in between transmissions.

Note 3: During the U-NII Detection Bandwidth detection test, radar type 1 is used and for each frequency step the minimum percentage of detection is 90 percent. Measurements are performed with no data traffic.

1.5 Radar Test Waveforms

This section provides the parameters for required test waveforms, minimum percentage of successful detections, and the minimum number of trials that must be used for determining DFS conformance. Step intervals of 0.1 microsecond for Pulse Width, 1 microsecond for PRI, 1 MHz for chirp width and 1 for the number of pulses will be utilized for the random determination of specific test waveforms.

Short Pulse Radar Test Waveforms

Radar Type	Pulse Width (μsec)	PRI (μsec)	Number of Pulses	Minimum Percentage of Successful Detection	Minimum Number of Trials
1	1	1428	18	60%	30
2	1-5	150-230	23-29	60%	30
3	6-10	200-500	16-18	60%	30
4	11-20	200-500	12-16	60%	30
Aggregate (Radar Types 1-4)				80%	120

A minimum of 30 unique waveforms are required for each of the Short Pulse Radar Type 2 through 4. For Short Pulse Radar Type 1, the same waveform is used a minimum of 30 times. If more than 30 waveforms are used for Short Pulse Radar Type 2 through 4, then each additional waveform must also be unique and not repeated from the previous waveforms.

The aggregate is the average of the percentage of successful detections of Short Pulse Radar Type 1-4.

Long Pulse Radar Test Waveforms

Radar Type	Pulse Width (μsec)	Chirp Width (MHz)	PRI (μsec)	Number of Pulses per Burst	Number of Bursts	Minimum Percentage of Successful Detection	Minimum Number of Trials
5	50-100	5-20	1000-2000	1-3	8-20	80%	30

The parameters for this waveform are randomly chosen. Thirty unique waveforms are required for the Long Pulse radar test signal. If more than 30 waveforms are used for the Long Pulse radar test signal, then each additional waveform must also be unique and not repeated from the previous waveforms.

Each waveform is defined as follows:


- 1) The transmission period for the Long Pulse Radar test signal is 12 seconds.
- 2) There are a total of 8 to 20 Bursts in the 12 second period, with the number of Bursts being randomly chosen. This number is Burst_Count.
- 3) Each Burst consists of 1 to 3 pulses, with the number of pulses being randomly chosen. Each Burst within the 12 second sequence may have a different number of pulses.
- 4) The pulse width is between 50 and 100 microseconds, with the pulse width being randomly chosen. Each pulse within a Burst will have the same pulse width. Pulses in different Bursts may have different pulse widths.
- 5) Each pulse has a linear FM chirp between 5 and 20 MHz, with the chirp width being randomly chosen. Each pulse within a Burst will have the same chirp width. Pulses in different Bursts may have different chirp widths. The chirp is centered on the pulse. For example, with a radar frequency of 5300 MHz and a 20 MHz chirped signal, the chirp starts at 5290 MHz and ends at 5310 MHz.
- 6) If more than one pulse is present in a Burst, the time between the pulses will be between 1000 and 2000 microseconds, with the time being randomly chosen. If three pulses are present in a Burst, the time between the first and second pulses is chosen independently of the time between the second and third pulses.
- 7) The 12 second transmission period is divided into even intervals. The number of intervals is equal to Burst_Count. Each interval is of length $(12,000,000 / \text{Burst_Count})$ microseconds. Each interval contains one Burst. The start time for the Burst, relative to the beginning of the interval, is between 1 and $[(12,000,000 / \text{Burst_Count}) - (\text{Total Burst Length}) + (\text{One Random PRI Interval})]$ microseconds, with the start time being randomly chosen. The step interval for the start time is 1 microsecond. The start time for each Burst is chosen independently.

A representative example of a Long Pulse radar test waveform:

- 1) The total test signal length is 12 seconds.
- 2) 8 Bursts are randomly generated for the Burst_Count.
- 3) Burst 1 has 2 randomly generated pulses.
- 4) The pulse width (for both pulses) is randomly selected to be 75 microseconds.

- 5) The PRI is randomly selected to be at 1213 microseconds.
- 6) Bursts 2 through 8 are generated using steps 3 – 5.
- 7) Each Burst is contained in even intervals of 1,500,000 microseconds. The starting location for Pulse 1, Burst 1 is randomly generated (1 to 1,500,000 minus the total Burst 1 length + 1 random PRI interval) at the 325,001 microsecond step. Bursts 2 through 8 randomly fall in successive 1,500,000 microsecond intervals (i.e. Burst 2 falls in the 1,500,001 – 3,000,000 microsecond range).

Graphical Representation of a Long Pulse radar Test Waveform



Frequency Hopping Radar Test Waveforms

Radars Type	Pulse Width (μ sec)	PRI (μ sec)	Pulses per Hop	Hopping Rate (kHz)	Hopping Sequence Length (msec)	Minimum Percentage of Successful Detection	Minimum Number of Trials
6	1	333	9	0.333	300	70%	30

For the Frequency Hopping Radar Type, the same *Burst* parameters are used for each waveform.

The hopping sequence is different for each waveform and a 100-length segment is selected from the hopping sequence defined by the following algorithm:

The first frequency in a hopping sequence is selected randomly from the group of 475 integer frequencies from 5250 – 5724 MHz. Next, the frequency that was just chosen is removed from the group and a frequency is randomly selected from the remaining 474 frequencies in the group. This process continues until all 475 frequencies are chosen for the set. For selection of a random frequency, the frequencies remaining within the group are always treated as equally likely.


1.6 Radar Waveform Calibration

The following equipment setup was used to calibrate the conducted radar waveform. A spectrum analyzer is used to establish the test signal level for each radar type. During this process, there were no transmissions by either Master or Client device. The spectrum analyzer was switched to the zero span (time domain) mode at the frequency of the radar waveform generator. The peak detection was utilized. The spectrum analyzer RBW and VBW were set to at least 3MHz.

The signal generator amplitude and/ or step attenuators were set so that the power level measured at the spectrum analyzer was equal to the DFS detection threshold that is required for the tests.

The signal generator amplitude was set so that the power level measured at the spectrum analyzer was -63dBm.


Conducted calibrated setup diagram:




1.6.1 Radar Waveform Calibration Plots

The following are the calibration plots for radar waveform of testing required.


Rader Type 1 (5300 MHz)




Rader Type 2 (5300 MHz)




Rader Type 3 (5300 MHz)




Rader Type 4 (5300 MHz)



Rader Type 5 (5300 MHz)



Rader Type 6 (5300 MHz)



1.7 Test instruments and setup

1.7.1 Test instruments

Intertek ID No.	Equipment	Brand	Model No.
EC1404-1	Spectrum Analyzer	Agilent	E4440A
NA	Radar waveform simulator software (Pulse Building)	Agilent	N7620A-101
EC1404-3	ESG Vector Signal Generator	Agilent	E4438C


Note: 1. The above equipments are within the valid calibration period.

1.7.1.1 Deviation about the radar waveform

No deviation.

1.7.2 Test setup

Setup for Client with injection at the Master (Client Mode without DFS detection)





1.8 DFS test results

1.8.1 Test summary


This EUT was defined as the Client without DFS detection.

Clause	Parameter	Required	Pass/ Fail
15.407	DFS Detection Threshold	Not Required	N/A
15.407	Channel Availability Check Time	Not Required	N/A
15.407	Channel Move Time	Applicable	Pass
15.407	Channel Closing Transmission Time	Applicable	Pass
15.407	Non-Occupancy Period	Applicable	Pass
15.407	Uniform Spreading	Not Required	N/A
15.407	UNII Detection Bandwidth	Not Required	N/A


1.8.2 DFS test result

1.8.2.1 Channel Move time


Rader Type 1 (5300 MHz)




Rader Type 2 (5300 MHz)




Rader Type 4 (5300 MHz)



Rader Type 5 (5300 MHz)




Rader Type 6 (5300 MHz)



1.8.2.2 Channel Closing Transmission Time


Rader Type 1 (5300 MHz)



Rader Type 2 (5300 MHz)

Reader Type


Traffic Signal




Rader Type 3 (5300 MHz)

Reader Type


Traffic Signal




Rader Type 4 (5300 MHz)




Rader Type 5 (5300 MHz)



Rader Type 6 (5300 MHz)



Traffic Signal (5300 MHz)



1.8.2.3 Non-Occupancy Period

No transmissions were observed on the previously active channel during 30 minutes observation time for the EUT.

