

The antenna kitting options for model F15G-CPAL-AB-C signal booster were done for 24 Outside Antenna kit options and 13 Inside Antenna kit options. The order of the attached calculations is as follows:

Outside Antenna Kit Options	
1	Kit 11-100400
2	Kit 11-7550
3	Kit 11-10050
4	Kit10-3050
5	Kit10-50400
6	Kit10-5050
7	Kit10-75400
8	Kit10-100400
9	Kit10-7550
10	Kit10-10050
11	Kit 9-50400
12	Kit 9-5050
13	Kit 9-75400
14	Kit 9-100400
15	Kit 9-7550
16	Kit 9-10050
17	Kit5-30400
18	Kit5-3050
19	Kit5-50400
20	Kit5-5050
21	Kit5-75400
22	Kit5-10400
23	Kit5-7550
24	Kit5-10050

Inside Antenna Kit Options	
1	Kit 52-5050-50
2	Kit 102-5050-50
3	Kit 103-7550-50
4	Kit 104-7550-50
5	Kit 3-5050
6	Kit 3-7550
7	Kit 3-10050
8	Kit 3-50400
9	Kit 3-75400
10	Kit 3-100400
11	Kit 32-50400-50
12	Kit 33-50400-50
13	Kit 34-50400-50

## Outside Antenna kit Options

Final Output Power Limited to 30 dBm EIRP in all Frequency Bands

Uplink Frequency(MHz)	704-716	776-787	824-849	1710-1755	1850-1910
Uplink Output Power(dBm)	23.6	23.8	23.7	22.8	21.9

1. Yagi 11dbi Antenna with 100' 400 N male Kit numbers: 11-100400

Antenna Gain (dBi)	10	10	10	11	11
Coax Cable Loss (dB)	4.8	4.8	4.8	7	7
Final Gain Less Loss (dB)	5.2	5.2	5.2	4	4
Final Output Power (dBm EIRP)	28.8	29	28.9	26.8	25.9

2. Yagi 11dbi Antenna with 75' 5D N male Kit numbers: 11-7550

Antenna Gain (dBi)	10	10	10	11	11
Coax Cable Loss (dB)	4.6	4.6	4.6	6	6
Final Gain Less Loss (dB)	5.4	5.4	5.4	5	5
Final Output Power (dBm EIRP)	29	29.2	29.1	27.8	26.9

3. Yagi 11dbi Antenna with 100' 5D N male Kit numbers: 11-10050

Antenna Gain (dBi)	10	10	10	11	11
Coax Cable Loss (dB)	5	5	5	8	8
Final Gain Less Loss (dB)	5	5	5	3	3
Final Output Power (dBm EIRP)	28.6	28.8	28.7	25.8	24.9

4. Panel 10dbi Antenna with 30' 5D N male Kit numbers:10-3050

Antenna Gain (dBi)	6.5	6.5	6.5	9.4	9.4
Coax Cable Loss (dB)	1.8	1.8	1.8	3.2	3.2
Final Gain Less Loss (dB)	4.7	4.7	4.7	6.2	6.2
Final Output Power (dBm EIRP)	28.3	28.5	28.4	29	28.1

5. Panel 10dbi Antenna with 50' 400 N male Kit numbers:10-50400

Antenna Gain (dBi)	6.5	6.5	6.5	9.4	9.4
Coax Cable Loss (dB)	2.8	2.8	2.8	3.5	3.5
Final Gain Less Loss (dB)	3.7	3.7	3.7	5.9	5.9
Final Output Power (dBm EIRP)	27.3	27.5	27.4	28.7	27.8

6. Panel 10dbi Antenna with 50' 5D N male Kit numbers:10-5050

Antenna Gain (dBi)	6.5	6.5	6.5	9.4	9.4
Coax Cable Loss (dB)	3	3	3	5	5
Final Gain Less Loss (dB)	3.5	3.5	3.5	4.4	4.4
Final Output Power (dBm EIRP)	27.1	27.3	27.2	27.2	26.3

7. Panel 10dbi Antenna with 75' 400 N male Kit numbers:10-75400

Antenna Gain (dBi)	6.5	6.5	6.5	9.4	9.4
Coax Cable Loss (dB)	3	3	3	5	5
Final Gain Less Loss (dB)	3.5	3.5	3.5	4.4	4.4
Final Output Power (dBm EIRP)	27.1	27.3	27.2	27.2	26.3

8. Panel 10dbi Antenna with 100' 400 N male Kit numbers:10-100400

Antenna Gain (dBi)	6.5	6.5	6.5	9.4	9.4
Coax Cable Loss (dB)	4.8	4.8	4.8	7	7
Final Gain Less Loss (dB)	1.7	1.7	1.7	2.4	2.4
Final Output Power (dBm EIRP)	25.3	25.5	25.4	25.2	24.3

9. Panel 10dbi Antenna with 75' 5D N male Kit numbers:10-7550

Antenna Gain (dBi)	6.5	6.5	6.5	9.4	9.4
Coax Cable Loss (dB)	4.6	4.6	4.6	6	6
Final Gain Less Loss (dB)	1.9	1.9	1.9	3.4	3.4
Final Output Power (dBm EIRP)	25.5	25.7	25.6	26.2	25.3

10. Panel 10dbi Antenna with 100' 5D N male Kit numbers:10-10050

Antenna Gain (dBi)	6.5	6.5	6.5	9.4	9.4
Coax Cable Loss (dB)	5	5	5	8	8
Final Gain Less Loss (dB)	1.5	1.5	1.5	1.4	1.4
Final Output Power (dBm EIRP)	25.1	25.3	25.2	24.2	23.3

11. Yagi 9dbi Antenna with 50' 400 N male Kit numbers:9-50400

Antenna Gain (dBi)	8	8	8	9.5	9.5
Coax Cable Loss (dB)	2.8	2.8	2.8	3.5	3.5
Final Gain Less Loss (dB)	5.2	5.2	5.2	6	6
Final Output Power (dBm EIRP)	28.8	29	28.9	28.8	27.9

12. Yagi 9dbi Antenna with 50' 5D N male Kit numbers:9-5050

Antenna Gain (dBi)	8	8	8	9.5	9.5
Coax Cable Loss (dB)	3	3	3	5	5
Final Gain Less Loss (dB)	5	5	5	4.5	4.5
Final Output Power (dBm EIRP)	28.6	28.8	28.7	27.3	26.4

13. Yagi 9dbi Antenna with 75' 400 N male Kit numbers:9-75400

Antenna Gain (dBi)	8	8	8	9.5	9.5
Coax Cable Loss (dB)	3	3	3	5	5
Final Gain Less Loss (dB)	5	5	5	4.5	4.5
Final Output Power (dBm EIRP)	28.6	28.8	28.7	27.3	26.4

14. Yagi 9dbi Antenna with 100' 400 N male Kit numbers:9-100400

Antenna Gain (dBi)	8	8	8	9.5	9.5
Coax Cable Loss (dB)	4.8	4.8	4.8	7	7
Final Gain Less Loss (dB)	3.2	3.2	3.2	2.5	2.5
Final Output Power (dBm EIRP)	26.8	27	26.9	25.3	24.4

15. Yagi 9dbi Antenna with 75' 5D N male Kit numbers:9-7550

Antenna Gain (dBi)	8	8	8	9.5	9.5
Coax Cable Loss (dB)	4.6	4.6	4.6	6	6
Final Gain Less Loss (dB)	3.4	3.4	3.4	3.5	3.5
Final Output Power (dBm EIRP)	27	27.2	27.1	26.3	25.4

16. Yagi 9dbi Antenna with 100' 5D N male Kit numbers:9-10050

Antenna Gain (dBi)	8	8	8	9.5	9.5
Coax Cable Loss (dB)	5	5	5	8	8
Final Gain Less Loss (dB)	3	3	3	1.5	1.5
Final Output Power (dBm EIRP)	26.6	26.8	26.7	24.3	23.4

17. Omni 5dbi Antenna with 30' 400 N male Kit numbers:5-30400

Antenna Gain (dBi)	5	5	5	5	5
Coax Cable Loss (dB)	1.1	1.1	1.1	1.8	1.8
Final Gain Less Loss (dB)	3.9	3.9	3.9	3.2	3.2
Final Output Power (dBm EIRP)	27.5	27.7	27.6	26	25.1

18. Omni 5dbi Antenna with 30' 5D N male Kit numbers:5-3050

Antenna Gain (dBi)	5	5	5	5	5
Coax Cable Loss (dB)	1.8	1.8	1.8	3.2	3.2
Final Gain Less Loss (dB)	3.2	3.2	3.2	1.8	1.8
Final Output Power (dBm EIRP)	26.8	27	26.9	24.6	23.7

19. Omni 5dbi Antenna with 50' 400 N male Kit numbers:5-50400

Antenna Gain (dBi)	5	5	5	5	5
Coax Cable Loss (dB)	2.8	2.8	2.8	3.5	3.5
Final Gain Less Loss (dB)	2.2	2.2	2.2	1.5	1.5
Final Output Power (dBm EIRP)	25.8	26	25.9	24.3	23.4

20. Omni 5dbi Antenna with 50' 5D N male Kit numbers:5-5050

Antenna Gain (dBi)	5	5	5	5	5
Coax Cable Loss (dB)	3	3	3	5	5
Final Gain Less Loss (dB)	2	2	2	0	0
Final Output Power (dBm EIRP)	25.6	25.8	25.7	22.8	21.9

21. Omni 5dbi Antenna with 75' 400 N male

Kit numbers:5-75400

Antenna Gain (dBi)	5	5	5	5	5
Coax Cable Loss (dB)	3	3	3	5	5
Final Gain Less Loss (dB)	2	2	2	0	0
Final Output Power (dBm EIRP)	25.6	25.8	25.7	22.8	21.9

22. Omni 5dbi Antenna with 100' 400 N male

Kit numbers:5-10400

Antenna Gain (dBi)	5	5	5	5	5
Coax Cable Loss (dB)	4.8	4.8	4.8	7	7
Final Gain Less Loss (dB)	0.2	0.2	0.2	-2	-2
Final Output Power (dBm EIRP)	23.8	24	23.9	20.8	19.9

23. Omni 5dbi Antenna with 75' 5D N male

Kit numbers:5-7550

Antenna Gain (dBi)	5	5	5	5	5
Coax Cable Loss (dB)	4.6	4.6	4.6	6	6
Final Gain Less Loss (dB)	0.4	0.4	0.4	-1	-1
Final Output Power (dBm EIRP)	24	24.2	24.1	21.8	20.9

24. Omni 5dbi Antenna with 100' 5D N male

Kit numbers:5-10050

Antenna Gain (dBi)	5	5	5	5	5
Coax Cable Loss (dB)	5	5	5	8	8
Final Gain Less Loss (dB)	0	0	0	-3	-3
Final Output Power (dBm EIRP)	23.6	23.8	23.7	19.8	18.9

## Inside Antenna kit Options

Uplink Frequency(MHz)	704-716	776-787	824-849	1710-1755	1850-1910
Measured Uplink Gain(dB)	60.40	61.40	60.50	64.40	64.30
MSCL Minimum (dB)	37	37.4	37.7	43	43.7
6' Separation Distance Path Loss (dB)	34.7	35.6	36.2	42.5	43.2
Polarity Loss (dB)	3.0	3.0	3.0	3.0	3.0
Max Antenna Gain with Coax Loss (dB)	0.7	1.2	1.5	2.5	2.5

1. 2 Whip 5dbi Antenna with 50' 5D N male & a 50 Ohm 2-Way Splitter Kit numbers: 52-5050-50

Antenna Gain (dBi)	5.0	5.0	5.0	5.0	5.0
Coax Cable Loss (dB)	6.5	6.5	6.5	8	8
Final Gain Less Loss (dB)	-1.5	-1.5	-1.5	-3.0	-3.0
Margin (dB)	-2.2	-2.7	-3.0	-5.5	-5.5

2. 2 Panel 10dbi Antenna with 50' 5D N male & a 50 Ohm 2-Way Splitter Kit numbers:102-5050-50

Antenna Gain (dBi)	6.5	6.5	6.5	9.4	9.4
Splitter/Coax Loss (dB)	6.5	6.5	6.5	8.5	8.5
Final Gain Less Splitter/Coax Loss (dB)	0	0	0	0.9	0.9
Margin (dB)	-0.70	-1.17	-1.46	-1.58	-1.59

3. 3 Panel 10dbi Antenna with 75' 5D N male & a 50Ohm 3-Way Splitter Kit numbers:103-7550-50

Antenna Gain (dBi)	6.5	6.5	6.5	9.4	9.4
Splitter/Coax Loss (dB)	9.6	9.6	9.6	11	11
Final Gain Less Splitter/Coax Loss (dB)	-3.1	-3.1	-3.1	-1.6	-1.6
Margin (dB)	-3.80	-4.27	-4.56	-4.08	-4.09

4. 4 Panel 10dbi Antenna with 75' 5D N male & three 50 Ohm 2-Way Splitter k it numbers:104-7550-50

Antenna Gain (dBi)	6.5	6.5	6.5	9.4	9.4
Splitter/Coax Loss (dB)	10.6	10.6	10.6	12	12
Final Gain Less Splitter/Coax Loss (dB)	-4.1	-4.1	-4.1	-2.6	-2.6
Margin (dB)	-4.80	-5.27	-5.56	-5.08	-5.09

## 5. Omni 3dBi Antenna with 50' 5D N Male

Kit numbers:3-5050

Antenna Gain (dBi)	3	3	3	3	3
Coax Cable Loss (dB)	3	3	3	5	5
Final Gain Less Loss (dB)	0	0	0	-2	-2
Margin (dB)	-0.70	-1.17	-1.46	-4.48	-4.49

## 6. Omni 3dBi Antenna with 75' 5D N Male

Kit numbers:3-7550

Antenna Gain (dBi)	3	3	3	3	3
Coax Cable Loss (dB)	4.6	4.6	4.6	6	6
Final Gain Less Loss (dB)	-1.6	-1.6	-1.6	-3	-3
Margin (dB)	-2.30	-2.77	-3.06	-5.48	-5.49

## 7. Omni 3dBi Antenna with 100' 5D N Male

Kit numbers:3-10050

Antenna Gain (dBi)	3	3	3	3	3
Coax Cable Loss (dB)	5	5	5	8	8
Final Gain Less Loss (dB)	-2	-2	-2	-5	-5
Margin (dB)	-2.70	-3.17	-3.46	-7.48	-7.49

## 8. Omni 3dBi Antenna with 50' 400 N Male

Kit numbers:3-50400

Antenna Gain (dBi)	3	3	3	3	3
Coax Cable Loss (dB)	2.8	2.8	2.8	3.5	3.5
Final Gain Less Loss (dB)	0.2	0.2	0.2	-0.5	-0.5
Margin (dB)	-0.50	-0.97	-1.26	-2.98	-2.99

## 9. Omni 3dBi Antenna with 75' 400 N Male

Kit numbers:3-75400

Antenna Gain (dBi)	3	3	3	3	3
Coax Cable Loss (dB)	3	3	3	5	5
Final Gain Less Loss (dB)	0	0	0	-2	-2
Margin (dB)	-0.70	-1.17	-1.46	-4.48	-4.49

## 10. Omni 3dBi Antenna with 100' 400 N Male

Kit numbers:3-100400

Antenna Gain (dBi)	3	3	3	3	3
Coax Cable Loss (dB)	4.8	4.8	4.8	7	7
Final Gain Less Coax /Splitter Loss(dB)	-1.8	-1.8	-1.8	-4	-4
Margin (dB)	-2.50	-2.97	-3.26	-6.48	-6.49

## 11. 2 Omni 3dBi Antenna with 50' 400 N male &amp; a 50 Ohm 2-Way Splitter

Kit numbers:32-50400-50

Antenna Gain (dBi)	3	3	3	3	3
Splitter/Coax Loss (dB)	5.8	5.8	5.8	6.5	6.5
Final Gain Less Splitter/Coax Loss (dB)	-2.8	-2.8	-2.8	-3.5	-3.5
Margin (dB)	-3.50	-3.97	-4.26	-5.98	-5.99

12. 3 Omni 3dBi Antenna with 50' 400 N male & a 50 Ohm 3-Way Splitter Kit numbers:33-50400-50

Antenna Gain (dBi)	3	3	3	3	3
Splitter/Coax Loss (dB)	7.8	7.8	7.8	8.5	8.5
Final Gain Less Splitter/Coax Loss (dB)	-4.8	-4.8	-4.8	-5.5	-5.5
Margin (dB)	-5.50	-5.97	-6.26	-7.98	-7.99

13. 4 Omni 3dBi Antenna with 50' 400 N male & three 50 Ohm 2-Way Splitter Kit numbers:34-50400-50

Antenna Gain (dBi)	3	3	3	3	3
Splitter/Coax Loss (dB)	8.8	8.8	8.8	9.5	9.5
Final Gain Less Splitter/Coax Loss (dB)	-5.8	-5.8	-5.8	-6.5	-6.5
Margin (dB)	-6.50	-6.97	-7.26	-8.98	-8.99