



Conducted Output Power


The PBA is fulfilled. The EUT was tested according to the requirements of the FCC 3G procedures and the TS 34.121. The EUT's WCDMA and HSPA function is Release 6 version supporting HSDPA Category 8, and HSUPA Category 5. A detailed analysis of the output power for all WCDMA, HSPDA, and HSPA (HSUPA&HSDPA) modes is provided in the tables below. According to the FCC 3G procedures, handsets with both HSDPA and HSUPA should be tested according to Release 6 HSPA test procedures, and the EUT does not support VOIP function over the HSPA function. Device was tested according to procedure KDB941225 - section Release 6 HSPA Data Devices as documented/evaluated in the following table. Power values for HSPA are less than ¼ dB higher than the basic 12.2 kbps RMC configurations in WCDMA.

WCDMA Test mode - Conducted Power							
Mode	Setup	Cell band (850)			PCS band (1900)		
		CH4132	CH4182	CH4233	CH9262	CH9400	CH9538
		826.4 (MHz)	836.4 (MHz)	846.6 (MHz)	1852.4 (MHz)	1880.0 (MHz)	1907.6 (MHz)
R99- WCDMA	RMC 12.2Kbps	22.74	22.8	22.94	20.66	20.74	20.35
R5-HSDPA	HSDPA - subtest 1	22.72	22.74	22.85	20.54	20.58	20.25
	HSDPA - subtest 2	21.94	22.04	22.23	20.26	20.33	19.91
	HSDPA - subtest 3	22.1	22.03	22.24	20.21	20.38	19.97
	HSDPA - subtest 4	21.51	21.47	21.54	19.82	19.91	19.55
R6- HSPA (HSUPA&HSDPA)	HSUPA - subtest 1	22.4	22.21	22.59	20.3	20.47	20.3
	HSUPA - subtest 2	19.98	19.81	20.08	18.22	18.23	18.01
	HSUPA - subtest 3	21.25	21.08	21.32	19.31	19.3	19.04
	HSUPA - subtest 4	20.77	20.58	20.81	18.66	18.93	18.6
	HSUPA - subtest 5	22.4	22.07	22.31	20.26	20.29	20.16



WCDMA Setup Configuration:

- a. The EUT was connected to Base Station referred to the drawing of Setup Configuration.
- b. The RF path losses were compensated into the measurements.
- c. A call was established between EUT and Base Station with following setting
 - i. Data rates: Varied from RMC 12.2Kbps.
 - ii. RMC Test Loop=Loop Mode 1
 - iii. Power Ctrl Mode= All Up bits.
- d. The transmitted maximum output power was recorded.



Setup Configuration



HSDPA Setup Configuration

- a. The EUT was connected to Base Station referred to the drawing of Setup Configuration.
- b. The RF path losses were compensated into the measurements.
- c. A call was established between EUT and Base Station with following setting:
 - i. Set Gain Factors(β_c , and β_d) and parameters were set according to each
 - ii. specific sub-test in the following table, C10.1.4, quoted from the TS 34.121.
 - iii. Set RMC12.2Kbps + HSDPA mode.
 - iv. Set Cell Power = -86 dBm
 - v. Set HS-DSCH Configuration Type to FRC (H-set 1, QPSK)
 - vi. Select HSDPA Uplink Parameters.
 - vii. Set DeltaACK , DeltaNACK and DeltaCQI =8.
 - viii. Set Ack-Nack Repetition Factor to 3
 - ix. Set CQI Feedback Cycle (k) to 4 ms
 - x. Set CQI Repetition Factor to 2 .
 - xi. Power Ctrl Mode= All Up bits.
- d. The transmitted maximum output power was recorded.

Table C.10.1.4: β values for transmitter characteristics tests with HS-DPCCH

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	β_{hs} (Note 1, Note 2)	CM (dB) (Note 3)	MPR (dB) (Note 3)
1	2/15	15/15	64	2/15	4/15	0.0	0.0
2	12/15 (Note 4)	15/15 (Note 4)	64	12/15 (Note 4)	24/15	1.0	0.0
3	15/15	8/15	64	15/8	30/15	1.5	0.5
4	15/15	4/15	64	15/4	30/15	1.5	0.5

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 30/15$ with $\beta_{hs} = 30/15 * \beta_c$.

Note 2: For the HS-DPCCH power mask requirement test in clause 5.2C, 5.7A, and the Error Vector Magnitude (EVM) with HS-DPCCH test in clause 5.13.1A, and HSDPA EVM with phase discontinuity in clause 5.13.1AA, Δ_{ACK} and $\Delta_{NACK} = 30/15$ with $\beta_{hs} = 30/15 * \beta_c$, and $\Delta_{CQI} = 24/15$ with $\beta_{hs} = 24/15 * \beta_c$.

Note 3: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCCH, DPCCH and HS-DPCCH the MPR is based on the relative CM difference. This is applicable for only UEs that support HSDPA in release 6 and later releases.

Note 4: For subtest 2 the β_c/β_d ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 11/15$ and $\beta_d = 15/15$.



HSPA(HSUPA & HSPDA) Setup Configuration

- a. The EUT was connected to Base Station referred to the drawing of Setup Configuration.
- b. The RF path losses were compensated into the measurements.
- c. A call was established between EUT and Base Station with following setting * :
 - i. Call Configs = 5.2B, 5.9B, 5.10B, and 5.13.2B with QPSK
 - ii. Set the Gain Factors (β_c and β_d) and parameters (AG Index) were set according to each specific sub-test in the following table, C11.1.3, quoted from the TS 34.121.
 - iii. Set Cell Power = -86 dBm
 - iv. Set Channel Type = 12.2k + HSPA
 - v. Set UE Target Power
 - vi. Power Ctrl Mode= Alternating bits.
 - vii. Set and observe the E-TFCI
 - viii. Confirm that E-TFCI is equal to the target E-TFCI of 75 for sub-test 1, and other subtests' E-TFCI.
- d. The transmitted maximum output power was recorded.

Table C.11.1.3: β values for transmitter characteristics tests with HS-DPCCH and E-DCH

Sub-test	β_c	β_d	β_d (SF)	β_o/β_d	β_{HS} (Note 1)	β_{ec}	β_{ed} (Note 5) (Note 6)	β_{ed} (SF)	β_{ed} (Codes)	CM (dB) (Note 2)	MPR (dB) (Note 2)	AG Index (Note 6)	E-TFCI
1	11/15 (Note 3)	15/15 (Note 3)	64	11/15 (Note 3)	22/15	209/25	1309/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67
3	15/15	9/15	64	15/9	30/15	30/15	β_{ed1} : 47/15 β_{ed2} : 47/15	4	2	2.0	1.0	15	92
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15 (Note 4)	15/15 (Note 4)	64	15/15 (Note 4)	30/15	24/15	134/15	4	1	1.0	0.0	21	81

Note 1: $\Delta_{ACK}, \Delta_{NACK}$ and $\Delta_{CQI} = 30/15$ with $\beta_{hs} = 30/15 * \beta_c$.

Note 2: CM = 1 for $\beta_o/\beta_d = 12/15, \beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.

Note 3: For subtest 1 the β_o/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 10/15$ and $\beta_d = 15/15$.

Note 4: For subtest 5 the β_o/β_d ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signalled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 14/15$ and $\beta_d = 15/15$.

Note 5: In case of testing by UE using E-DPDCH Physical Layer category 1, Sub-test 3 is omitted according to TS25.306 Table 5.1g.

Note 6: β_{ed} can not be set directly, it is set by Absolute Grant Value.

* For details settings in the Agilent 8960 test equipment, please refer to the user guide “HSUPA Measurement Guide with 8960 V7.5.0 Release 7 (2007-06) Ver.: v.02.18”



Example for HSPA Subtest 1, and other subtests following table, C11.1.3

Call Setup Screen						
Call Control	Active Cell Operating Mode				Call Parms	
Channel (UARFCN) Info	UE Information				Cell Power	
	INSI: IMEI: Power Class:				-86.00 dBm/3.84 MHz	
Cell Parameters	UE Expected Open Loop Transmit Power				Channel Type	
	Initial PRACH TX Power: -11.70 dBm Initial DPCH TX Power: -0.56 dBm				12.2k + HSPA	
Generator Info	Uplink Parameters				Paging Service	
		Value			RB Test Mode	
Uplink Parameters	PRACH Preambles	64			HSPA Parameters	
	PRACH Ramping Cycles(MAX)	2				
	Available Subchannels (Bit Mask)	000000000001				
UE Rep Neas	Uplink DPCH Scrambling Code	0			34,121 Preset Call Configs	
	Uplink DPCH Bc/Bd Control	Manual				
	Manual Uplink DPCH Bc	11			Channel (UARFCN) Parms	
Close Menu	Manual Uplink DPCH Bd	15				
	Maximum Uplink Transmit Power Level	21 dBm				
		Active Cell	Sys Type: UTRA FDD			
		Idle				
2 of 4		IntRef	Offset		1 of 3	

Gain Factors ($\beta_c = 11$ and $\beta_d = 15$)

Call Setup Screen						
Call Control	Active Cell Operating Mode				Serving Grant	
Additional Screens	UE Information				AG Mode	
	INSI: IMEI: Power Class:				Single Shot	
Cell Parameters	UE Expected Open Loop Transmit Power				Single Shot AG	
	Initial PRACH TX Power: -11.70 dBm Initial DPCH TX Power: -0.56 dBm				20: (119/15)*2	
Generator Info	Call Processing Status				Send Single Shot Absolute Grant	
	Current Service Type	None			Send Relative Grant Up	
Uplink Parameters	Min Status:	Abs Single Shot AG			Send Relative Grant Down	
	Min State:	Index 15: (67/15)*2			Return	
	Current DPCH	Index 16: (75/15)*2				
UE Rep Neas	HSUPA In	Index 17: (84/15)*2				
	UE Rep E-DCH	Index 18: (95/15)*2				
Trig Output Setup	Last Received	Index 19: (106/15)*2				
Sys Frame Clock	Throughput:	Index 20: (119/15)*2				
	ACKs Transmit					
		Active Cell	Sys Type: UTRA FDD			
		Idle				
2 of 4		IntRef	Offset		1 of 2	

Example: AG – Index = 20 for HSPA subtest 1



Call Setup Screen						
Screen Ctrl	Recorded E-TFCI Information					E-TFCI Record
Channel (UARFCN) Info	E-TFCI Recording State					E-TFCI Rec Count
	Idle					15
HSPA Information	Recorded E-TFCI Values					Start Recording E-TFCI Values
E-TFCI Recording Information	1: 75	11: 75	21: ----	31: ----	41: ----	
	2: 75	12: 75	22: ----	32: ----	42: ----	
	3: 75	13: 75	23: ----	33: ----	43: ----	
	4: 75	14: 75	24: ----	34: ----	44: ----	
	5: 75	15: 75	25: ----	35: ----	45: ----	
	6: 75	16: ----	26: ----	36: ----	46: ----	
	7: 75	17: ----	27: ----	37: ----	47: ----	Send Step Up TPC Bit Pattern
	8: 75	18: ----	28: ----	38: ----	48: ----	
	9: 75	19: ----	29: ----	39: ----	49: ----	Send Step Down TPC Bit Pattern
	10: 75	20: ----	30: ----	40: ----	50: ----	
Clear UE Info	15/15					
Return						Return
	Background	Active Cell Connected		Sys Type: UTRA FDD		
		IntRef	Offset			

Example: Confirm that E-TFCI is equal to the target E-TFCI of 75 for sub-test 1

Reference:

- [1.] 941225 D01 SAR test for 3G devices v02, SAR Measurement Procedures for 3G Devices CDMA 2000/Ev-Do/WCDMA/HSDPA/HSPA Oct. 2007 Laboratory Division Office of Engineering and Technology Federal Communications Commission
- [2.] TS 34.121 Universal Mobile Telecommunications System (UMTS); Terminal Conformance Specification, Radio Transmission and Reception (FDD)
- [3.] HSUPA Measurement Guide with 8960 V7.5.0 Release 7 (2007-06) Ver.: v.02.18