T450 PoC Radio Quick Guide

Please read carefully the Safety Information before using the product.

Kirisun Communication Co., Ltd.

Version : V1.0

Appearance





Attachments

No.	Name
1	Radio
2	Battery
3	Antenna
4	USB cable
5	Power adapter
6	Quick Guide
7	Safety information
8	Strap
9	Desktop charger (optional)

Charging the Battery

Method 1: Charging through Micro USB Cable

1. Connect the USB cable to a qualified AC power socket as required.
2. Power off the radio. Connect one end of the micro USB cable to the power adapter, and the other end to the USB port on the radio. Red indicator light is on.

Method 2: Desktop charger

1. Connect the power cable into a qualified AC power socket.
2. Connect the USB cable of the power adapter to the USB port at the back of the desktop charger. Green indicator light is on.
3. Insert the battery only or together with the radio into the desktop charger.
4. Make sure the battery contacts the charging points properly and red indicator light is on.
5. When the indicator light turns from red to green, charging is finished.

Installing the Battery

1. Press the upper part of the belt clip gently so that it springs up. (Figure ①)
2. Insert the two positioning columns at the top of the battery into the corresponding holes at the back of the radio, and push the battery downwards until it reach the upper edge of the battery slot. (Figure ②)
3. Press the battery down, and you will hear a "do" sound. The battery is installed. (Figure ③)

Uninstalling the battery

1. Press the upper part of the belt clip gently so that it springs up. (Figure ①)
2. Unlock the battery latch by pushing it to the right, and the battery will go up. (Figure ②)
3. Take off the battery. (Figure ③)

Installing a SIM Card

1. Remove the battery and the SIM card holder in the upper part of the radio. Open the cover of the SIM card holder rightwards and then open the cover.
2. Insert a Nano-SIM card into the guide slot of the cover, and make sure the card is in position.
3. Press the cover of the SIM card holder back onto the holder, and then close rightwards to lock it.

Note: Please use a standard Nano-SIM card.

LED Indicator

Indicator State	Device State
Red light on	Voice signals inputted or received improperly Device booted Data access to the server or SIM card failed In locked condition (Figure 1) Downloading/Upgrading radio voice started
Green light on	In individual call standby state
Blue light on	In individual call standby state
Red light flashing fast	Incoming individual call Invalid SIM card
Red light flashing slow	Network registration succeeded. Enter standby state.
Blue light flashing fast	Registering to protocols Device not configured on the server. Device not fully configured (...) Device booted
No light	In power-off state.

Programmable keys

To suit you operation habits, programmable keys 1 and 2 are provided. You may enable various functions on these keys using the CPS. The functions are listed as below.

No.	Function	Description
1	Alarm on/off	Send/quit an emergency alarm.
2	Remaining battery capacity	Announce remaining battery capacity.
3	User announcement	Announce the user name of the radio.
4	Group announcement	Announce the current group in which you are.
5	Playback	Play back the latest 5S voice records.
6	Bluetooth on/off	Enable/disable Bluetooth function.
7	Wi-Fi on/off	Enable/disable Wi-Fi function.
8	Individual Call	Make a quick individual call.
9	Kill Call	Make a kill call.
10	Broadcast	Make a broadcast call.

Icons

Icon	Description
	2G/3G/4G received signal strength
2G,3G,4G	2G/3G/4G transmission
	Wi-Fi signal strength
	Searching GPS signal
	GPS signal acquired
	In group call
	In individual call
	In all call
	Remaining battery capacity
	Short message
	Bluetooth enabled
	Connected to Bluetooth device
	In emergency alarm
	Alarm message
	Stun
	Kill

Basic Operation

1. Powering On/Off

To power on the radio, rotate the 【Power/volume knob】 clockwise until you hear a tick. Wait a while. The screen backlight and yellow indicator light is on, and the message "Starting" is displayed on the screen.

To power off the radio, rotate the 【Power/volume knob】 counterclockwise until you hear a tick.

2. Adjusting the Volume

Rotate the 【Power/volume knob】 clockwise to increase the volume, or counterclockwise to decrease it.

3. Individual Call

① Initiating Individual Call

- In the standby status, press the 【OK】 key, select 【Contacts】, and choose a contact.
- Press the 【OK】 key, select 【Initiate Individual Call】. You will hear a voice prompt "Enter individual call mode".
- Press the 【PTT】 key.

② Ending Individual Call

An individual call can be ended in either of the following ways.

- During an individual call, press the 【OK】 key, select 【Contacts】, and select first Individual Call.
- After entering individual call mode, if you do not press the 【PTT】 key within 5 seconds, the radio will quit this mode, and you will hear a voice prompt "Individual call timed out".

4. Group Call

① Initiating Group Call

Under individual/group/broadcast call mode, you can call the members of a group by pressing the 【PTT】 key. If there is no member online, you will hear a voice prompt "Group call timed out" after a period of time terminated.

Note: A group is set through the network management system.

② Switching Groups

Method 1: After the radio registers successfully and enters standby state, rotate the 【Group knob】 to select a group.

Method 2: In the standby interface, press the 【Menu】 key to enter the Menu interface, press navigation keys to select 【Group List】 and then a group, and then press the 【OK】 key.

5. All Call

After programming an all-call key through the CPS, you may enter all-call mode by pressing the key, and then initiate an all call by pressing the 【PTT】 key. An all call should be answered within 5 seconds,otherwise it will be quitted. An all call can interrupt an individual call or a group call.

6. Broadcast Call

After programming a broadcast call key through the CPS, you may enter broadcast-call mode by pressing the key, and then initiate a broadcast call by pressing the 【PTT】 key. An broadcast call should be answered within 3 seconds,otherwise it will be quitted.An broadcast call can interrupt an individual call or a group call.

7. Receiving a Call

By switching to a group set through the NMS, the radio can receive an individual call, a group call or an all call from the group and output voice.

8. Late Entry

This function enables the radio to join an undergoing group call after a delay.

9. Priority Call

Different call priority can be set on the radio. A radio with a higher call priority initiates a call prior to a radio with a lower call priority.

Note: The default call time of all types of calls is 60 seconds, which is modifiable through the NMS. A call is terminated automatically after this time is up.

10. Playback

After voice recording and playback are enabled on the NMS, you can download the voice files to the internal 5th voice records by pressing a pre-programmed playback key.

11. Positioning

To enable or disable GPS positioning, go to the standby interface, press the 【OK】 key, select 【Setting】 and then 【GPS】, and slide the switch.

The GPS module inside the radio locates the radio and reports position information to the NMS. The real-time location and movement track of the radio can be displayed on a GIS map on the NMS or a dispatcher.

12. Low-Power Alert

When the remaining battery of the radio is below 10%, you will hear the voice alert "Low power," at a certain interval. Please replace or charge the battery after powering off the radio.

13. Wi-Fi

To enable or disable Wi-Fi, go to the standby interface, press the【OK】key, select【Setting】and then【Wi-Fi】, and slide the switch.

By enabling Wi-Fi, you can search Wi-Fi networks nearby in real time. The radio can only be connected to a Wi-Fi hotspot, which should be preset through the CPS. To view or select from preset hotspots, go to Saved Network.

14. Bluetooth

To enable or disable Bluetooth, go to the standby interface, press the【OK】key, select【Setting】and then【Bluetooth】, and slide the switch.

After enabling Bluetooth, you can connect the radio to a Bluetooth earphone by wire.

15. Short Message

To view sent short messages, go to the standby interface, press the【OK】key, and select【Message】- Short Message and then Inbox.

16. Mobile Networks

GSM, WCDMA, TDD-LTE and FDD-LTE networks are supported.

17. Advanced Functions

The radio supports manual alarm. After programming an emergency alarm key through the CPS, you may enter alarm mode by pressing the key to quit an emergency alarm. There are two modes of an emergency alarm.

Silent Alarm: In this mode, the radio sends an alarm silently, but receives an acknowledgment of a voice prompt "Alarm from ***".

Alarm and Call: If silent alarm is disabled, the radio sends an alarm and rings a siren, but receives an alarm with a voice prompt "Alarm from*** " and rings a siren.

To view the alarms sent and received, go to the standby interface, press the【OK】key, and select 【Message】 - 【SOS Message】.

Troubleshooting

No.	Problem	Solution
1	Power-on failed	Reason: The battery is used up. Solution: Charge or replace the battery.
		Reason: Volume switch is faulty. Solution: Get it repaired at the specified maintenance center.
2	Small voice	Reason: Speak too far from the microphone. Solution: The suggested distance is 3~10 cm from the mouth.
		Reason: The volume is too low. Solution: Increase the volume.
3	Communication failed	Reason: SIM card expired. Solution: Renewal or replace the card.
		Reason: Network signal is poor. Solution: Choose a correct group and try again.
		Reason: The platform service expired. Solution: Renew PoC platform service again.

This document is only for reference, and actual product prevails.
Kirisun reserves the right to the final interpretation of this document.

FCC Statement

15.19 Labeling requirements.
This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

15.21 Information to user.
Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

15.105 Information to user.
This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Specific Absorption Rate (SAR) information:
This product meets the government's requirements for exposure to radio waves. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The standards include a substantial safety margin designed to assure the safety of all persons regardless of age or health.

FCC RF Exposure Information and Statement The SAR limit of USA (FCC) is 1.6 W/kg averaged over one gram of tissue. This device was tested for typical body-worn operations with the back of the handset kept 15mm for body worn. To maintain compliance with FCC RF exposure requirements, use accessories that maintain a 15mm separation distance between the user's body and the back of the handset. The use of belt clips, holsters and similar accessories should not contain metallic components in its assembly. The use of accessories that do not satisfy these requirements may not comply with FCC RF exposure requirements, and should be avoided.

IC Statement

This device complies with Industry Canada's licence-exempt RSSs. Operation is subject to the following two conditions:
(1)This device may not cause interference;
(2)This device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes: (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Specific Absorption Rate (SAR) information:
This product meets the government's requirements for exposure to radio waves. The guidelines are based on standards that were developed by independent scientific organizations through periodic and thorough evaluation of scientific studies. The standards include a substantial safety margin designed to assure the safety of all persons regardless of age or health.

IC RF Exposure Information and Statement The SAR limit of USA (IC) is 1.6 W/kg averaged over one gram of tissue. This device was tested for typical body-worn operations with the back of the handset kept 15mm for body worn. To maintain compliance with IC RF exposure requirements, use accessories that maintain a 15mm separation distance between the user's body and the back of the handset. The use of belt clips, holsters and similar accessories should not contain metallic components in its assembly. The use of accessories that do not satisfy these requirements may not comply with IC RF exposure requirements, and should be avoided.

RED Statement

1. Risk of explosion if battery is replaced by an incorrect type. Dispose of used batteries according to the instructions.
2. The product shall only be connected to a USB interface of version USB2.0 or higher.
3. Adapter shall be installed near the equipment and shall be easily accessible.
4. The operating temperature of the EUT can't exceed 45℃ and shouldn't be less than 0℃.
5. The plug considered as disconnect device of adapter.
6. The device complies with RF specifications when the device used at 20mm from your body. Use only supplied or approved antenna.
7. User careful with the earphone maybe possible excessive sound pressure from earphones and headphones can cause hearing loss.

Hereby, Kirisun Communication Co., Ltd. declares that this mobile phone product is in compliance with essential requirements and other relevant provisions of Directive 2014/53/EU. This product is allowed to be used in all EU member states.

CE

MDN0A0B00016