



Leica CS10/CS15 User Manual

Version 1.0
English

- when it has to be **right**

Leica
Geosystems

Introduction

Purchase

Congratulations on the purchase of a Leica CS10/CS15.



This manual contains important safety directions as well as instructions for setting up the product and operating it. Refer to "5 Safety Directions" for further information.

Read carefully through the User Manual before you switch on the product.

Product identification





The type and serial number of your product are indicated on the type plate. Enter the type and serial number in your manual and always refer to this information when you need to contact your agency or Leica Geosystems authorised service workshop.

Type: _____

Serial No.: _____

Symbols

The symbols used in this manual have the following meanings:

Type	Description
 Danger	Indicates an imminently hazardous situation which, if not avoided, will result in death or serious injury.
 Warning	Indicates a potentially hazardous situation or an unintended use which, if not avoided, could result in death or serious injury.
 Caution	Indicates a potentially hazardous situation or an unintended use which, if not avoided, may result in minor or moderate injury and/or appreciable material, financial and environmental damage.
	Important paragraphs which must be adhered to in practice as they enable the product to be used in a technically correct and efficient manner.

Trademarks



- Windows is a registered trademark of Microsoft Corporation in the United States and other countries
- CompactFlash and CF are trademarks of SanDisk Corporation
- Bluetooth is a registered trademark of Bluetooth SIG, Inc.
- SD is a trademark of the SD Card Association



All other trademarks are the property of their respective owners.



Validity of this manual

This manual applies to the CS10 and CS15 field controllers. Differences between the various models are marked and described.

Available documentation

Name	Description/Format		
CS10/CS15 User Manual	All instructions required in order to operate the product to a basic level are contained in the User Manual. Provides an overview of the product together with technical data and safety directions.	✓	✓

Name	Description/Format		
Viva GNSS Getting Started Guide	Describes the general working of the product in standard use. Intended as a quick reference field guide.	✓	✓

Name	Description/Format		
Viva TPS Getting Started Guide	Describes the general working of the product in standard use. Intended as a quick reference field guide.	✓	✓
Viva Series Technical Reference Manual	Overall comprehensive guide to the product and application functions. Included are detailed descriptions of special software/hardware settings and software/hardware functions intended for technical specialists.		✓

Refer to the following resources for all CS10/CS15 documentation/software:

- the CS field controller CD-ROM
- <https://myworld.leica-geosystems.com>



myWorld@Leica Geosystems (<https://myworld.leica-geosystems.com>) offers a wide range of services, information and training material.

With direct access to myWorld, you are able to access all relevant services whenever it is convenient for you, 24 hours a day, 7 days per week. This increases your efficiency and keeps you and your equipment instantly updated with the latest information from Leica Geosystems.

Service	Description
myProducts	Simply add all Leica Geosystems products that you and your company own. View detailed information on your products, buy additional options or Customer Care Packages (CCPs), update your products with the latest software and keep up-to-date with the latest documentation.
myService	View the service history of your products in Leica Geosystems Service Centers and detailed information on the services performed on your products. For your products that are currently in Leica Geosystems Service Centers view the current service status and the expected end date of service.
mySupport	Create new support requests for your products that will be answered by your local Leica Geosystems Support Team. View the complete history of your Support and view detailed information on each request in case you want to refer to previous support requests.
myTraining	Enhance your product knowledge with the Leica Geosystems Campus - Information, Knowledge, Training. Study the latest online training material or download training material on your products. Keep up-to-date with the latest News on your products and register for Seminars or Courses in your country.



Table of Contents

In this manual	Chapter	Page
	1 Description of the System	11
	1.1 Overview	11
	1.2 Terminology	12
	1.3 System Concept	14
	1.3.1 Software Concept	14
	1.3.2 Power Concept	16
	1.3.3 Data Storage Concept	17
	1.4 CS Components	19
	1.4.1 CS10	19
	1.4.2 CS15	21
	1.5 Docking Station Components	23
	2 User Interface	24
	2.1 Keyboard	24
	2.2 Operating Principles	28
	3 Operation	29
	3.1 Equipment Setup	29

3.1.1	Fixing the Display Foil to the CS	29
3.1.2	Fixing a Hand Strap to the CS	31
3.1.3	Fixing the Slot Cover to the CS	33
3.1.4	Setting up as Handheld GNSS	34
3.1.5	Setting up the Docking Station	36
3.1.6	Connecting to a Personal Computer	37
3.2	Power Functions	42
3.3	Batteries	44
3.3.1	Operating Principles	44
3.3.2	Changing the Battery	45
3.3.3	Charging the Battery	47
3.4	Working with the Memory Device	49
3.5	LED Indicators on CS10/CS15	53
3.6	Using the Digital Camera	56
4	Care and Transport	58
4.1	Transport	58
4.2	Storage	59
4.3	Cleaning and Drying	60
5	Safety Directions	61
5.1	General Introduction	61

CS10/CS15, Table of Contents	10
5.2 Intended Use	62
5.3 Limits of Use	64
5.4 Responsibilities	65
5.5 Hazards of Use	67
5.6 Electromagnetic Compatibility EMC	73
5.7 FCC Statement, Applicable in U.S.	76
6 Technical Data	79
6.1 CS10/CS15 Technical Data	79
6.2 GS05/GS06 Technical Data	84
6.2.1 Tracking Characteristics	84
6.2.2 Accuracy	86
6.2.3 Technical Data	87
6.3 Antennas Technical Data	90
6.4 Conformity to National Regulations	93
6.4.1 CS10	93
6.4.2 CS15	96
7 International Limited Warranty, Software Licence Agreement	98
Appendix A Pin Assignments and Sockets	100
Index	103


1

Description of the System

1.1

Overview

System components




1.2 Terminology

CS general description

CS is a collective term describing the various models (CS10/CS15) of the multi-purpose field controller which is used with GNSS and TPS instruments.


CS available models

Model	Touch screen	Colour display	Internal radio modem ^{*1}	Internal battery ^{*2}	SD card	CompactFlash card	Bluetooth	Wireless LAN IEEE 802.11b/g ^{*1}	Windows CE
CS10	✓	✓	✓	✓	✓	✓	✓	✓	✓
CS15	✓	✓	✓	✓	✓	✓	✓	✓	✓
 Use the supplied stylus on the screens of the touch screen.									

*1 optional

*2 removable

CS available radios Radios for remote control (RCS) are available for the following devices:

Radio Modem	Description
CS10	Field controller with an integrated radio modem. This field controller has a colour display.
CS15	Field controller with an integrated radio modem. This field controller has a colour display.
 All devices contain the same spread spectrum transceiver radio modem.	

1.3 System Concept

1.3.1 Software Concept

Software for all CS models


Software type	Description
CS firmware (CS_xx.fw)	This software includes: <ul style="list-style-type: none"> - The language-specific version of Windows CE. - The basic functionality of the CS.

Software upload



Uploading CS firmware can take some time. Ensure that the battery is at least 75% full before beginning the upload, and do not remove the battery during the upload process.

Software for	Description
All CS models	The software is stored in the flash RAM of the CS field controller. The software can be uploaded onto an Leica SD card, Leica CompactFlash card or a USB stick.

Software for	Description
	<p data-bbox="996 240 1653 280">CS firmware update instructions</p> <ul data-bbox="996 293 2101 919" style="list-style-type: none"><li data-bbox="996 293 2101 432">• Download the most recent CS firmware file from https://myworld.leica-geosystems.com. Refer to "Introduction".<li data-bbox="996 448 2101 544">• Connect the CS field controller to your PC. Refer to "3.1.6 Connecting to a Personal Computer".<li data-bbox="996 560 2101 655">• Copy CS firmware file onto a folder on the Leica SD card, Leica CompactFlash card or USB stick.<li data-bbox="996 671 2101 767">• Tap the Loader icon from the desktop, to run the Loader application.<li data-bbox="996 783 2101 879">• Browse to the directory into which you copied CS firmware file, select it and start the upload.<li data-bbox="996 895 2101 919">• A message will appear when the upload is complete. <p data-bbox="996 935 2101 1074"> Ensure that a Leica SD card or a Leica CF card is inserted into the CS field controller before starting the upload.</p>

1.3.2 Power Concept

General

Use the Leica Geosystems batteries, chargers and accessories or accessories recommended by Leica Geosystems to ensure the correct functionality of the instrument.

Power options

Model	Power supply
all CS models	Internally via GEB211/GEB212 battery, or Externally via docking station, or Externally via GEV235 cable, or Externally via GDC221 car adapter If an external power supply is connected and the internal battery is inserted, then the external power is used.

1.3.3

Data Storage Concept

Description

Data is stored on a memory device. The memory device can be an SD card, CompactFlash card, USB stick or internal memory.

Memory device

SD card: All CS field controllers have an SD card slot fitted as standard. An SD card can be inserted and removed. Available capacity: 256 MB, 1 GB.

CompactFlash card: All CS field controllers have a CF card slot fitted as standard. A CompactFlash card can be inserted and removed. Available capacity: 256 MB, 1 GB.

USB stick: All CS field controllers have a USB port fitted as standard.

Internal memory: All CS field controllers have an internal memory fitted as standard. Available capacity: 1 GB.



While other SD cards or CompactFlash cards can be used, Leica Geosystems recommends to only use Leica SD cards or Leica CompactFlash cards and is not responsible for data loss or any other error that can occur while using a non-Leica card.



Removing the SD card, CompactFlash card or USB stick while the CS field controller is turned on can cause loss of data. Only remove the SD card, CompactFlash card or USB stick or unplug connecting cables when the CS field controller is switched off.

Transfer data

Data can be transferred in various ways. Refer to "3.1.6 Connecting to a Personal Computer".



CompactFlash cards and SD cards can directly be used in an OMNI drive as supplied by Leica Geosystems. Other PC card drives can require an adaptor.


1.4

CS Components

1.4.1

CS10


Upside of CS10



CS.001

- a) Slot Cover
- b) Screen
- c) Keyboard
- d) Port cover
- e) Power socket
- f) USB A Host port
- g) Docking station contacts
- h) LEMO port (USB and serial)
- i) USB Mini port
- j) DSUB9 port

Underside of CS10



- a) Hand strap bottom clips
- b) Hand strap
- c) Battery compartment
- d) Digital camera
- e) Hand strap top clips
- f) Slots
- g) Slot cover
- h) Stylus
- i) GS05 contacts
- j) CompactFlash card slot
- k) SD card slot

CS_008




A Bluetooth port is included inside to facilitate connectivity to a digital cellular phone.

1.4.2

CS15


Upside of CS15



CS.002

- a) Slot cover
- b) Screen
- c) Keyboard
- d) Port cover
- e) Power socket
- f) USB A Host port
- g) Docking station contacts
- h) LEMO port (USB and serial)
- i) USB Mini port
- j) DSUB9 port

Underside of CS15



- a) Hand strap bottom clips
- b) Hand strap
- c) Battery compartment
- d) Digital camera
- e) Hand strap top clips
- f) Slots
- g) Slot cover
- h) Stylus
- i) GS06 contacts
- j) CompactFlash card slot
- k) SD card slot


CS_007

 A Bluetooth port is included inside to facilitate connectivity to a digital cellular phone.

1.5

Docking Station Components


Docking station



2 User Interface


2.1 Keyboard

Keyboard display CS10



- a) Home
- b) ON/OFF
- c) Arrow keys, **OK**
- d) **Fn**
- e) ± key
- f) Brightness
- g) Favourites
- h) ESC
- i) Enter
- j) Backspace
- k) Volume
- l) Numeric keys










Keyboard display CS15








- a) Home
- b) Arrow keys, **OK**
- c) ON/OFF
- d) **Fn**
- e) ± key
- f) Numeric keys
- g) Brightness
- h) Function keys **F7 - F12**
- i) CAPS Lock
- j) Function keys **F1 - F6**
- k) Favourites
- l) ESC
- m) ENTER
- n) Backspace
- o) Volume
- p) Alpha keys
- q) ENTER
- r) SPACE

Keys

Key	Function
Function keys F1 - F6	Correspond to six softkeys that appear on the bottom of the screen when the screen is activated.

Key	Function
Function keys F7-F12	 User definable keys to execute chosen commands or access chosen screens.
Alpha keys	 To type letters.
Numeric keys	 To type numbers.
Caps Lock	 Switches between upper case and lower case letters.
Backspace	 Clears all entry at the beginning of user input. Clears the last character during user input.
Esc	 Leaves the current screen without storing any changes.
Fn	 Switches between the first and second level of function keys.
Space	 Enters a blank.
Enter	 Selects the highlighted line and leads to the next logical menu / dialog.

Key	Function
	<p>Starts the edit mode for editable fields.</p> <p>Opens a selectable list.</p>
ON/OFF	<p> If CS10/CS15 already off: Turns on CS10/CS15 when held for 2 s.</p> <p>If CS10/CS15 already on: Turns to Power Options menu when held for 2 s.</p>
Favourites	<p> Goes to a website by simply clicking its name.</p>
Home	<p> Switches to the Windows CE Start Menu.</p>
Arrow keys	<p> Move the focus on the screen.</p>
OK	<p> Selects the highlighted line and leads to the next logical menu / dialog.</p> <p>Starts the edit mode for editable fields.</p> <p>Opens a selectable list.</p>

2.2 Operating Principles

Keyboard and touch screen

The user interface is operated either by the keyboard or by the touch screen with supplied stylus. The workflow is the same for keyboard and touch screen entry, the only difference lies in the way information is selected and entered.

Operation by keyboard

Information is selected and entered using the keys. Refer to "2.1 Keyboard" for a detailed description of the keys on the keyboard and their function.

Operation by touch screen

Information is selected and entered on the screen using the supplied stylus.

Operation	Description
To select an item	Tap on the item.
To start the edit mode in editable fields	Tap on the editable field.
To highlight an item or parts of it for editing	Drag the supplied stylus from the left to the right.
To accept data entered into an editable field and exit the edit mode	Tap on the screen outside of the editable field.
To open a context-sensitive menu	Tap on the item and hold for 2 s.

3

Operation


3.1

Equipment Setup




3.1.1



Fixing the Display Foil to the CS

Fixing the display foil to the CS step-by-step



CS.029


	Description
	Ensure that the display of the CS is free of dust and grease.
	The non-reflecting display foil has a silver-coloured sticker to peel away the carrier foil from the actual display foil.
1.	Touch the silver-coloured sticker with two fingers and pull it slowly upwards. The carrier foil is peeling away.  Do not peel the carrier foil more than 2 cm - 3 cm away.

	Description
2.	Fix the laid open adhesive underside of the display foil at the display border.  Pay attention that the display foil is not fixed between display and display frame.
3.	Peel away the carrier foil bit by bit and smooth it out slowly onto the display.
4.	Potential air bubbles between display and display foil have to be smoothed out using the included microfibre cloth.  Do not use sharp objects!


3.1.2

Fixing a Hand Strap to the CS

Fixing the CS to a hand strap step-by-step



CS_009


	Description
	Turn the CS field controller over.
1.	Take the end of the hand strap and clip it to the base of CS field controller.
2.	Compress the clips of the main hook.
3.	Lower the main hook onto the pivot knob of the CS field controller. A click can be felt when the clip is secure.

	Description
4.	Adjust the length of the hand strap.


3.1.3

Fixing the Slot Cover to the CS

Fixing the slot cover to the CS step-by-step



CS.016


	Description
1.	Press the screwdriver end of the supplied stylus on the quarter-turn screws and loosen them.
2.	Remove the slot cover.
	Reattach the slot cover with the stylus, making sure the quarter-turn screws are seated.

3.1.4 Setting up as Handheld GNSS



The setup GS05/CS10 is identical to the setup GS06/CS15. For simplicity, the setup GS05/CS10 is used in the following.

Attaching the GS05 to the CS10 step-by-step




CS.011

	Description
	Detach the slot cover from the CS10. Refer to "3.1.3 Fixing the Slot Cover to the CS".
1.	Check the position of the contacts in the inner surface of the GS05.

	Description
2.	Attach the GS05 to the CS10.
3.	Press the screwdriver end of the supplied stylus on the quarter-turn screws and tighten them.
4.	To achieve the optimal satellite tracking performance, mount the AS05 (external GNSS antenna) on the GS05.

3.1.5 Setting up the Docking Station

Mounting components of the docking station step-by-step



CS.027

	Description
1.	Hold the docking station bracket as shown in the illustration in relation to the docking station rack.
2.	Slightly press the holder into the docking station rack. A click can be felt when the holder is secure.


3.1.6

Connecting to a Personal Computer





Microsoft ActiveSync (for PCs with Windows XP operating system) or Windows Mobile Device Center (for PCs with Windows Vista operating system) is the synchronisation software for Windows mobile-based pocket PCs. Microsoft ActiveSync or Windows Mobile Device Center enables a PC and a Windows mobile-based pocket PC to communicate.

Connect USB cable to PC for the first time step-by-step




CS.025

	Description
1.	Start the PC.





	Description
2.	Plug the GEV234 cable into CS field controller.  For CS field controllers with DSUB9 connector, the GEV223 cable has to be used.
3.	Turn the CS field controller on.
4.	Wait until the Windows CE desktop is visible.
5.	Plug the GEV234 cable into the USB port of the PC.  The new hardware wizard starts up automatically.
6.	Select No, not at this time.
7.	Next>.
8.	Select Install from a list or specific location (Advanced).
9.	Next>.
10.	Insert the CS field controller CD-ROM.
11.	Select Search removable media (floppy, CD-ROM...).
12.	Next>.
13.	Confirm Hardware Installation window with Continue Anyway.
14.	Finish.

	Description
	For PCs with Windows XP operating system:
15.	Run the ActiveSync installation program if not already installed.
16.	Allow USB connections inside the Connection Settings window of ActiveSync.
	For PCs with Windows Vista operating system:
17.	Run the Windows Mobile Device Center installation if not already installed.

Connect to PC via USB cable step-by-step



	Description
1.	Start the PC.

	Description
2.	<p>Plug the GEV234 cable into CS field controller.</p> <p> For CS field controllers with DSUB9 connector, the GEV223 cable has to be used.</p>
3.	Turn the CS field controller on.
4.	Plug the GEV234 cable into the USB port of the PC.
	For PCs with Windows XP operating system:
	<p> ActiveSync starts up automatically. If does not start automatically, start ActiveSync. If not already installed, run the ActiveSync installation program.</p>
5.	Allow USB connections inside the Connection Settings window of ActiveSync.
6.	Click Explore in ActiveSync.
	<p> The folders on the CS field controller are displayed under Mobile Devices. The folders of the data storage device can be found in StorageCard.</p>
	For PCs with Windows Vista operating system:
	<p> Windows Mobile Device Center starts up automatically. If does not start automatically, start Windows Mobile Device Center. If not already installed, run the Windows Mobile Device Center installation program.</p>

3.2 Power Functions


Turning CS field controller on

Press and hold power key () for 2 s.




CS field controller must have a power supply.

Power Options menu

Press and hold power key () for 2 s to open **Power Options** menu.



CS field controller must be on.

Option	Description
Turn off	Turn CS field controller off.
Sleep	Put CS field controller into sleep mode.  In sleep mode, CS field controller shuts down and reduces power consumption. Rebooting from sleep mode is quicker than a cold start after turning off.
Lock keyboard	Lock the keyboard. Option turns to Unlock keyboard .
Turn off touch screen	Disable touch screen. Option turns to Turn on touch screen .

Option	Description
Reset	Perform one of the following options: <ul style="list-style-type: none"><li data-bbox="1146 293 1774 336">• Restart (restart Windows CE)<li data-bbox="1146 347 2029 391">• Reset registry (reset Windows CE registry)<li data-bbox="1146 402 1966 496">• Reset application (reset all application settings)<li data-bbox="1146 507 2101 601">• Reset application and registry (reset all applications settings and Windows CE registry)

3.3 Batteries

3.3.1 Operating Principles

Charging / first-time use

- The battery must be charged prior to using it for the first time because it is delivered with an energy content as low as possible.
- The permissible temperature range for charging is between 0°C to +40°C/ +32°F to +104°F. For optimal charging, we recommend charging the batteries at a low ambient temperature of +10°C to +20°C/+50°F to +68°F if possible.
- It is normal for the battery to become warm during charging. Using the chargers recommended by Leica Geosystems, it is not possible to charge the battery if the temperature is too high.
- For new batteries or batteries that have been stored for a long time (> three months), it is effectual to make only one charge/discharge cycle.
- For Li-Ion batteries, a single discharging and charging cycle is sufficient. We recommend carrying out the process when the battery capacity indicated on the charger or on a Leica Geosystems product deviates significantly from the actual battery capacity available.


Operation / Discharging

- The batteries can be operated from -20°C to +55°C/-4°F to +131°F.
 - Low operating temperatures reduce the capacity that can be drawn; high operating temperatures reduce the service life of the battery.
-


3.3.2

Changing the Battery

Insert and remove the battery step-by-step



CS_010

	Description
	Turn CS field controller over to gain access to the battery compartment.
1.	Push the slide fastener in the direction of the arrow with the open-lock symbol.
2.	Open the battery compartment.
3.	Pull the battery from the battery compartment.
4.	Place the battery into the battery compartment with the Leica logo facing to the top.


	Description
5.	Close the battery compartment by pushing the slide fastener in the direction of the arrow with the close-lock symbol.

3.3.3


Charging the Battery

Charge battery step-by-step


A



B



CS_024

	Description
1.	Connect the GEV235 power adapter or GDC221 car adapter with the CS field controller (A) or the docking station (B) and an A/C plug.
2.	The power LED on the CS field controller switches on. When CS field controller's battery is fully charged the LED switches off again.  Refer to "LED indicators" for information about the power LED.



The following advice is only valid for battery charger, power adapter and car adapter.



Warning

If you open the product, either of the following actions may cause you to receive an electric shock.

- Touching live components
- Using the product after incorrect attempts were made to carry out repairs

Precautions:

Do not open the product. Only Leica Geosystems authorised service workshops are entitled to repair these products.



The following advice is only valid for batteries, power adapter or docking station.



Caution

The product is not designed for use under wet and severe conditions. If unit becomes wet it may cause you to receive an electric shock.

Precautions:

Use the product only in dry environments, for example in buildings or vehicles.

Protect the product against humidity. If the product becomes humid, it must not be used!



3.4

Working with the Memory Device




- Keep the card dry.
- Use it only within the specified temperature range.
- Do not bend the card.
- Protect the card from direct impacts.





Failure to follow these instructions could result in data loss and/or permanent damage to the card.


Insert and remove a CompactFlash card step-by-step





CS_017

	Description
	The CompactFlash card is inserted into a slot inside the top of the CS10/CS15.
1.	Refer to "Fixing the slot cover to the CS step-by-step". Loosen the screws inside the slot cover on top of the CS10/CS15 using the screwdriver end of the stylus.
2.	Detach the slot cover from the CS10/CS15.
3.	Slide the card firmly into the slot until it clicks into position.  Do not force the card into the slot.
4.	The card must be held with the contacts facing the slot.
5.	Attach the slot cover and tighten the screws.
6.	To remove the card, detach the slot cover of the CS10/CS15.
7.	Press the eject button next to the card slot twice.
8.	Remove the CompactFlash card and attach the slot cover.

Insert and remove an SD card step-by-step



CS.018

	Description
	The SD card is inserted into a slot inside the top of the CS10/CS15.
1.	Refer to "Fixing the slot cover to the CS step-by-step". Loosen the screws inside the slot cover on top of the CS10/CS15 using the screwdriver end of the stylus.
2.	Detach the slot cover from the CS10/CS15.
3.	Slide the card firmly into the slot until it clicks into position.  Do not force the card into the slot.
4.	The card must be held with the contacts facing the slot.

	Description
5.	Attach the slot cover and tighten the screws.
6.	To remove the card, detach the slot cover of the CS10/CS15.
7.	Gently press the top of the card to release it from the slot.
8.	Remove the SD card and attach the slot cover.

3.5


LED Indicators on CS10/CS15

LED indicators

Description

The CS field controller has **L**ight **E**mitting **D**iode indicators. They indicate the basic field controller status.

Diagram



Description of the LEDs

IF the	is	THEN
Bluetooth LED	green	Bluetooth is in data mode and ready for connecting.
	purple	Bluetooth is connecting.
	blue	Bluetooth has connected.
	flashing blue	data is being transferred
Power LED	off	power is off.
	green	power is okay.
	flashing green	power is okay. The battery is being charged.
	yellow	power is low. The remaining time for which enough power is available depends on the use of wireless modules, the temperature and the age of the battery.
	flashing yellow	power is low. The remaining time for which enough power is available depends on the use of wireless modules, the temperature and the age of the battery. The battery is being charged.
	red	power is very low. The battery should be changed.


IF the	is	THEN
	flashing red	power is very low. The battery is being charged.

3.6 Using the Digital Camera


Overview

Both CS field controllers are equipped with a digital camera located at the underside (refer to "1.4 CS Components"). If a hand strap or pole holder plate is mounted, the camera view is not limited. The camera application can be started from the desktop icon **Camera** or from the Start menu **Start - Programs - Camera**.

Taking a picture step-by-step

	Description
1.	Aim the camera to the desired target.
2.	Check the view at the display.
3.	Press OK or click Capture to take the picture.  Capture changes to Save .
4.	Press OK again or click Save to open the Save As dialog.
5.	Click Discard to reject the picture.

Storing a picture step-by-step

	Description
	The Save As dialog is Windows CE standard and allows to name the picture, choose the location or to create a folder.

	Description
1.	Browse to the desired folder or create a new one.
2.	Name the picture.
3.	Press OK to save it and return to the camera view.
4.	Press Cancel to reject the picture and to return to the camera view without saving the picture.

4 Care and Transport

4.1 Transport

Transport in a road vehicle

Never carry the product loose in a road vehicle, as it can be affected by shock and vibration. Always carry the product in its transport container and secure it.

Shipping

When transporting the product by rail, air or sea, always use the complete original Leica Geosystems packaging, transport container and cardboard box, or its equivalent, to protect against shock and vibration.

Shipping, transport of batteries

When transporting or shipping batteries, the person in charge of the product must ensure that the applicable national and international rules and regulations are observed. Before transportation or shipping, contact your local passenger or freight transport company.

4.2

Storage

Product

Respect the temperature limits when storing the equipment, particularly in summer if the equipment is inside a vehicle. Refer to "6 Technical Data" for information about temperature limits.

Li-Ion batteries

- Refer to "6 Technical Data" for information about storage temperature range.
 - At the recommended storage temperature range, batteries containing a 10% to 50% charge can be stored for up to one year. After this storage period the batteries must be recharged.
 - Remove batteries from the product and the charger before storing.
 - After storage recharge batteries before using.
 - Protect batteries from damp and wetness. Wet or damp batteries must be dried before storing or use.
 - A storage temperature range of -20°C to +30°C/-4°F to 86°F in a dry environment is recommended to minimise self-discharging of the battery.
-


4.3 Cleaning and Drying

Product and accessories

- Use only a clean, soft, lint-free cloth for cleaning. If necessary, moisten the cloth with water or pure alcohol. Do not use other liquids; these may attack the polymer components.
-

Damp products

Dry the product, the transport container, the foam inserts and the accessories at a temperature not greater than 40°C/104°F and clean them. Do not repack until everything is dry. Always close the transport container when using in the field.



Cables and plugs

Keep plugs clean and dry. Blow away any dirt lodged in the plugs of the connecting cables.

Connectors with dust caps

Wet connectors must be dry before attaching the dust cap.

5 Safety Directions

5.1 General Introduction

Description

The following directions enable the person responsible for the product, and the person who actually uses the equipment, to anticipate and avoid operational hazards.

The person responsible for the product must ensure that all users understand these directions and adhere to them.

5.2 Intended Use

Permitted use

- Remote control of product.
 - Data communication with external appliances.
-

Adverse use

- Use of the product without instruction.
- Use outside of the intended limits.
- Disabling safety systems.
- Removal of hazard notices.
- Opening the product using tools, for example screwdriver, unless this is permitted for certain functions.
- Modification or conversion of the product.
- Use after misappropriation.
- Use of products with recognisable damages or defects.
- Use with accessories from other manufacturers without the prior explicit approval of Leica Geosystems.
- Inadequate safeguards at the working site, for example when measuring on roads.
- Controlling of machines, moving objects or similar monitoring application without additional control- and safety installations.



Warning

Adverse use can lead to injury, malfunction and damage.

It is the task of the person responsible for the equipment to inform the user about hazards and how to counteract them. The product is not to be operated until the user has been instructed on how to work with it.

5.3 Limits of Use

Environment

Suitable for use in an atmosphere appropriate for permanent human habitation: not suitable for use in aggressive or explosive environments.



Local safety authorities and safety experts must be contacted before working in hazardous areas, or close to electrical installations or similar situations by the person in charge of the product.



[The following advice is only valid for battery charger, power adapter and car adapter.](#)

Environment

Suitable for use in dry environments only and not under adverse conditions.



5.4

Responsibilities

Manufacturer of the product

Leica Geosystems AG, CH-9435 Heerbrugg, hereinafter referred to as Leica Geosystems, is responsible for supplying the product, including the user manual and original accessories, in a safe condition.


Manufacturers of non Leica Geosystems accessories

The manufacturers of non Leica Geosystems accessories for the product are responsible for developing, implementing and communicating safety concepts for their products, and are also responsible for the effectiveness of those safety concepts in combination with the Leica Geosystems product.

Person in charge of the product

The person in charge of the product has the following duties:

- To understand the safety instructions on the product and the instructions in the user manual.
 - To be familiar with local regulations relating to safety and accident prevention.
 - To inform Leica Geosystems immediately if the product and the application becomes unsafe.
 - To ensure that the national laws, regulations and conditions for the operation of radio transmitters are respected.
-

 **Warning** The person responsible for the product must ensure that it is used in accordance with the instructions. This person is also accountable for the training and the deployment of personnel who use the product and for the safety of the equipment in use.

5.5

Hazards of Use

Warning

The absence of instruction, or the inadequate imparting of instruction, can lead to incorrect or adverse use, and can cause accidents with far-reaching human, material, financial and environmental consequences.

Precautions:


All users must follow the safety directions given by the manufacturer and the directions of the person responsible for the product.





Danger

Because of the risk of electrocution, it is dangerous to use poles and extensions in the vicinity of electrical installations such as power cables or electrical railways.

Precautions:

Keep at a safe distance from electrical installations. If it is essential to work in this environment, first contact the safety authorities responsible for the electrical installations and follow their instructions.



-
-  **Warning** During dynamic applications, for example stakeout procedures there is a danger of accidents occurring if the user does not pay attention to the environmental conditions around, for example obstacles, excavations or traffic.
- Precautions:**
The person responsible for the product must make all users fully aware of the existing dangers.
-
-  **Warning** Inadequate securing of the working site can lead to dangerous situations, for example in traffic, on building sites, and at industrial installations.
- Precautions:**
Always ensure that the working site is adequately secured. Adhere to the regulations governing safety and accident prevention and road traffic.
-
-  **Warning** If computers intended for use indoors are used in the field there is a danger of electric shock.
- Precautions:**
Adhere to the instructions given by the computer manufacturer regarding field use with Leica Geosystems products.
-
-  **Caution** If the accessories used with the product are not properly secured and the product is subjected to mechanical shock, for example blows or falling, the product may be damaged or people can sustain injury.

Precautions:

When setting-up the product, make sure that the accessories are correctly adapted, fitted, secured, and locked in position.

Avoid subjecting the product to mechanical stress.

 **Warning**

If the product is used with accessories, for example masts, staffs, poles, you may increase the risk of being struck by lightning.

Precautions:

Do not use the product in a thunderstorm.

 **Warning**

Using a battery charger not recommended by Leica Geosystems can destroy the batteries. This can cause fire or explosions.

Precautions:

Only use chargers recommended by Leica Geosystems to charge the batteries.

 **Caution**

During the transport, shipping or disposal of batteries it is possible for inappropriate mechanical influences to constitute a fire hazard.

Precautions:

Before shipping the product or disposing of it, discharge the batteries by running the product until they are flat.

When transporting or shipping batteries, the person in charge of the product must ensure that the applicable national and international rules and regulations are

observed. Before transportation or shipping contact your local passenger or freight transport company.

 **Warning**

High mechanical stress, high ambient temperatures or immersion into fluids can cause leakage, fire or explosions of the batteries.

Precautions:

Protect the batteries from mechanical influences and high ambient temperatures. Do not drop or immerse batteries into fluids.

 **Warning**

If battery terminals come in contact with jewellery, keys, metallised paper or other metals, short circuited battery terminals can overheat and cause injury or fire, for example by storing or transporting in pockets.

Precautions:

Make sure that the battery terminals do not come into contact with metallic objects.



[The following advice is only valid for battery charger, power adapter and car adapter.](#)

 **Warning**

If you open the product, either of the following actions may cause you to receive an electric shock.

- Touching live components
- Using the product after incorrect attempts were made to carry out repairs

Precautions:

Do not open the product. Only Leica Geosystems authorised service workshops are entitled to repair these products.

**Caution**

The following advice is only valid for batteries, power adapter or docking station.

The product is not designed for use under wet and severe conditions. If unit becomes wet it may cause you to receive an electric shock.

Precautions:

Use the product only in dry environments, for example in buildings or vehicles. Protect the product against humidity. If the product becomes humid, it must not be used!


**Warning**

If the product is improperly disposed of, the following can happen:

- If polymer parts are burnt, poisonous gases are produced which may impair health.
- If batteries are damaged or are heated strongly, they can explode and cause poisoning, burning, corrosion or environmental contamination.
- By disposing of the product irresponsibly you can enable unauthorised persons to use it in contravention of the regulations, exposing themselves and third

parties to the risk of severe injury and rendering the environment liable to contamination.

Precautions:



The product must not be disposed with household waste. Dispose of the product appropriately in accordance with the national regulations in force in your country. Always prevent access to the product by unauthorised personnel.

Product-specific treatment and waste management information can be downloaded from the Leica Geosystems home page at <http://www.leica-geosystems.com/treatment> or received from your Leica Geosystems dealer.



Warning

Only Leica Geosystems authorised service workshops are entitled to repair these products.

5.6

Electromagnetic Compatibility EMC

Description

The term Electromagnetic Compatibility is taken to mean the capability of the product to function smoothly in an environment where electromagnetic radiation and electrostatic discharges are present, and without causing electromagnetic disturbances to other equipment.



Warning

Electromagnetic radiation can cause disturbances in other equipment.

Although the product meets the strict regulations and standards which are in force in this respect, Leica Geosystems cannot completely exclude the possibility that other equipment may be disturbed.

The product is a class A product when operated with the internal batteries. In a domestic environment this product may cause radio interference in which case the user may be required to take adequate measures (remove internal batteries and power the product directly with a power cable).



Caution

There is a risk that disturbances may be caused in other equipment if the product is used with accessories from other manufacturers, for example field computers, personal computers, two-way radios, non-standard cables or external batteries.

Precautions:

Use only the equipment and accessories recommended by Leica Geosystems. When combined with the product, they meet the strict requirements stipulated by the guidelines and standards. When using computers and two-way radios, pay attention to the information about electromagnetic compatibility provided by the manufacturer.

**Caution**

Disturbances caused by electromagnetic radiation can result in erroneous measurements.

Although the product meets the strict regulations and standards which are in force in this respect, Leica Geosystems cannot completely exclude the possibility that the product may be disturbed by intense electromagnetic radiation, for example, near radio transmitters, two-way radios or diesel generators.

Precautions:

Check the plausibility of results obtained under these conditions.

**Warning**

If the product is operated with connecting cables attached at only one of their two ends, for example external supply cables, interface cables, the permitted level of electromagnetic radiation may be exceeded and the correct functioning of other products may be impaired.

Precautions:

While the product is in use, connecting cables, for example product to external battery, product to computer, must be connected at both ends.

Radios or digital cellular phones



Warning

Use of product with radio or digital cellular phone devices:

Electromagnetic fields can cause disturbances in other equipment, in installations, in medical devices, for example pacemakers or hearing aids and in aircraft. It can also affect humans and animals.

Precautions:

Although the product meets the strict regulations and standards which are in force in this respect, Leica Geosystems cannot completely exclude the possibility that other equipment can be disturbed or that humans or animals can be affected.

- Do not operate the product with radio or digital cellular phone devices in the vicinity of filling stations or chemical installations, or in other areas where an explosion hazard exists.
 - Do not operate the product with radio or digital cellular phone devices near to medical equipment.
 - Do not operate the product with radio or digital cellular phone devices in aircraft.
-

5.7 FCC Statement, Applicable in U.S.



The greyed paragraph below is only applicable for products without radio.



Warning

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, can cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.


If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
 - Increase the separation between the equipment and the instrument.
 - Connect the equipment into an outlet on a circuit different from that to which the instrument is connected.
 - Consult the dealer or an experienced radio/TV technician for help.
-

 **Warning**

Changes or modifications not expressly approved by Leica Geosystems for compliance could void the user's authority to operate the equipment.

Labelling CS10



CS.014

Type: S.No.:

Art.No.:

Equi.No.:


Power: xxV \approx nominal/x.x A max.


Leica Geosystems AG

CH-9435 Heerbrugg

Manufactured: 2009

Made in Switzerland

 0681





2022WWW08562801


IC:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC-ID:
Bluetooth QPL:

Labelling CS15



CS.015

Type: S.No.:

Art.No.:

Equi.No.:


Power: xxV \approx nominal/x.x A max.


Leica Geosystems AG

CH-9435 Heerbrugg

Manufactured: 2009

Made in Switzerland

 0681





2022WWW08562801


IC:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FCC-ID:
Bluetooth QPL:


Labelling GS05,
GS06



CS_012

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.


Labelling internal
battery GEB211,
GEB212



GEB_001

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

UL US LISTED
ITE Accessory
E179078 . 70YL



6

Technical Data

6.1

CS10/CS15 Technical Data

Design

Glass reinforced polymer housing with optional integrated battery and radio modem.

Control unit

CS10

Display: VGA (480 x 640 pixels),
graphics capable LCD, illumination,
touch screen, colour

Keyboard: 26 keys, illumination

Touch screen: Toughened film on glass

Sound: Integrated sealed speaker and microphone

Digital camera: Resolution: 1600 x 1200 pixels, fixed focus lens, image
capture: JPEG

CS15

Display: VGA (640 x 480 pixels),
graphics capable LCD, illumination,
touch screen, colour

Keyboard: 65 keys including 12 function keys, illumination

Touch screen: Toughened film on glass

Sound: Integrated sealed speaker and microphone

Digital camera: Resolution: 1600 x 1200 pixels, fixed focus lens, image capture: JPEG

Dimensions

Type	Length [m]	Width [m]	Thickness [m]
CS10	0.200	0.102	0.045
CS15	0.245	0.125	0.045

Weight

Type	Weight [kg]/[lbs]
CS10, with GEB211 or GEB212	0.720/1.587
CS15, with GEB211 or GEB212	0.870/1.918

Recording

Data can be recorded on the SD card, CompactFlash card, USB stick or in the internal memory.

Power

Type	Consumption [W]	External supply voltage
CS10/CS15	2.0	Nominal voltage 12 V DC (---) Voltage range 10.5 V-28 V

Internal battery

Type	Battery	Voltage	Capacity	Operating time, typical*
CS10/CS15	Li-Ion	7.4 V	GEB212: 2.6 Ah	10 h

* Operating time depends on use of wireless communication devices.

Environmental specifications

Temperature

Type	Operating temperature [°C]	Storage temperature [°C]
CS10/CS15	-30 to +60 Colour display: -10 to +60	-40 to +80
Internal battery	-20 to +55	-40 to +70

Protection against water, dust and sand

Type	Protection
CS10/CS15	IP67 (IEC60529) Dust tight Waterproof to 1 m temporary immersion

Humidity

Type	Protection
CS10/CS15	Up to 100 % The effects of condensation are to be effectively counteracted by periodically drying out CS10/CS15.

Interfaces

Type	RS232	USB Host	USB OTG	Bluetooth	WLAN
CS10/CS15	LEMO port or DSUB9	LEMO port or USB A	LEMO port, USB Mini-AB or docking station contacts	Class 2	IEEE 802.11b/g

Data format for RS232

The default values are:

Baud rate: 115200
 Parity: None
 Terminator: CR/LF
 Data bits: 8
 Stop bits: 1

Ports

Type	8 pin LEMO-1	DSUB9	USB A Host	USB Mini	Docking station contacts
CS10/CS15	For power and/or communication	For communication			For power and/or communication

6.2 GS05/GS06 Technical Data

6.2.1 Tracking Characteristics

Instrument technology

SmartTrack+

Satellite reception

Single frequency

Instrument channels

GS05/GS06: Up to 14 channels continuous tracking on L1 (GPS); up to 14 channels continuous tracking on L1 (GLONASS); one channel tracking SBAS.



Depending on the satellite systems and signals configured, a maximum number of 14 channels is allocated.

Supported codes and phases

GPS

Type	L1
GS05/GS06	Carrier phase, C/A-code

GLONASS

Type	L1
GS05/GS06	Carrier phase, C/A-code



Carrier phase and code measurements on L1 (GPS) are fully independent with AS on or off.

Satellites tracked

GS05/GS06: Up to 14 simultaneously on L1 (GPS) + up to 14 simultaneously on L1 (GLONASS) + up to one SBAS

6.2.2

Accuracy

Accuracy is dependent upon various factors including the number of satellites tracked, constellation geometry, observation time, ephemeris accuracy, ionospheric disturbance, multipath and resolved ambiguities.

The following accuracies, given as **root mean square**, are based on measurements processed using LGO and on real-time measurements.

The use of multiple GNSS systems can increase accuracy by up to 30% relative to GPS only.

Differential code

The baseline precision of a differential code solution for static and kinematic surveys is 40 cm.

**Differential phase
in post-processing**

Static	Kinematic
10 mm + 2 ppm	20 mm + 2 ppm

6.2.3

Technical Data

Description and use

The table gives a description and the intended use of the GS05/GS06.

Type	Description	Use
GS05	L1 GPS, GLONASS SmartTrack+ antenna.	With CS10 field controller.
GS06	L1 GPS, GLONASS SmartTrack+ antenna.	With CS15 field controller.

Dimensions

Type	Length [m]	Width [m]	Thickness [m]
GS05 with CS10	0.290	0.102	0.045
GS06 with CS15	0.290	0.125	0.045

Connector

5 pin interface port

Weight

Type	Weight [kg]/[lbs]
GS05 with CS10 and GEB211/GEB212	0.900/1.984
GS06 with CS15 and GEB211/GEB212	1.045/2.304

Power

Power consumption: 0.5 W typically, 45 mA
 External supply voltage: Nominal 12 V DC (==), voltage range 5 V-28 V DC

Electrical data

Type	GS05/GS06
Voltage	-
Current	-
Frequency	GPS L1 1575.42 MHz GLONASS L1 1602.5625 MHz-1611.5 MHz
Gain	Typically 27 dBi
Noise Figure	Typically < 2 dBi

Environmental specifications

Temperature

Operating temperature [°C]	Storage temperature [°C]
-30 to +60	-40 to +80

Protection against water, dust and sand

Protection
IP67 (IEC 60529) Dust tight Protected against water jets Waterproof to 1 m temporary immersion

Humidity

Protection
Up to 100 % The effects of condensation are to be effectively counteracted by periodically drying out the antenna.

6.3 Antennas Technical Data

Description and use

The table gives a description and the intended use of the antenna.

Type	Description	Use
AS05	L1 GPS, GLONASS SmartTrack+ antenna with built-in ground plane.	With CS10/GS05, CS15/GS06.

Dimensions

Type	AS05
Height	6.2 cm
Diameter	17.0 cm

Connector

AS05: TNC female

Mounting

AS05: 5/8" Whitworth

Weight

AS05: 0.4 kg

Electrical data

Type	AS05
Voltage	4.5 V to 18 V DC
Current	35 mA typical
Frequency	GPS L1 1575.42 MHz GLONASS L1 1602.5625 MHz-1611.5 MHz
Gain (typically)	27 dBi
Noise Figure (typically)	< 2 dBi

Environmental specifications

Temperature

Type	Operating temperature [°C]	Storage temperature [°C]
AS05	-40 to +70	-55 to +85

Protection against water, dust and sand

Type	Protection
AS05	IP67 (IEC 60529) Dust tight Protected against water jets

Type	Protection
	Waterproof to 1 m temporary immersion

Humidity

Type	Protection
AS05	Up to 100 % The effects of condensation are to be effectively counter-acted by periodically drying out the antenna.

Cable length

Separation distance from instrument ...	to antenna	Supplied cable lengths [m]
GS05/GS06	AS05	1.2

6.4

6.4.1

Conformity to national regulations

Conformity to National Regulations

CS10

- FCC Part 15 (applicable in US)
- Hereby, Leica Geosystems AG, declares that the product CS10 is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC. The declaration of conformity can be consulted at <http://www.leica-geosystems.com/ce>.



Class 2 equipment according European Directive 1999/5/EC (R&TTE) for which following EEA Member States apply restrictions on the placing on the market or on the putting into service or require authorisation for use:

- France
 - Italy
 - Norway (if used in the geographical area within a radius of 20km from the centre of Ny-Ålesund)
- The conformity for countries with other national regulations not covered by the FCC part 15 or European directive 1999/5/EC has to be approved prior to use and operation.
-

Frequency band

Type	Frequency band [MHz]
CS10, Bluetooth	2402 - 2480
CS10, WLAN	2400 - 2484

Output power

Type	Output power [mW]
CS10, Bluetooth	2.5
CS10, WLAN (802.11b)	50
CS10, WLAN (802.11g) 6 Mbit/s-36 Mbit/s	50
CS10, WLAN (802.11b) 48 Mbit/s-56 Mbit/s	31.6

Antenna

Type	Antenna	Gain [dBi]	Connector	Frequency band [MHz]
CS10, Bluetooth	Integrated antenna	-	-	-
CS10, WLAN	Integrated antenna	-	-	-

Type	Antenna	Gain [dBi]	Connector	Frequency band [MHz]
GS05	Internal GNSS antenna element (receive only)	-	-	-

6.4.2

CS15

Conformity to national regulations

- FCC Part 15 (applicable in US)
- Hereby, Leica Geosystems AG, declares that the product CS15 is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC. The declaration of conformity can be consulted at <http://www.leica-geosystems.com/ce>.



Class 2 equipment according European Directive 1999/5/EC (R&TTE) for which following EEA Member States apply restrictions on the placing on the market or on the putting into service or require authorisation for use:

- France
 - Italy
 - Norway (if used in the geographical area within a radius of 20km from the centre of Ny-Ålesund)
- The conformity for countries with other national regulations not covered by the FCC part 15 or European directive 1999/5/EC has to be approved prior to use and operation.

Frequency band

Type	Frequency band [MHz]
CS15, Bluetooth	2402 - 2480
CS15, WLAN	2400 - 2484

Output power

Type	Output power [mW]
CS15, Bluetooth	2.5
CS15, WLAN (802.11b)	50
CS15, WLAN (802.11g) 6 Mbit/s-36 Mbit/s	50
CS15, WLAN (802.11b) 48 Mbit/s-56 Mbit/s	31.6

Antenna

Type	Antenna	Gain [dBi]	Connector	Frequency band [MHz]
CS15, Bluetooth	Integrated antenna	-	-	-
CS15, WLAN	Integrated antenna	-	-	-
GS06	Internal GNSS antenna element (receive only)	-	-	-

7 International Limited Warranty, Software Licence Agreement

International Limited Warranty

This product is subject to the terms and conditions set out in the International Limited Warranty which you can download from the Leica Geosystems home page at <http://www.leica-geosystems.com/internationalwarranty> or collect from your Leica Geosystems distributor. The foregoing warranty is exclusive and is in lieu of all other warranties, terms or conditions, express or implied, either in fact or by operation of law, statutory or otherwise, including warranties, terms or conditions of merchantability, fitness for a particular purpose, satisfactory quality and non-infringement, all which are expressly disclaimed.

Software Licence Agreement

This product contains software that is preinstalled on the product, or that is supplied to you on a data carrier medium, or that can be downloaded by you online according to prior authorisation from Leica Geosystems. Such software is protected by copyright and other laws and its use is defined and regulated by the Leica Geosystems Software Licence Agreement, which covers aspects such as, but not limited to, Scope of the Licence, Warranty, Intellectual Property Rights, Limitation of Liability, Exclusion of other Assurances, Governing Law and Place of Jurisdiction. Please make sure, that at any time you fully comply with the terms and conditions of the Leica Geosystems Software Licence Agreement.

Such agreement is provided together with all products and can also be referred to and downloaded at the Leica Geosystems home page at <http://www.leica-geosystems.com/swlicense> or collected from your Leica Geosystems distributor.


You must not install or use the software unless you have read and accepted the terms and conditions of the Leica Geosystems Software Licence Agreement. Installation or use of the software or any part thereof, is deemed to be an acceptance of all the terms and conditions of such Licence Agreement. If you do not agree to all or some of the terms of such Licence Agreement, you must not download, install or use the software and you must return the unused software together with its accompanying documentation and the purchase receipt to the distributor from whom you purchased the product within ten (10) days of purchase to obtain a full refund of the purchase price.

Appendix A Pin Assignments and Sockets

Description

Some applications require knowledge of the pin assignments for the CS10/CS15 ports. In this chapter, the pin assignments and sockets for the ports of the CS10/CS15 are explained.


Ports at the instrument bottom panel - DSUB9 connector



CS_022

- a) DSUB9 port
- b) USB Mini port
- c) USB A Host port


Ports at the instrument bottom panel - Lemo connector



CS_021

- a) Lemo port (USB and serial)
- b) USB A Host port


Pin assignments for RS232 serial port



PIN_002

Pin	Signal Name	Function	Direction
1	NC	Not connected	-
2	RxD	RS232, receive data	In
3	TxD	RS232, transmit data	Out
4	NC	Not connected	-
5	GND	Signal Ground	-
6	NC	Not connected	-
7	RTS	RS232, request to send	Out
8	CTS	RS232, clear to send	In
9	NC	Not connected	-

Pin assignments for 8 pin LEMO-1



PIN_001

Pin	Signal Name	Function	Direction
1	USB_D+	USB data line	In or out
2	USB_D-	USB data line	In or out
3	GND	Signal ground	-
4	RxD	RS232, receive data	In
5	TxD	RS232, transmit data	Out

Pin	Signal Name	Function	Direction
6	ID	Identification pin	In or out
7	PWR	Power input, 10.5 V-28 V	In
8	TRM_ON/USB_ID	RS232, general purpose signal	In or out

Sockets

9 pin RS232: RS232, 9 pin, DE9
 8 pin LEMO-1: LEMO-1, 8 pin, LEMO EGI.1B.308.CLN

Index

A

ActiveSync	37
Antennas	
Operating Temperature	91
Storing Temperature	91
Type	90

B

Batteries	
Charge in CS10/CS15	47
Charging, first-time use	44
Operation, Discharging	44
Battery	
Change in CS10/CS15	45
Charge in CS10/CS15	47
Storage temperature	81
Bluetooth	
LED on CS10	53
LED on CS15	53

C

CompactFlash card

Insert	49
Memory device	17
Remove	49
Connector	
GS05	87
GS06	87
Connector, antennas	90
CS	
Available models	12
Display foil	29
Docking Station	23, 36
Firmware for all CS models	14
Lock keyboard	42
Operating principles	28
Power Options menu	42
System components	11
Unlock keyboard	42
CS10	
Operating temperature	81
Status	53
Storage temperature	81

Underside	20	E	
Upside	19	Electrical Data	
CS15		GS05	88
Operating temperature	81	GS06	88
Status	53	Electrical data, antennas	91
Storage temperature	81	Environmental specifications	
Underside	22	Antenna	91
Upside	21	GS05	89
D		GS06	89
Data transfer	18	F	
Description of the system	11	FCC Statement	76
Digital Camera	56	G	
Dimensions		GEB211 (internal battery)	
Antennas	90	Operating temperature	81
SmartAntenna	87	GEB212 (internal battery)	
Display foil	29	Operating temperature	81
Docking Station		GS05	
Components	23	Operating Temperature	89
Mounting	36	Storage Temperature	89
Documentation	4	GS06	
Drive		Operating Temperature	89
PC card, on office computer	18	Storage Temperature	89

H			
Hand strap	31	Caps Lock	26
Handheld GNSS	34	Description of	25
I		ENTER key	26
Indicators, LED		ESC key	26
CS10	53	Favourites	27
CS15	53	Fn key	26
Insert		Function keys	25
CompactFlash card	49	Home	27
SD card	51	Hot keys	26
Intended Use	62	Numeric keys	26
Internal memory		OK	27
Memory device	17, 17	ON/OFF	27
International Limited Warranty	98	SPACE key	26
K		L	
Keyboard		Labelling	
CS10 Graphical overview	24	CS10	77
CS15 Graphical overview	25	CS15	77
Operating principles	28	GS05	78
Keys		GS06	78
Alpha keys	26	LED	
Arrow keys	27	CS10, description	44
Backspace key	26	CS15, description	54
		Light Emitting Diode	

CS10	53	GS05	88
CS15	53	GS06	88
Li-Ion battery		Power LED	
Storage	59	CS10	53
		CS15	53
M		Power supply	16
Memory device		R	
Available	17	Radio Modem	
Microsoft ActiveSync	37	Available radios	13
Mount, antennas	90	Recording	80
		Remove	
O		CompactFlash card	49
Operating Temperature		SD card	51
Antennas	91	Reset	
CS10	81	Options	43
CS15	81	Responsibilities	65
GEB211 (internal battery)	81	S	
GEB212 (internal battery)	81	Safety Directions	61
GS05	89	SD card	
GS06	89	Insert	51
		Memory device	17
P		Remove	51
PC card drive on office computer	18	Slot Cover	33
Pin Assginement	100		
Power			

Socket	100	GS05	84
Software		GS06	84
Upload	14	Dimensions	80
Software Licence Agreement	98	Display and keyboard	79
Specifications, environmental		Environmental specifications	81
Antennas	91	Interface	82
GS05	89	Internal battery GEB211	81
GS06	89	Internal battery GEB212	81
Status, CS10	53	Ports	83
Status, CS15	53	Power supply	80
Storage Temperature		Weight	80
CS10	81	Temperature range	
CS15	81	Product, drying	60
For internal battery GEB211	81	Temperature, charging internal battery	44
For internal battery GEB212	81	Touch screen	
GS05	89	Turn off	42
GS06	89	Turn on	42
Storing Temperature		Touch Screen, operating principles	28
Antennas	91	Transfer data	18
T		U	
Technical Data		Upload software	14
CS10	79	USB stick	
CS15	79	Memory device	17

User Interface	24
User Manual	
Validity of	4

W

Weight	
Antennas	90
GS05	88
GS06	88
Windows CE	
Reset registry	43
Restart	43
Windows Mobile Device Center	37
WLAN	12

Total Quality Management: Our commitment to total customer satisfaction.



Leica Geosystems AG, Heerbrugg, Switzerland, has been certified as being equipped with a quality system which meets the International Standards of Quality Management and Quality Systems (ISO standard 9001) and Environmental Management Systems (ISO standard 14001).

Ask your local Leica Geosystems dealer for more information about our TQM program.

Leica Geosystems AG

Heinrich-Wild-Strasse

CH-9435 Heerbrugg

Switzerland

Phone +41 71 727 31 31

www.leica-geosystems.com

- when it has to be **right**

