

Operational Description

1) Description

The Digital keyboard is introduced keyboard input availability password work out wireless transmit, the Digital keyboard wireless is a low-power hand held remote control device operating at a frequency of 310MHz. The signal output is a binary-coded, 32-bit hopping code generated by non-linear encryption algorithm, with a 28-bit serial number and six status bits. It utilizes hopping code which for high security and keyless entry (RKE) systems from Microchip Technology Inc.

Actuating push buttons illuminates a light-emitting diode (LED) and activates the transmitter. Releasing the push-button immediately terminates transmission. Transmission time is limited to 30 seconds if button is held on.

2) Functional Description

Digital encoding combines a 32-bit hopping code generated by a non-linear encryption algorithm, with a 28-bit serial number and six status bits to create a 66-bit transmission stream. The length of the transmission eliminates the threat of code scanning and the code hopping mechanism makes each transmission unique, thus rendering code capture and resend (code grabbing) schemes useless.

The RF oscillator functions as a high-frequency circuit which is composed by Q4, C14, C15, L1, L2 and the frequency of circuit is 310MHz, the signal is emitted by annular antenna L2. The frequency of oscillation is controlled by X1 (NDR310) resonator. T1 is the RF output amplifier. Base bias capacitor C14 & C15 regulates the power output of the oscillator.