

3. Common mode sensitivity

DASY measurement parameters:

Auto Zero Time: 3 sec,

Measuring time: 3 sec

High/Low Range

in μV	Common mode Input Voltage	High Range Reading	Low Range Reading
Channel X	200mV	5.15	5.17
	- 200mV	-4.35	-4.88
Channel Y	200mV	9.00	8.70
	- 200mV	-10.57	-10.21
Channel Z	200mV	8.93	8.00
	- 200mV	-10.74	-10.51

4. Channel separation

DASY measurement parameters:

Auto Zero Time: 3 sec,

Measuring time: 3 sec

High Range

in μV	Input Voltage	Channel X	Channel Y	Channel Z
Channel X	200mV	-	0.87	-0.39
Channel Y	200mV	0.80	-	2.29
Channel Z	200mV	-2.73	-0.30	-

5. AD-Converter Values with inputs shorted

in LSB	Low Range	High Range
Channel X	16102	16311
Channel Y	16055	16139
Channel Z	15811	15833

6. Input Offset Measurement

DASY measurement parameters:

Auto Zero Time: 3 sec,

Measuring time: 3 sec

Number of measurements:

100, Low Range

Input 10M Ω

in μV	Average	min. Offset	max. Offset	Std. Deviation
Channel X	0.25	-1.75	1.20	0.43
Channel Y	-1.47	-2.17	0.46	0.35
Channel Z	-1.64	-2.78	0.28	0.45

6. Input Offset Measurement (cont'd)

Input shorted

in μV	Average	min. Offset	max. Offset	Std. Deviation
Channel X	-0.02	-0.85	0.97	0.27
Channel Y	-0.69	-2.12	0.97	0.35
Channel Z	-0.96	-2.39	0.43	0.35

7. Input Offset Current

Nominal Input circuitry offset current on all channels: <25fA

8. Input Resistance

In MOhm	Calibrating	Measuring
Channel X	0.2001	199.9
Channel Y	0.1999	203.3
Channel Z	0.2000	200.4

9. Low Battery Alarm Voltage

in V	Alarm Level
Supply (+ Vcc)	7.72
Supply (- Vcc)	7.55

10. Power Consumption

in mA	Switched off	Stand by	Transmitting
Supply (+ Vcc)	0.00	8.71	14.4
Supply (- Vcc)	-0.01	-8.03	-9.20