

Contact person RISE

Tomas Lennhager
Division Safety and Transport
+46 10 516 54 09
tomas.lennhager@ri.se

Date

2020-12-08

Reference

P107282-F30

Page

1 (74)

Ericsson AB
Anders Karlsson
BURA DURA RP QRM
Torshamnsgatan 21
164 80 Stockholm

Radio measurements on AIR 1281 B260

Product name: AIR 1281 B260

Product number: KRD 901 166/6

RISE Research Institutes of Sweden AB **Vehicles and Automation – EMC-IKT**

Performed by

Examined by

Tomas Lennhager

Daniel Lundgren

RISE Research Institutes of Sweden AB

Postal address

Box 857
SE-501 15 BORÅS
Sweden

Office location

Brinellgatan 4
SE-504 62 BORÅS

Phone / Fax / E-mail

+46 10 516 50 00
+46 33 13 55 02
info@ri.se

This report may not be reproduced other than in full, except
with the prior written approval of the issuing laboratory.



Summary	3
Description of the test object	4
Purpose of test.....	5
Operation modes during measurements	5
Measurements	5
References.....	6
Measurement equipment.....	7
EAB Measurement equipment.....	7
Uncertainties	8
Reservation	8
Delivery of test object.....	8
Manufacturer’s representative.....	8
Test engineers	8
Test participant(-s).....	8
Test frequencies used for radiated measurements.....	9
Test setup: radiated measurements	10
RF power output measurements according to CFR 47 §30.202	11
Test set-up and procedure	11
Results.....	13
Limits	15
Occupied bandwidth measurements according to CFR47 2.1049	16
Test set-up and procedure	16
Results.....	16
Field strength of spurious radiation measurements according to CFR 47 §30.203	22
Measurement equipment.....	26
EAB Measurement equipment.....	26
Results.....	27
Limits	29

Summary

Standard Listed part of	Compliant
FCC CFR 47 part 30	
2.1046 RF power output	Yes
2.1049 Occupied bandwidth	Yes
2.1053 Field strength of spurious radiation	Yes

Description of the test object

Equipment:	Radio equipment AIR 1281 B260 Product number: KRD 901 166/6 FCC ID: TA8AKRD901166
Hardware revision state:	R1D
Tested configuration:	3GPP NR TDD
Frequency range:	TX/ RX: 38400 – 40000 MHz
No of supported beams:	Config mode 1: 2 beams in 2 orthogonal polarizations each, 4 beams in total. Config mode 2: 1 beam in 2 orthogonal polarizations each, 2 beams in total.
Operating bandwidth:	Config mode 1: Two segments of 400 MHz Config mode 2: One segment of 400 MHz
Nominal Output power (EIRP):	47 dBm/ beam and polarization config mode 2 41 dBm/ beam and polarization config mode 1
RF configurations:	TX Diversity, SU and MU MIMO up to 2 layers 1x(2x2), Contiguous Spectrum (CS) and Non-Contiguous spectrum (NCS), Carrier Aggregation (CA) intra-band supported
Antenna beam steering:	Azimuth ± 60 deg, elevation ± 15 deg
Channel bandwidth(s)/ Sub Carrier Spacing:	50 MHz and 100 MHz/ 120 kHz
Modulations:	QPSK, 16QAM and 64QAM
Emission designators:	46M2W7D and 95M4W7D
Emission designators Carrier Aggregation:	395MW7D (4x 100 MHz) and 792MW7D (8x 100 MHz)
RF power Tolerance:	+2.4/ -2.0 dB
CPRI Speed	10.1 Gbps

The information above is supplied by the manufacturer.

Purpose of test

The purpose of the tests is to verify compliance to the performance characteristics specified in applicable items of FCC CFR 47 Part 30.

Operation modes during measurements

The measurements were performed with the test object transmitting test models as defined in 3GPP TS 38.141-2. Test model NR-FR2 TM 1.1 is used to represent QPSK, test model NR-FR2 TM 3.2 to represent 16QAM, test model NR-FR2 TM 3.1 to represent 64QAM modulation

The settings below were deemed representative for worst case settings, for all traffic scenarios when settings with different modulations and RF configurations was found to represent worst case settings.

MIMO mode, NR-FR2 TM1.1, QPSK with the beams locked in boresight. All measurements were performed with the test object configured for maximum transmit power.

The measurement shall be done during active part of transmission, or if the measurement is performed with constant duty cycle <98%, the result shall be adjusted for the duty cycle according to ANSI C63.26 5.2.4.3.4. The duty cycle was measured to 74% and to compensate for this 1.29 dB was added to the test results.

Measurements

The test object was powered with 120 VAC 60 Hz by an external power supply. Additional connections are documented in the setup drawings for radiated measurements.

Far field distance for power, OBW and Band edge measurements is 2.68 m, based on the EUT antenna dimensions and the highest transmitter frequency (40 GHz).

Far field distances for OOB emissions is based on the measurement antenna dimension and highest frequency in the measurement range :

Frequency range [GHz]	Far field distance R [m]	Measurement distance [m]
18 – 26.5	0.73	3
26.5 – 40	0.48	3
40 – 60	0.34	3
60 – 90	0.22	1
90 – 110	0.17	1
110 – 150	0.13	1
150 – 170	0.13	0.5
170 – 200	0.10	0.5

Formula for far field distance calculation, with R being far field distance and D meaning antenna aperture size:

$$R = 2x D^2 / \lambda$$

References

Measurements were done according to relevant parts of the following standards:

CFR 47 part 30, May 2020

ANSI C63.26-2015

KDB 842590 D01 Upper Microwave Flexible Use Service v01r01

KDB 971168 D01 Power Meas License Digital Systems v03r01

KDB 971168 D03 IM Emission Repeater Amp v01

3GPP TS 38.141-2 V15.5.0 (2020-03)

3GPP TR 37.842 V13.3.0 (2020-01)

Measurement equipment

	Calibration Due	RISE number
Anechoic chamber, Hertz	2021-09	BX50194
R&S FSW 43	2021-07	902 073
R&S ESU	2021-07	901 385
R&S ZNB 40	2021-07	BX50051
RF Cable VNA-calibration	2021-01	BX50189
RF Cable VNA-calibration	2021-01	BX50190
RF Cable	2021-05	BX50236
RF Cable	2021-09	BX50192
RF Cable	2021-01	BX81431
RF Cable	2021-05	BX81423
RF Cable	2021-09	503 681
RF Cable FSW-B21	2021-09	BX62069
RF Cable FSW-B21	2021-09	BX62073
Bilog antenna Schaffner 6143A	2021-08	504079
EMCO Horn Antenna 3115	2021-07	502 175
EMCO Horn Antenna 3115	2021-12	902 212
EMCO Horn Antenna 3116	2021-07	503 279
Flann STD Gain Horn Antenna 20240-20	-	KWP02600
Flann STD Gain Horn Antenna 22240-20	-	KWP02601
Flann STD Gain Horn Antenna 24240-20	-	BX92414
Flann STD Gain Horn Antenna 26240-20	-	BX92416
Flann STD Gain Horn Antenna 27240-20	-	BX92417
Flann STD Gain Horn Antenna 29240-20	-	BX92419
Flann STD Gain Horn Antenna 30240-20	-	BX92420
Mixer FS-Z60	2021-12	BX90566
Mixer FS-Z90	2022-01	BX90567
Mixer FS-Z110	2021-07	BX81425
Mixer FS-Z170	2021-02	BX81426
Mixer FS-Z220	2021-07	BX81427
µComp Nordic, Low Noise Amplifier	2021-01	901 544
Miteq, Low Noise Amplifier	2021-01	503 278
Temperature and humidity meter, Testo 615	2021-06	503 498

EAB Measurement equipment

Calibrated at RISE before testing.

	Calibration Due	S/N
Marki Microwave FLP2650 Low pass filter	2021-04	1827
Qualwave QBF-26400-33000-60 Band pass filter	2021-04	182704

Uncertainties

Measurement and test instrument uncertainties are described in the quality assurance documentation "SP-QD 10885". The uncertainties are calculated with a coverage factor $k=2$ (95% level of confidence).

Compliance evaluation is based on a shared risk principle with respect to the measurement uncertainty.

Reservation

The test results in this report apply only to the particular test object as declared in the report.

Delivery of test object

The test object was delivered: 2020-11-14.

Manufacturer's representative

Mikael Jansson, Ericsson AB.

Test engineers

Tomas Lennhager, Björn Skönvall and Karl Flysjö, RISE


Test participant(-s)

Xiang Yue, Ericsson AB (partly)

Test frequencies used for radiated measurements

Frequency Hor/ Ver [MHz]	Symbolic name	Comment
38425.08	BL ₅₀	50 MHz BW, TX bottom frequency configuration lower band
38574.96	TL ₅₀	50 MHz BW, TX top frequency configuration lower band
38625.00	BH ₅₀	50 MHz BW, TX bottom frequency configuration higher band
39300.00	MH ₅₀	50 MHz BW, TX middle frequency configuration higher band
39975.00	TH ₅₀	50 MHz BW, TX top frequency configuration higher band
38450.04	BL ₁₀₀	100 MHz BW, TX bottom frequency configuration lower band
38550.00	TL ₁₀₀	100 MHz BW, TX bottom frequency configuration lower band
38649.96	BH ₁₀₀	100 MHz BW, TX top frequency configuration lower band
39300.00	MH ₁₀₀	100 MHz BW, TX bottom frequency configuration higher band
39949.92	TH ₁₀₀	100 MHz BW, TX middle frequency configuration higher band
38450.04 38550.00	BL ₂₁₀₀	100 MHz BW, 2 carrier, TX bottom frequencies configuration lower band
39849.96 39949.92	TH ₂₁₀₀	100 MHz BW, 2 carrier, TX top frequencies configuration higher band
38425.08 38475.00 38775.00	Bim ₅₀	50 MHz BW, 3 carrier, TX bottom frequencies configuration lower band
39625.08 39924.96 39975.00	Tim ₅₀	50 MHz BW, 3 carrier, TX top frequencies configuration higher band
38450.04 38550.00 38649.96 38749.92	BL ₄₁₀₀	100 MHz BW, 4 carrier, TX bottom frequencies configuration lower band
39649.92 39750.00 39849.96 39949.92	TH ₄₁₀₀	100 MHz BW, 4 carrier, TX top frequencies configuration higher band
38450.04 38550.00 39649.96 38749.92 38850.00 38949.96 39049.92 39150.00	BL ₈₁₀₀	100 MHz BW, 8 carrier, TX Bottom frequencies configuration lower band
39249.96 39349.92 39450.00 39549.96 39649.92 39750.00 39849.96 39949.92	TH ₈₁₀₀	100 MHz BW, 8 carrier, TX top frequencies configuration higher band

Test setup: radiated measurements



Test object:

1.	AIR 1281 B260, KR D 901 166/6, rev. R1D, s/n: C82A593388 with FCC ID: TA8AKRD901166 Radio Software: CXP 203 0045/1, rev. R6A611
----	---

Associated equipment:

2.	Testing Equipment: Baseband 6630, KDU 137 848/1, rev. R3B, s/n: E23B220389 with software: CXP9024418/15, rev. R20A154
----	---

Functional test equipment:

3.	Computer, HP ZBook, BAMS - 1001530471
4.	GPS Active Antenna, KRE 101 2082/1 GPS 02 01, NCD 901 41/1, rev. R1D, s/n: A401804384

Interfaces:

1, Optical Interface Link, single mode opto fibre	Signal
2, Optical Interface Link, single mode opto fibre	Signal
3, Optical Interface Link, single mode opto fibre	Signal
4, Optical Interface Link, single mode opto fibre	Signal
Power input configuration AC: 120 VAC 60Hz	Power
EXT Alarm, shielded multi-wire	Signal
Ground wire	Ground

RF power output measurements according to CFR 47 §30.202

Date	Temperature	Humidity
2020-11-16	23 °C ± 3 °C	36 % ± 5 %
2020-11-17	23 °C ± 3 °C	23 % ± 5 %
2020-11-18	23 °C ± 3 °C	36 % ± 5 %
2020-12-01	23 °C ± 3 °C	20 % ± 5 %

Test set-up and procedure

The test object was located in an anechoic chamber. The measuring antenna was aligned to the centre of the PAAM. A turn table was used to find the highest output power. A signal analyzer with the channel power function activated was used to measure the output power with the RMS detector activated. The bandwidth setting of the channel power function was set to 100 MHz.

A substitution measurement defined in 3GPP TR 37.842 chapter 10.3.1.1.2 was used to get the actual correction factor (Transducer factor A-D in the figure 1 below) with a Network analyzer (ZNB 40).




Figure 1: Indoor Anechoic Chamber calibration system setup for EIRP

Stage 1 - Calibration:

- 1) Connect the reference antenna and the receiving antenna to the measurement RF out port and RF in port of the network analyzer, respectively, as shown in figure 1.
- 2) Install the reference antenna with its *beam peak direction* and the height of its phase centre aligned with the receiving antenna.
- 3) Set the centre frequency of the network analyzer to the carrier centre frequency of the tested signal for EIRP measurement of the EUT and measure $LF_{EIRP, E \rightarrow D}$, which is equivalent to $20 \log |S_{21}|$ (dB) obtained by the network analyzer:
 $LF_{EIRP, E \rightarrow D}$: Pathloss between E and D in figure 1.

- 4) Measure the cable loss, $LF_{EIRP, E \rightarrow F}$ between the reference antenna connector and the network analyzer connector:
 $LF_{EIRP, E \rightarrow F}$: Cable loss between E and F in figure 1.
- 5) Calculate the calibration value between A and D with the following formula:
 $L_{EIRP_cal, A \rightarrow D} = LF_{EIRP, E \rightarrow D} + G_{REF_ANT_EIRP, A \rightarrow F} - LF_{EIRP, E \rightarrow F}$.
 $L_{EIRP_cal, A \rightarrow D}$: Calibration value between A and D in figure 1. Was implemented in the spectrum analyzer as a transducer.
 $G_{REF_ANT_EIRP, A \rightarrow F}$: Antenna gain of the reference antenna.

Stage 2 - Measurement:

- 6) Uninstall the reference antenna and install the EUT with the manufacturer declared coordinate system reference point in the same place as the phase centre of the reference antenna. The manufacturer declared coordinate system orientation of the EUT is set to be aligned with the testing system.
- 7) Measure the mean power, $P_{R_EUT_EIRP, D}$, D in figure 1.
- 8) Calculate the EIRP with the following formula:

$$EIRP = P_{R_EUT_EIRP, D} + L_{EIRP_cal, A \rightarrow D}$$

Test Setup, measuring distance 3m:

Measurement equipment	RISE number
Anechoic chamber, Hertz	BX50194
R&S FSW 43	902 073
R&S ZNB 40	BX50051
EMCO Horn Antenna 3116	503 279
FLANN Std gain 22240-20	KWP02601
RF Cable	BX81423
Testo 615, temperature and humidity meter	503 498

Measurement uncertainty: 3.3 dB

Results

Single carrier Config mode 2

Beam index 0 Bore site, Bandwidth 50MHz, QPSK
Nominal rated output power (EIRP) per Beam: 47 dBm/ Polarization.

	Output power per 100 MHz, EIRP [RMS dBm] Vertical/ Horizontal
Symbolic name	Carrier 1
BL ₅₀	47.18/ 46.94
TL ₅₀	47.21/ 47.04
BH ₅₀	47.39/ 47.25
MH ₅₀	47.02/ 46.91
TH ₅₀	46.48/ 45.94

Beam index 0 Bore site, Bandwidth 100MHz, QPSK
Nominal rated output power (EIRP) per Beam: 47 dBm/ Polarization.

	Output power per 100 MHz, EIRP [RMS dBm] Vertical/ Horizontal
Symbolic name	Carrier 1
BL1 ₁₀₀	47.00/ 46.87
TL1 ₁₀₀	46.59/ 46.94
BH1 ₁₀₀	46.95/ 47.06
MH1 ₁₀₀	47.14/ 46.87
TH1 ₁₀₀	46.20/ 45.88

Multi carrier

2-Carrier Config mode 2

Beam index 0 Bore site, Bandwidth 100MHz, QPSK

Nominal rated output power (EIRP) per Beam: 50 dBm/ Polarization.

	Output power per 100 MHz, EIRP [RMS dBm] Vertical/ Horizontal		
Symbolic name	Carrier 1	Carrier 2	Total (per 200 MHz)
BL2 ₁₀₀	43.85/ 43.90	44.54/ 43.97	47.23/ 46.96
TH2 ₁₀₀	43.00/ 43.05	43.10/ 48.43	46.06/ 45.86

4-Carrier Config mode 2

Beam index 0 Bore site, Bandwidth 100MHz, QPSK

Nominal rated output power (EIRP) per Beam: 50 dBm/ Polarization.

	Output power per 100 MHz, EIRP [RMS dBm] Vertical/ Horizontal				
Symbolic name	Carrier 1	Carrier 2	Carrier 3	Carrier 4	Total (per 400 MHz)
BL4 ₁₀₀	40.76/ 41.58	40.76/ 41.16	41.34/ 41.21	41.25/ 42.24	47.06/ 47.60
TH4 ₁₀₀	40.59/ 41.46	39.97/ 40.27	40.03/ 39.69	39.82/ 40.70	46.13/ 46.60

8-Carrier Config mode 1

Beam index 0 Boresight, Carrier Bandwidth 100 MHz, QPSK

Nominal rated output power (EIRP) per Beam: 41.0 dBm/ Polarization.

	Output power per 100 MHz, EIRP [RMS dBm] Vertical/ Horizontal									
	Beam 1					Beam 2				
Symbolic name	A	B	C	D	Total Power Beam 1 (per 400 MHz)	E	F	G	H	Total power Beam 2 (per 400 MHz)
BL8 ₁₀₀	34.95/ 35.14	34.69/ 34.85	35.15/ 34.92	35.52/ 35.87	41.11/ 41.23	35.52/ 36.41	36.01/ 36.26	36.83/ 36.29	37.14/ 37.23	42.44/ 42.59
TH8 ₁₀₀	34.88/ 35.02	34.35/ 34.41	34.91/ 34.49	35.29/ 35.33	40.89/ 40.85	34.86/ 35.54	34.32/ 34.45	34.65/ 34.10	34.63/ 34.72	40.64/ 40.76

Limits

CFR47 §30.202 Power limits.

- (a) For fixed and base stations operating in connection with mobile systems, the average power of the sum of all antenna elements is limited to an equivalent isotropically radiated power (EIRP) density of +75dBm/100 MHz. For channel bandwidths less than 100 MHz the EIRP must be reduced proportionally and linearly based on the bandwidth relative to 100 MHz.

Complies?	Yes
-----------	-----

Occupied bandwidth measurements according to CFR47 2.1049

Date	Temperature	Humidity
2020-11-16	23 °C ± 3 °C	36 % ± 5 %
2020-11-17	23 °C ± 3 °C	23 % ± 5 %
2020-11-18	23 °C ± 3 °C	36 % ± 5 %
2020-12-01	23 °C ± 3 °C	20 % ± 5 %

Test set-up and procedure

The test object was located in a anechoic chamber. The measuring antenna was aligned to the centre of the of the PAAM. A turn table was used to find the highest output power. A signal analyzer with Peak detector and max hold was used to measure the OBW.

Test Setup, measuring distance 3m:

Measurement equipment	RISE number
Anechoic chamber, Hertz	BX50194
R&S FSW 43	902 073
R&S ZNB 40	BX50051
EMCO Horn Antenna 3116	503 279
FLANN Std gain 22240-20	KWP02601
RF Cable	BX81423
Testo 615, temperature and humidity meter	503 498

Measurement uncertainty: 3.3 dB

Results

Single carrier, Config mode 2, Bandwidth: 50MHz Modulation: QPSK

Diagram	Symbolic name	Polarization	Occupied BW (99%) [MHz]
1.1	TL ₅₀	Hor	46.220
1.2	TL ₅₀	Ver	46.188

Single carrier, Config mode 2, Bandwidth: 100MHz Modulation: QPSK

Diagram	Symbolic name	Polarization	Occupied BW (99%) [MHz]
1.3	TL ₁₀₀	Hor	95.364
1.4	TL ₁₀₀	Ver	95.307

Carrier Aggregation, Config mode 2, Bandwidth: 4x 100MHz, Modulation: QPSK

Diagram	Symbolic name	Polarization	Occupied BW (99%) [MHz]
1.5	BL4 ₁₀₀	Hor	395.221
1.6	BL4 ₁₀₀	Ver	394.422

Carrier Aggregation, Config mode 1, Bandwidth: 8x 100MHz, Modulation: QPSK

Diagram	Symbolic name	Polarization	Occupied BW (99%) [MHz]
1.7	BL8 ₁₀₀	Hor	792.262
1.8	BL8 ₁₀₀	Ver	792.509

Diagram 1.1, TL₅₀, QPSK, Horizontal:



Diagram 1.2, TL₅₀, QPSK, Vertical:



Diagram 1.3, TL₁₀₀, QPSK, Horizontal:



Diagram 1.4, TL₁₀₀, QPSK, Vertical::



Diagram 1.5, BL4₁₀₀, QPSK, Horizontal:



13:16:11 01.12.2020

Diagram 1.6, BL4₁₀₀, QPSK, Vertical::



13:14:01 01.12.2020

Diagram 1.7, BL8₁₀₀, QPSK, Horizontal:



10:33:55 01.12.2020

Diagram 1.8, BL8₁₀₀, QPSK, Vertical::



11:04:49 01.12.2020

Field strength of spurious radiation measurements according to CFR 47 §30.203

Date	Temperature	Humidity
2020-11-16	23 °C ± 3 °C	36 % ± 5 %
2020-11-17	23 °C ± 3 °C	23 % ± 5 %
2020-11-18	23 °C ± 3 °C	36 % ± 5 %
2020-11-19	23 °C ± 3 °C	23 % ± 5 %
2020-11-20	24 °C ± 3 °C	15 % ± 5 %
2020-11-21	24 °C ± 3 °C	21 % ± 5 %
2020-11-25	23 °C ± 3 °C	28 % ± 5 %
2020-11-26	23 °C ± 3 °C	26 % ± 5 %
2020-11-30	23 °C ± 3 °C	17 % ± 5 %
2020-12-01	23 °C ± 3 °C	20 % ± 5 %
2020-12-02	23 °C ± 3 °C	20 % ± 5 %

The measurements were performed with both horizontal and vertical polarization of the antenna. The measurement was performed with a RBW of 1 MHz. The antenna distance and test object height in the different frequency ranges is described below.

In the test range from 40 – 200 GHz

A propagation loss in free space was calculated. The used formula was

$$\gamma = 20 \log \left(\frac{4\pi D}{\lambda} \right), \gamma \text{ is the propagation loss and } D \text{ is the antenna distance.}$$

For 40 – 60 GHz D was 3.0m, for 60 – 150 GHz D was 1.0m and for 150 – 200 GHz D was 0.5m.

In the test range from 30MHz – 40 GHz a substitution measurement defined in 3GPP TR 37.842 chapter 10.3.1.1.2 was used to get the actual correction factor (Transducer factor A-D in the figure 1 below) with a Network analyzer (ZNB 40).




Figure 1: Indoor Anechoic Chamber calibration system setup for EIRP

Stage 1 - Calibration:

- 1) Connect the reference antenna and the receiving antenna to the measurement RF out port and RF in port of the network analyzer, respectively, as shown in figure 1.
- 2) Install the reference antenna with its *beam peak direction* and the height of its phase centre aligned with the receiving antenna.
- 3) Set the centre frequency of the network analyzer to the carrier centre frequency of the tested signal for EIRP measurement of the EUT and measure $LF_{EIRP, E \rightarrow D}$, which is equivalent to $20\log|S21|$ (dB) obtained by the network analyzer:
 $LF_{EIRP, E \rightarrow D}$: Pathloss between E and D in figure 1.
- 4) Measure the cable loss, $LF_{EIRP, E \rightarrow F}$ between the reference antenna connector and the network analyzer connector:
 $LF_{EIRP, E \rightarrow F}$: Cable loss between E and F in figure 1.
- 5) Calculate the calibration value between A and D with the following formula:
 $LEIRP_{cal, A \rightarrow D} = LF_{EIRP, E \rightarrow D} + G_{REF_ANT_EIRP, A \rightarrow F} - LF_{EIRP, E \rightarrow F}$.
 $LEIRP_{cal, A \rightarrow D}$: Calibration value between A and D in figure 1. Was implemented in the spectrum analyzer as a transducer.
 $G_{REF_ANT_EIRP, A \rightarrow F}$: Antenna gain of the reference antenna.

Stage 2 - Measurement:

- 6) Uninstall the reference antenna and install the EUT with the manufacturer declared coordinate system reference point in the same place as the phase centre of the reference antenna. The manufacturer declared coordinate system orientation of the EUT is set to be aligned with the testing system.
- 7) Measure the mean power, $P_{R_EUT_EIRP, D}$, D in figure 1.
- 8) Calculate the EIRP with the following formula:

$$EIRP = P_{R_EUT_EIRP, D} + L_{EIRP_cal, A \rightarrow D}$$

The measurement procedure was as the following:

1. An EIRP pre-scan with the measurement antenna in horizontal and vertical polarization is performed with RMS detector and Max Hold on the spectrum analyzer. The turn table was slowly rotating from 0-360 degrees.
2. EIRP spurious radiation on frequencies closer than 10 dB to the TRP limit in the pre-scan a manual search for maximum response was done.
3. If the recorded EIRP value was above the TRP limit, a TRP measurement was done according to KDB 842590 D01 chapter 4.4. Overview of the methods.
 - a. Two Cut method according to KDB 842590 D01 chapter 4.4.2.2
 - i. EUT set in vertical orientation
 - ii. EIRP measurement samples with horizontal and vertical polarization of the measurement antenna. Angular step size based on frequency and dimension of the EUT
 - iii. EUT set in horizontal orientation
 - iv. EIRP measurement samples with horizontal and vertical polarization of the measurement antenna. Angular step size based on frequency and dimension of the EUT.
 - v. $TRP = EIRP$ measurement samples averaged $+ \Delta TRP$. ($\Delta TRP =$ Margin factor based on grid selection).

- b. Two Cut method when pattern multiplication is applicable and used according to KDB 842590 D01 chapter 4.4.2.3
 - i. EUT set in vertical orientation
 - ii. EIRP measurement samples with horizontal and vertical polarization of the measurement antenna. Angular step size based on frequency and dimension of the EUT
 - iii. EUT set in horizontal orientation
 - iv. EIRP measurement samples with horizontal and vertical polarization of the measurement antenna. Angular step size based on frequency and dimension of the EUT.
 - v. TRP is calculated using the formula in Appendix E of KDB 842590 D01
- c. EIRP to Conducted Power Conversion in Band Edge Using Antenna Gain according to KDB 842590 D01 chapter 4.4.2.5
 - i. Convert each radiated measurement to conducted power/BW using the equations:
Conducted Power level (dBm) at any frequency/BW = Measured EIRP level (dBm)/BW – EUT antenna Gain (dBi)
 - ii. Sum the radiated power Horizontal and Vertical polarisations for total conducted power level/BW.
 - iii. Evaluate the pass/fail decision by comparing total conducted power level/BW against the applicable TRP limit.
- d. Spherical Grid Method, according to KDB 842590 D01 chapter 4.4.2.4
 - i. EUT set in horizontal orientation bottom of the EUT to the right.
 - ii. EIRP measurement samples with horizontal and vertical polarization of the measurement antenna. Angular step size of the turn table was 15 degrees from 0 – 165 degrees and 195 – 360 degrees. In cone of radiation 165 – 195 degrees the step size of the turn table was 1 degree.
 - iii. EUT was changed in 15 degrees step from horizontal bottom right to horizontal bottom to the left (twelve steps). Step ii. was repeated for all twelve steps.
 - iv. TRP was calculated according to Appendix B in KDB 842590.

Measurement equipment

	RISE number
Anechoic chamber, Hertz	BX50194
R&S FSW 43	902 073
R&S ESU	901 553
R&S ZNB 40	BX50051
RF Cable VNA-calibration	BX50189
RF Cable VNA-calibration	BX50190
RF Cable	BX50236
RF Cable	BX50192
RF Cable	BX81431
RF Cable	BX81423
RF Cable	503 681
RF Cable FSW-B21	BX62069
RF Cable FSW-B21	BX62073
Bilog antenna Schaffner 6143A	504079
EMCO Horn Antenna 3115	502 175
EMCO Horn Antenna 3115	902 212
EMCO Horn Antenna 3116	503 279
Flann STD Gain Horn Antenna 20240-20	KWP02600
Flann STD Gain Horn Antenna 22240-20	KWP02601
Flann STD Gain Horn Antenna 24240-20	BX92414
Flann STD Gain Horn Antenna 26240-20	BX92416
Flann STD Gain Horn Antenna 27240-20	BX92417
Flann STD Gain Horn Antenna 29240-20	BX92419
Flann STD Gain Horn Antenna 30240-20	BX92420
Mixer FS-Z60	BX90566
Mixer FS-Z90	BX90567
Mixer FS-Z110	BX81427
Mixer FS-Z170	BX81428
Mixer FS-Z220	BX81429
µComp Nordic, Low Noise Amplifier	901 544
Miteq, Low Noise Amplifier	503 278
Temperature and humidity meter, Testo 615	503 498

EAB Measurement equipment

Calibrated at RISE before testing.

	S/N
Marki Microwave FLP2650 Low pass filter	1827
Qualwave QBF-26400-33000-60 Band pass filter	182704

Results

The diagrams represents worst case configurations for each frequency range.

Diagram	Symbolic name	Config mode	Pol	Frequency range	Measurement method	“Early exit?”
2.1a	BL ₁₀₀	2	Hor	30-1000 MHz	Pre scan Max hold EIRP	Yes
2.1b	BL ₁₀₀	2	Ver	30-1000 MHz	Pre scan Max hold EIRP	Yes
2.2a	BL ₈₁₀₀	1	Hor	30-1000 MHz	Pre scan Max hold EIRP	Yes
2.2b	BL ₈₁₀₀	1	Ver	30-1000 MHz	Pre scan Max hold EIRP	Yes
2.3a	BL ₁₀₀	2	Hor	1-18 GHz	Pre scan Max hold EIRP	Yes
2.3b	BL ₁₀₀	2	Ver	1-18 GHz	Pre scan Max hold EIRP	Yes
2.4a	BL ₈₁₀₀	1	Hor	1-18 GHz	Pre scan Max hold EIRP	Yes
2.4b	BL ₈₁₀₀	1	Ver	1-18 GHz	Pre scan Max hold EIRP	Yes
2.5a	BL ₁₀₀	2	Hor	18-26.5 GHz	Pre scan Max hold EIRP	Yes
2.5b	BL ₁₀₀	2	Ver	18-26.5 GHz	Pre scan Max hold EIRP	Yes
2.6a	BL ₈₁₀₀	1	Hor	18-26.5 GHz	Pre scan Max hold EIRP	Yes
2.6b	BL ₈₁₀₀	1	Ver	18-26.5 GHz	Pre scan Max hold EIRP	Yes
2.7a	TH ₁₀₀	2	Hor	26.5-33 GHz	Pre scan Max hold EIRP	Yes
2.7b	TH ₁₀₀	2	Ver	26.5-33 GHz	Pre scan Max hold EIRP	Yes
2.8a	TH ₈₁₀₀	1	Hor	26.5-33 GHz	Pre scan Max hold EIRP	Yes
2.8b	TH ₈₁₀₀	1	Ver	26.5-33 GHz	Pre scan Max hold EIRP	Yes
2.9a	BL ₅₀	2	Hor	33-40 GHz 33-37.4 GHz	Pre scan Max hold EIRP	No Yes ²
2.9b	BL ₅₀	2	Ver	33-40 GHz 33-37.4 GHz	Pre scan Max hold EIRP	No Yes ²
2.9c	BL ₅₀	2	Hor	37.4-38.4 GHz	Pre scan Max average EIRP	Yes ¹
2.9d	BL ₅₀	2	Ver	37.4-38.4 GHz	Pre scan Max average EIRP	Yes ¹
2.10a	BL ₈₁₀₀	1	Hor	33-40 GHz 33-37.4 GHz	Pre scan Max hold EIRP	No Yes ²
2.10b	BL ₈₁₀₀	1	Ver	33-40 GHz 33-37.4 GHz	Pre scan Max hold EIRP	No Yes ²
2.10c	BL ₈₁₀₀	1	Hor	37.4-38.4 GHz	Pre scan Max average EIRP	Yes ¹
2.10d	BL ₈₁₀₀	1	Ver	37.4-38.4 GHz	Pre scan Max average EIRP	Yes ¹
2.11a	Bim ₅₀	2	Hor	33-40 GHz 33-37.4 GHz	Pre scan Max hold EIRP	No Yes ²
2.11b	Bim ₅₀	2	Ver	33-40 GHz 33-37.4 GHz	Pre scan Max hold EIRP	No Yes ²
2.11c	Bim ₅₀	2	Hor	37.4-38.4 GHz	Pre scan Max average EIRP	Yes ¹
2.11d	Bim ₅₀	2	Ver	37.4-38.4 GHz	Pre scan Max average EIRP	Yes ¹
2.12a	TH ₄₁₀₀	2	Hor	33-40 GHz	Pre scan Max hold EIRP	No
2.12b	TH ₄₁₀₀	2	Ver	33-40 GHz	Pre scan Max hold EIRP	No
2.12c	TH ₄₁₀₀	2	Hor/Ver	35.67-35.77 GHz	Two cut TRP	Compliant to TRP limit
2.13a	TL ₅₀	2	Hor	38.35-38.85 GHz	Pre scan Max average EIRP	Yes ¹
2.13b	TL ₅₀	2	Ver	38.35-38.85 GHz	Pre scan Max average EIRP	Yes ¹
2.14a	BH ₅₀	2	Hor	38.35-38.85 GHz	Pre scan Max average EIRP	Yes ¹
2.14b	BH ₅₀	2	Ver	38.35-38.85 GHz	Pre scan Max average EIRP	Yes ¹

¹⁾ Calculated conducted power based on antenna gain below limit

²⁾ Compliant to TRP limit based on Lower EIRP compared to TH₄₁₀₀ (Diagram 2.12)

Diagram	Symbolic name	Config mode	Pol	Frequency range	Measurement method	“Early exit?”
2.15a	TH ₅₀	2	Hor	40-43 GHz	Pre scan Max hold EIRP	No
2.15b	TH ₅₀	2	Ver	40-43 GHz	Pre scan Max hold EIRP	No
2.15c	TH ₅₀	2	Hor	40-43 GHz	Pre scan Max average EIRP	Yes ¹
2.15d	TH ₅₀	2	Ver	40-43 GHz	Pre scan Max average EIRP	Yes ¹
2.16a	TH ₈₁₀₀	1	Hor	40-43 GHz	Pre scan Max hold EIRP	No
2.16b	TH ₈₁₀₀	1	Ver	40-43 GHz	Pre scan Max hold EIRP	No
2.16c	TH ₈₁₀₀	1	Hor	40-43 GHz	Pre scan Max average EIRP	Yes ¹
2.16d	TH ₈₁₀₀	1	Ver	40-43 GHz	Pre scan Max average EIRP	Yes ¹
2.17a	Tim ₅₀	2	Hor	40-43 GHz 40.4-43 GHz	Pre scan Max hold EIRP	No Yes ³
2.17b	Tim ₅₀	2	Ver	40-43 GHz 40.4-43 GHz	Pre scan Max hold EIRP	No Yes ³
2.17c	Tim ₅₀	2	Hor	40-43 GHz	Pre scan Max average EIRP	No
2.17d	Tim ₅₀	2	Ver	40-43 GHz	Pre scan Max average EIRP	No
2.17e	Tim ₅₀	2	Hor/ Ver	40-40.4 GHz	Two cut TRP	Compliant to TRP limit
2.18a	BL ₁₀₀	2	Hor	40-43 GHz	Pre scan Max hold EIRP	No
2.18b	BL ₁₀₀	2	Ver	40-43 GHz	Pre scan Max hold EIRP	No
2.18c	BL ₁₀₀	2	Hor/ Ver	40.6-41.6 GHz	Spherical grid Method TRP	Compliant to TRP limit
2.19a	BL ₅₀	2	Hor	43-60 GHz	Pre scan Max hold EIRP	Yes
2.19b	BL ₅₀	2	Ver	43-60 GHz	Pre scan Max hold EIRP	Yes
2.20a	BL ₈₁₀₀	1	Hor	43-60 GHz	Pre scan Max hold EIRP	Yes
2.20b	BL ₈₁₀₀	1	Ver	43-60 GHz	Pre scan Max hold EIRP	Yes
2.21a	BL ₁₀₀	2	Hor	60-80 GHz	Pre scan Max hold EIRP	Yes
2.21b	BL ₁₀₀	2	Ver	60-80 GHz	Pre scan Max hold EIRP	Yes
2.22a	BL ₈₁₀₀	1	Hor	60-80 GHz	Pre scan Max hold EIRP	Yes
2.22b	BL ₈₁₀₀	1	Ver	60-80 GHz	Pre scan Max hold EIRP	Yes
2.23a	BL ₁₀₀	2	Hor	80-100 GHz	Pre scan Max hold EIRP	Yes
2.23b	BL ₁₀₀	2	Ver	80-100 GHz	Pre scan Max hold EIRP	Yes
2.24a	BL ₈₁₀₀	1	Hor	80-100 GHz	Pre scan Max hold EIRP	Yes
2.24b	BL ₈₁₀₀	1	Ver	80-100 GHz	Pre scan Max hold EIRP	Yes
2.25a	BL ₁₀₀	2	Hor	100-110 GHz	Pre scan Max hold EIRP	Yes
2.25b	BL ₁₀₀	2	Ver	100-110 GHz	Pre scan Max hold EIRP	Yes
2.26a	BL ₈₁₀₀	1	Hor	100-110 GHz	Pre scan Max hold EIRP	Yes
2.26b	BL ₈₁₀₀	1	Ver	100-110 GHz	Pre scan Max hold EIRP	Yes
2.27a	BL ₁₀₀	2	Hor	110-130 GHz	Pre scan Max hold EIRP	Yes
2.27b	BL ₁₀₀	2	Ver	110-130 GHz	Pre scan Max hold EIRP	Yes
2.28a	BL ₈₁₀₀	1	Hor	110-130 GHz	Pre scan Max hold EIRP	Yes
2.28b	BL ₈₁₀₀	1	Ver	110-130 GHz	Pre scan Max hold EIRP	Yes
2.29a	BL ₁₀₀	2	Hor	130-150 GHz	Pre scan Max hold EIRP	Yes
2.29b	BL ₁₀₀	2	Ver	130-150 GHz	Pre scan Max hold EIRP	Yes
2.30a	BL ₈₁₀₀	1	Hor	130-150 GHz	Pre scan Max hold EIRP	Yes
2.30b	BL ₈₁₀₀	1	Ver	130-150 GHz	Pre scan Max hold EIRP	Yes

³⁾ Compliant to TRP limit based on Lower EIRP compared to BL₁₀₀ (Diagram 2.18)

Diagram	Symbolic name	Config mode	Pol	Frequency range	Measurement method	“Early exit?”
2.31a	BL ₁₀₀	2	Hor	150-170 GHz	Pre scan Max hold EIRP	Yes
2.31b	BL ₁₀₀	2	Ver	150-170 GHz	Pre scan Max hold EIRP	Yes
2.32a	BL ₈₁₀₀	1	Hor	150-170 GHz	Pre scan Max hold EIRP	Yes
2.32b	BL ₈₁₀₀	1	Ver	150-170 GHz	Pre scan Max hold EIRP	Yes
2.33a	BL ₁₀₀	2	Hor	170-185 GHz	Pre scan Max hold EIRP	Yes
2.33b	BL ₁₀₀	2	Ver	170-185 GHz	Pre scan Max hold EIRP	Yes
2.34a	BL ₈₁₀₀	1	Hor	170-185 GHz	Pre scan Max hold EIRP	Yes
2.34b	BL ₈₁₀₀	1	Ver	170-185 GHz	Pre scan Max hold EIRP	Yes
2.35a	BL ₁₀₀	2	Hor	185-200 GHz	Pre scan Max hold EIRP	Yes
2.35b	BL ₁₀₀	2	Ver	185-200 GHz	Pre scan Max hold EIRP	Yes
2.36a	BL ₈₁₀₀	1	Hor	185-200 GHz	Pre scan Max hold EIRP	Yes
2.36b	BL ₈₁₀₀	1	Ver	185-200 GHz	Pre scan Max hold EIRP	Yes

Measurement uncertainty: 30 – 1000 MHz 3.1 dB
 1 – 18 GHz, 3.0 dB
 18 – 40 GHz, 3.1 dB
 40 – 60 GHz, 2.27 dB
 60 – 75 GHz, 2.70 dB
 75 – 110 GHz, 4.24 dB
 110 – 150 GHz, 3.61 dB
 150 – 170 GHz, 4.67 dB
 170 – 200 GHz, 5.10 dB

Limits

CFR 47 §30.203 Emission limits.

(a) The conductive power or the total radiated power of any emission outside a licensee's frequency block shall be –13 dBm/MHz or lower. However, in the bands immediately outside and adjacent to the licensee's frequency block, having a bandwidth equal to 10 percent of the channel bandwidth, the conductive power or the total radiated power of any emission shall be –5 dBm/MHz or lower.


(b)(1) Compliance with this provision is based on the use of measurement instrumentation employing a resolution bandwidth of 1 megahertz or greater.

(2) When measuring the emission limits, the nominal carrier frequency shall be adjusted as close to the licensee's frequency block edges as the design permits.

(3) The measurements of emission power can be expressed in peak or average values.


Complies?	Yes
-----------	-----

Diagram 2.1a: Pre scan 30 – 1000 MHz, Symbolic name: BL₁₀₀, EIRP Horizontal polarization




Date: 19.NOV.2020 16:51:19

Diagram 2.1b: Pre scan 30 – 1000 MHz, Symbolic name: BL₁₀₀, EIRP Vertical polarization




Date: 19.NOV.2020 17:00:07

Diagram 2.2a: Pre scan 30 – 1000 MHz, Symbolic name: BL8₁₀₀, EIRP Horizontal polarization



Date: 19.NOV.2020 16:41:51

Diagram 2.2b: Pre scan 30 – 1000 MHz, Symbolic name: BL8₁₀₀, EIRP Vertical polarization



Date: 19.NOV.2020 16:36:35

Diagram 2.3a: Pre scan 1 – 18 GHz, Symbolic name: BL₁₀₀, EIRP Horizontal polarization




Diagram 2.3b: Pre scan 1 – 18 GHz, Symbolic name: BL₁₀₀, EIRP Vertical polarization




Diagram 2.4a: Pre scan 1 – 18 GHz, Symbolic name: BL8₁₀₀, EIRP Horizontal polarization




Diagram 2.4b: Pre scan 1 – 18 GHz, Symbolic name: BL8₁₀₀, EIRP Vertical polarization




Diagram 2.5a: Pre scan 18 – 26.5 GHz, Symbolic name: BL₁₀₀, EIRP Horizontal polarization




Diagram 2.5b: Pre scan 18 – 26.5 GHz, Symbolic name: BL₁₀₀, EIRP Vertical polarization




Diagram 2.6a: Pre scan 18 – 26.5 GHz, Symbolic name: BL8₁₀₀, EIRP Horizontal polarization




Diagram 2.6b: Pre scan 18 – 26.5 GHz, Symbolic name: BL8₁₀₀, EIRP Vertical polarization






Diagram 2.7a: Pre scan 26.5 – 33 GHz, Symbolic name TH₁₀₀, EIRP Horizontal polarization



16:10:30 16.11.2020

Diagram 2.7a: Pre scan 26.5 – 33 GHz, Symbolic name TH₁₀₀, EIRP Vertical polarization



16:02:12 16.11.2020

Diagram 2.8a: Pre scan 26.5 – 33 GHz, Symbolic name TH8₁₀₀, EIRP Horizontal polarization




Diagram 2.8a: Pre scan 26.5 – 33 GHz, Symbolic name TH8₁₀₀, EIRP Vertical polarization




Diagram 2.9a: 33 – 40 GHz, QPSK, BL₅₀, EIRP Horizontal polarization




Diagram 2.9b: 33 – 40 GHz, QPSK, BL₅₀, EIRP Vertical polarization




Diagram 2.9c: 36 – 37 GHz, QPSK, BL₅₀, EIRP Horizontal polarization






Diagram 2.9d: 36 – 37 GHz, QPSK, BL₅₀, EIRP Vertical polarization




Power EIRP for 38.4 GHz Hor/ Ver [dBm]	Power EIRP for 38.395 GHz Hor/ Ver [dBm]	Antenna Gain Hor/ Ver [dBi]	Total conducted power/BW for 38.4 GHz (Limit -5 dBm) [dBm]/ Verdict	Total conducted power/BW for 38.395 GHz (Limit -13 dBm) [dBm]/ Verdict
2.85/ 1.43	-3.72/ -4.25	29.01/ 29.14	-23.86/ Pass	-30.04/ Pass

Diagram 2.10a: 33 – 40 GHz, QPSK, BL8₁₀₀, EIRP Horizontal polarization



10:27:26 01.12.2020

Diagram 2.10b: 33 – 40 GHz, QPSK, BL8₁₀₀, EIRP Vertical polarization



11:13:15 01.12.2020

Diagram 2.10c: 37.4 – 38.4 GHz, QPSK, BL8₁₀₀, EIRP Horizontal polarization





Diagram 2.10d: 37.4 – 38.4 GHz, QPSK, BL8₁₀₀, EIRP Vertical polarization



Power EIRP for 38.4 GHz Hor/ Ver [dBm]	Power EIRP for 38.39 GHz Hor/ Ver [dBm]	Antenna Gain Hor/ Ver [dBi]	Total conducted power/BW for 38.4 GHz (Limit -5 dBm) [dBm]/ Verdict	Total conducted power/BW for 38.39 GHz (Limit -13 dBm) [dBm]/ Verdict
-9.77/ -10.45	-14.67/ -14.03	25.98/ 26.43	-33.27/ Pass	-37.54/ Pass

Diagram 2.11a: 33 – 40 GHz, QPSK, Bim₅₀, EIRP Horizontal polarization




Diagram 2.11b: 33 – 40 GHz, QPSK, Bim₅₀, EIRP Vertical polarization




Diagram 2.11c: 37.4 – 38.4 GHz, QPSK, Bim₅₀, EIRP Horizontal polarization






Diagram 2.11d: 37.4 – 38.4 GHz, QPSK, Bim₅₀, EIRP Vertical polarization



Power EIRP for 38.4 GHz Hor/ Ver [dBm]	Power EIRP for 38.395 GHz Hor/ Ver [dBm]	Antenna Gain Hor/ Ver [dBi]	Total conducted power/BW for 38.4 GHz (Limit -5 dBm) [dBm]/ Verdict	Total conducted power/BW for 38.395 GHz (Limit -13 dBm) [dBm]/ Verdict
-1.38/ -7.98	-14.67/ -7.64	29.01/ 29.14	-29.55/ Pass	-35.97/ Pass


Power EIRP for 38.13 GHz Hor/ Ver [dBm]	Antenna Gain Hor/ Ver [dBi]	Total conducted power/BW for 38.13 GHz (Limit -5 dBm) [dBm]/ Verdict
-2.30/ -3.35	29.01/ 29.14	-28.85/ Pass

Diagram 2.12a: 33 – 40 GHz, QPSK, TH₄₁₀₀, EIRP Horizontal polarization
See diagram 2.12c for TRP result



08:47:18 18.11.2020

Diagram 2.12b: 33 – 40 GHz, QPSK, TH₄₁₀₀, EIRP Vertical polarization
See diagram 2.12c for TRP result



09:05:08 18.11.2020

Diagram 2.12c: Two cut TRP 35.67 – 35.77 GHz, Symbolic name: TH4₁₀₀




Diagram 2.13a: 38.35 – 38.85 GHz, QPSK, TL₅₀, EIRP Horizontal polarization






Diagram 2.13b: 38.35 – 38.85 GHz, QPSK, TL₅₀, EIRP Vertical polarization




Power EIRP for 38.6 GHz Hor/ Ver [dBm]	Power EIRP for 38.61 GHz Hor/ Ver [dBm]	Antenna Gain Hor/ Ver [dBi]	Total conducted power/BW for 38.6 GHz (Limit -5 dBm) [dBm]/ Verdict	Total conducted power/BW for 38.61 GHz (Limit -13 dBm) [dBm]/ Verdict
3.70/ 3.99	-6.14/ -5.11	29.01/ 29.14	-22.22/ Pass	-31.67/ Pass

Diagram 2.14a: 38.35 – 38.85 GHz, QPSK, BH₅₀, EIRP Horizontal polarization



13:29:07 18.11.2020

Diagram 2.14b: 38.35 – 38.85 GHz, QPSK, BH₅₀, EIRP Vertical polarization



14:01:46 18.11.2020

Power EIRP for 38.6 GHz Hor/ Ver [dBm]	Power EIRP for 38.59 GHz Hor/ Ver [dBm]	Antenna Gain Hor/ Ver [dBi]	Total conducted power/BW for 38.6 GHz (Limit -5 dBm) [dBm]/ Verdict	Total conducted power/BW for 38.59 GHz (Limit -13 dBm) [dBm]/ Verdict
4.46/ 3.66	-4.48/ -4.90	29.01/ 29.14	-21.98/ Pass	-30.75/ Pass

Diagram 2.15a: 40 – 43 GHz, QPSK, TH₅₀, EIRP Horizontal polarization




Diagram 2.15b: 40 – 43 GHz, QPSK, TH₅₀, EIRP Vertical polarization




Diagram 2.15c: 40 – 43 GHz, QPSK, TH₅₀, EIRP Horizontal polarization





Diagram 2.15d: 40 – 43 GHz, QPSK, TH₅₀, EIRP Vertical polarization



Power EIRP for 40.0 GHz Hor/ Ver [dBm]	Power EIRP for 40.01 GHz Hor/ Ver [dBm]	Antenna Gain Hor/ Ver [dBi]	Total conducted power/BW for 40.0 GHz (Limit -5 dBm) [dBm]/ Verdict	Total conducted power/BW for 40.01 GHz (Limit -13 dBm) [dBm]/ Verdict
-0.63/ -0.17	-8.29/ -6.92	29.37/ 29.34	-26.74/ Pass	-33.89/ Pass

Diagram 2.16a: 40 – 43 GHz, QPSK, TH₈₁₀₀, EIRP Horizontal polarization




Diagram 2.16b: 40 – 43 GHz, QPSK, TH₈₁₀₀, EIRP Vertical polarization




Diagram 2.16c: 40 – 43 GHz, QPSK, TH₈₁₀₀, EIRP Horizontal polarization





Diagram 2.16d: 40 – 43 GHz, QPSK, TH₈₁₀₀, EIRP Vertical polarization



Power EIRP for 40.0 GHz Hor/ Ver [dBm]	Power EIRP for 40.01 GHz Hor/ Ver [dBm]	Antenna Gain Hor/ Ver [dBi]	Total conducted power/BW for 40.0 GHz (Limit -5 dBm) [dBm]/ Verdict	Total conducted power/BW for 40.01 GHz (Limit -13 dBm) [dBm]/ Verdict
-11.15/ -9.75	-12.40/ -10.78	26.09/ 26.54	-33.73/ Pass	-34.86/ Pass

Diagram 2.17a: 40 – 43 GHz, QPSK, Tim₅₀, EIRP Horizontal polarization

See diagram 2.17e for TRP result




Diagram 2.17b: 40 – 43 GHz, QPSK, Tim₅₀, EIRP Vertical polarization

See diagram 2.17e for TRP result






Diagram 2.17c: 40 – 43 GHz, QPSK, Tim₅₀, EIRP Horizontal polarization
See diagram 2.17e for TRP result



11:02:47 19.11.2020

Diagram 2.17d: 40 – 43 GHz, QPSK, Tim₅₀, EIRP Vertical polarization
See diagram 2.17e for TRP result



10:54:10 19.11.2020

Power EIRP for 40.0 GHz Hor/ Ver [dBm]	Power EIRP for 40.01 GHz Hor/ Ver [dBm]	Antenna Gain Hor/ Ver [dBi]	Total conducted power/BW for 40.0 GHz (Limit -5 dBm) [dBm]/ Verdict	Total conducted power/BW for 40.01 GHz (Limit -13 dBm) [dBm]/ Verdict
-2.77/ -3.36	-7.02/ -7.16	29.37/ 29.34	-29.40/ Pass	-33.43/ Pass

Diagram 2.17e: Two cut TRP 40 – 40.4 GHz, Symbolic name: Tim₅₀






Diagram 2.18a: 40 – 43 GHz, QPSK, BL₁₀₀, EIRP Horizontal polarization
See diagram 2.18c for TRP result



14:08:41 25.11.2020

Diagram 2.18b: 40 – 43 GHz, QPSK, BL₁₀₀, EIRP Vertical polarization
See diagram 2.18c for TRP result



14:10:53 25.11.2020

Diagram 2.18c: Spherical grid Method TRP 40.6 – 41.6 GHz, Symbolic name: BL₁₀₀




Diagram 2.19a: 43 – 60 GHz, QPSK, BL₅₀, EIRP Horizontal polarization




Diagram 2.19b: 43 – 60 GHz, QPSK, BL₅₀, EIRP Vertical polarization




Diagram 2.20a: 43 – 60 GHz, QPSK, BL₈₁₀₀, EIRP Horizontal polarization




Diagram 2.20b: 43 – 60 GHz, QPSK, BL₈₁₀₀, EIRP Vertical polarization




Diagram 2.21a: 60 – 80 GHz, QPSK, BL₁₀₀, EIRP Horizontal polarization




Diagram 2.21b: 60 – 80 GHz, QPSK, BL₁₀₀, EIRP Vertical polarization




Diagram 2.22a: 60 – 80 GHz, QPSK, BL8₁₀₀, EIRP Horizontal polarization




Diagram 2.22b: 60 – 80 GHz, QPSK, BL8₁₀₀, EIRP Vertical polarization




Diagram 2.23a: 80 – 100 GHz, QPSK, BL₁₀₀, EIRP Horizontal polarization




Diagram 2.23b: 80 – 100 GHz, QPSK, BL₁₀₀, EIRP Vertical polarization




Diagram 2.24a: 80 – 100 GHz, QPSK, BL8₁₀₀, EIRP Horizontal polarization




Diagram 2.24b: 80 – 100 GHz, QPSK, BL8₁₀₀, EIRP Vertical polarization




Diagram 2.25a: 100 – 110 GHz, QPSK, BL₁₀₀, EIRP Horizontal polarization




Diagram 2.25b: 100 – 110 GHz, QPSK, BL₁₀₀, EIRP Vertical polarization




Diagram 2.26a: 100 – 110 GHz, QPSK, BL₈₁₀₀, EIRP Horizontal polarization




Diagram 2.26b: 110 – 110 GHz, QPSK, BL₈₁₀₀, EIRP Vertical polarization




Diagram 2.27a: 110 – 130 GHz, QPSK, BL₁₀₀, EIRP Horizontal polarization




Diagram 2.27b: 110 – 130 GHz, QPSK, BL₁₀₀, EIRP Vertical polarization




Diagram 2.28a: 110 – 130 GHz, QPSK, BL₈₁₀₀, EIRP Horizontal polarization




Diagram 2.28b: 110 – 130 GHz, QPSK, BL₈₁₀₀, EIRP Vertical polarization




Diagram 2.29a: 130 – 150 GHz, QPSK, BL₁₀₀, EIRP Horizontal polarization




Diagram 2.29b: 130 – 150 GHz, QPSK, BL₁₀₀, EIRP Vertical polarization




Diagram 2.30a: 130 – 150 GHz, QPSK, BL₈₁₀₀, EIRP Horizontal polarization




Diagram 2.30b: 130 – 150 GHz, QPSK, BL₈₁₀₀, EIRP Vertical polarization




Diagram 2.31a: 150 – 170 GHz, QPSK, BL₁₀₀, EIRP Horizontal polarization




Diagram 2.31b: 150 – 170 GHz, QPSK, BL₁₀₀, EIRP Vertical polarization




Diagram 2.32a: 150 – 170 GHz, QPSK, BL₈₁₀₀, EIRP Horizontal polarization




Diagram 2.32b: 150 – 170 GHz, QPSK, BL₈₁₀₀, EIRP Vertical polarization




Diagram 2.33a: 170 – 185 GHz, QPSK, BL₁₀₀, EIRP Horizontal polarization




Diagram 2.33b: 170 – 185 GHz, QPSK, BL₁₀₀, EIRP Vertical polarization




Diagram 2.34a: 170 – 185 GHz, QPSK, BL₈₁₀₀, EIRP Horizontal polarization




Diagram 2.34b: 170 – 185 GHz, QPSK, BL₈₁₀₀, EIRP Vertical polarization




Diagram 2.35a: 185 – 200 GHz, QPSK, BL₁₀₀, EIRP Horizontal polarization




Diagram 2.35b: 185 – 200 GHz, QPSK, BL₁₀₀, EIRP Vertical polarization




Diagram 2.36a: 185 – 200 GHz, QPSK, BL₈₁₀₀, EIRP Horizontal polarization





Diagram 2.36b: 185 – 200 GHz, QPSK, BL₈₁₀₀, EIRP Vertical polarization



End of report.