

Tenda

Quick Installation Guide

For product or function details, please go to www.tendacn.com.
AC1200 Smart Dual-Band WiFi Router
AC7

Package contents


- WiFi router * 1
- Power adapter * 1
- Ethernet cable * 1
- Quick installation guide * 1




Scan to download the Tenda WiFi app or get it on Google Play/App Store.

2 Connect to your devices

Connect your wireless devices to the router's WiFi network using the SSID labeled on the bottom of the router. There is no WiFi password by default.



Connect your wired devices to port 1, 2 or 3/IPTV of the router using Ethernet cables. The LAN LED indicator lights on.




1 Connect your router

If you want to replace your original router connected to the internet with a PPPoE user name and password, start from **Step 1**. Otherwise, start from **Step 2**.


Step 1: Migrate your PPPoE user name and password from your original router

1. Power on your original and new routers.
2. Connect the WAN port of the original router to port 1, 2 or 3/IPTV of the new router using an Ethernet cable.
3. Wait about 6 seconds. When the WAN and LAN LED indicators of the new router turn solid on after blinking fast, your migration is successful.
4. Remove the original router.



Step 2: Connect your router to the upstream device.

1. Power on the new router.
2. Connect the WAN port of the new router to the LAN port of your modem or the Ethernet jack using an Ethernet cable. Then the WAN LED indicator lights on.



3 Set up the router for internet access

1. Start a web browser on a device that has connected to the router, and visit tendawifi.com.




Tips
If you cannot log in to the web UI of the router, refer to **Q1** in **FAQ**.

2. The router detects your internet connection type automatically. PPPoE is used for illustration here. Enter the **User Name** and **Password** provided by your ISP (Internet Service Provider).

If you migrated your PPPoE **user name** and **password** from your original router, this router auto-fills the User Name and Password.

3. Customize your **WiFi Name** and **WiFi Password**, and click **OK**.



Done.

To access the internet:
Wireless devices: Connect your WiFi-enabled devices to the WiFi network of the router using the WiFi name and WiFi password you set.
2.4 GHz WiFi name (SSID): The WiFi name you set here.
5 GHz WiFi name: The 2.4 GHz WiFi name plus a suffix **_5G**.

Tips
To modify the WiFi name and WiFi password, see **Q4** in **FAQ**.

Wired devices: Your wired devices connected to the router can access the internet directly now.

LED indicators

LED indicator	Status	Description
SYS	Solid on	<ul style="list-style-type: none"> The router is starting. If the indicator still light solid on after the router completes startup, it indicates that the system is faulty.
	Blinking	The system is working properly.
WiFi	Solid on	At least the 2.4 GHz or 5 GHz WiFi network is enabled.
	Fast blinking	Data is being transmitted wirelessly.
	Slow blinking	The router is performing WPS negotiation.
	Off	The WiFi network is disabled.
WAN	Solid on	The WAN port is connected properly.
	Blinking	Data is being transmitted over the WAN port.
	Off	The WAN port is disconnected or improperly connected.
LAN	Solid on	At least a LAN port is connected properly.
	Blinking	Data is being transmitted over the LAN port.
	Off	No device is connected to any LAN port of the router properly.

Jack, ports and buttons

Jack/Port/Button	Description
POWER	Power jack. Used to connect to the included power adapter.
WiFi	Used to enable/disable the WiFi Networks of the router.
RST/WPS	Used to start the WPS negotiation process, or to reset the router. <ul style="list-style-type: none"> WPS: Press the button of the router for 1 to 3 seconds. Within 2 minutes, enable the WPS function of the other WPS-supported device to establish a WPS connection. Reset: When the SYS LED indicator blinks, Release it when all the LED indicators blink once.
WAN	Used to connect this router to the internet.
1/2	They are LAN ports used to connect to wired devices such as computers or switches.
3/IPTV	<ul style="list-style-type: none"> By default, it is a LAN port. If the IPTV function of the router is enabled, it serves only as an IPTV port used to connect to a set-top box.

FAQ

Q1: I cannot log in to the web UI of the router after entering tendawifi.com, what should I do?

- A1: Try the following solutions and log in again:
- Ensure that your Ethernet cable with internet connectivity is plugged into the WAN port of the router rather than a LAN port.
 - Ensure that your WiFi-enabled device is connected to the router's SSID.
 - Ensure that your computer is connected to port 1, 2 or 3/IPTV of the router properly by an Ethernet cable. And it is set to **Obtain an IP address automatically** and **Obtain DNS server address automatically**.
 - Ensure that tendawifi.com is entered correctly, or try logging by **192.168.0.1**.
 - Replace the web browser.
 - Reset the router.

Q2: I cannot access the internet after the configuration, what should I do?

- A2: Try the following methods:
- Check if the WAN port of the router is connected properly.
 - Log in to the web UI of the router, check if the internet connection status on the **Status** page is connected. If not, navigate to the **Internet Settings** page, and follow the on-screen instructions to solve it.
 - If your wired devices cannot access the internet:
 - Check if your computer is connected to port 1, 2, or 3/IPTV properly.
 - Check if your computer is set to **obtain an IP address automatically** and **Obtain DNS server address automatically**.
 - If your WiFi-enabled devices cannot access the internet:
 - Check if your WiFi-enabled devices are connected to the WiFi network of the router with the SSID you set.
 - Change your WiFi name and WiFi password on **Wireless Settings** page. Then try again.

Q3: How to reset the router?

A3: When the **SYS** indicator blinks, hold down the **RST/WPS** button for about 8 seconds. Release it when all the LED indicators blink once. The router is reset successfully.

Q4: How to change my WiFi names and passwords?

A4: Log in to the web UI of the router on your wired or wireless device, navigate to **Wireless Settings** Page, and follow the on-screen instructions to customize your WiFi names and passwords.



CE Mark Warning

This is a Class B product. In a domestic environment, this product may cause radio interference, in which case the user may be required to take adequate measures.
Operations in the 5.15-5.25GHz band are restricted to indoor use only. This equipment should be installed and operated with minimum distance 20cm between the device and your body.
The mains plug is used as disconnect device, the disconnect device shall remain readily operable.

NOTE: (1) The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. (2) To avoid unnecessary radiation interference, it is recommended to use a shielded RJ45 cable.

Declaration of Conformity

Hereby, SHENZHEN TENDA TECHNOLOGY CO., LTD. declares that the radio equipment type AC7 is in compliance with Directive 2014/53/EU. The full text of the EU declaration of conformity is available at the following internet address:
<http://www.tendacn.com/en/service/download-cata-101.html>
Operate Frequency:
2.4G: EU / 2400-2483.5 MHz (CH1-CH13)
5G: EU / 5150-5250 MHz (CH36-CH48)
EIRP Power (Max.):
2.4 GHz: 19.86 dBm
5 GHz: 22.96 dBm
Software Version: V15.03.06.XX



Caution:
Adapter Model: BN052-A09009E/BN052-A09009B
Manufacture: SHENZHEN HEWEISHUN NETWORK TECHNOLOGY CO., LTD.
Input: 100 - 240V AC, 50/60 Hz, 0.3 A
Output: 9V DC, 1 A
⚡ : DC Voltage



FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
— Reorient or relocate the receiving antenna.
— Increase the separation between the equipment and receiver.
— Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
— Consult the dealer or an experienced radio/TV technician for help.
The device is for indoor usage only.
Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Radiation Exposure Statement

This device complies with FCC radiation exposure limits set forth for an uncontrolled environment and it also complies with Part 15 of the FCC RF Rules.
This equipment should be installed and operated with minimum distance 25cm between the device and your body.

!	BE	BG	CZ	DK	DE	EE	IE	EL	ES	FR	HR	IT	CY	LV
	LT	LU	HU	MT	NL	AT	PL	PT	RO	SI	SK	FI	SE	UK

Operating Temperature: 0 °C - 40 °C
Operating Humidity: (10% - 90%) RH, non-condensing



RECYCLING

This product bears the selective sorting symbol for Waste electrical and electronic equipment (WEEE). This means that this product must be handled pursuant to European directive 2012/19/EU in order to be recycled or dismantled to minimize its impact on the environment.
User has the choice to give his product to a competent recycling organization or to the retailer when he buys a new electrical or electronic equipment.

Caution:

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.
This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.
Operating frequency: 2412-2462MHz, 5150-5250MHz, 5725-5850MHz
NOTE: (1) The manufacturer is not responsible for any radio or TV interference caused by unauthorized modifications to this equipment. (2) To avoid unnecessary radiation interference, it is recommended to use a shielded RJ45 cable.

Using two screws, the size is PA3*14mm

Copyright

© 2019 Shenzhen Tenda Technology Co., Ltd. All rights reserved.
Tenda is a registered trademark legally held by Shenzhen Tenda Technology Co., Ltd. Other brand and product names mentioned herein are trademarks or registered trademarks of their respective holders. Specifications are subject to change without notice.

Technical Support

Shenzhen Tenda Technology Co., Ltd.
6-8 Floor, Tower E3, NO.1001, Zhongshanyuan Road, Nanshan District, Shenzhen, China. 518052
USA hotline: 1-800-570-5892
Toll Free: 7 x 24 hours
Canada hotline: 1-888-998-8966
Toll Free: Mon - Fri 9 am - 6 pm PST
Hong Kong hotline: 00852-81931998
Global hotline: +86 755-2765 7180 (China Time Zone)
Website: www.tendacn.com
E-mail: support@tenda.com.cn