



KONICA MINOLTA

# *AeroDR*

**DIRECT DIGITIZER  
AeroDR SYSTEM  
AeroDR SYSTEM 2  
SKR 3000**

**Operation Manual**

**CE 0197**



**KONICA MINOLTA, INC.**

1 Sakura-machi, Hino-shi, Tokyo, 191-8511, Japan

**EN**

**38**



# Contents

## Introduction . . . . . 5

Introduction . . . . .	6
USA only. . . . .	7
For EEA (European Economic Area), Swiss, Turkey and Canada . . . . .	7
EU member states only . . . . .	7
Summary of usability specifications (for IEC/EN 60601-1-6, IEC/EN 62366) . . . . .	8
Disclaimer. . . . .	9
Trademark . . . . .	9
Name correspondence table . . . . .	10
Term description. . . . .	11

## Chapter 1

### Safety Precautions & Warnings. . . . . 13

1.1 Symbols relating to safety . . . . .	14
1.1.1 Safety alert symbol . . . . .	14
1.1.2 Warning notice (signal words). . . . .	14
1.1.3 Graphical symbols . . . . .	14
1.2 Warning labels. . . . .	16
1.2.1 DR Detector . . . . .	16
1.2.2 AeroDR Generator Interface Unit2. . .	17
1.2.3 AeroDR Battery Charger . . . . .	17
1.2.4 AeroDR Battery Charger2 . . . . .	17
1.3 Safety precautions. . . . .	18
1.3.1 Precautions before usage . . . . .	18
1.3.2 Precautions for usage . . . . .	18
1.3.3 Precautions regarding electromagnetic waves . . . . .	23
1.3.4 Precautions regarding wireless communication. . . . .	28
1.3.5 Precautions for installing, moving, and storing. . . . .	30
1.3.6 Precautions regarding maintenance. . .	31
1.3.7 Precautions on service life. . . . .	31

## Chapter 2

### Product Overview . . . . . 33

2.1 Overview of this device . . . . .	34
2.1.1 Functions . . . . .	34
2.1.2 System configuration and connection examples . . . . .	35
2.2 Component names and functions . . . . .	43
2.2.1 AeroDR Detector . . . . .	43
2.2.2 AeroDR 2 Detector. . . . .	44
2.2.3 AeroDR 3 Detector. . . . .	45

2.2.4 AeroDR Interface Unit . . . . .	46
2.2.5 AeroDR Interface Unit2 . . . . .	47
2.2.6 Detector Interface Unit. . . . .	48
2.2.7 Detector Interface Unit 2 . . . . .	49
2.2.8 Power Supply Unit . . . . .	50
2.2.9 AeroDR Generator Interface Unit. . .	51
2.2.10 AeroDR Generator Interface Unit2. . .	52
2.2.11 Generator Interface Unit 3. . . . .	53
2.2.12 GIU SZ. . . . .	54
2.2.13 AeroDR Battery Charger . . . . .	55
2.2.14 AeroDR Battery Charger2 . . . . .	56
2.2.15 AeroDR Access Point. . . . .	57
2.2.16 I/F Cable . . . . .	58
2.2.17 AeroDR UF Cable . . . . .	58

## Chapter 3

### General Operations . . . . . 59

3.1 Startup and shutdown . . . . .	60
3.1.1 Startup of this device . . . . .	60
3.1.2 Shutdown of this device. . . . .	63
3.2 Operation of DR Detector . . . . .	67
3.2.1 Exposure with basic connection or Aero Sync connection . . . . .	67
3.2.2 Exposure under the S-SRM connection example . . . . .	67
3.2.3 Exposure using Aero Storage . . . . .	68
3.2.4 Serial exposure . . . . .	72
3.2.5 DR Detector orientation . . . . .	74
3.2.6 Precautions for exposure. . . . .	75
3.3 Charging of DR Detector . . . . .	82
3.3.1 Charging with AeroDR Battery Charger . .	82
3.3.2 Charging with AeroDR Battery Charger2 . . . . .	83
3.3.3 Charging with the wired cable . . . . .	84
3.3.4 Charging time guide. . . . .	85
3.3.5 DR Detector battery level display. . . . .	86
3.4 Registration and selection of the DR Detector. . . . .	87
3.4.1 Registration with AeroDR Battery Charger . . . . .	87
3.4.2 Registration with AeroDR Battery Charger2 . . . . .	88
3.4.3 Registration with the wired cable . . . . .	88
3.4.4 Registration in the AeroDR 3 Detector. . .	89
3.4.5 Selection of the DR Detector . . . . .	90
3.4.6 Manual selection of the DR Detector . . .	90
3.5 Calibration . . . . .	91

3.6	Position to affix DR Detector identification label and AeroDR Grip sheet . . . . .	92
3.6.1	Position to affix DR Detector identification label . . . . .	92
3.6.2	AeroDR Grip sheet. . . . .	92

## Chapter 4

### Status (LED) Display . . . . . 93

4.1	LED display of respective devices. . . . .	94
4.1.1	AeroDR Detector . . . . .	95
4.1.2	AeroDR 2 Detector. . . . .	96
4.1.3	AeroDR 3 Detector. . . . .	97
4.1.4	AeroDR Interface Unit . . . . .	101
4.1.5	AeroDR Interface Unit2 . . . . .	102
4.1.6	Detector Interface Unit/Detector Interface Unit 2. . . . .	103
4.1.7	Power Supply Unit . . . . .	103
4.1.8	AeroDR Generator Interface Unit. . .	104
4.1.9	AeroDR Generator Interface Unit2. .	104
4.1.10	Generator Interface Unit 3 . . . . .	105
4.1.11	AeroDR Battery Charger . . . . .	105
4.1.12	AeroDR Battery Charger2 . . . . .	106
4.1.13	AeroDR Access Point. . . . .	107

## Chapter 5

### Troubleshooting. . . . . 109

5.1	Support flow during trouble . . . . .	110
5.2	Various problems and countermeasures . . .	112
5.2.1	DR Detector . . . . .	112
5.2.2	AeroDR Interface Unit . . . . .	116
5.2.3	AeroDR Interface Unit2 . . . . .	117
5.2.4	Detector Interface Unit. . . . .	117
5.2.5	Detector Interface Unit 2 . . . . .	118
5.2.6	Power Supply Unit . . . . .	118
5.2.7	AeroDR Generator Interface Unit. . .	118
5.2.8	AeroDR Generator Interface Unit2. .	119
5.2.9	Generator Interface Unit 3 . . . . .	119
5.2.10	GIU SZ. . . . .	119
5.2.11	AeroDR Battery Charger . . . . .	120
5.2.12	AeroDR Battery Charger2 . . . . .	120
5.2.13	AeroDR Access Point. . . . .	120
5.2.14	Image processing controller/Images . .	121

## Chapter 6

### Maintenance . . . . . 123

6.1	Maintenance and inspection items . . . .	124
6.1.1	Maintenance schedule. . . . .	124
6.1.2	Cleaning. . . . .	124
6.1.3	Disinfection of the DR Detector . . . . .	127
6.1.4	Consumables. . . . .	127
6.1.5	AeroDR Grip sheet affixing and replacement. . . . .	127

## Chapter 7

### Specifications . . . . . 129

7.1	Specifications . . . . .	130
7.1.1	DR Detector . . . . .	130
7.1.2	AeroDR Interface Unit . . . . .	134
7.1.3	AeroDR Interface Unit2 . . . . .	134
7.1.4	Detector Interface Unit. . . . .	135
7.1.5	Detector Interface Unit 2 . . . . .	135
7.1.6	Power Supply Unit . . . . .	136
7.1.7	AeroDR Generator Interface Unit. . .	136
7.1.8	AeroDR Generator Interface Unit2. .	137
7.1.9	Generator Interface Unit 3 . . . . .	137
7.1.10	GIU SZ. . . . .	138
7.1.11	AeroDR Battery Charger . . . . .	138
7.1.12	AeroDR Battery Charger2 . . . . .	139
7.1.13	AeroDR Access Point. . . . .	139
7.1.14	I/F Cable . . . . .	140
7.1.15	AeroDR UF Cable . . . . .	141
7.1.16	Cables and minor components . . . .	142
7.1.17	AeroDR SYSTEM . . . . .	143
7.1.18	AeroDR SYSTEM 2. . . . .	143
7.1.19	SKR 3000. . . . .	144
7.1.20	Label . . . . .	145

---

# Introduction

## Introduction

The digital radiography AeroDR SYSTEM, AeroDR SYSTEM 2 and SKR 3000 (hereinafter, both are referred to as this device) perform X-ray imaging of the human body using an X-ray planar detector that outputs a digital signal, which is then input into an image processing device, and the acquired image is then transmitted to a filing system, printer, and image display device as diagnostic image data.

- This device is not intended for use in mammography.
- This device is also used for carrying out exposures on children.

The CS-7 or ImagePilot (hereafter referred to as the image processing controller), which controls the receiving, processing, and output of image data, is required for operation. For the operation of the image processing controller, refer to the "Operation Manual" of the image processing controller. Also, regarding the connectable devices, contact Konica Minolta technical representative.

This operation manual provides instructions on the basic functions for operation of this device. Those operating this device for the first time should read this manual beforehand.

Also, store this manual close to this device after reading it through, so it can be used as a guide to allow optimum operating conditions.

### IMPORTANT

- This operation manual (English version) is effective only outside Japan.
- This Operation Manual is common to the digital radiography AeroDR SYSTEM, digital radiography AeroDR SYSTEM 2 and digital radiography SKR 3000.
- If the pages of the operation manual are smudged and illegible, replace it with a new one. (a fee is required.)
- The illustrations in this manual use the AeroDR 3 1417HD and AeroDR Battery Charger2 as the example.

**USA only****Indications for Use**

This device is indicated for use in generating radiographic images of human anatomy. It is intended to replace radiographic film/screen system in general-purpose diagnostic procedures.

This device is not indicated for use in mammography, fluoroscopy, and angiography applications.

**CAUTION**

- Federal law restricts this device to sale by or on the order of a physician.

**For EEA (European Economic Area), Swiss, Turkey and Canada****Intended purpose:**

A device is intended for use in the acquisition and process of radiographic images of human anatomy. It is intended to replace radiographic film/screen system in general-purpose diagnostic procedures.

**Intended use:**

SKR 3000 is intended to image the X-ray transmitted through the human body by an X-ray flat panel detector, and to output an X-ray Image. The X-ray image does not include any mammographic image.

**Intended Users:**

It is used by highly trained specialists, such as medical physicians or radiologic technologists working in diagnostic imaging.

**Intended patient population:**

- Age group: No limitation
- Weight range: Up to 130 kg
- Country: No limitation
- Other(s): No limitation for body site

**Intended patient medical condition:**

No limitation for medical condition.

**EU member states only****CAUTION**

- Any serious incidents or side-effects that could have occurred in relation to the device should be reported to your Konica Minolta service representative and the EU competent authorities.

## Summary of usability specifications (for IEC/EN 60601-1-6, IEC/EN 62366)

- (1) Medical purposes
  - Provision and reading of disease and injury diagnostic images.
- (2) Patient groups
  - No patient population exists who uses the device.
  - Patient population for the X-ray images read is not specified.
- (3) Parts of body or organizations to which the device is mounted or that interact with the device.
  - DR Detector contacts the body surfaces of a patient and an operator.
  - Devices other than DR Detector contact the body surface of an operator.
- (4) Operating principle
  - DR Detector forms the still images according to the X-ray energy passing through the human and animal body; after digitizing the exposed image, it is transmitted to the console (the image processing controller) with wired communication or wireless communication.
  - In the serial radiography mode, it allows to capture multiple frames of radiography image serially taken by the pulse irradiation from an X-ray generator device during one time. This device continues not to be intended to connect with the x-ray device for mammography, fluoroscopy, angiography and cone-beam CT, and not to be used for such procedures.
  - AeroDR Interface Unit and AeroDR Interface Unit2 supply the power to DR Detector, AeroDR Generator Interface Unit, AeroDR Generator Interface Unit2, and access point (radio communication device). It also relays wired communication.
  - Detector Interface Unit and Detector Interface Unit 2 supply the power to DR Detector. It also relays wired communication.
  - Power Supply Unit supply the power to Detector Interface Unit, Detector Interface Unit 2, AeroDR Generator Interface Unit, AeroDR Generator Interface Unit2 and Generator Interface Unit 3. It also relays wired communication.
  - AeroDR Interface Unit2, AeroDR Generator Interface Unit, AeroDR Generator Interface Unit2 and Generator Interface Unit 3 interfaces with an X-ray device.
  - GIU SZ supplies the power to DR detector. It also relays wired communication and interfaces with an X-ray device.
  - Access point (radio communication device) performs a wireless communication with DR Detector.
  - The console (the image processing controller) processes the image data into the diagnostic image, and then stores and outputs the images added with the patient information.
  - The AeroDR Battery Charger and AeroDR Battery Charger2 charge the DR Detector. It registers the using DR Detector with the exposure room.
- (5) Significant physical characteristics
  - Refer to "7.1 Specifications".
- (6) Significant performance characteristics
  - Refer to "2.1 Overview of this device".
- (7) User of this device
  - No special training is required to use this device. The intended users of this device are as follows.  
A professional in good health with specialist knowledge/qualifications who has fully understood the content of this document. (Such as a doctor or radiological technologist)



## Disclaimer

- (1) This manual may not be reproduced in whole or in part without the permission of Konica Minolta, Inc.
- (2) The contents of this manual may be subject to change without prior notice.
- (3) Konica Minolta, Inc. is not responsible for any claims made for malfunction or damage caused by installation, relocation, modification, maintenance, and repair made by anyone except Konica Minolta and contractors designated by Konica Minolta.
- (4) Konica Minolta, Inc. is not responsible for any claims made for malfunction or damage to Konica Minolta products, caused by third-party products not installed by Konica Minolta.
- (5) Konica Minolta, Inc. is not responsible for any claims made for malfunction or damage caused by maintenance and repair using maintenance parts other than those specified by Konica Minolta.
- (6) Konica Minolta, Inc. is not responsible for any claims made for malfunction or damage caused by not observing the precautions and operation methods described in the operation manual.
- (7) Konica Minolta, Inc. is not responsible for any claims made for malfunction or damage caused by the environment that is not suitable for the installation requirements such as power source and installation environment described in the Installation Requirement or operation manual.
- (8) Konica Minolta, Inc. is not responsible for any claims for malfunction or damage caused by acts of nature such as fires, earthquakes, floods, or lightning strikes.
- (9) Konica Minolta, Inc. is not responsible for any claims for malfunction or damage caused by using this device for any purpose other than that specified for this device.
- (10) Diagnostic and treatment action is performed under the responsibility of the physician(s). Konica Minolta, Inc. is not responsible for any diagnostic/treatment conditions or diagnostic/treatment results.
- (11) Konica Minolta, Inc. is unable to assume any liability relating to the following events arising due to systems infected by computer viruses, worms and other malicious software potentially harmful to computers (hereunder referred to as "malwares"):
  - The erasure, corruption, or unwanted disclosure of data stored within this device, including personal and sensitive patient information.
  - Malfunction of the device or accidents occurring as a result of the malfunction of the device.
  - Infection of other products upon connection with the device, or damages arising therefrom.
- (12) Whenever you use this service, you are required to take some security or safety measures for the following items related to the service:

Please understand that Konica Minolta, Inc. is unable to assume liability for certain events, such as malfunctions or incidents of information leakage resulting from such events.

  - Client and network equipment managed by our facility
  - The network and ISP in our facility used for connection with this service
  - Your equipment to be connected to the same network as that of this service
- (13) When this device is used, various user and patient data stored within the device and external storage devices must be adequately managed under the full responsibility of the user. Konica Minolta, Inc. is unable to assume any liability relating to damages arising due to leakage of various data at the time of disposal.

## Trademark

Company names and product names in this manual are trademarks or registered trademarks of their respective owners.

Please note that ©, ® and ™ marks are omitted hereafter.

Copyright © 2011 - 2024 Konica Minolta, Inc. All Rights Reserved.

## Name correspondence table

Operation Manual name			Model name (nameplate name)
DR Detector	AeroDR Detector	AeroDR 1417HQ	AeroDR P-11
		AeroDR 1417S	AeroDR P-12
		AeroDR 1717HQ	AeroDR P-21
		AeroDR 1012HQ	AeroDR P-31
	AeroDR 2 Detector	AeroDR 2 1417HQ	AeroDR P-51
		AeroDR 2 1417S	AeroDR P-52
	AeroDR 3 Detector	AeroDR 3 1417HD	P-61
		AeroDR 3 1717HD	P-71
		AeroDR 3 1012HQ	P-81
		AeroDR 3 1417HD2	P-65
		AeroDR 3 1717HD2	P-75
		AeroDR 3 1417HL	P-85
		AeroDR 3 1417SL	P-82
AeroDR 3 1717HL		P-95	
AeroDR 3 1417S	P-53		
AeroDR Interface Unit			AeroDR B-1
AeroDR Interface Unit2			AeroDR Interface Unit2
Detector Interface Unit			G-21
Detector Interface Unit 2			G-52
Power Supply Unit			G-11
AeroDR Generator Interface Unit			AeroDR X-1
AeroDR Generator Interface Unit2			AeroDR Generator Interface Unit2
Generator Interface Unit 3			G-51
GIU SZ			G-59
AeroDR Battery Charger			AeroDR D-1
AeroDR Battery Charger2			AeroDR Battery Charger2
AeroDR Access Point			AeroDR C-1

## Term description

Terms	Explanation
DR Detector	Collective term indicating AeroDR 1417HQ, AeroDR 1417S, AeroDR 1717HQ, AeroDR 1012HQ, AeroDR 2 1417HQ, AeroDR 2 1417S, AeroDR 3 1417HD, AeroDR 3 1717HD, AeroDR 3 1012HQ, AeroDR 3 1417HD2, AeroDR 3 1717HD2, AeroDR 3 1417HL, AeroDR 3 1417SL, AeroDR 3 1717HL, and AeroDR 3 1417S.
AeroDR Detector	Collective term indicating AeroDR 1417HQ, AeroDR 1417S, AeroDR 1717HQ, and AeroDR 1012HQ.
AeroDR 2 Detector	Collective term indicating AeroDR 2 1417HQ, and AeroDR 2 1417S.
AeroDR 3 Detector	Collective term indicating AeroDR 3 1417HD, AeroDR 3 1717HD, AeroDR 3 1012HQ, AeroDR 3 1417HD2, AeroDR 3 1717HD2, AeroDR 3 1417HL, AeroDR 3 1417SL, AeroDR 3 1717HL, and AeroDR 3 1417S.
Image processing controller	The CS-7 or ImagePilot is referred to as the image processing controller.
Calibration	Processing for calibrating the characteristics of the DR Detector for each pixel.
PoE	An abbreviation for Power over Ethernet. Provides power using an Ethernet cable.
Aero Sync	This is a mode in which exposure is performed without being synchronized with the X-ray device.
Aero Storage	This function allows you to expose without using the image processing controller.
Aero Indicator	When the Aero Storage mode is used, this function allows you to view information in the DR Detector on a mobile terminal.
Mobile terminal	This is an external device to use for Aero Indicator.
Access Point	Collective term indicating the AeroDR Access Point and general-purpose access points. The AeroDR Access Point 2 is included.
I/F Cable	Collective term indicating the AeroDR I/F Cable, AeroDR I/F Cable2, I/F Cable3(0.67mU, 1mU, 8mD, 8mU), and I/F Cable4(1.5mD, 2mU, 8mD, 8mU).
Wired cable	Collective term indicating I/F Cable and AeroDR UF Cable.
Serial exposure	An exposure method to capture multiple frame images serially taken by the pulse irradiation from an X-ray generator device.
Serial Link Unit	<ul style="list-style-type: none"> <li>• An alternative name of GIU SZ I/F cable.</li> <li>• To perform serial exposure using wireless connection, connect the DR Detector to the GIU SZ I/F cable (Serial Link Unit).</li> </ul> <p>— For details, refer to the "3.2.4 Serial exposure".</p>

---

# **Chapter 1**

---

## **Safety Precautions & Warnings**

## 1.1 Symbols relating to safety

### 1.1.1 Safety alert symbol



This is a "safety alert symbol". This symbol alerts you to matters and/or operation potentially hazardous to yourself and other people. Read these messages and follow the instructions carefully.

### 1.1.2 Warning notice (signal words)

Signal words indicate the degree of potential hazards in the use of the product.

Signal words include the following three types, which are used according to risk of damage caused by danger and the severity of damage.



Indicates an imminently hazardous situation which, if not avoided, will result in death or serious injury.






Indicates a potentially hazardous situation which, if not avoided, could result in death or serious injury.



Indicates a potentially hazardous situation which, if not avoided, could result in minor or moderate injury. It may also be used to indicate hazardous situation where only physical damage is likely to occur.

### 1.1.3 Graphical symbols

Graphical symbols	Description
	Power On
	Power Off
	Power on / stand-by
	Earth (ground)
	Refer to instruction for use
	Type B applied part
	Fragile, handle with care
	Non-ionizing electromagnetic radiation
	Date of manufacture
	Manufacturer
	Serial number
	Medical Device
	Model number
	Catalogue number
	Consult instructions for use

Graphical symbols	Description
	Unique device identifier
<b>IPX6</b>	Indicates that the level of water ingress protection is equivalent to IPX6.
<b>IP56</b>	Indicates that the level of water and dust ingress protection is equivalent to IP56.
	Indicates that the item contains substances covered by the Chinese RoHS directive in amounts that exceed regulations. The number indicates the number of years of the Environment Friendly Use Period.
	Authorized representative in the European Community
<b>CE</b> <sup>0197</sup>	This symbol indicates that this device is in conformity with the Regulation (EU) 2017/745.
<b>CE</b>	This symbol indicates that this device is in conformity with the Regulation (EU) 2017/745.
	It means conformity with the Radio Equipment Directive 2014/53/EU.

## 1.2 Warning labels

Various warning labels are attached to this device on the locations shown below. Do not remove these labels from this device. Warning labels are there to make sure that the user recognizes potential hazards when operating this device.

### IMPORTANT


- If a warning label is too dirty or damaged to read, contact Konica Minolta technical representatives to have a new warning label attached, and redisplay by parts replacement. (a fee is required.)

### 1.2.1 DR Detector







### 1.2.2 AeroDR Generator Interface Unit2



### 1.2.3 AeroDR Battery Charger



### 1.2.4 AeroDR Battery Charger2



## 1.3 Safety precautions

Read all safety precautions thoroughly before using this device.

Be sure to observe the safety precautions described in this section.

### 1.3.1 Precautions before usage

#### CAUTION

- The operators (hospitals and clinics) hold responsibility for the usage and maintenance of this device. Do not use this device unless you are a physician or certified person under law.
- This device excluding the image processing controller is suitable for use in the patient environment. (PC used for the image processing controller is not suitable for use in the patient environment.)
- Confirm that this device is operating normally before using.
- When a problem occurs with this device, turn the power off, attach an appropriate sign, such as "malfunction", on this device, and contact Konica Minolta technical representatives.
- This device is not explosion-proof, so do not use any flammable or explosive gas near this device.
- For the basic operation of the computer, display monitor, and optional parts for this device, refer to their operation manuals.

Please follow the rules and regulations of your relevant authorities in the disposal of this product, accessories, options, consumables, media and their packing materials.



This symbol means: Do not dispose of this product together with your household waste!

Please refer to the information of your local community or contact our dealers regarding the proper handling of end-of-life electric and electronic equipments.


Recycling of this product will help to conserve natural resources and prevent potential negative consequences for the environment and human health caused by inappropriate waste handling.

- Certain components of DR Detector may contain Perchlorate Material - Special handling may apply, See <http://www.dtsc.ca.gov/hazardouswaste/perchlorate>.


### 1.3.2 Precautions for usage

#### WARNING

- The DR Detector is a precision instrument. If it is dropped or hit against any object, a failure may occur due to strong impact or excessive load.
- Take note of the following when using this device:
  - Do not subject the DR Detector to strong shocks or excessive loads by dropping it, etc.



- Do not exceed the specified overall load range when applying a load to an DR Detector.
- Do not disassemble or modify this device.
- Do not connect any devices that were not purchased from Konica Minolta.
- Do not turn the power switch off or pull out the power cable, Ethernet cable while the system is operating.
- Be careful not to drop the DR Detector on any part of a person's body by catching the wired cable on your feet.
- Do not lean on or put pressure on the AeroDR Battery Charger installed on a wall.
- The wired cable is connected to the DR Detector using magnetic force. When moving the DR Detector, do not hold onto the wired cable, and always hold on the DR Detector. Also, do not grasp and pull the DR Detector forcefully.



**WARNING**





- If there is any smoke, odor, or abnormal sound, it may cause a fire if use is continued, so immediately turn the power switch off, unplug the power plug from the wall outlet, and contact Konica Minolta technical representatives.
- Take note of the following to reduce the risk of fire, electric shock, or electrical leakage:
  - Use specified cables for the power cable, etc. and AC adapter.
  - Use a wall outlet with the correct rating as a power source.
  - Confirm that the power plug is properly connected to the wall outlet without any slack.
  - Use a grounded power source.
  - If you do not plan to use this device for an extended period of time, unplug the power plug.
  - The supplied power cable and AC adapter are dedicated for this device, so do not use it elsewhere.
  - Avoid exposure to liquid such as water.
  - Make sure that foreign material, such as pieces of metal or wire, does not get inside.
  - Do not allow any metal or conductive objects to come into contact with the spring connector of the AeroDR Battery Charger2 or wired cable.
  - Do not handle the power plug with wet hands.
  - Do not let soil or dust accumulate on the power plug, AeroDR Battery Charger2 or wired cable.
  - Do not use extension cords.
  - Do not connect many plugs to a single electrical outlet.
  - Do not damage the power cable, AC adapter or wired cable. Also, do not use damaged cables.
  - Do not block the ventilation openings.
  - Do not apply a load on the power cable.
- If there is any abnormality in appearance such as deformation of the housing or a crack, stop using the device immediately and contact Konica Minolta technical representatives.
- Images exposed using Aero Storage do not have patient information. It is recommended, therefore, to keep record so that you can associate the patient exposed with the number of saved images displayed on DR Detector.
- When the images exposed using Aero Storage are imported, the history of exposure sequence, exposure failure, and divider in the DR Detector is updated. Before importing images, check the information associated with the image information recorded on paper.
- Exposure failure or division display functions of Aero Indicator is not associated to the exposed images. Record the associated information on a piece of paper with the patient information.

**CAUTION**

- Take note of the following when using this device:
  - Do not use devices that emit electromagnetic waves such as high-frequency therapy equipment, mobile phones, pocket pagers, or electric blankets, close to this device.
  - Use under the specified environmental conditions. Failure to do so may result in degradation of performance or malfunction.
  - Limit the duration of continuous use of the AeroDR 1012HQ and AeroDR 3 1012HQ in a hot and humid environment (35 °C to 37 °C/95 % or lower) in an incubator to 25 minutes or less.
  - Do not insert the AeroDR 1012HQ and AeroDR 3 1012HQ into the AeroDR Battery Charger because the charger cannot be used for registration or charging the battery.
  - Note that the AeroDR Battery Charger cannot charge the AeroDR 2 1417S and AeroDR 3 Detector.



## **CAUTION**

- Take the following notes when using the DR Detector:
  - Use the DR Detector on a flat base. If the DR Detector is placed on a sloping surface and subjected to a load, its internal sensor may be damaged.



- When laying the patient onto the DR Detector during positioning, do so very slowly.
- When placing the DR Detector under the patient as part of the exposure process, insert and pull out the detector slowly.
- Use the recommended adapter when you need to perform exposure on a stretcher or a place where load is to be applied locally.



- Exposing or immersing the DR Detector to patient body fluids, chemicals, water, etc. may allow such liquids to enter through exterior gaps and cause a failure. Make sure to cover the DR Detector with a vinyl sheet, etc.
- Be careful of the ingress of patient body fluids, chemicals, water, etc., because the AeroDR Detector is not designed to be waterproof.
- The AeroDR 2 Detector and AeroDR 3 Detector are designed to have waterproof capabilities, but be careful when handling them because they are not guaranteed to be completely waterproof. Also, be careful because subjecting them to strong impacts or excessive loads by dropping or hitting them against other objects may diminish their waterproof capabilities.



- Never leave DR Detectors in hot and humid environments for long periods of time.
- The DR Detector has wireless antennae positioned at 2 places. Do not block them with the body or metal because that will interfere with, disconnect or slow down wireless communication.
- Pressing the power switch on the AeroDR Detector and AeroDR 2 Detector causes each LED (green, orange, blue) to light temporarily or flash. After this, only green begins to flash in a slow cycle. Please check the lighting or flashing of each color once.
- Pressing the Power SW of the AeroDR 3 Detector causes the Information LED (white) to flash or light. After this, the Battery LED (blue) lights. Please check the flashing or lighting of each color.

## CAUTION

- The battery capacity is designed to allow the life period calculated based on the standard usage of the DR Detector, but replace with a new battery as necessary.
- Check that the buzzer sounds when inserted in the AeroDR Battery Charger or AeroDR Battery Charger2.
- Check that the LED indicates the fully charged state when inserted in the AeroDR Battery Charger.
- Check that the LED indicates recharging status when inserted in the AeroDR Battery Charger2.
- Be careful not to get your hand caught when inserting the DR Detector into the AeroDR Battery Charger or AeroDR Battery Charger2.
- If the DR Detector is inserted into the AeroDR Battery Charger or AeroDR Battery Charger2, make sure that the AeroDR Battery Charger or AeroDR Battery Charger2 will not tip over due to any shock applied to the DR Detector.



- The DR Detector is precision equipment, and therefore impact or vibration during radiography or image transfer may affect the image quality. Be careful when handling the DR Detector during and just after radiography.

- When using the remote table for exposure, take caution to prevent shocks and vibrations during exposure and/or image transmission, because affect from shocks and vibrations may be large.
- Never leave DR Detectors around heat generators such as electric carpet.
- Do not damage or deform the DR Detector; doing so may have an effect on exposed images, or lead to injury.
- Do not use a sharp object to operate the switch; doing so may damage the AeroDR 2 Detector and AeroDR 3 Detector.
- When using a tool to affix the AeroDR Grip sheet or perform replacement, be careful not to get injured by a tip or edge of the tool.
- When using the wired cable, observe the following:
  - Remove the cable by holding the connector housing.
  - Do not let the cable get pinched by doors and do not place heavy objects on it.
  - Do not bend or pull the cable excessively.
  - Make sure that the cable is properly connected to the DR Detector without wobbling.
  - Do not connect the connector housing backwards.
- Do not sit on or put your feet on the AeroDR Battery Charger or AeroDR Battery Charger2.
- Take note of the following if the DR Detector is damaged and fluorescent medium or lead is exposed:
  - Immediately stop using the device, and contact Konica Minolta technical representatives.
  - If the fluorescent medium gets in your eyes, do not rub and instead wash with running water immediately.
  - If you have swallowed any of the fluorescent medium or if the fluorescent medium has gotten into your eyes, administer first-aid treatment immediately, and consult a doctor.
  - If the medium comes into contact with your skin directly, wash the affected area thoroughly with water.
  - Use and store in a location inaccessible to children.
- When the DR Detector is used for exposure, pay attention to the following items.
  - Start exposure after confirming on the display of the image processing controller that the machine is ready for exposure.
  - Perform exposure under the X-ray imaging conditions that has been confirmed by us.
  - Use the specified grid to perform exposure.
  - Apply the specified operation methods to use the grid.
  - Do not let the DR Detector vibrate or receive shock until the preview image is displayed.
  - If the irradiation field is larger than DR Detector when you take an image, an artifact may occur due to the X-ray backscatter effect. Adjust the irradiation field to fit within the imaging range.



- Precautions when performing exposure in Aero Sync mode.
  - Confirm that the image processing controller is ready for exposure through its display before performing exposure.
  - Confirm that a confirmation is sounded from the image processing controller after the start of exposure.
  - Do not let the DR Detector vibrate or receive shock until the preview image is displayed.
  - Confirm that the DR Detector's battery level is full before performing exposure.
  - Use the system under the exposure condition confirmed prior to exposure.
- Please pay attention on the followings when using Aero Storage and Aero Indicator:
  - Ensure that the DR Detector LED display or Aero Indicator display indicates that it is ready for exposure, before performing an exposure operation.
  - If Aero Indicator experiences a connection failure, check the DR Detector LED display before performing an exposure operation.
  - After an exposure operation, do not give impact or vibration to the DR Detector until the DR Detector LED display or Aero Indicator display indicates that the device is ready for exposure. In addition, if the display cannot be verified, do not give shocks and/or vibrations to the DR Detector for six (6) seconds after an exposure operation.
  - Ensure that the battery level of the DR Detector is 10 % or more before performing an exposure operation.
  - Note that the exposed image is not displayed in Aero Indicator when the connection to the DR Detector is disconnected.
  - When exposing images using Aero Indicator, check the number of saved images on the DR Detector Information LED display, or ensure that the exposed image is displayed in Aero Indicator.
  - Do not give medical diagnoses using the images displayed in Aero Indicator.
- If there are any radioactive substances remaining in the patient's body after nuclear medicine testing or some other reason, the AeroDR 2 Detector and AeroDR 3 Detector may recognize that X-rays were emitted and start image transfer. When the image is transferred, change the X-ray sensitive setting of the image processing controller to "Large" before performing exposure.

- If you change the X-ray sensitivity to "Large" in the AeroDR 2 Detector, make sure that all of the following conditions are met before performing exposure. If you perform exposure under other conditions, you may not be able to get an image.
  - On the DR Detector, set up an area (2 cm x 2 cm or larger) on which the X-rays are emitted directly.
  - Emit the X-rays onto the entire DR Detector.
  - Emit the X-rays by using a tube current of 140 mA or higher or a tube voltage of 90 kV or higher.
- If you change the X-ray sensitivity to "Large" or "Med" in the AeroDR 3 Detector, make sure that all of the following conditions are met before performing exposure. If you perform exposure under other conditions, you may not be able to get an image.
  - Emit the X-rays onto the entire DR Detector.
  - Emit the X-rays by using a tube current of 140 mA or higher or a tube voltage of 90 kV or higher.
- When using AeroDR 3 1417HD2, AeroDR 3 1717HD2, AeroDR 3 1417HL, AeroDR 3 1417SL, AeroDR 3 1717HL, or AeroDR 3 1417S for exposure with the "Med" X-ray sensitivity in Portable Unit operation, use the configuration of SID120 cm and tube voltage of 80 kV.
- Set the maximum exposure time at the suitable exposure time with the image processing controller when performing exposure.
- When setting the maximum exposure time to 4.0, 6.7, 10.3, be sure to contact Konica Minolta technical representatives.
- When the maximum exposure time of the AeroDR 3 Detector is set at 10.3, the interval between exposures should be 2 minutes or longer. The following exposures also require 2 minutes intervals.
- If you use Ethernet cables, please pay attention to the following.
  - If the power of this device is on, do not connect nor remove the Ethernet cables.
  - Install the cables so that you do not catch them on your feet and so on.
  - Do not apply a load.
  - Use shielded Ethernet cables. However, for connections between AeroDR Interface Unit and AeroDR Battery Charger or AeroDR Battery Charger2 and between AeroDR Interface Unit and access points, you can use unshielded Ethernet cables.
  - Communication speed is low or communication is down, it is necessary to check the Ethernet cable replacement. Contact Konica Minolta technical representatives.

### 1.3.3 Precautions regarding electromagnetic waves

#### EMC Statement

This device has been tested and found to comply with the limits for medical devices in IEC 60601-1-2: 2007 or IEC 60601-1-2: 2014.

These limits are designed to provide reasonable protection against harmful interference in a typical medical installation. The device generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to other devices in its vicinity. However, there is no guarantee that interference will not occur in a particular installation.

Whether this device does cause harmful interference to other devices can be determined by turning this device off and on. If it causes harmful interference, the user is encouraged to try to correct the interference by 1 or more of the following measures:

- Reorient or relocate the receiving device.
- Increase the separation between the devices.
- Connect this device into a wall outlet on a circuit different from that to which the other devices are connected.
- Contact Konica Minolta technical representatives.

#### WARNING

- Do not use mobile RF communication devices such as mobile phones or pocket pagers in the vicinity of this device. Use of such RF devices near this device can cause errors in operation due to electromagnetic wave interference. When using a mobile RF device, ensure that the distance between the RF device in use and this device is at least 30 cm (12 inches).
- The use of accessories, transducers and cables other than those sold by Konica Minolta, Inc. as internal components, may result in increased emissions or decreased electromagnetic immunity of this device, possibly causing malfunction.
- Do not use this device adjacent to or stacked with other devices. If adjacent or stacked use is necessary, confirm normal operation in the configuration in which this device will be used.

#### Supplementary information regarding IEC 60601-1-2:2007 and IEC 60601-1-2:2014

- (1) Take precautions against this device especially regarding EMC. Install and put into service according to the electromagnetic compatibility (EMC) information provided in the manual (Table 1 - Table 5).

- (2) This device is suitable for use in medical institutions such as hospitals and clinics. However, this device is not suitable for use in environments with high degree of electromagnetic wave interference (such as near an electric operation device in use for output, or near a high frequency treatment device).

- (3) Cable list

- Power cable (3.048 m/3-Wire/No Shielding)
- Ethernet cable (max 30 m/Shielding)
- Non-shielded Ethernet cable can be used for connecting to the AeroDR Battery Charger and the AeroDR Battery Charger2
- Ethernet cable to connect to GIU SZ (max. 10 m/shielded)

- (4) Specifications regarding RF transmitters frequency:

- Frequency
  - AeroDR SYSTEM: 5150 MHz to 5350 MHz, 5470 MHz to 5850 MHz
  - AeroDR SYSTEM 2: 2412 MHz to 2472 MHz, 5180 MHz to 5320 MHz, 5500 MHz to 5825 MHz
  - SKR 3000: 2412 MHz to 2462 MHz, 5180 MHz to 5320 MHz, 5500 MHz to 5700 MHz, 5745 MHz to 5825 MHz
- Modulation
  - AeroDR SYSTEM: OFDM
  - AeroDR SYSTEM 2: 2412 MHz to 2472 MHz: DSSS/CCK/OFDM, 5180 MHz to 5320 MHz, 5500 MHz to 5825 MHz: OFDM
  - SKR 3000: 2412 MHz to 2462 MHz: DSSS/CCK/OFDM, 5180 MHz to 5320 MHz, 5500 MHz to 5700 MHz, 5745 MHz to 5825 MHz: OFDM
- Maximum effective radiation power
  - AeroDR SYSTEM: +15 dBm
  - AeroDR SYSTEM 2: +10 dBm
  - SKR 3000: +15 dBm
- This device may be interfered with by other devices that conform to CISPR emission requirements.



**Table 1 (support for IEC 60601-1-2:2007 and IEC 60601-1-2:2014)**

Guidelines and manufacture's declaration - electromagnetic emissions		
This device is intended for use in the electromagnetic environment specified below. The customer or the user of this device should assure that it is used in such an environment.		
Emissions test	Compliance	Electromagnetic environment - guidelines
RF emissions CISPR 11	Group 1	The device uses RF energy only for its internal function. Therefore, its RF emissions are very low and are not likely to cause any interference in nearby electronic equipment.
RF emissions CISPR 11	Class B	This device is suitable for use in all establishments including the following: Domestic establishments and those directly connected to the public low-voltage power supply network that supplies buildings for domestic purposes.
Harmonic emissions IEC 61000-3-2	Class A	
Voltage fluctuations/flicker emissions IEC 61000-3-3	Complies	

**IMPORTANT**


- If I/F Cable4 1.5mD, I/F Cable4 8mD, I/F Cable4 8mU and/or I/F Cable4 2mU is used, the emissions characteristics of this device is CISPR 11 class A that is suitable for the industrial areas and the hospitals. If it is used in a residential environment, for which CISPR 11 class B is normally required, this equipment might not offer adequate protection to radio-frequency communication services, and it may be necessary to take a mitigation measures, for example, by relocating or re-orientating the device.

**Table 2 (support for IEC 60601-1-2:2007)**

Guidelines and manufacturer's declaration - electromagnetic immunity			
This device is intended for use in the electromagnetic environment specified below. The customer or the user of this device should assure that it is used in such an environment.			
Immunity test	IEC 60601 test level	Compliance level	Electromagnetic environment - guidelines
Electrostatic discharge (ESD) IEC 61000-4-2	±6 kV contact	±6 kV contact	Floors should be wood, concrete or ceramic tile. If floors are covered with synthetic material, the relative humidity should be at least 30 %. Mains power quality should be that of a typical commercial or hospital environment.
	±8 kV air	±8 kV air	
Electrical fast transient/burst IEC 61000-4-4	±2 kV for power supply lines	±2 kV for power supply lines	Mains power quality should be that of a typical commercial or hospital environment.
	±1 kV for input/output lines	±1 kV for input/output lines	
Surge IEC 61000-4-5	±1 kV line(s) to line(s)	±1 kV line(s) to line(s)	
	±2 kV line(s) to earth	±2 kV line(s) to earth	
Voltage dips, short interruptions and voltage variations on power supply input lines IEC 61000-4-11	<5 % $U_T$ (>95 % dip in $U_T$ ) for 0.5 cycle	<5 % $U_T$ (>95 % dip in $U_T$ ) for 0.5 cycle	Mains power quality should be that of a typical commercial or hospital environment. If the user of the device requires continued operation during power mains interruptions, it is recommended that the device be powered from an uninterrupted power supply or a battery.
	40 % $U_T$ (60 % dip in $U_T$ ) for 5 cycles	40 % $U_T$ (60 % dip in $U_T$ ) for 5 cycles	
	70 % $U_T$ (30 % dip in $U_T$ ) for 25 cycles	70 % $U_T$ (30 % dip in $U_T$ ) for 25 cycles	
	<5 % $U_T$ (<95 % dip in $U_T$ ) for 5 sec	<5 % $U_T$ (<95 % dip in $U_T$ ) for 5 sec	
Power frequency (50/60 Hz) magnetic field IEC 61000-4-8	3 A/m	3 A/m	Power frequency magnetic fields should be at levels characteristic of a typical location in a typical commercial or hospital environment.
[NOTE] $U_T$ is the AC mains voltage prior to application of the test level.			



Table 3 (support for IEC 60601-1-2:2007)

Guidelines and manufacturer's declaration - electromagnetic immunity			
This device is intended for use in the electromagnetic environment specified below. The customer or the user of this device should assure that it is used in such an environment.			
Immunity test	IEC 60601 test level	Compliance level	Electromagnetic environment - guidelines
Conducted RF IEC 61000-4-6	3 Vrms 150 kHz to 80 MHz	[3] V	Portable and mobile RF communications equipment should be used no closer to any part of this device, including cables, than the recommended separation distance calculated from the equation applicable to the frequency of the transmitter. Recommended separation distance $d=[1.2] \sqrt{P}$  $d=[1.2] \sqrt{P}$ 80 MHz to 800 MHz $d=[2.3] \sqrt{P}$ 800 MHz to 2.5 GHz  where P is the maximum output power rating of the transmitter in watts (W) according to the transmitter manufacturer and d is the recommended separation distance in meters (m).  Field strengths from fixed RF transmitters, as determined by an electromagnetic site survey <sup>a</sup> , should be less than the compliance level in each frequency range <sup>b</sup> .  Interference may occur in the vicinity of equipment marked with the following symbol:  
Radiated RF IEC 61000-4-3	3 V/m 80 MHz to 2.5 GHz	[3] V/m	
<div>[NOTE] At 80 MHz and 800 MHz, the separation distance for the higher frequency range applies.</div> <div>[NOTE] These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflection from structures, objects and people.</div>			
<div>a Field strengths from fixed transmitters, such as base stations for radio (cellular/cordless) telephones and land mobile radios, amateur radio, AM and FM radio broadcast and TV broadcast cannot be predicted theoretically with accuracy. To assess the electromagnetic environment due to fixed RF transmitters, an electromagnetic site survey should be considered. If the measured field strength in the location in which this device is used exceeds the applicable RF compliance level above, this device should be observed to verify normal operation. If abnormal performance is observed, additional measures may be necessary, such as reorienting or relocating this device.</div> <div>b Over the frequency range 150 kHz to 80 MHz, field strength should be less than [3] V/m.</div>			

**Table 4 (support for IEC 60601-1-2:2007)**

Recommended separation distance between portable and mobile RF communications equipment and the device			
This device is intended for use in an electromagnetic environment in which radiated RF disturbances are controlled. The customer or the user of this device can help prevent electromagnetic interference by maintaining a minimum distance between portable and mobile RF communications equipment (transmitters) and this device as recommended below, according to the maximum output power of the communications equipment.			
Rated maximum output power of the transmitter W	Separation distance according to frequency of transmitter m		
	150 kHz to 80 MHz $d=[1.2] \sqrt{P}$	80 MHz to 800 MHz $d=[1.2] \sqrt{P}$	800 MHz to 2.5 GHz $d=[2.3] \sqrt{P}$
0.01	0.12	0.12	0.23
0.1	0.38	0.38	0.73
1	1.2	1.2	2.3
10	3.8	3.8	7.3
100	12	12	23
For transmitters rated at a maximum output power not listed above, the recommended separation distance d in meters (m) can be estimated using the equation applicable to the frequency of the transmitter, where P is the maximum output power rating of the transmitter in watts (W) according to the transmitter manufacturer. [NOTE] At 80 MHz and 800 MHz, the separation distance for the higher frequency range applies. [NOTE] These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflection from structures, objects and people.			

**Table 5 (support for IEC 60601-1-2:2014)**

Phenomenon	Basic EMC standard or test method	Immunity test levels
Electrostatic discharge	IEC 61000-4-2	±8 kV contact ±2 kV, ±4 kV, ±8 kV, ±15 kV air
Radiated RF EM fields	IEC 61000-4-3	3 V/m 80 MHz - 2.7 GHz, 5.1 GHz - 5.8 GHz 80 % AM at 1 kHz
Proximity fields from RF wireless communications equipment	IEC 61000-4-3	See the following table "Test specifications for Enclosure port immunity to RF wireless communications equipment"
Electrical fast transients / bursts	IEC 61000-4-4	±2 kV input a.c. power port ±1 kV signal input/output parts port 100 kHz repetition frequency
Surges	IEC 61000-4-5	±0.5 kV, ±1 kV line-to-line ±0.5 kV, ±1 kV, ±2 kV line-to-ground
Conducted disturbances induced by RF fields	IEC 61000-4-6	3 V 0.15 MHz - 80 MHz 6 V in ISM bands between 0.15 MHz and 80 MHz <sup>a</sup> 80 % AM at 1 kHz
Rated power frequency magnetic fields	IEC 61000-4-8	30 A/m
Voltage dips	IEC 61000-4-11	0 % U <sub>T</sub> ; 0.5 cycle At 0°, 45°, 90°, 135°, 180°, 225°, 270° and 315°
		0 % U <sub>T</sub> ; 1 cycle and 70 % U <sub>T</sub> ; 25/30 cycle <sup>b</sup> Single phase: at 0°
Voltage interruptions	IEC 61000-4-11	0 % U <sub>T</sub> ; 250/300 cycle <sup>b</sup>
[NOTE] U <sub>T</sub> is the a.c. mains voltage prior to application of the test level.		
<sup>a</sup> The ISM (industrial, scientific and medical) bands between 0.15 MHz and 80 MHz are 6.765 MHz to 6.795 MHz; 13.553 MHz to 13.567 MHz; 26.957 MHz to 27.283 MHz; and 40.66 MHz to 40.70 MHz.		
<sup>b</sup> E.g. 10/12 means 10 periods at 50 Hz or 12 periods at 60 Hz.		

**Test specifications for Enclosure port immunity to RF wireless communications equipment**

Test frequency (MHz)	Modulation	Immunity test level (V/m)
385	Pulse modulation 18 Hz	27
450	Frequency modulation ±5 kHz deviation 1 kHz sine	28
710	Pulse modulation 217 Hz	9
745		
780		
810	Pulse modulation 18 Hz	28
870		
930		
1720	Pulse modulation 217 Hz	28
1845		
1970		
2450	Pulse modulation 217 Hz	28
5240	Pulse modulation 217 Hz	9
5500		
5785		

### 1.3.4 Precautions regarding wireless communication



#### CAUTION

- This device is equipped with a communication function that operates via wireless LAN. Conformance is required with the relevant regulations defined by the countries in which this device is to be used.
- Inappropriate usage may cause interference in radio communication. Also, if this device is modified, approval and warranty according to the radio law of the applicable government will be voided.
- It may affect aeronautical systems, so do not use on-board airplanes.
- This device may be affected by other wireless devices. Make sure that the environment is free of wireless communications.
- DR Detector has been confirmed to comply with the relevant regulations of the following countries:

#### United States & Canada

##### **Federal Communications Commission Statement / Canadian Department of Communications**

- DR Detector complies with Part 15 of FCC Rules and Innovation, Science and Economic Development Canada's (ISED) licence-exempt RSS standard(s). Operation is subject to the following 2 conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of this device.
- This transmitter must not be co-located or operated in conjunction with any other antenna or transmitter.
- The 5.15 GHz-5.35 GHz band is restricted to indoor operation only.
- The available scientific evidence does not show that any health problems are associated with using low power wireless devices. There is no proof, however, that these low power wireless devices are absolutely safe. Low power Wireless devices emit low levels of radio frequency energy (RF) in the micro-wave range while being used. Whereas high levels of RF can produce health effects (by heating tissue), exposure of low-level RF that does not produce heating effects causes no known adverse health effects. Many studies of low-level RF exposures have not found any biological effects. Some studies have suggested that some biological effects might occur, but such findings have not been confirmed by additional research. DR Detector has been tested and found to comply with FCC/ISED radiation exposure limits set forth for controlled equipment and meets the FCC radio frequency (RF) Exposure Guidelines and RSS-102 of the ISED radio frequency (RF) Exposure rules.

- High-power radars are allocated as primary users (i.e. priority users) of the 5250 MHz-5350 MHz and 5650 MHz-5850 MHz bands, and these radars could cause interference and/or damage to LE-LAN devices.
- Compliance with FCC requirement 15.407(c): Data transmission is always initiated by software, which is passed down through the MAC, through the digital and analog baseband, and finally to the RF chip. Several special packets are initiated by the MAC. These are the only ways the digital baseband portion will turn on the RF transmitter, which it then turns off at the end of the packet. Therefore, the transmitter will be on only while one of the aforementioned packets is being transmitted. In other words, this device automatically discontinues transmission in case of either absence of information to transmit or operational failure.
- Compliance with FCC requirement 15.407(g): Frequency Tolerance: 20 ppm

#### **FCC WARNING**

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

#### European Union

##### **European Union Directives Conformance Statement**

DR Detector conforms with the Declaration of Conformity (DoC) to Radio Equipment Directive 2014/53/EU or R&TTE Directive 1999/5/EC. This device purposely connects to an access point of a 5 GHz network.

The 5.15-5.35 GHz band is restricted to indoor operation only.

Hereby, Konica Minolta, Inc., declares that the AeroDR SYSTEM, AeroDR SYSTEM 2 and SKR3000 are in compliance with Directive 2014/53/EU or 1999/5/EC. The full text of the EU declaration of conformity is available at the following internet address:

<https://www.konicaminolta.eu/>

## Taiwan

Any company, corporation, or user shall not change frequencies, original characteristics or performance, or increase output without permission for low-power wireless devices which have received approval of models.

Use of a low-power wireless device shall not affect safety of aircrafts, or interfere with legal communication. If any interference is observed, stop using the device immediately. Do not use the device until the interference is eliminated.

Legal communication in the previous article refers to the wireless communication based on the provisions of the Telecommunications Business Act.

Low-power wireless devices must accept interference from legal communication or from electric equipment with radio wave emissivity for industrial, chemical and medical use.

Avoid using the device in the vicinity of radar systems.

## China

- Clearly indicate the technical indicators and the scope of usage in the accompanying document, and explain the usage of all controls, adjustments, and switches, etc.
    - Operating frequency range: 5725 MHz-5850 MHz
    - Transmit power:  $\leq 500$  mW and  $\leq 27$  dBm
    - Equivalent isotropic radiated power (EIRP):  $\leq 2$  W and  $\leq 33$  dBm
    - Maximum radiation power density:  $\leq 13$  dBm/MHz and  $\leq 19$  dBm/MHz (EIRP)
    - Frequency Tolerance limit: 20 ppm
    - Transmit power at the band edge (EIRP):  $\leq 80$  dBm/Hz ( $\leq 5725$  MHz or  $\geq 5850$  MHz)
    - Spurious emissions:
      - $\leq -36$  dBm/100 kHz (30 MHz-1000 MHz)
      - $\leq -40$  dBm/1 MHz (2400 MHz-2483.5 MHz)
      - $\leq -40$  dBm/1 MHz (3400 MHz-3530 MHz)
      - $\leq -33$  dBm/100 kHz (5725 MHz-5850 MHz)

(Note: Other than  $\pm 2.5$ -times supported channel bandwidth)

  - $\leq -30$  dBm/1 MHz (Other 1 GHz-40 GHz)
- Do not arbitrarily change frequency or increase transmit power (including the added radio frequency amplifier). In addition, do not mount an antenna without permission, or change to another transmission antenna.
  - When in use, do not cause harmful interference in other legal wireless communication services. If you find interference to be occurring, discontinue use immediately. After taking measures to eliminate interference, you may continue using the device.
  - If you use low power radio equipment, you must accept interference from various wireless services or radiation interference from industrial, scientific and medical application equipment.
  - Do not use near a plane or an airport.

## South Korea

Because this wireless equipment may be affected by radio interference, it cannot provide services related with life safety.

## Thailand

DR Detector conforms to NTC technical requirement.

## Brazil

This equipment operates secondarily, that is, it doesn't benefit from protection against harmful interference, even from stations of the same type, and cannot cause interference to systems that operate primarily.

DR Detector has been approved by ANATEL in compliance with the procedures regulated by Resolution 242/2000 and complies with the applicable technical requirements.

AeroDR system and Stitching system fulfill the requirements set forth in INMETRO Ordinance No 350, dated 06/09/2010, and other regulations pertaining to compulsory certification of Electrical Equipment Subject to Sanitary Surveillance by ANVISA (RDC No 27, dated 21/06/2011, and Normative Instruction No 11, dated 16/12/2014).

When used appropriately on the body, the highest SAR value reported during product certification is 0.051 W/kg (for the P-61 model), 0.054 (for the P-71 model) and 0.074 (for the P-81 model).

Konica Minolta hereby declares that the AeroDR System and Stitching System products fulfill the biocompatibility aspects of ISO 10993-1:2009.

This equipment operates with a voltage of AC 127V.

This equipment is not entitled to harmful interference protection and may not cause interference to duly authorized systems.

For more information, please visit:

<http://www.anatel.gov.br>

## Mexico

This equipment operates on a secondary basis; consequently, you must accept harmful interferences from equipment of the same type, and cannot cause interferences to systems operating on a primary basis.

### 1.3.5 Precautions for installing, moving, and storing



#### WARNING

- Take note of the following when moving this device not including the DR Detector:
  - Do not subject to shocks or vibration .
  - Do not start moving until the power is turned off, and operation has stopped completely.
  - Do not move with the power cable or any other cable connected.
  - Do not install the power cable, Ethernet cable and wired cable so that you do not catch them on your feet and so on.
  - Be careful not to drop the DR Detector on any part of a person's body.
  - Install on a horizontal and stable surface.
- When installing the AeroDR Battery Charger or AeroDR Battery Charger2 on a table top, observe the following:
  - Install on a base that can withstand maximum patient weight because load is inserted when setting the DR Detector.
  - The contact area for the AeroDR Battery Charger or AeroDR Battery Charger2 must be larger than the area of the AeroDR Battery Charger or AeroDR Battery Charger2 so that it will not fall down when the DR Detector is inserted or when people touch it by accident.
  - Do not use a base that has a surface made of slippery material such as teflon.
  - Connect power cable and wires so that no one will trip.
  - Install in a place easy to insert the DR Detector.
  - Install so that the vent on the back side of the AeroDR Battery Charger is not blocked.



#### CAUTION

- Because connections of the X-ray device can only be made by Konica Minolta or its designated contractors, contact Konica Minolta or its designated contractors.
- For the X-ray devices enabled to connect, contact Konica Minolta technical representatives.
- Contact Konica Minolta or dealers specified by Konica Minolta to install or move this device.
- Since it is required to meet the specification provided by the X-ray device manufacturer to connect with an X-ray device, contact Konica Minolta or dealers specified by Konica Minolta.
- Take note of the following when installing or storing this device.
  - Install or store this device within the specified storage and usage conditions and environment.

- Do not install or store in a location where it may be adversely affected by atmospheric pressure, temperature, humidity, ventilation, sunlight, dust, salt-air, or air containing sulfur.
- Do not install or store in a location where it is not stable, ventilation is insufficient, the difference in light-dark is great, electromagnetic waves are generated, or where subject to vibration or shock.
- Do not install or store in a location where chemical agents are used or stored.
- Do not install this device facing up or upside down.
- Do not install the AeroDR Interface Unit, AeroDR Interface Unit2 and AeroDR Generator Interface Unit stacked on each other.
- Connect the AeroDR Interface Unit2, AeroDR Generator Interface Unit, AeroDR Generator Interface Unit2, Generator Interface Unit 3 and GIU SZ to an X-ray device that conforms to IEC 60601 or an equivalent standard.
- Contact Konica Minolta or dealers specified by Konica Minolta with regard to the information of compatible X-ray devices.


### 1.3.6 Precautions regarding maintenance

#### WARNING

- Perform the maintenance and inspection periodically. In addition to the user periodical maintenance that needs to be performed, periodical maintenance by a service engineer is also required.
- If there are stains such as body fluids, clean and disinfect.

#### CAUTION

- Based on the warranty, parts that are no longer under warranty (1 year) can be replaced for a fee.
- Turn off the power and disconnect the power plug from the wall outlet before cleaning or maintaining this device.
- Securely connect the power cable, wired cable and Ethernet cable after cleaning and maintenance.
- Clean the dirt from the gaps between the exterior of DR Detector, and the terminal using a commercial plastic brush. Do not clean with sharp or hard objects.
- DR Detector needs disinfection.
- The exteriors of AeroDR 3 1417HD2, AeroDR 3 1717HD2, AeroDR 3 1417HL, AeroDR 3 1417SL, AeroDR 3 1717HL, and AeroDR 3 1417S contain antibacterial agents. They also need to be disinfected the same as any other DR Detectors.
- Take care regarding the following when disinfecting the DR Detector.
  - Use ethanol for disinfection, isopropanol for disinfection, or commercial chlorine bleach, or 1 % hypochlorite (5-fold dilution of household bleach) when disinfecting. However, bleach and hypochlorite are corrosive, so wash the bleach off well to avoid corrosion.
  - Please note that if you use chemical for disinfection other than the above, it may affect the quality, performance, and safety of the DR Detector.
  - If you directly apply or spray disinfecting solution on the DR Detector, the solution will enter the instrument through exterior gaps, causing a failure. Dampen a lint-free, soft cloth with disinfecting solution, and use after wringing it thoroughly. AeroDR Detector is not waterproofed. Do not apply disinfecting solution onto the wired connection connector and LED when cleaning.



— Disinfecting solution is a chemical agent, so follow the precautions of the manufacturer.

- Fully charge battery once a month even if the DR Detector has not been used for a long time.

### 1.3.7 Precautions on service life

#### CAUTION

##### Service life

Name	Service life
DR Detector	6 years
AeroDR Interface Unit	6 years
AeroDR Interface Unit2	6 years
Detector Interface Unit	6 years
Detector Interface Unit 2	6 years
Power Supply Unit	6 years
AeroDR Generator Interface Unit	6 years
AeroDR Generator Interface Unit2	6 years
Generator Interface Unit 3	6 years
GIU SZ	6 years
AeroDR Battery Charger	6 years
AeroDR Battery Charger2	6 years
AeroDR Access Point	6 years
I/F Cable	6 years
AeroDR UF Cable	6 years

- The above service life is valid only if the product has been properly operated while following the precautions for use and performing the specified maintenance. (By self certification <our data>)
- The service life may differ depending on usage conditions and environment.
- Some component parts of this device are commercially available parts that have a short cycle of model changes, therefore, it might not be possible to supply service parts even within the service life. In addition, related component parts may need to be replaced to maintain compatibility at the time of model change.

---

---



# **Chapter 2**

---

## **Product Overview**

## 2.1 Overview of this device

### 2.1.1 Functions

The AeroDR SYSTEM consists of AeroDR Detector, AeroDR Interface Unit, AeroDR Interface Unit2, AeroDR Generator Interface Unit, AeroDR Battery Charger, AeroDR Battery Charger2, AeroDR Access Point, etc. With the DR Detector, diagnostic X-ray digital image data is generated by the irradiation signal and exposure from an X-ray device, and sent to the image processing controller.

Furthermore, the DR Detector can be connected with (or inserted in) the AeroDR Interface Unit, AeroDR Interface Unit2, AeroDR Battery Charger and AeroDR Battery Charger2 or removed from them.

The AeroDR SYSTEM 2 consists of the AeroDR 2 Detector, AeroDR Interface Unit, AeroDR Interface Unit2, AeroDR Generator Interface Unit, AeroDR Generator Interface Unit2, AeroDR Battery Charger, AeroDR Battery Charger2, etc. With the DR Detector, diagnostic X-ray digital image data is generated by the irradiation signal or exposure from an X-ray device and sent to the image processing controller.

Furthermore, the DR Detector can be connected with (or inserted in) or removed from the AeroDR Interface Unit, AeroDR Interface Unit2, AeroDR Battery Charger and AeroDR Battery Charger2.

The SKR 3000 consists of the AeroDR 3 Detector, AeroDR Interface Unit, AeroDR Interface Unit2, Detector Interface Unit, Detector Interface Unit 2, Power Supply Unit, AeroDR Generator Interface Unit, AeroDR Generator Interface Unit2, Generator Interface Unit 3, GIU SZ, AeroDR Battery Charger2, etc. The DR Detector uses the exposure signal or exposure from the X-ray device to generate X-ray digital image data for diagnosis, including serial exposure images, and send to the image processing controller.

Furthermore, the DR Detector can be connected with (or inserted in) or removed from the AeroDR Interface Unit, AeroDR Interface Unit2, Detector Interface Unit, Detector Interface Unit 2, GIU SZ and AeroDR Battery Charger2.

#### For EEA (European Economic Area), Swiss and Turkey

The SKR 3000 consists of the AeroDR 3 Detector, Detector Interface Unit, Detector Interface Unit 2, Power Supply Unit, AeroDR Generator Interface Unit 2, Generator Interface Unit 3, AeroDR Battery Charger2, etc. The DR Detector uses the exposure signal or exposure from the X-ray device to generate X-ray digital image data for diagnosis, including serial exposure images, and send to the image processing controller.

X-ray irradiation enable by the switch located in the X-ray device, which is not a part of SKR 3000.

The X-ray irradiation signal is sent from the switch to X-ray generator inside the X-ray system. X-ray device checks if all the peripheral devices such as SKR 3000, Wall stand, Table, and radiation-shielded door of X-ray imaging room, are ready for the X-ray exposure. If all the peripheral devices are ready and the X-ray irradiation signal is sent to the X-ray generator, then the X-ray device can perform X-ray irradiation.

#### HINT

- The AeroDR SYSTEM, AeroDR SYSTEM 2 and SKR 3000 can be used together.

## 2.1.2 System configuration and connection examples

### Basic configuration example


2

Number	Name	Functions
(1)	DR Detector	<ul style="list-style-type: none"> <li>• There are 15 types of DR Detectors: AeroDR 1417HQ, AeroDR 1417S, AeroDR 1717HQ, AeroDR 1012HQ, AeroDR 2 1417HQ, AeroDR 2 1417S, AeroDR 3 1417HD, AeroDR 3 1717HD, AeroDR 3 1012HQ, AeroDR 3 1417HD2, AeroDR 3 1717HD2, AeroDR 3 1417HL, AeroDR 3 1417SL, AeroDR 3 1717HL, and AeroDR 3 1417S.</li> <li>• DR Detector is of B-type Applied Parts.</li> </ul>
(2)	AeroDR Interface Unit	<ul style="list-style-type: none"> <li>• Supplies power to the AeroDR Generator Interface Unit, AeroDR Generator Interface Unit2, and access point.</li> <li>• Supplies power to and charges the DR Detector when the wired cable is used.</li> <li>• It has a built-in hub function.</li> <li>• 2 DR Detectors can be connected via wired connection.</li> <li>• The expansion AeroDR Interface Unit is required for connecting the third to seventh DR Detectors via wired connection.</li> </ul>
(3)	AeroDR Interface Unit2	<ul style="list-style-type: none"> <li>• Supplies power to the access point.</li> <li>• Supplies power to and charges the DR Detector when the wired cable is used.</li> <li>• It has a built-in hub function.</li> <li>• 2 DR Detectors can be connected via wired connection.</li> <li>• The expansion AeroDR Interface Unit is required for connecting the third to seventh DR Detectors via wired connection.</li> <li>• Relays signals between the X-ray device, the DR Detector, and the image processing controller.</li> </ul>
(4)	Hub	<ul style="list-style-type: none"> <li>• Used to connect the AeroDR Generator Interface Unit2 or access point.</li> <li>• General-purpose product.</li> <li>• Product conforming to IEC 60950 (CLASS I) or equivalent standards.</li> </ul>
(5)	Detector Interface Unit	<ul style="list-style-type: none"> <li>• Relays signals between the DR Detector and the image processing controller.</li> <li>• Supplies power to the DR Detector.</li> </ul>
(6)	Detector Interface Unit 2	<ul style="list-style-type: none"> <li>• Relays signals between the DR Detector and the image processing controller.</li> <li>• Supplies power to the DR Detector.</li> <li>• Relays signals for serial exposure.</li> </ul>
(7)	Power Supply Unit	<ul style="list-style-type: none"> <li>• Supplies power to the Detector Interface Unit, Detector Interface Unit 2, AeroDR Generator Interface Unit, AeroDR Generator Interface Unit2, Generator Interface Unit 3 and access point.</li> <li>• Relays signals between the Detector Interface Unit, Detector Interface Unit 2, AeroDR Generator Interface Unit, AeroDR Generator Interface Unit2, Generator Interface Unit 3, access point and the image processing controller.</li> </ul>
(8)	AeroDR Generator Interface Unit	Relays signals between the X-ray device, the DR Detector, and the image processing controller.
(9)	AeroDR Generator Interface Unit2	Relays signals between the X-ray device, the DR Detector, and the image processing controller.
(10)	Generator Interface Unit 3	<ul style="list-style-type: none"> <li>• Relays signals between the X-ray device, the DR Detector, and the image processing controller.</li> <li>• Relays signals for serial exposure, using GIU3 Serial I/F Kit.</li> </ul>
(11)	GIU SZ	<ul style="list-style-type: none"> <li>• Relays signals between the X-ray device, the DR Detector, and the image processing controller. An exposure using wired connection is not supported.</li> <li>• Supplies power to the DR Detector.</li> <li>• Relays signals for serial exposure.</li> </ul>
(12)	AeroDR Battery Charger	Charges the DR Detector. It also has the registration function for the DR Detector.
(13)	AeroDR Battery Charger2	Charges the DR Detector. It also has the registration function for the DR Detector.
(14)	AeroDR Access Point	This communicates with DR Detector when performing an exposure using wireless connection.
(15)	Access Point	<ul style="list-style-type: none"> <li>• This communicates with DR Detector when performing an exposure using wireless connection.</li> <li>• General-purpose product.</li> <li>• The AeroDR Access Point 2 is included.</li> </ul>


## Overview of this device

Number	Name	Functions
(16)	I/F Cable	<ul style="list-style-type: none"> <li>This communicates with DR Detector when performing an exposure using wired connection. Also used for charging and registering the DR Detector.</li> <li>I/F Cable4 1.5mD, I/F Cable4 8mD, I/F Cable4 8mU, and I/F Cable4 2mU relay signals for serial exposure.</li> </ul>
(17)	AeroDR UF Cable	Registers the orientation when the DR Detector is used for exposure in the wall stand/table position.
(18)	Image processing controller	<ul style="list-style-type: none"> <li>Controls the reception, management, and output of image data.</li> <li>Up to 7 DR Detectors can be registered.</li> </ul>
(19)	AeroDR XG Cable	Performs signal relay between the X-ray device and the AeroDR Interface Unit2, AeroDR Generator Interface Unit and AeroDR Generator Interface Unit2.
(20)	AeroDR Collimator Cable	Performs exposure field signal relay between the X-ray device and the AeroDR Interface Unit2 or AeroDR Generator Interface Unit.
(21)	AeroDR S-SRM Cable	Performs signal relay between the X-ray device operation panel and AeroDR Interface Unit2, AeroDR Generator Interface Unit, and AeroDR Generator Interface Unit2.
(22)	S-SRM	Synchronizes AeroDR Interface Unit2, AeroDR Generator Interface Unit, and AeroDR Generator Interface Unit. Exposure is performed using the AeroDR Generator Interface Unit.


### Basic connection example 1



## Basic connection example 2




## Basic connection example 3



### HINT

- The AeroDR Generator Interface Unit2 and access point can also be powered from the AC adapter.


## Basic connection example 4



### HINT

- The Generator Interface Unit 3 can also be powered from the GIU3 AC Adapter.


## Basic connection example 5




### HINT

- The Detector Interface Unit can also be powered from the DI Unit AC Adapter.


## S-SRM connection example 1



## S-SRM connection example 2




### S-SRM connection example 3



#### HINT


- The AeroDR Generator Interface Unit2 and access point can also be powered the AC adapter.

### S-SRM connection example 4







## Aero Sync connection example 1




## Aero Sync connection example 2



## Serial exposure connection example



## Serial exposure connection example 2




### IMPORTANT

- DR Detector connected to to GIU SZ with wired connection can be used for charging and registrations, but not for exposures. Use DR Detector with wireless connection for exposures with this configuration example.


## 2.2 Component names and functions

### 2.2.1 AeroDR Detector




Number	Name	Functions
(1)	Triangular mark	<ul style="list-style-type: none"> <li>Indicates the direction to place the DR Detector in during exposure. <ul style="list-style-type: none"> <li>When exposing in portrait, place the triangular mark upward.</li> <li>When exposing in landscape, place the triangular mark to the left or right.</li> <li>(Left and right are set during installation according to the exposure environment.)</li> </ul> </li> </ul>
(2)	Power switch	Used to turn the DR Detector on/off.
(3)	Antenna display	Displays the place where a wireless antenna is attached.
(4)	AeroDR Grip sheet attachment areas	<ul style="list-style-type: none"> <li>Indicates the attachment positions for AeroDR Grip sheet use.</li> <li>The AeroDR 1012HQ does not have AeroDR Grip sheet attachment areas.</li> </ul>
(5)	Exterior	Protects the internal parts.
(6)	Protective cover	Absorbs external shocks.
(7)	LEDs	Indicate the status of the DR Detector.
(8)	Selection switch	Notifies the image processing controller that this DR Detector will be used for the exposure.
(9)	Wired connection connector	Connects to the AeroDR Battery Charger, AeroDR Battery Charger2, wired cable, and AeroDR UF Cable.

## 2.2.2 AeroDR 2 Detector



Number	Name	Functions
(1)	Triangular mark	<ul style="list-style-type: none"> <li>Indicates the direction to place the DR Detector in during exposure.</li> <li>— When exposing in portrait, place the triangular mark upward.</li> <li>— When exposing in landscape, place the triangular mark to the left or right.</li> <li>— (Left and right are set during installation according to the exposure environment.)</li> </ul>
(2)	Power switch	Used to turn the DR Detector on/off.
(3)	Antenna display	Displays the place where a wireless antenna is attached.
(4)	AeroDR Grip sheet attachment areas	Indicates the attachment positions for AeroDR Grip sheet use.
(5)	Exterior	Protects the internal parts.
(6)	Protective cover	Absorbs external shocks.
(7)	LEDs	Indicate the status of the DR Detector.
(8)	Selection switch	Notifies the image processing controller that this DR Detector will be used for the exposure.
(9)	Wired connection connector	Connects to the AeroDR Battery Charger, AeroDR Battery Charger2, and wired cable.

2.2.3 AeroDR 3 Detector




Number	Name	Functions
(1)	Power SW	Used to turn the DR Detector on/off.
(2)	Selection SW	Notifies the image processing controller that this DR Detector will be used for the exposure.
(3)	Front board	Protects the internal parts.
(4)	Triangular mark	<ul style="list-style-type: none"><li>Indicates the direction to place the DR Detector in during exposure.</li><li>— When exposing in portrait, place the triangular mark upward.</li><li>— When exposing in landscape, place the triangular mark to the left or right.</li><li>— (Left and right are set during installation according to the exposure environment.)</li></ul>
(5)	Antenna	Displays the place where a wireless antenna is attached.
(6)	Back board	Protects the internal parts.
(7)	Battery LED	Toggles DR Detector status displays and the modes.
(8)	LINK LED	
(9)	Status LED	
(10)	Mode LED	
(11)	Information LED	Toggles DR Detector status displays and the modes.
(12)	Wired connection connector	
		Connects to the AeroDR Battery Charger2, and wired cable.

HINT

- AeroDR 3 1417HD, AeroDR 3 1717HD, AeroDR 3 1012HQ, AeroDR 3 1417HL, AeroDR 3 1417SL, AeroDR 3 1717HL, and AeroDR 3 1417S have the back board with a different design.




## 2.2.4 AeroDR Interface Unit




Number	Name	Functions
(1)	Top cover	Protects the internal parts.
(2)	Side cover	Protects the internal parts.
(3)	Power switch	Turns the AeroDR Interface Unit on/off.
(4)	Rear cover	Protects the internal parts.
(5)	Exhaust outlet	Exhausts internal heat.
(6)	Front cover	Protects the internal parts.
(7)	LEDs	Indicate the status of the AeroDR Interface Unit.
(8)	Cable outlet	Outlet for various cables.
(9)	Spacer	Prevents exhaust outlet from being blocked after installation.

2.2.5 AeroDR Interface Unit2



Number	Name	Functions
(1)	Exhaust outlet	Exhausts internal heat.
(2)	Top cover	Protects the internal parts.
(3)	Detector Connection LEDs	Indicate the status of the AeroDR Interface Unit2.
(4)	Power switch	Turns the AeroDR Interface Unit2 on/off.
(5)	Rear cover	Protects the internal parts.
(6)	Side cover	Protects the internal parts.
(7)	Spacer	<ul style="list-style-type: none"> <li>Prevents exhaust outlet from being blocked after installation.</li> <li>No spacers may be provided on some side covers that will not come in contact with walls.</li> </ul>
(8)	Front cover	Protects the internal parts.
(9)	Generator Interface LEDs	Indicate the status of the AeroDR Interface Unit2.
(10)	Cable outlet	Outlet for various cables.
(11)	Hand switch	When S-SRM connection is adopted, a hand switch is installed in the AeroDR Interface Unit2.


## 2.2.6 Detector Interface Unit



Number	Name	Functions
(1)	Base cover	Protects the internal parts.
(2)	LED	Indicates the status of the Detector Interface Unit.
(3)	Cable outlet	Outlet for I/F Cable.
(4)	LAN port	Connector port for the Ethernet cable.
(5)	Unit fixed plate	Used to attach this device to a wall stand or table, etc.
(6)	Power cable connector socket	Connector socket for the Power cable connector.
(7)	Location for connecting the grounding cable	Used to connect the grounding cable. Not usually used.
(8)	Power cable connector	Plug into the power cable socket of Detector Interface Unit.
(9)	Power cable	
(10)	AC adapter	



2.2.7 Detector Interface Unit 2



Number	Name	Functions
(1)	Top plate	Protects the internal parts.
(2)	LED	Indicates the status of the Detector Interface Unit 2.
(3)	Cable outlet	Outlet for I/F Cable.
(4)	Sync port	<ul style="list-style-type: none"><li>• Connects to the Ethernet cable.</li><li>• Relays signals for serial exposure.</li></ul>
(5)	LAN port	Connector port for the Ethernet cable.
(6)	Unit fixed plate	Used to attach this device to a wall stand or table, etc.
(7)	Location for connecting the grounding cable	Used to connect the grounding cable. Not usually used.