

Location Number: 1, Latitude 32-06-14.92 N Longitude 110-56-17.28 W

Use: Re-radiation system used 100% for testing installed antennas

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 2, Latitude 32-06-26.32 N Longitude 110-56-39.76 W

Use: Re-radiation system used 7% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 2, Latitude 32-06-26.32 N Longitude 110-56-39.76 W

Use: Re-radiation system used 7% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 4, Latitude 32-08-17.62 N Longitude 110-55-13.56 W

Use: Re-radiation system used 10% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 5, Latitude 32-07-38.55 N Longitude 110-56-06.84 W

Use: Re-radiation system used 10% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 6, Latitude 32-06-07.73 N Longitude 110-56-26.39 W

Use: Re-radiation system used 10% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 7, Latitude 32-06-11.13 N Longitude 110-56-23.01 W

Use: Re-radiation system used 1% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 8, Latitude 32-06-11.29 N Longitude 110-56-29.11 W

Use: Re-radiation system used 1% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 9, Latitude 32-06-07.43 N Longitude 110-56-29.28 W

Use: Re-radiation system used 1% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 10, Latitude 32-06-21.82 N Longitude 110-56-34.93 W

Use: Re-radiation system used 100% for testing installed antennas

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 11, Latitude 32-06-21.66 N Longitude 110-56-36.50 W

Use: Re-radiation system used 1% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 12, Latitude 32-06-13.85 N Longitude 110-56-22.24 W

Use: Re-radiation system used in anechoic chamber or under a hood for testing installed antennas

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 13, Latitude 32-06-09.71 N Longitude 110-56-19.49 W

Use: Re-radiation system used 5% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 14, Latitude 32-06-14.55 N Longitude 110-56-13.90 W

Use: Re-radiation system used 1% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 15, Latitude 32-06-23.06 N Longitude 110-56-45.30 W

Use: Re-radiation system used 40% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 16, Latitude 32-06-23.06 N Longitude 110-56-49.58 W

Use: Re-radiation system used 40% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 17, Latitude 32-06-20.07 N Longitude 110-56-52.00 W

Use: Re-radiation system used in anechoic chamber 100% for testing installed antennas

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 18, Latitude 32-06-20.06 N Longitude 110-56-52.18 W

Use: Re-radiation system used in anechoic chamber 100% for testing installed antennas

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 19, Latitude 32-06-20.07 N Longitude 110-56-52.46 W

Use: Re-radiation system used in anechoic chamber 100% for testing installed antennas

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 20, Latitude 32-06-19.91 N Longitude 110-56-55.23 W

Use: Re-radiation system used 25% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 21, Latitude 32-06-21.84 N Longitude 110-56-54.50 W

Use: Re-radiation system used 5% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 22, Latitude 32-06-21.13 N Longitude 110-56-57.40W

Use: Re-radiation system used 5% for testing installed antennas, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 23, Latitude 32-06-27.26 N Longitude 110-56-44.86W

Use: Re-radiation system used in anechoic chamber, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 24, Latitude 32-06-25.92 N Longitude 110-56-43.58W

Use: Re-radiation system used in anechoic chamber, hard-wired otherwise

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 25, Latitude 32-06-24.95 N Longitude 110-56-17.35W

Use: Re-radiation system used 100% of time.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 26, Latitude 32-06-26.67 N Longitude 110-56-18.86W

Use: Re-radiation system used 100% of time.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 27, Latitude 32-06-22.34 N Longitude 110-57-14.19W

Use: Re-radiation system used 10% of time; hard-wired otherwise.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 28, Latitude 32-06-22.36 N Longitude 110-57-19.22W

Use: Re-radiation system used in anechoic chamber; hard-wired otherwise.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 29, Latitude 32-06-25.21 N Longitude 110-57-18.18W

Use: Re-radiation system used in anechoic chamber; hard-wired otherwise.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 30, Latitude 32-06-15.92 N Longitude 110-57-12.26 W

Use: Re-radiation system used 10% for testing installed antennas; hard-wired otherwise.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 31, Latitude 32-05-38.47 N Longitude 110-56-03.79 W

Use: Re-radiation system used 100% for testing installed antennas.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 32, Latitude 32-05-40.08 N Longitude 110-55-36.72 W

Use: Re-radiation system used 100% for testing installed antennas.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 33, Latitude 32-07-39.63 N Longitude 110-56-07.19 W

Use: Re-radiation system used for testing installed antennas either hooded or hard-wired.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 34, Latitude 32-07-41.99 N Longitude 110-56-06.31 W

Use: Re-radiation system used for testing installed antennas either hooded or hard-wired.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 35, Latitude 32-05-46.35 N Longitude 110-56-47.39 W

Use: Re-radiation system used 10% for testing installed antennas; otherwise hard-wired.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 36, Latitude 32-05-46.29 N Longitude 110-57-06.67 W

Use: Re-radiation system used 10% for testing installed antennas; otherwise hard-wired.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 37, Latitude 32-05-30.02 N Longitude 110-56-47.16 W

Use: Re-radiation system used 10% for testing installed antennas; otherwise hard-wired.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 38, Latitude 32-06-29.46 N Longitude 110-56-46.35 W

Use: Re-radiation system used 30% for testing installed antennas; otherwise hard-wired.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 39, Latitude 32-08-12.77 N Longitude 110-55-13.90 W

Use: Re-radiation system used 20% for testing installed antennas; otherwise hard-wired.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 40, Latitude 32-08-23.01 N Longitude 110-54-57.81 W

Use: Re-radiation system used 20% for testing installed antennas; otherwise hard-wired.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 41, Latitude 32-05-40.21 N Longitude 110-48-28.90 W

Use: Re-radiation system used in anechoic chamber; otherwise hard-wired.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 42, Latitude 32-05-38.58 N Longitude 110-48-41.65 W

Use: Re-radiation system used in anechoic chamber; otherwise hard-wired.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 43, Latitude 32-05-38.99 N Longitude 110-48-40.00 W

Use: Re-radiation system used in anechoic chamber; otherwise hard-wired.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.78E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.75E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.38E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.12E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.000128
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.83E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.38E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.43E-08

Location Number: 44, Latitude 33-39-02.00 N Longitude 92-39-06.12 W

Use: Re-radiation system used 100% for testing installed antennas.

GPS Signal Analysis - L1 Link Budget

Frequency	1575.42	MHz	Signal Level		
Wavelength	0.19042541	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-36.38969194	dB	-131.1	7.8E-17	7.781E-05
Signal level at unit under test EIRP to ERP			-133.2	4.8E-17	4.754E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-66.06999119	dB	-160.8	8.4E-20	8.375E-08
Signal level at 100 ft ERP			-162.9	5.1E-20	5.117E-08

GPS Signal Analysis - L2 Link Budget

Frequency	1227.6	MHz	Signal Level		
Wavelength	0.244379277	meters	dBm	Watts	picoWatts
GPS Input Signal Level	-130	dBm	-130	1E-16	0.0001
GPS Receive Antenna amplifier gain	38	dB	-92	6.3E-13	0.63
GPS RF Amplifier gain	23	dB	-69	1.3E-10	125.89
GPS RF Attenuator	-22	dB	-91	7.9E-13	0.79
LMR400 Coax loss per foot	-0.067	dB			
Coax Length	100	feet			
Total Coax Loss	-6.7	dB	-97.7	1.7E-13	0.170
GPS Transmitting Antenna Gain	3	dB	-94.7	3.4E-13	0.339
Distance from transmit antenna	1	meters			
Distance from transmit antenna	3.2808399	feet			
Pathloss to unit under test	-34.22290244	dB	-128.9	1.3E-16	0.0001281
Signal level at unit under test EIRP to ERP			-131.1	7.8E-17	7.829E-05
Distance from transmit antenna	30.48	meters			
Distance from transmit antenna	100.0000002	feet			
Pathloss to 100 ft	-63.9032017	dB	-158.6	1.4E-19	1.379E-07
Signal level at 100 ft ERP			-160.7	8.4E-20	8.427E-08