

Exhibit - Radiation Hazard Analysis
Starling Advanced Communications, Ltd
StarCar3000

This analysis predicts the radiation levels around a proposed vehicle mounted earth station (VMES), comprised of one flat-panel type antenna. This report is developed in accordance with the prediction methods contained in OET Bulletin No. 65, Evaluating Compliance with FCC Guidelines for Human Exposure to Radio Frequency Electromagnetic Fields, Edition 97-01, pp 26-30. The maximum level of non-ionizing radiation to which employees may be exposed is limited to a power density level of 5 milliwatts per square centimeter (5 mW/cm^2) averaged over any 6 minute period in a controlled environment and the maximum level of non-ionizing radiation to which the general public is exposed is limited to a power density level of 1 milliwatt per square centimeter (1 mW/cm^2) averaged over any 30 minute period in a uncontrolled environment. Note that the worse-case radiation hazards exist along the beam axis. Under normal circumstances, it is highly unlikely that the antenna axis will be aligned with any occupied area since that would represent a blockage to the desired signals, thus rendering the link unusable.

Earth Station Technical Parameter Table

Antenna Diameter (azimuth)	0.88 meters x 0.18 meters
Antenna Surface Area	0.15840 sq. meters
Antenna Isotropic Gain	33.00 dBi
Number of Identical Adjacent Antennas	1
Nominal Antenna Efficiency (ϵ)	44.5%
Nominal Frequency	14.25 GHz
Nominal Wavelength (λ)	0.0211 meters
Maximum Transmit Power / Carrier	20.0 Watts
Number of Carriers	1
Total Transmit Power	20.0 Watts
W/G Loss from Transmitter to Feed	2.1 dB
Total Feed Input Power	12.5 Watts
Near Field Limit	$R_{nf} = D^2/4\lambda = 9.20$ meters
Far Field Limit	$R_{ff} = 0.6 D^2/\lambda = 22.07$ meters
Transition Region	R_{nf} to R_{ff}

In the following sections, the power density in the above regions, as well as other critically important areas will be calculated and evaluated. The calculations are done in the order discussed in OET Bulletin 65.

1.0 At the Antenna Surface

The power density at the panel surface can be calculated from the expression:

$$PD_{refl} = P/A = 7.872 \text{ mW/cm}^2 \quad (1)$$

Where: P = total power at feed, milliwatts

A = Total area of panel, sq. cm

In the normal range of transmit powers for satellite antennas, the power densities at or around the panel surface is expected to exceed safe levels. This area will not be accessible to the general public. Operators and technicians shall receive training specifying this area as a high exposure

area. Procedures have been established that will assure that all transmitters are rerouted or turned off before access by maintenance personnel to this area is possible.

2.0 On-Axis Near Field Region

The geometrical limits of the radiated power in the near field approximate a cylindrical volume with a diameter equal to that of the antenna. In the near field, the power density is neither uniform nor does its value vary uniformly with distance from the antenna. For the purpose of considering radiation hazard it is assumed that the on-axis flux density is at its maximum value throughout the length of this region. The length of this region, i.e., the distance from the antenna to the end of the near field, is computed as R_{nf} above.

The maximum power density in the near field is given by:

$$PD_{nf} = (16\eta P)/(\pi D^2) = \mathbf{3.645 \text{ mW/cm}^2} \quad (2)$$

from 0 to 9.20 meters

Evaluation

Uncontrolled Environment: **Does Not Meet Controlled Limits**

Controlled Environment: **Meets Uncontrolled Limits**

3.0 On-Axis Transition Region

The transition region is located between the near and far field regions. As stated in Bulletin 65, the power density begins to vary inversely with distance in the transition region. The maximum power density in the transition region will not exceed that calculated for the near field region, and the transition region begins at that value. The maximum value for a given distance within the transition region may be computed for the point of interest according to:

$$PD_t = (PD_{nf})(R_{nf})/R = \text{dependent on } R \quad (3)$$

where: PD_{nf} = near field power density

R_{nf} = near field distance

R = distance to point of interest

For: $9.20 < R < 22.1$ meters

We use Eq (3) to determine the safe on-axis distances required for the two occupancy conditions:

Evaluation

Uncontrolled Environment Safe Operating Distance,(meters), R_{safeu} : 33.5

Controlled Environment Safe Operating Distance,(meters), R_{safec} : 6.7

4.0 On-Axis Far-Field Region

The on- axis power density in the far field region (PD_{ff}) varies inversely with the square of the distance as follows:

$$PD_{ff} = PG/(4\pi R^2) = \text{dependent on } R \quad (4)$$

where: P = total power at feed

G = Numeric Antenna gain in the direction of interest relative to isotropic radiator

R = distance to the point of interest
 For: $R > R_{ff} = 22.1$ meters
 $PD_{ff} = \mathbf{0.407}$ mW/cm² at R_{ff}

We use Eq (4) to determine the safe on-axis distances required for the two occupancy conditions:

Evaluation

Uncontrolled Environment Safe Operating Distance,(meters), R_{safeu} : See Section 3
 Controlled Environment Safe Operating Distance,(meters), R_{safec} : See Section 3

5.0 Off-Axis Levels at the Far Field Limit and Beyond

In the far field region, the power is distributed in a pattern of maxima and minima (sidelobes) as a function of the off-axis angle between the antenna center line and the point of interest. Off-axis power density in the far field can be estimated using the antenna radiation patterns prescribed for the antenna in use. Usually this will correspond to the antenna gain pattern envelope defined by the FCC or the ITU, which takes the form of:

$$G_{off} = 32 - 25\log(\Theta)$$

for Θ from 1 to 48 degrees; -10 dBi from 48 to 180 degrees
 (Applicable for commonly used satellite transmit antennas)

Considering that satellite antenna beams are aimed skyward, power density in the far field will usually not be a problem except at low look angles. In these cases, the off axis gain reduction may be used to further reduce the power density levels.

For example: At one (1) degree off axis At the far-field limit, we can calculate the power density as:

$$G_{off} = 32 - 25\log(1) = 32 - 0 \text{ dBi} = 1585 \text{ numeric}$$

$$PD_{1 \text{ deg off-axis}} = PD_{ff} \times 1585/G = \mathbf{0.3229} \text{ mW/cm}^2 \text{ (5)}$$

6.0 Off-Axis power density in the Near Field and Transitional Regions

According to Bulletin 65, off-axis calculations in the near field may be performed as follows: assuming that the point of interest is at least one antenna diameter removed from the center of the main beam, the power density at that point is at least a factor of 100 (20 dB) less than the value calculated for the equivalent on-axis power density in the main beam. Therefore, for regions at least D meters away from the center line of the dish, whether behind, below, or in front under of the antenna's main beam, the power density exposure is at least 20 dB below the main beam level as follows:

$$PD_{nf(off-axis)} = PD_{nf} / 100 = \mathbf{0.03645} \text{ mW/cm}^2 \text{ at D off axis (6)}$$

See Section 7 for the calculation of the distance vs. elevation angle required to achieve this rule for a given object height.

7.0 Evaluation of Safe Occupancy Area in Front of Antenna

The distance (S) from a vertical axis passing through the dish center to a safe off axis location in front of the antenna can be determined based on the dish diameter rule (Item 6.0). Assuming a flat terrain in front of the antenna, the relationship is:

$$S = (D / \sin \alpha) + (2h - D - 2) / (2 \tan \alpha) \quad (7)$$

Where: α = minimum elevation angle of antenna

D = dish diameter in meters

h = maximum height of object to be cleared, meters

For distances equal or greater than determined by equation (7), the radiation hazard will be below safe levels.

For	D =	0.88 meters
	h =	2.0 meters
Then:		
	α	S
	10	2.6 meters
	15	1.8meters
	20	1.4 meters
	28	1.0 meters
	30	1.0 meters

8.0 Conclusions

The worse-case radiation hazards exist at the panel surface and along the main beam axis. In the case of the proposed experimental operations, it is highly unlikely that the antenna axis will be aligned with any uncontrolled area since experiments and demos will be carefully monitored and limited in time, the antenna will be mounted on a vehicle rooftop, and transmit operations will only be conducted with a clear field of view towards the serving satellite. In this case, the safety radius where the General Population/Uncontrolled Exposure limits are satisfied is 1.0 meters at a 28 degree elevation angle.

That said, commissioning and testing of the StarCar antenna will only be conducted by trained personnel in a controlled environment. By maintaining the necessary safety radius during transmit operations, it can be guaranteed that the General Population/Uncontrolled Exposure limits will not be exceeded under any test conditions.

The table below summarizes all of the above calculations.

Table - Summary of All RadHaz Parameters				StarCar3000
Parameter	Abbr.		Units	Formula
Dish #		Hub		
Antenna Diameter (major)	Df	0.88	meters	
Antenna Diameter (minor)		0.18	meters	
Antenna Centerline	h	2.0	meters	
Antenna Surface Area	Sa	0.15840	meters ²	$(\pi * Df^2) / 4$
Antenna Ground Elevation	GE	0.0	meters	
Frequency of Operation	f	14.25	GHz	
Wavelength	λ	0.0211	meters	c / f
HPA Output Power	P _{HPA}	20.0	watts	
HPA to Antenna Loss	L _{tx}	2.1	dB	
Transmit Power at Flange	P	11.0	dBW	$10 * \log(P_{HPA}) - L_{tx}$
		12.5	watts	
Antenna Gain	G _{es}	33.00	dBi	
		1996.3	n/a	
PI	π	3.1415927	n/a	
Antenna Aperture Efficiency	η	44.5%	n/a	$G_{es} / (\pi * Df / \lambda)^2$
1. Panel Surface Region Calculations				
Panel Surface Power Density	PD _{as}	78.72	W/m ²	P/A
		7.872	mW/cm ²	Does Not Meet Controlled Limits
				Does Not Meet Uncontrolled Limits
2. On-Axis Near Field Calculations				
Extent of Near Field	R _n	9.20	meters	$D^2 / (4 * \lambda)$
		30.16	feet	
Near Field Power Density	PD _{nf}	36.45	W/m ²	$(16 * \eta * P) / (\pi * D^2)$
		3.645	mW/cm ²	Does Not Meet Controlled Limits
				Meets Uncontrolled Limits
3. On-Axis Transition Region Calculations				
Extent of Transition Region (min)	R _{tr}	9.20	meters	$D^2 / (4 * \lambda)$
Extent of Transition Region (min)		30.16	feet	
Extent of Transition Region (max)	R _{tr}	22.07	meters	$(0.6 * D^2) / \lambda$
Extent of Transition Region (max)		72.39	feet	
Worst Case Transition Region Power Density	PD _{tr}	36.45	W/m ²	$(16 * \eta * P) / (\pi * D^2)$
		3.645	mW/cm ²	Does Not Meet Controlled Limits
				Meets Uncontrolled Limits
Uncontrolled Environment Safe Operating Distance	R _{su}	33.5	m	$=(PD_{nf} * (R_{nf}) / R_{su})$
Controlled Environment Safe Operating Distance	R _{sc}	6.7	m	$=(PD_{nf} * (R_{nf}) / R_{sc})$
4. On-Axis Far Field Calculations				
Distance to the Far Field Region	R _f	22.1	meters	$(0.6 * D^2) / \lambda$
		72.39	feet	
On-Axis Power Density in the Far Field	PD _{ff}	4.07	W/m ²	$(G_{es} * P) / (4 * \pi * R_f^2)$
		0.407	mW/cm ²	Meets Controlled Limits
				Meets Uncontrolled Limits
5. Off-Axis Levels at the Far Field Limit and Beyond				
Panel Surface Power Density	PD _s	3.229	W/m ²	$(G_{es} * P) / (4 * \pi * R_f^2) * (Goa / G_{es})$
Goa/Ges at example angle θ 1 degree		0.794		$Goa = 32 - 25 * \log(\theta)$
		0.3229	mW/cm ²	Meets Uncontrolled Limits
6. Off-axis Power Density in the Near Field and Transitional Regions Calculations				
Power density 1/100 of W _n for one diameter removed	PD _s	0.3645	W/m ²	$((16 * \eta * P) / (\pi * D^2)) / 100$
		0.03645	mW/cm ²	Meets Uncontrolled Limits
7. Off-Axis Safe Distances from Earth Station				
$S = (D / \sin \alpha) + (2h - D - 2) / (2 \tan \alpha)$				
α = minimum elevation angle of antenna		28	deg	
h = maximum height of object to be cleared, meters		2.0	m	
RD = Roof Elevation Delta antenna-obstacle		1.0	m	
elevation angle	10	2.6	m	
	15	1.8	m	
	20	1.4	m	
	28	1.0	m	
	30	1.0	m	
Note: Maximum FCC power density limits for 6 GHz is 1 mW/cm ² for general population/uncontrolled exposure as per FCC OE&T Bulletin No. 65, Edition 97-01 August 1997, Appendix A page 67.				

