

Shenzhen Most Technology Service Co., Ltd.

East A, 1 floor of New Aolin Factory building, Langshan Erlu, North District, Hi-tech Industry Park, Nanshan, Shenzhen, Guangdong, China

RF Exposure Evaluation Report

Compiled by

(position+printed name+signature)..: File administrators Alisa Luo

Supervised by

(position+printed name+signature)..: Test Engineer Sunny Deng

Approved by

(position+printed name+signature)..: Manager Yvette Zhou

Date of issue...... Nov. 07,2023

Representative Laboratory Name.: Shenzhen Most Technology Service Co., Ltd.

Nanshan, Shenzhen, Guangdong, China.

Applicant's name...... Zhejiang Haozhonghao Health Product Co., Ltd.

Pingyang, Wenzhou, Zhejiang, China

Test specification/ Standard: 47 CFR Part 1.1307;47 CFR Part 1.1310

KDB447498D01 General RF Exposure Guidance v06

TRF Originator...... Shenzhen Most Technology Service Co., Ltd.

Shenzhen Most Technology Service Co., Ltd. All rights reserved.

This publication may be reproduced in whole or in part for non-commercial purposes as long as the Shenzhen Most Technology Service Co., Ltd. is acknowledged as copyright owner and source of the material. Shenzhen Most Technology Service Co., Ltd. takes no responsibility for and will not assume liability for damages resulting from the reader's interpretation of the reproduced material due to its placement and context.

Test item description Massage Chair

Trade Mark N/A

Model/Type reference...... A665-6

Modulation Type GFSK

GFSK, π/4DQPSK

Operation Frequency...... From 2402MHz to 2480MHz

Hardware Version......V1.1

Software Version V1.0

Rating 110-120V~, 60Hz, 160W

Result..... PASS

Report No.: MTEB23110056-H Page 2 of 6

TEST REPORT

Equipment under Test : Massage Chair

Model /Type : A665-6

Listed Models : A860, SL-A665, SL-A661-2, SL-A663, SL-A667, SL-A665-6

Remark All models are identical to each other, except model names.

Applicant : Zhejiang Haozhonghao Health Product Co., Ltd.

Address No.18 Xinglong Road, Furniture Garden, Wanquan Industry Base,

Pingyang, Wenzhou, Zhejiang, China

Manufacturer : Zhejiang Haozhonghao Health Product Co., Ltd.

Address : No.18 Xinglong Road, Furniture Garden, Wanquan Industry Base,

Pingyang, Wenzhou, Zhejiang, China

Test Result:	PASS

The test report merely corresponds to the test sample.

It is not permitted to copy extracts of these test result without the written permission of the test laboratory.

Report No.: MTEB23110056-H Page 3 of 6

1. Revision History

Revision	Issue Date	Revisions	Revised By
00	2023.11.07	Initial Issue	Alisa Luo

Report No.: MTEB23110056-H Page 4 of 6

2. SAR Evaluation

2.1 RF Exposure Compliance Requirement

2.1.1 Standard Requirement

According to KDB447498D01 General RF Exposure Guidance v06

4.3.1. Standalone SAR test exclusion considerations

Unless specifically required by the published RF exposure KDB procedures, standalone 1-g head or body and 10-g extremity SAR evaluation for general population exposure conditions, by measurement or numerical simulation, is not required when the corresponding SAR Exclusion Threshold condition, listed below, is satisfied.

2.1.2 Limits

According to FCC Part1.1310: The criteria listed in the following table shall be used to evaluate the environment impact of human exposure to radio frequency (RF) radiation as specified in part1.1307(b)

TABLE 1—LIMITS FOR MAXIMUM PERMISSIBLE EXPOSURE (MPE)

Frequency range (MHz)	Electric field strength (V/m)	Magnetic field strength (A/m)	Power density (mW/cm²)	Averaging time (minutes)
(A) Lim	its for Occupational	/Controlled Exposure	es	
0.3–3.0 3.0–30 30–300 300–1500 1500–100,000	614 1842/ī 61.4	1.63 4.89/f 0.163	*(100) *(900/12) 1.0 f/300	6 6 6 6
***		on/Uncontrolled Exp	ASSESSES.	
0.3–1.34 1.34–30	614 824/f	1.63 2.19/f	*(100) *(180/f²)	30
30–300	27.5	0.073	0.2	30
300–1500 1500–100,000			f/1500 1.0	30 30

F= Frequency in MHz

Friis Formula

Friis transmission formula: Pd = (Pout*G)/(4* Pi * R 2) Where

Pd = power density in mW/cm2

Pout = output power to antenna in mW

G = gain of antenna in linear scale

Pi = 3.1416

R = distance between observation point and center of the radiator in cm

Pd id the limit of MPE, 1 mW/cm2. If we know the maximum gain of the antenna and the total power input to the antenna, through the calculation, we will know the distance r where the MPE limit is reached.

2.1.3 EUT RF Exposure

Antenna Gain: -1.39dBi

BLE

	GFSK					
Test channel Peak Output Power (dBm)		Tune up tolerance	Maximum tune-up Power			
	(dBm)	(dBm)				
Lowest(2402	4.235	4.235±1	5.235			
Middle(2440MHz)	5.195	5.195±1	6.195			
Highest(2480MHz)	4.678	4.678±1	5.678			

BLE

	Worst case: GFSK					
Channel	Maximum tune-up Power (dBm)	Maximum tune-up Power (MW)	Antenna Gain (dBi)	Power Density at R = 20 cm (mW/cm2)	Limit	Result
Middle(2440MHz)	6.195	4.16	-1.39	0.0006	1.0	Pass

Note: 1) Refer to report MTEB23110056-R for EUT test Max Conducted average Output Power value. Note: 2) Pd = $(Pout*G)/(4*Pi*R2)=(4.16*0.73)/(4*3.1416*20^2)=0.0006$

BT classic

GFSK					
Test channel P	Peak Output Power	Tune up tolerance	Maximum tune-up Power		
	(dBm)	(dBm)	(dBm)		
Lowest(2402MHz)	1.472	1.472±1	2.472		
Middle(2441MHz)	2.475	2.475 ± 1	3.475		
Highest(2480MHz)	1.954	1.954±1	2.954		

π /4DQPSK					
Test channel	Peak Output Power	Tune up tolerance	Maximum tune-up Power		
	(dBm)	(dBm)	(dBm)		
Lowest(2402MHz)	2.289	2.289 ± 1	3.289		
Middle(2441MHz)	1.326	1.326±1	2.326		
Highest(2480MHz)	2.708	2.708±1	3.708		

Worst case: π /4DQPSK						
Channel	Maximum tune-up Power (dBm)	Maximum tune-up Power (MW)	Antenna Gain (dBi)	Power Density at R = 20 cm (mW/cm2)	Limit	Result
Highest(2480MHz)	3.708	2.35	-1.39	0.00034	1.0	Pass

Note: 1) Refer to report MTEB23110056-R1 for EUT test Max Conducted average Output Power value.

Note: 2) Pd = (Pout*G)/(4* Pi * R2)=(2.35*0.73)/(4*3.1416*202)=0.00034 Note: 3)EUT's Bluetooth module is more than 20cm away from the human body.