



TEST REPORT

APPLICANT : You Tec Ltd
PRODUCT NAME : Smartphone
MODEL NAME : X3
BRAND NAME : STK
FCC ID : 2A2KI-STKX3
STANDARD(S) : FCC 47 CFR Part 2(2.1093)
IEEE 1528-2013
RECEIPT DATE : 2021-06-18
TEST DATE : 2021-07-03 to 2021-07-15
ISSUE DATE : 2021-08-09

Edited by : Liang Yumei
Liang Yumei (Rapporteur)
Approved by: Shen Junsheng
Shen Junsheng (Supervisor)

NOTE: This document is issued by Shenzhen Morlab Communications Technology Co., Ltd., the test report shall not be reproduced except in full without prior written permission of the company. The test results apply only to the particular sample(s) tested and to the specific tests carried out which is available on request for validation and information confirmed at our website.





IRECTORY

- 1. SAR Results Summary..... 5
- 2. Technical Information..... 7
 - 2.1. Applicant and Manufacturer Information..... 7
 - 2.2. Equipment under Test (EUT) Description..... 7
 - 2.3. Environment of Test Site/Conditions 10
- 3. Specific Absorption Rate (SAR)..... 11
 - 3.1. Introduction 11
 - 3.2. SAR Definition 11
- 4. RF Exposure Limits 12
 - 4.1. Uncontrolled Environment 12
 - 4.2. Controlled Environment..... 12
- 5. Applied Reference Documents 13
- 6. SAR Measurement System 14
 - 6.1. E-Field Probe 15
 - 6.2. Data Acquisition Electronics (DAE)..... 16
 - 6.3. Robot 16
 - 6.4. Measurement Server 17
 - 6.5. Light Beam Unit..... 17
 - 6.6. Phantom 18
 - 6.7. Device Holder 18
 - 6.8. Data Storage and Evaluation..... 19
 - 6.9. Test Equipment List..... 22
- 7. Tissue Simulating Liquids 24
- 8. SAR System Verification..... 26
- 9. EUT Testing Position..... 30
- 10. Measurement Procedures 34



10.1. Spatial Peak SAR Evaluation 35

10.2. Power Reference Measurement 35

10.3. Area Scan Procedures 35

10.4. Zoom Scan Procedures..... 36

10.5. SAR Averaged Methods 36

10.6. Power Drift Monitoring 36

11. SAR Test Procedure 37

11.1. General Scan Requirements..... 37

11.2. Test Procedure 38

11.3. Description of Interpolation/Extrapolation Scheme..... 38

11.4. Wireless Router..... 38

12. SAR Test Configuration 40

13. Conducted RF Output Power 52

14. Hot-Spot Mode Evaluation Procedure 52

15. Block Diagram of the Tests to be Performed..... 54

15.1. Head..... 54

15.2. Body..... 55

16. Test Results List 56

16.1. Test Guidance..... 56

16.2. Head SAR Data 58

16.3. Body SAR Data..... 65

16.4. Repeated SAR Assessment..... 73

16.5. Extremity SAR Assessment 74

17. Simultaneous Transmission Evaluation..... 75

17.1. Simultaneous Transmission Consideration..... 75

17.2. Simultaneous Transmission Analysis..... 76

18. Uncertainty Assessment..... 82

Annex A General Information..... 85



- Annex B Test Setup Photos**
- Annex C Plots of System Performance Check**
- Annex D Plots of Maximum SAR Test Results**
- Annex E Conducted Power**
- Annex F DASY Calibration Certificate**

Changed History		
Version	Date	Reason for Change
1.0	2021-08-09	First edition



1. SAR Results Summary

The maximum results of Specific Absorption Rate (SAR) found during test as bellows:

Frequency Band		Highest SAR Summary		
		Head (Separation 0mm)	Body-worn (Separation 10mm)	Hotspot (Separation 10mm)
		1g SAR (W/kg)		
GSM	GSM850	0.360	0.585	0.585
	GSM1900	0.104	0.452	0.452
WCDMA	WCDMA Band II	0.108	0.482	0.482
	WCDMA Band IV	0.152	0.924	0.924
	WCDMA Band V	0.199	0.336	0.336
LTE	LTE Band 5	0.304	0.367	0.367
	LTE Band 7	0.098	1.198	1.198
	LTE Band 12/17	0.213	0.384	0.384
	LTE Band 13	0.215	0.259	0.282
	LTE Band 14	0.204	0.239	0.239
	LTE Band 25/2	0.191	0.568	0.568
	LTE Band 26	0.257	0.329	0.329
	LTE Band 30	0.051	1.068	1.068
	LTE Band 40A	0.105	0.569	0.569
	LTE Band 40B	0.091	0.537	0.537
	LTE Band 41	0.421	0.547	0.547
	LTE Band 66/4	0.232	0.952	0.952
	LTE Band 71	0.143	0.543	0.543
WLAN	2.4GHz WLAN	1.024	0.205	0.255
	5GHz WLAN	1.031	0.310	0.393
2.4GHz Band	Bluetooth	N/A	0.055	0.055

Max Scaled SAR _{1g} (W/Kg):	Head:	1.031 W/kg	Limit(W/kg): 1.6 W/kg
	Body-worn:	1.198 W/kg	
	Hotspot:	1.198 W/kg	

Highest Simultaneous Transmission SAR _{1g} (W/Kg):	1.508 W/kg	Limit(W/kg): 1.6 W/kg
---	------------	-----------------------

Note:

1. This device is in compliance with Specific Absorption Rate (SAR) for general population or uncontrolled exposure limits (1.6W/kg as averaged over any 1 gram of tissue; specified in FCC



47 CFR part 2 (2.1093) and ANSI/IEEE C95.1-1992), and had been tested in accordance with the measurement methods and procedures specified in IEEE 1528-2013 and FCC KDB publications.

2. For FDD-LTE Band 2/4/17 is full covered by FDD-LTE Band 25/66/12, therefore only FDD-LTE Band 25/66/12 was tested.
3. When the test result is a critical value, we will use the measurement uncertainty give the judgment result based on the 95% risk level.



2. Technical Information

Note: Provide by applicant.

2.1. Applicant and Manufacturer Information

Applicant:	You Tec Ltd
Applicant Address:	Santok House Unit L, Braintree Industrial Estate, Braintree Road, South Ruislip, Middlesex, United Kingdom, HA4 0EJ
Manufacturer:	You Tec Ltd
Manufacturer Address:	Santok House Unit L, Braintree Industrial Estate, Braintree Road, South Ruislip, Middlesex, United Kingdom, HA4 0EJ

2.2. Equipment under Test (EUT) Description

Product Name:	Smartphone
IMEI:	353766700000358 / 78 3537667000003311 / 78
Hardware Version:	STKX3XW1
Software Version:	SW2_V1.6_HW1_V.1_DSVLTEEU_SIG_240721
Frequency Bands:	GSM 850: 824 MHz ~ 849 MHz GSM 1900: 1850 MHz ~ 1910 MHz WCDMA Band II: 1850 MHz ~ 1910 MHz WCDMA Band IV: 1710 MHz ~ 1755 MHz WCDMA Band V: 824 MHz ~ 849 MHz LTE Band 2: 1850 MHz ~ 1910 MHz LTE Band 4: 1710 MHz ~ 1755 MHz LTE Band 5: 824 MHz ~ 849 MHz LTE Band 7: 2500 MHz ~ 2570 MHz LTE Band 12: 699 MHz ~ 716 MHz LTE Band 13: 777 MHz ~ 787 MHz LTE Band 14: 788 MHz ~ 798 MHz LTE Band 17: 704 MHz ~ 716 MHz LTE Band 25: 1850 MHz ~ 1915 MHz LTE Band 26: 814 MHz ~ 849 MHz LTE Band 30: 2305 MHz ~ 2315 MHz LTE Band 40A: 2305 MHz ~ 2315 MHz LTE Band 40B: 2350 MHz ~ 2360 MHz LTE Band 41: 2535 MHz ~ 2655 MHz



	LTE Band 66: 1710 MHz ~ 1780 MHz LTE Band 71: 663 MHz ~ 698 MHz WLAN 2.4GHz: 2412 MHz ~ 2462 MHz WLAN 5.2GHz: 5180 MHz ~ 5240 MHz WLAN 5.3GHz: 5260 MHz ~ 5320 MHz WLAN 5.8GHz: 5745 MHz ~ 5825 MHz Bluetooth: 2402 MHz ~ 2480 MHz	
Modulation Mode:	GSM/GPRS: GMSK EDGE: 8PSK WCDMA: QPSK, 16QAM LTE: QPSK, 16QAM 802.11b: DSSS 802.11g/n-HT20/40: OFDM 802.11a/ac-VHT20/40/80: OFDM Bluetooth: GFSK(1Mbps), $\pi/4$ -DQPSK(2Mbps), 8-DPSK(3Mbps)	
Multi-slot Class:	GPRS: Multi-slot Class 12; EDGE: Multi-slot Class 12;	
Operation Class:	Class B	
Hotspot Mode:	WWAN/WLAN 2.4GHz/WLAN 5.2GHz/WLAN 5.8GHz	
Antenna Type:	WWAN: Fixed Internal WLAN: IFA Antenna Bluetooth: IFA Antenna	
SIM Cards Description:	SIM 1	GSM+WCDMA+LTE
	SIM 2	GSM+WCDMA+LTE
	For dual SIM card version, both SIM 1 and SIM 2 share the same chipset unit and tested as a single chipset, the SIM 1 was selected for testing.	

Note:

- The model name: X3 (FCC ID: 2A2KI-STKX3), there are 2 models of CPU, only the model suffix is different; Memory (EMMC+LPDDR4X) and camera have 2 Suppliers. It's just that the supplier is different. details as follows:

Part Name		Supplier (Main Supply)	Supplier (Secondary Supply)
CPU		MediaTek.Inc (Model: MT6762V/CB)	MediaTek.Inc (Model: MT6762V/WA)
Memory	EMMC	Hosin Global Electronics Co.,Ltd.	Shenzhen Longsys Electronics Co., Ltd.
	LPDDR4X	Rayson Hi-Tech (HK) Limited	Shenzhen Longsys Electronics Co., Ltd.
Camera		Chongqing Ts-Precision	Shen zhen Holitechopto-Electronics



	Technology Co., Ltd.	Co.,Ltd.
--	----------------------	----------

Except for the above differences, their electrical circuit design, layout, components used and internal wiring are identical

2. For a more detailed description, please refer to specification or user manual supplied by the applicant and/or manufacturer.



2.3. Environment of Test Site/Conditions

Normal Temperature (NT):	20-25 °C
Relative Humidity:	30-75 %
Air Pressure:	980-1020 hPa

Test Frequency:	GSM 850MHz/1900MHz WCDMA Band II/IV/V FDD-LTE Band 2/4/5/7/12/13/14/17/25/26/30/66/71 TDD-LTE Band 40A/40B/41 WLAN 2.4GHz WLAN 5GHz Bluetooth
Operation Mode:	Call established
Power Level:	GSM 850 MHz Maximum output power(level 5) GSM 1900MHz Maximum output power(level 0) WCDMA Band II/IV/V (All Up Bits) FDD-LTE Band 2/4/5/7/12/13/14/17/25/26/30/66/71 (Maximum output power) TDD-LTE Band 40A/40B/41 (Maximum output power) WLAN 2.4GHz WLAN 5GHz Bluetooth

During SAR test, EUT is in Traffic Mode (Channel Allocated) at Normal Voltage Condition. A communication link is set up with a System Simulator (SS) by air link, and a call is established.

The EUT shall use its internal transmitter. The antenna(s), battery and accessories shall be those specified by the Factory. The EUT battery must be fully charged and checked periodically during the test to ascertain uniform power output. If a wireless link is used, the antenna connected to the output of the base station simulator shall be placed at least 50 cm away from the handset. The signal transmitted by the simulator to the antenna feeding point shall be lower than the output power level of the handset by at least 35 dB.

3. Specific Absorption Rate (SAR)

3.1. Introduction

SAR is related to the rate at which energy is absorbed per unit mass in an object exposed to a radio field. The SAR distribution in a biological body is complicated and is usually carried out by experimental techniques or numerical modeling. The standard recommends limits for two tiers of groups, occupational or controlled and general population or uncontrolled, based on a person's awareness and ability to exercise control over his or her exposure. In general, occupational or controlled exposure limits are Middle than the limits for general population or uncontrolled.

3.2. SAR Definition

The SAR definition is the time derivative (rate) of the incremental energy (dW) absorbed by(dissipated in) an incremental mass (dm) contained in a volume element (dv) of a given density. (ρ). The equation description is as below:

$$\text{SAR} = \frac{d}{dt} \left(\frac{dW}{dm} \right) = \frac{d}{dt} \left(\frac{dW}{\rho dv} \right)$$

SAR is expressed in units of Watts per kilogram (W/kg).

SAR measurement can be either related to the temperature elevation in tissue by,

$$\text{SAR} = C \left(\frac{\delta T}{\delta t} \right)$$

Where C is the specific head capacity, δT is the temperature rise and δt the exposure duration, or related to the electrical field in the tissue by

$$\text{SAR} = \frac{\sigma |E|^2}{\rho}$$

Where σ is the conductivity of the tissue, ρ is the mass density of the tissue and $|E|$ is the rmselectrical field strength.

However for evaluating SAR of low power transmitter, electrical field measurement is typically applied.



4. RF Exposure Limits

4.1. Uncontrolled Environment

Uncontrolled Environments are defined as locations where there is the exposure of individuals who have no knowledge or control of their exposure. The general population/uncontrolled exposure limits are applicable to situations in which the general public may be exposed or in which persons who are exposed as a consequence of their employment may not be made fully aware of the potential for exposure or cannot exercise control over their exposure. Members of the general public would come under this category when exposure is not employment-related; for example, in the case of a wireless transmitter that exposes persons in its vicinity.

4.2. Controlled Environment

Controlled Environments are defined as locations where there is exposure that may be incurred by persons who are aware of the potential for exposure, (i.e. as a result of employment or occupation). In general, occupational/controlled exposure limits are applicable to situations in which persons are exposed as a consequence of their employment, who have been made fully aware of the potential for exposure and can exercise control over their exposure. The exposure category is also applicable when the exposure is of a transient nature due to incidental passage through a location where the exposure levels may be higher than the general population/uncontrolled limits, but the exposed person is fully aware of the potential for exposure and can exercise control over his or her exposure by leaving the area or by some other appropriate means.

Limits for General Population/Uncontrolled Exposure (W/kg)

Type Exposure	Uncontrolled Environment Limit
Spatial Peak SAR (1g cube tissue for head and trunk)	1.6 W/kg
Spatial Peak SAR (10g cube tissue for limbs)	4.0 W/kg
Spatial Peak SAR (1g cube tissue for whole body)	0.08 W/kg

Note:

- Occupational/Uncontrolled Environments are defined as locations where there is exposure that may be incurred by people who are aware of the potential for exposure (i.e. as a result of employment or occupation).
- Whole-Body SAR is averaged over the entire body, partial-body SAR is averaged over any 1gram of tissue defined as a tissue volume in the shape of a cube. SAR for hands, wrists, feet and ankles is averaged over any 10 grams of tissue defined as a tissue volume in the shape of a cube.

5. Applied Reference Documents

Leading reference documents for testing:

Identity	Document Title	Method Determination /Remark
FCC 47CFR Part 2(2.1093)	Radio Frequency Radiation Exposure Evaluation: Portable Devices	No deviation
IEEE 1528-2013	IEEE Recommended Practice for Determining the Peak Spatial-Average Specific Absorption Rate (SAR) in the Human Head from Wireless Communications Devices: Measurement Techniques	No deviation
KDB 447498 D01v06	General RF Exposure Guidance	No deviation
KDB 248227 D01v02r02	SAR Measurement Procedures for 802.11 Transmitters	No deviation
KDB 865664 D01v01r04	SAR Measurement 100 MHz to 6 GHz	No deviation
KDB 865664 D02v01r02	RF Exposure Reporting	No deviation
KDB 648474 D04v01r03	Handset SAR	No deviation
KDB 941225 D01v03r01	3G SAR MEAUREMENT PROCEDURES	No deviation
KDB 941225 D05v02r05	SAR Evaluation Consideration for LTE Devices	No deviation
KDB 941225 D06v02r01	SAR Evaluation Procedures For Portable Devices With Wireless Router Capabilities	No deviation
<p>Note 1: The test item is not applicable.</p> <p>Note 2: Additions to, deviation, or exclusions from the method shall be judged in the "method determination" column of add, deviate or exclude from the specific method shall be explained in the "Remark" of the above table.</p>		

6. SAR Measurement System




Fig 6.1 SPEAG DASY System Configurations

The DASY system for performance compliance tests is illustrated above graphically. This system consists of the following items:

- A standard high precision 6-axis robot with controller, a teach pendant and software.
- A data acquisition electronic (DAE) attached to the robot arm extension.
- A dosimetric probe equipped with an optical surface detector system.
- The electro-optical converter (ECO) performs the conversion between optical and electrical signals
- A measurement server performs the time critical tasks such as signal filtering, control of the robot operation and fast movement interrupts.
- A probe alignment unit which improves the accuracy of the probe positioning.
- A computer operating Windows XP.
- DASY software.
- Remote control with teach pendant and additional circuitry for robot safety such as warning lamps, etc.
- The SAM twin phantom.
- A device holder.
- Tissue simulating liquid.
- Dipole for evaluating the proper functioning of the system.
- Some of the components are described in details in the following sub-sections.

6.1. E-Field Probe

The SAR measurement is conducted with the dosimetric probe (manufactured by SPEAG). The probe is specially designed and calibrated for use in liquid with high permittivity. The dosimetric probe has special calibration in liquid at different frequency. This probe has a built in optical surface detection system to prevent from collision with phantom.

E-Field Probe Specification

<ES3DV3 Probe>


Construction	Symmetrical design with triangular core Built-in optical fiber for surface detection system. Built-in shielding against static charges. PEEK enclosure material (resistant to organic solvents, e.g., DGBE)	
Frequency	10 MHz to 3 GHz; Linearity: ± 0.2 dB	
Directivity	± 0.2 dB in HSL (rotation around probe axis) ± 0.4 dB in HSL (rotation normal to probe axis)	
Dynamic Range	5 μ W/g to 100 mW/g; Linearity: ± 0.2 dB	
Dimensions	Overall length: 330 mm (Tip: 16 mm) Tip diameter: 6.8 mm (Body: 12 mm) Distance from probe tip to dipole centers: 2.7 mm	

Fig 6.2 Photo of ES3DV3

<EX3DV4 Probe>


Construction	Symmetrical design with triangular core Built-in shielding against static charges PEEK enclosure material (resistant to organic solvents, e.g., DGBE)	
Frequency	10 MHz to 6 GHz; Linearity: ± 0.2 dB	
Directivity	± 0.3 dB in HSL (rotation around probe axis) ± 0.5 dB in tissue material (rotation normal to probe axis)	
Dynamic Range	10 μ W/g to 100 mW/g; Linearity: ± 0.2 dB	
Dimensions	Overall length: 330 mm (Tip: 20 mm) Tip diameter: 2.5 mm (Body: 12 mm) Typical distance from probe tip to dipole centers: 1 mm	

Fig 6.3 Photo of EX3DV4

E-Field Probe Calibration

Each probe needs to be calibrated according to a dosimetric assessment procedure with accuracy better than $\pm 10\%$. The spherical isotropy shall be evaluated and within ± 0.25 dB. The sensitivity parameters (NormX, NormY, and NormZ), the diode compression parameter (DCP) and the conversion factor (ConvF) of the probe are tested. The calibration data can be referred to appendix C of this report.

6.2. Data Acquisition Electronics (DAE)

The data acquisition electronics(DAE) consists of a highly sensitive electrometer-grade preamplifier with auto-zeroing, a channel and gain-switching multiplexer, a fast16 bit AD-converter and a command decoder and control logic unit. AD-converter and a command decoder and control logic unit. Transmission to the measurement server is accomplished through an optical downlink for data and status information as well as an optical uplink for commands and the clock. The input impedance of the DAE is 200M Ω ; the inputs are symmetrical and floating. Common mode rejection is above 80 dB.



Fig 6.4 Photo of DAE

6.3. Robot

The SPEAG DASY system uses the high precision robots (DASY4: RX90BL; DASY5: TX90XL) type from Stäubli SA (France). For the 6-axis controller system, the robot controller version (DASY4: CS7MB; DASY5: CS8c) from Stäubli is used. The Stäubli robot series have many features that are important for our application:

High precision (repeatability ± 0.035 mm)

High reliability (industrial design)

Jerk-free straight movements

Low ELF interference (the closed metallic construction shields against motor control fields)



Fig 6.5 Photo of DASY5

6.4. Measurement Server

The measurement server is based on a PC/104 CPU board with CPU (DASY4: 166 MHz, Intel Pentium; DASY5: 400 MHz, Intel Celeron), chip disk (DASY4: 32 MB; DASY5: 128 MB), RAM (DASY4: 64 MB, DASY5: 128 MB). The necessary circuits for communication with the DAE electronic box, as well as the 16 bit AD converter system for optical detection and digital I/O interface are contained on the DASY I/O board, which is directly connected to the PC/104 bus of the CPU board.

The measurement server performs all the real-time data evaluation for field measurements and surface detection, controls robot movements and handles safety operations.



Fig 6.6 Photo of Server for DASY5

6.5. Light Beam Unit

The light beam switch allows automatic "tooling" of the probe. During the process, the actual position of the probe tip with respect to the robot arm is measured, as well as the probe length and the horizontal probe offset. The software then corrects all movements, such that the robot coordinates are valid for the probe tip.

The repeatability of this process is better than 0.1 mm. If a position has been taught with an aligned probe, the same position will be reached with another aligned probe within 0.1 mm, even if the other probe has different dimensions. During probe rotations, the probe tip will keep its actual position.



Fig. 6.7 Photo of Light Beam

6.6. Phantom

<SAM Twin Phantom>


Shell Thickness	2 ± 0.2 mm (sagging: <1%) Center ear point: 6 ± 0.2 mm	
Filling Volume	Approx. 25 liters	
Dimensions	Length: 1000 mm; Width: 500 mm; Height: adjustable feet	
Measurement Areas	Left Head, Right Head, Flat Phantom	

Fig. 6.8 Photo of SAM Phantom

The bottom plate contains three pair of bolts for locking the device holder. The device holder positions are adjusted to the standard measurement positions in the three sections. A white cover is provided to tap the phantom during off-periods to prevent water evaporation and changes in the liquid parameters. On the phantom top, three reference markers are provided to identify the phantom position with respect to the robot.

6.7. Device Holder

<Device Holder for SAM Twin Phantom>

The SAR in the phantom is approximately inversely proportional to the square of the distance between the source and the liquid surface. For a source at 5 mm distance, a positioning uncertainty of ± 0.5 mm would produce a SAR uncertainty of ± 20 %. Accurate device positioning is therefore crucial for accurate and repeatable measurements. The positions in which the devices must be measured are defined by the standards.

The DASY device holder is designed to cope with different positions given in the standard. It has two scales for the device rotation (with respect to the body axis) and the device inclination (with respect to the line between the ear reference points). The rotation center for both scales is the ear reference point (EPR). Thus the device needs no repositioning when changing the angles.

The DASY device holder is constructed of low-loss POM material having the following dielectric parameters: relative permittivity $\epsilon = 3$ and loss tangent $\delta = 0.02$. The amount of dielectric material has been reduced in the closest vicinity of the device, since measurements have suggested that the influence of the clamp on the test results could thus be lowered.

<Laptop Extension Kit>

The extension is lightweight and made of POM, acrylic glass and foam. It fits easily on the upper part of the mounting device in place of the phone positioned. The extension is fully compatible with the SAM Twin and ELI phantoms.



Fig 6.9 Device Holder




Fig 6.10 Laptop Extension Kit

6.8. Data Storage and Evaluation

➤ Data Storage

The DASY software stores the assessed data from the data acquisition electronics as raw data (in microvolt readings from the probe sensors), together with all the necessary software parameters for the data evaluation (probe calibration data, liquid parameters and device frequency and modulation data) in measurement files. The post-processing software evaluates the desired unit and format for output each time the data is visualized or exported. This allows verification of the complete software setup even after the measurement and allows correction of erroneous parameter settings. For example, if a measurement has been performed with an incorrect crest factor parameter in the device setup, the parameter can be corrected afterwards and the data can be reevaluated.

The measured data can be visualized or exported in different units or formats, depending on the selected probe type (e.g., [V/m], [A/m], [mW/g]). Some of these units are not available in certain situations or give meaningless results, e.g., a SAR-output in a non-lose media, will always be zero. Raw data can also be exported to perform the evaluation with other software packages.

➤ Data Evaluation

The DASY post-processing software (SEMCAD) automatically executes the following procedures to calculate the field units from the microvolt readings at the probe connector. The parameters used in the evaluation are stored in the configuration modules of the software.



Probe parameters:	- Sensitivity	Norm _i , a _{i0} , a _{i1} , a _{i2}
	- Conversion factor	ConvF _i
	- Diode compression point	dcpi
Device parameters:	- Frequency	f
	- Crest factor	cf
Media parameters:	- Conductivity	σ
	- Density	ρ

These parameters must be set correctly in the software. They can be found in the component documents or they can be imported into the software from the configuration files issued for the DASY components. In the direct measuring mode of the multi-meter option, the parameters of the actual system setup are used. In the scan visualization and export modes, the parameters stored in the corresponding document files are used.

The first step of the evaluation is a linearization of the filtered input signal to account for the compression characteristics of the detector diode. The compensation depends on the input signal, the diode type and the DC-transmission factor from the diode to the evaluation electronics. If the exciting field is pulsed, the crest factor of the signal must be known to correctly compensate for peak power.

The formula for each channel can be given as:

$$V_i = U_i + U_i^2 \times \frac{cf}{dcp_i}$$

With V_i = compensated signal of channel i , ($i = x, y, z$)
 U_i = input signal of channel i , ($i = x, y, z$)
 cf = crest factor of exciting field (DASY parameter)
 dcp_i = diode compression point (DASY parameter)

From the compensated input signals, the primary field data for each channel can be evaluated:

$$\text{E-field Probes: } E_i = \sqrt{\frac{V_i}{\text{Norm}_i \times \text{ConvF}}}$$

$$\text{H-field Probes: } H_i = \sqrt{V_i} \times \frac{a_{i0} + a_{i1} + a_{i2} f^2}{f}$$

With V_i = compensated signal of channel i , ($i = x, y, z$)
 Norm_i = sensor sensitivity of channel i , ($i = x, y, z$), $\mu\text{V}/(\text{V}/\text{m})^2$ for E-field Probes
 ConvF = sensitivity enhancement in solution
 a_{ij} = sensor sensitivity factors for H-field probes
 f = carrier frequency [GHz]



E_i = electric field strength of channel i in V/m

H_i = magnetic field strength of channel i in A/m

The RSS value of the field components gives the total field strength (Hermitian magnitude):

$$E_{\text{tot}} = \sqrt{E_x^2 + E_y^2 + E_z^2}$$

The primary field data are used to calculate the derived field units.

$$\text{SAR} = E_{\text{tot}}^2 \times \frac{\sigma}{\rho \times 1000}$$

with SAR = local specific absorption rate in mW/g

E_{tot} = total field strength in V/m

σ = conductivity in [mho/m] or [Siemens/m]

ρ = equivalent tissue density in g/cm^3

Note that the density is set to 1, to account for actual head tissue density rather than the density of the tissue simulating liquid.



6.9. Test Equipment List

Manufacturer	Name of Equipment	Type/Model	Serial Number	Calibration	
				Last Cal.	Due Date
SPEAG	750MHz System Validation Kit	D750V2	1173	2021.06.21	2024.06.20
SPEAG	900MHz System Validation Kit	D900V2	1d064	2018.10.29	2021.10.28
SPEAG	1800MHz System Validation Kit	D1800V2	2d158	2018.10.31	2021.10.30
SPEAG	2000MHz System Validation Kit	D2000V2	1050	2018.10.31	2021.10.30
SPEAG	2300MHz System Validation Kit	D2300V2	1107	2020.06.03	2023.06.02
SPEAG	2450MHz System Validation Kit	D2450V2	805	2018.10.26	2021.10.25
SPEAG	2600MHz System Validation Kit	D2600V2	1139	2021.06.25	2024.06.24
SPEAG	5000MHz System Validation Kit	D5GHzV2	1176	2018.11.06	2021.11.05
SPEAG	DOSIMETRIC ASSESSMENT SYSTEM	DASY52	52.10.4.1527	NCR	NCR
SPEAG	Dosimetric E-Field Probe	EX3DV4	7608	2020.11.27	2021.11.26
SPEAG	Data Acquisition Electronics	DAE4	1643	2020.11.30	2021.11.29
SPEAG	Dielectric Assessment KIT	DAK-3.5	1279	2020.10.20	2021.10.19
SPEAG	Twin-SAM	QD 000 P41 Ax	2020	NCR	NCR
SPEAG	Phone Positioner	N/A	N/A	NCR	NCR
R&S	Network Emulator	CMW500	165755	2021.02.25	2022.02.24
Agilent	Network Analyzer	E5071B	MY42404762	2021.03.29	2022.03.28
mini-circuits	Amplifier	ZHL-42W+	608501717	NCR	NCR
mini-circuits	Amplifier	ZVE-8G+	754401735	NCR	NCR
Agilent	Signal Generator	N5182B	MY53050509	2021.03.25	2022.03.24
Agilent	Power Sensor	N8482A	MY41090849	2020.10.19	2021.10.18
Agilent	Power Meter	E4416A	MY45102093	2020.10.19	2021.10.18
Anritsu	Power Sensor	MA2411B	N/A	2020.10.19	2021.10.18
Anritsu	Power Meter	NRVD	101066	2020.10.19	2021.10.18
Agilent	Dual Directional Coupler	778D	50422	NA	NA
MCL	Attenuation1	351-218-010	N/A	NA	NA
KTJ	Thermo meter	TA298	N/A	2021.01.15	2022.01.14
N/A	Tissue Simulating Liquids	700-6000MHz	N/A	24H	

Note:

1. The calibration certificate of DASY can be referred to appendix F of this report.
2. The Insertion Loss calibration of Dual Directional Coupler and Attenuator were characterized via the network analyzer and compensated during system check.



3. The dielectric probe kit was calibrated via the network analyzer, with the specified procedure (calibrated in pure water) and calibration kit (standard) short circuit, before the dielectric measurement. The specific procedure and calibration kit are provided by Speag.
4. In system check we need to monitor the level on the power meter, and adjust the power amplifier level to have precise power level to the dipole; the measured SAR will be normalized to 1W input power according to the ratio of 1W to the input power to the dipole. For system check, the calibration of the power amplifier is deemed not critically required for correct measurement; the power meter is critical and we do have calibration for it.
5. Attenuator insertion loss is calibrated by the network Analyzer, which the calibration is valid, before system check.
6. N.C.R means No Calibration Requirement.

7. Tissue Simulating Liquids

For SAR measurement of the field distribution inside the phantom, the phantom must be filled with homogeneous tissue simulating liquid to a depth of at least 15cm. For head SAR testing, the liquid height from the ear reference point (ERP) of the phantom to the liquid top surface is larger than 15cm. For body SAR testing, the liquid height from the center of the flat phantom to the liquid top surface is larger than 15cm, which is shown in Fig. 7.1. For body SAR testing, the liquid height from the center of the flat phantom to the liquid top surface is larger than 15 cm, which is shown in Fig. 7.2. The nominal dielectric values of the tissue simulating liquids in the phantom and the tolerance of 5% are listed in below table.




Fig 7.1 Photo of Liquid Height for Head SAR



Fig 7.2 Photo of Liquid Height for Body SAR

The following table gives the recipes for tissue simulating liquids.

Frequency (MHz)	Water (%)	Sugar (%)	Cellulose (%)	Salt (%)	Preventol (%)	DGBE (%)	Conductivity (σ)	Permittivity (ϵ_r)
Head								
750	41.1	57.0	0.2	1.4	0.2	0	0.89	41.9
835	40.3	57.9	0.2	1.4	0.2	0	0.90	41.5
1800,1900,2000	55.2	0	0	0.3	0	44.5	1.40	40.0
2450	55.0	0	0	0	0	45.0	1.80	39.2
2600	54.8	0	0	0.1	0	45.1	1.96	39.0
Body								
750	51.7	47.2	0	0.9	0.1	0	0.96	55.5
835	50.8	48.2	0	0.9	0.1	0	0.97	55.2
1800, 1900, 2000	70.2	0	0	0.4	0	29.4	1.52	53.3
2450	68.6	0	0	0	0	31.4	1.95	52.7
2600	68.1	0	0	0.1	0	31.8	2.16	52.5

Simulating Liquid for 5GHz, Manufactured by SPEAG.

Ingredients	(% by weight)
Water	64~78%
Mineral oil	11~18%
Emulsifiers	9~15%



Additives and Salt	2~3%
--------------------	------

Note: Please refer to the validation results for dielectric parameters of each frequency band. The dielectric properties of the tissue simulating liquids were verified prior to the SAR evaluation using a SPEAG Dielectric Assessment KIT and an Agilent Network Analyzer.

Table 1: Dielectric Performance of Tissue Simulating Liquid

Frequency (MHz)	Tissue Type	Liquid Temp.(°C)	Conductivity (σ)	Conductivity Target (σ)	Delta (σ)(%)	Limit (%)	Date
750	HSL	22.1	0.906	0.89	1.80	±5	2021.07.03
900	HSL	22.1	0.945	0.97	-2.58	±5	2021.07.05
1800	HSL	22.3	1.381	1.40	-1.36	±5	2021.07.12
2000	HSL	22.3	1.422	1.40	1.57	±5	2021.07.09
2300	HSL	22.2	1.685	1.67	0.90	±5	2021.07.15
2450	HSL	22.1	1.826	1.80	1.44	±5	2021.07.12
2600	HSL	22.1	2.015	1.96	2.81	±5	2021.07.07
5250	HSL	22.2	4.822	4.71	2.38	±5	2021.07.14
5750	HSL	22.3	5.222	5.22	0.04	±5	2021.07.13

Frequency (MHz)	Tissue Type	Liquid Temp.(°C)	Permittivity (ϵ_r)	Permittivity Target (ϵ_r)	Delta (ϵ_r)(%)	Limit (%)	Date
750	HSL	22.1	41.793	41.90	-0.26	±5	2021.07.03
900	HSL	22.1	41.622	41.50	0.29	±5	2021.07.05
1800	HSL	22.3	40.159	40.00	0.40	±5	2021.07.12
2000	HSL	22.3	40.088	40.00	0.22	±5	2021.07.09
2300	HSL	22.2	39.726	39.50	0.57	±5	2021.07.15
2450	HSL	22.1	39.334	39.20	0.34	±5	2021.07.12
2600	HSL	22.1	39.157	39.00	0.40	±5	2021.07.07
5250	HSL	22.2	36.233	35.95	0.79	±5	2021.07.14
5750	HSL	22.3	35.449	35.35	0.28	±5	2021.07.13



8. SAR System Verification

Each DASY system is equipped with one or more system validation kits. These units, together with the predefined measurement procedures within the DASY software, enable the user to conduct the system performance check and system validation. System validation kit includes a dipole, tripod holder to fix it underneath the flat phantom and a corresponding distance holder.

➤ System Validation

According to FCC KDB 865664 D02, SAR system verification is required to confirm measurement accuracy. The SAR systems (including SAR probes, system components and software versions) used for this device were validated against its performance specifications prior to the SAR measurements. Reference dipoles are used with the required tissue-equivalent media for system validation, according to the procedures outlined in FCC KDB 865664 D01 and IEEE 1528-2013. Since SAR probe calibrations are frequency dependent, each probe calibration point must be validated at a frequency within the valid frequency range of the probe calibration point, using the system that normally operates with the probe for routine SAR measurements and according to the required tissue-equivalent media. A tabulated summary of the system validation status, measurement frequencies, SAR probes, calibrated signal type(s) and tissue dielectric parameters has been included.

➤ Purpose of System Performance Check

The system performance check verifies that the system operates within its specifications. System and operator errors can be detected and corrected. It is recommended that the system performance check be performed prior to any usage of the system in order to guarantee reproducible results. The system performance check uses normal SAR measurements in a simplified setup with a well characterized source. This setup was selected to give a high sensitivity to all parameters that might fail or vary over time. The system check does not intend to replace the calibration of the components, but indicates situations where the system uncertainty is exceeded due to drift or failure.

➤ System Setup

The output power on dipole port must be calibrated to 24 dBm (250 mW) before dipole is connected. In the simplified setup for system evaluation, the DUT is replaced by a calibrated dipole and the power source is replaced by a continuous wave which comes from a signal generator. The calibrated dipole must be placed beneath the flat phantom section of the SAM twin phantom with the correct distance holder. The distance holder should touch the phantom surface with a light pressure at the reference marking and be oriented parallel to the long side of the phantom. The system check verifies that the system operates within its specifications. It is performed daily or before every SAR measurement. The system check uses normal SAR measurements in the flat

section of the phantom with a matched dipole at a specified distance. The system verification setup is shown as below.




Fig 8.1 Photo of Dipole Setup




Fig 8.2 System Setup for System Evaluation

➤ **Validation Results**

After system check testing, the SAR result will be normalized to 1W forward input power and compared with the reference SAR value derived from validation dipole certificate report. The deviation of system check should be within 10 %.

<Validation Setup>

Dipole S/N	Probe S/N	DAE S/N
D750V3-1173	7608	1643
D900V2-1d064	7608	1643
D1800V2-2d158	7608	1643
D2000V2-1050	7608	1643
D2300V2-1107	7608	1643
D2450V2-805	7608	1643
D2600V2-1139	7608	1643
D5GHzV2-1176-5250	7608	1643
D5GHzV2-1176-5750	7608	1643

Frequency (MHz)	Tissue Type	Conductivity (σ)	Permittivity (ϵ_r)	CW Signal Validation		
				Sensitivity	Probe Linearity	Probe Isotropy
750	HSL	0.851	42.43	PASS	PASS	PASS
835	HSL	0.898	41.88	PASS	PASS	PASS
1750	HSL	1.386	39.91	PASS	PASS	PASS
1800	HSL	1.449	41.26	PASS	PASS	PASS
1900	HSL	1.435	39.65	PASS	PASS	PASS
2000	HSL	1.451	39.42	PASS	PASS	PASS
2300	HSL	1.764	38.99	PASS	PASS	PASS



2450	HSL	1.863	38.85	PASS	PASS	PASS
2600	HSL	1.973	38.58	PASS	PASS	PASS
5250	HSL	4.528	35.32	PASS	PASS	PASS
5600	HSL	4.905	34.89	PASS	PASS	PASS
5750	HSL	5.077	34.28	PASS	PASS	PASS

Frequency (MHz)	Tissue Type	Conductivity (σ)	Permittivity (ϵ_r)	Modulation Signal Validation		
				Mod. Type	Duty Factor	PAR
750	HSL	0.851	42.43	N/A	N/A	N/A
835	HSL	0.898	41.88	GMSK	PASS	N/A
1750	HSL	1.386	39.91	N/A	N/A	N/A
1800	HSL	1.449	41.26	N/A	N/A	N/A
1900	HSL	1.435	39.65	GMSK	PASS	N/A
2000	HSL	1.451	39.42	GMSK	PASS	N/A
2300	HSL	1.764	38.99	OFDM	PASS	PASS
2450	HSL	1.863	38.85	OFDM	PASS	PASS
2600	HSL	1.973	38.58	TDD	PASS	N/A
5250	HSL	4.528	35.32	OFDM	N/A	PASS
5600	HSL	4.905	34.89	OFDM	N/A	PASS
5750	HSL	5.077	34.28	OFDM	N/A	PASS

<Validation Results>

Date	Freq. (MHz)	Tissue Type	Input Power (mW)	Measured 1g SAR (W/kg)	Targeted 1g SAR (W/kg)	Normalized 1g SAR (W/kg)	Deviation (%)
2021.07.03	750	HSL	250	2.08	8.26	8.32	0.73
2021.07.05	900	HSL	250	2.66	10.90	10.64	-2.39
2021.07.12	1800	HSL	250	9.43	39.20	37.72	-3.78
2021.07.09	2000	HSL	250	10.08	40.90	40.32	-1.42
2021.07.15	2300	HSL	250	12.15	48.40	48.6	0.41
2021.07.12	2450	HSL	250	13.25	52.00	53	1.92
2021.07.07	2600	HSL	250	13.75	54.00	55	1.85
2021.07.14	5250	HSL	100	7.98	78.90	79.8	1.14
2021.07.13	5750	HSL	100	8.11	80.00	81.1	1.37

Date	Freq. (MHz)	Tissue Type	Input Power (mW)	Measured 10g SAR (W/kg)	Targeted 10g SAR (W/kg)	Normalized 10g SAR (W/kg)	Deviation (%)
2021.07.03	750	HSL	250	1.35	5.45	5.4	-0.92



2021.07.05	900	HSL	250	1.69	6.97	6.76	-3.01
2021.07.12	1800	HSL	250	5.02	20.60	20.08	-2.52
2021.07.09	2000	HSL	250	5.19	20.90	20.76	-0.67
2021.07.15	2300	HSL	250	5.75	23.00	23	0.00
2021.07.12	2450	HSL	250	6.24	24.10	24.96	3.57
2021.07.07	2600	HSL	250	6.35	24.50	25.4	3.67
2021.07.14	5250	HSL	100	2.31	22.50	23.1	2.67
2021.07.13	5750	HSL	100	2.26	22.60	22.6	0.00

Note: System checks the specific test data please see Annex C.

9. EUT Testing Position

This EUT was tested in six different positions. They are right cheek/right tilted/left cheek/left tilted for head, Front/Back of the EUT with phantom 10 mm gap, as illustrated below, please refer to Appendix B for the test setup photos.

➤ Handset Reference Points

The vertical centre line passes through two points on the front side of the handset – the midpoint of the width w_t of the handset at the level of the acoustic output, and the midpoint of the width w_b of the bottom of the handset.

The horizontal line is perpendicular to the vertical centre line and passes the center of the acoustic output. The horizontal line is also tangential to the handset at point A.

The two lines intersect at point A. Note that for many handsets, point A coincides with the center of the acoustic output; however, the acoustic output may be located elsewhere on the horizontal line. Also note that the vertical centre line is not necessarily parallel to the front face of the handset, especially for clamshell handsets, handsets with flip covers, and other irregularly shaped handsets.



Fig. 9.1 Illustration for Cheek Position




Fig. 9.2 Illustration for Handset Vertical and Horizontal Reference Lines

➤ **Positioning for Cheek / Touch**

To position the device with the vertical center line of the body of the device and the horizontal line crossing the center piece in a plane parallel to the sagittal plane of the phantom. While maintaining the device in this plane, align the vertical center line with the reference plane containing the three ear and mouth reference point (M: Mouth, RE: Right Ear and LE: Left Ear) and align the center of the ear piece with the line RE-LE.

To move the device towards the phantom with the ear piece aligned with the line LE-RE until the phone touched the ear. While maintaining the device in the reference plane and maintaining the phone contact with the ear, move the bottom of the phone until any point on the front side is in contact with the cheek of the phantom or until contact with the ear is lost (see below figure)




Fig 9.3 Illustration for Cheek Position

➤ **Positioning for Ear / 15° Tilt**

To position the device in the “cheek” position described above.

While maintaining the device the reference plane described above and pivoting against the ear, moves it outward away from the mouth by an angle of 15 degrees or until contact with the ear is lost (see figure below).




Fig 9.4 Illustration for Tilted Position

➤ **Near the Mouth/Jaw Regions of the SAM Phantom**

Antennas located near the bottom of a phone may require SAR measurements around the mouth and jaw regions of the SAM head phantom. This typically applies to clam-shell style phones that are generally longer in the unfolded normal use positions or to certain older style long rectangular phones.

Under these circumstances, the following procedures apply, adopted from the FCC guidance on SAR handsets document FCC KDB Publication 648474 D04v01r03. The SAR required in these regions of SAM should be measured using a flat phantom. The phone should be positioned with a separation distance of 4 mm between the ear reference point (ERP) and the outer surface of the flat phantom shell. While maintaining this distance at the ERP location, the low (bottom) edge of the phone should be lowered from the phantom to establish the same separation distance between the peak SAR locations identified by the truncated partial SAR distribution measured with the SAM phantom. The distance from the peak SAR location to the phone is determined by the straight line passing perpendicularly through the phantom surface. When it is not feasible to maintain 4 mm separation at the ERP while also establishing the required separation at the peak SAR location, the top edge of the phone will be allowed to touch the phantom with a separation < 4 mm at the ERP. The phone should not be tilted to the left or right while placed in this inclined position to the flat phantom.

➤ **Body-worn Configurations**

The body-worn configurations shall be tested with the supplied accessories (belt-clips, holsters, etc.) attached to the device in normal use configuration.

For body-worn and other configurations a flat phantom shall be used which is comprised of material with electrical properties similar to the corresponding tissues.




Fig 9.5 Illustration for Body Worn Position

➤ **Hotspot Mode Exposure Position Conditions**

For handsets that support hotspot mode operations, with wireless router capabilities and various web browsing functions, the relevant hand and body exposure conditions are tested according to the hotspot SAR procedures in KDB 941225. A test separation distance of 10 mm is required between the phantom and all surfaces and edges with a transmitting antenna located within 25 mm from that surface or edge. When the form factor of a handset is smaller than 9 cm x 5 cm, a test separation distance of 5 mm (instead of 10 mm) is required for testing hotspot mode. When the separation distance required for body-worn accessory testing is larger than or equal to that tested for hotspot mode, in the same wireless mode and for the same surface of the phone, the hotspot mode SAR data may be used to support body-worn accessory SAR compliance for that particular configuration (surface).




Fig 9.6 Illustration for Hotspot Position

10. Measurement Procedures

The measurement procedures are as follows:

<Conducted power measurement>

- (a) For WWAN power measurement, use base station simulator to configure EUT WWAN transmission in conducted connection with RF cable, at maximum power in each supported wireless interface and frequency band.
- (b) Read the WWAN RF power level from the base station simulator.
- (c) For WLAN/BT power measurement, use engineering software to configure EUT WLAN/BT continuously transmission, at maximum RF power in each supported wireless interface and frequency band.
- (d) Connect EUT RF port through RF cable to the power meter, and measure WLAN/BT output power.

<SAR measurement>

- (a) Use base station simulator to configure EUT WWAN transmission in radiated connection, and engineering software to configure EUT WLAN/BT continuously transmission, at maximum RF power, in the highest power channel.
- (b) Place the EUT in the positions as Appendix D demonstrates.
- (c) Set scan area, grid size and other setting on the DASY software.
- (d) Measure SAR results for the highest power channel on each testing position.
- (e) Find out the largest SAR result on these testing positions of each band.
- (f) Measure SAR results for other channels in worst SAR testing position if the reported SAR of highest power channel is larger than 0.8 W/kg.

According to the test standard, the recommended procedure for assessing the peak spatial-average SAR value consists of the following steps:

- (a) Power reference measurement.
- (b) Area scan.
- (c) Zoom scan.
- (d) Power drift measurement.



10.1. Spatial Peak SAR Evaluation

The procedure for spatial peak SAR evaluation has been implemented according to the test standard. It can be conducted for 1g and 10g, as well as for user-specific masses. The DASY software includes all numerical procedures necessary to evaluate the spatial peak SAR value. The base for the evaluation is a "cube" measurement. The measured volume must include the 1g and 10g cubes with the highest averaged SAR values. For that purpose, the center of the measured volume is aligned to the interpolated peak SAR value of a previously performed area scan.

The entire evaluation of the spatial peak values is performed within the post-processing engine (SEMCAD). The system always gives the maximum values for the 1g and 10g cubes. The algorithm to find the cube with highest averaged SAR is divided into the following stages:

- (a) Extraction of the measured data (grid and values) from the Zoom Scan.
- (b) Calculation of the SAR value at every measurement point based on all stored data (A/D values and measurement parameters).
- (c) Generation of a high-resolution mesh within the measured volume.
- (d) Interpolation of all measured values from the measurement grid to the high-resolution grid.
- (e) Extrapolation of the entire 3-D field distribution to the phantom surface over the distance from sensor to surface.
- (f) Calculation of the averaged SAR within masses of 1g and 10g.

10.2. Power Reference Measurement

The Power Reference Measurement and Power Drift Measurements are for monitoring the power drift of the device under test in the batch process. The minimum distance of probe sensors to surface determines the closest measurement point to phantom surface. This distance cannot be smaller than the distance of sensor calibration points to probe tip as defined in the probe properties.

10.3. Area Scan Procedures

Area scans are defined prior to the measurement process being executed with a user defined variable spacing between each measurement point (integral) allowing low uncertainty measurements to be conducted. Scans defined for FCC applications utilize a 10mm² step integral, with 1mm interpolation used to locate the peak SAR area used for zoom scan assessments.



When an Area Scan has measured all reachable points, it computes the field maxima founding the scanned area, within a range of the global maximum. The range (in dB) is specified in the standards for compliance testing. For example, a 2 dB range is required in IEEE1528-2003.

10.4. Zoom Scan Procedures

Zoom Scans are used to assess the peak spatial SAR values within a cubic averaging volume containing 1 g and 10 g of simulated tissue. A density of 1000 kg/m³ is used to represent the head and body tissue density and not the phantom liquid density, in order to be consistent with the definition of the liquid dielectric properties, i.e. the side length of the 1g cube is 10mm, with the side length of the 10 g cube 21,5mm. The zoom scan integer steps can be user defined so as to reduce uncertainty, but normal practice for typical test applications utilize a physical step of 5x5x7 (8mmx8mmx5mm) providing a volume of 32mm in the X & Y axis, and 30mm in the Z axis.

10.5. SAR Averaged Methods

In DASy, the interpolation and extrapolation are both based on the modified Quadratic Sheppard's method. The interpolation scheme combines a least-square fitted function method and a weighted average method which are the two basic types of computational interpolation and approximation.

Extrapolation routines are used to obtain SAR values between the lowest measurement points and the inner phantom surface. The extrapolation distance is determined by the surface detection distance and the probe sensor offset. The uncertainty increases with the extrapolation distance. To keep the uncertainty within 1% for the 1 g and 10 g cubes, the extrapolation distance should not be larger than 5 mm.

10.6. Power Drift Monitoring

All SAR testing is under the DUT install full charged battery and transmit maximum output power. In DASy measurement software, the power reference measurement and power drift measurement procedures are used for monitoring the power drift of DUT during SAR test. Both these procedures measure the field at a specified reference position before and after the SAR testing. The software will calculate the field difference in dB. If the power drift more than 5%, the SAR will be retested.

11. SAR Test Procedure

11.1. General Scan Requirements

Probe boundary effect error compensation is required for measurements with the probe tip closer than half a probe tip diameter to the phantom surface. Both the probe tip diameter and sensor offset distance must satisfy measurement protocols; to ensure probe boundary effect errors are minimized and the higher fields closest to the phantom surface can be correctly measured and extrapolated to the phantom surface for computing 1-g SAR. Tolerances of the post-processing algorithms must be verified by the test laboratory for the scan resolutions used in the SAR measurements, according to the reference distribution functions specified in IEEE Std. 1528-2013.

		≤ 3 GHz	> 3 GHz	
Maximum distance from closest measurement point (geometric center of probe sensors) to phantom surface		5 mm \pm 1 mm	$\frac{1}{2} \cdot \delta \cdot \ln(2)$ mm \pm 0.5 mm	
Maximum probe angle from probe axis to phantom surface normal at the measurement location		30° \pm 1°	20° \pm 1°	
Maximum area scan spatial resolution: Δx_{Area} , Δy_{Area}		≤ 2 GHz: ≤ 15 mm 2 – 3 GHz: ≤ 12 mm	3 – 4 GHz: ≤ 12 mm 4 – 6 GHz: ≤ 10 mm	
		When the x or y dimension of the test device, in the measurement plane orientation, is smaller than the above, the measurement resolution must be \leq the corresponding x or y dimension of the test device with at least one measurement point on the test device.		
Maximum zoom scan spatial resolution: Δx_{Zoom} , Δy_{Zoom}		≤ 2 GHz: ≤ 8 mm 2 – 3 GHz: ≤ 5 mm*	3 – 4 GHz: ≤ 5 mm* 4 – 6 GHz: ≤ 4 mm*	
Maximum zoom scan spatial resolution, normal to phantom surface	uniform grid: $\Delta z_{Zoom}(n)$	≤ 5 mm	3 – 4 GHz: ≤ 4 mm 4 – 5 GHz: ≤ 3 mm 5 – 6 GHz: ≤ 2 mm	
	graded grid	$\Delta z_{Zoom}(1)$: between 1 st two points closest to phantom surface	≤ 4 mm	3 – 4 GHz: ≤ 3 mm 4 – 5 GHz: ≤ 2.5 mm 5 – 6 GHz: ≤ 2 mm
		$\Delta z_{Zoom}(n>1)$: between subsequent points	$\leq 1.5 \cdot \Delta z_{Zoom}(n-1)$ mm	
Minimum zoom scan volume	x, y, z	≥ 30 mm	3 – 4 GHz: ≥ 28 mm 4 – 5 GHz: ≥ 25 mm 5 – 6 GHz: ≥ 22 mm	
Note: δ is the penetration depth of a plane-wave at normal incidence to the tissue medium; see IEEE Std 1528-2013 for details. * When zoom scan is required and the <i>reported</i> SAR from the <i>area scan based 1-g SAR estimation</i> procedures of KDB Publication 447498 is ≤ 1.4 W/kg, ≤ 8 mm, ≤ 7 mm and ≤ 5 mm zoom scan resolution may be applied, respectively, for 2 GHz to 3 GHz, 3 GHz to 4 GHz and 4 GHz to 6 GHz.				

11.2. Test Procedure

The Following steps are used for each test position

1. Establish a call with the maximum output power with a base station simulator. The connection between the mobile and the base station simulator is established via air interface.
2. Measurement of the local E-field value at a fixed location. This value serves as a reference value for calculating a possible power drift.
3. Measurement of the SAR distribution with a grid of 8 to 16mm * 8 to 16 mm and a constant distance to the inner surface of the phantom. Since the sensors cannot directly measure at the inner phantom surface, the values between the sensors and the inner phantom surface are extrapolated. With these values the area of the maximum SAR is calculated by an interpolation scheme.
4. Around this point, a cube of 30 * 30 * 30 mm or 32 * 32 * 32 mm is assessed by measuring 5 or 8 * 5 or 8*4 or 5 mm. With these data, the peak spatial-average SAR value can be calculated.

11.3. Description of Interpolation/Extrapolation Scheme

The local SAR inside the phantom is measured using small dipole sensing elements inside a probe body. The probe tip must not be in contact with the phantom surface in order to minimize measurements errors, but the highest local SAR will occur at the surface of the phantom.

An extrapolation is using to determinate this highest local SAR values. The extrapolation is based on a fourth-order least-square polynomial fit of measured data. The local SAR value is then extrapolated from the liquid surface with a 1mm step.

The measurements have to be performed over a limited time (due to the duration of the battery) so the step of measurement is high. It could vary between 5 and 8 mm. To obtain an accurate assessment of the maximum SAR averaged over 10 grams and 1 gram requires a very fine resolution in the three dimensional scanned data array.

11.4. Wireless Router

Some battery-operated handsets have the capability to transmit and receive user through simultaneous transmission of WIFI simultaneously with a separate licensed transmitter. The FCC has provided guidance in FCC KDB Publication 941225 D06 v02r01 where SAR test considerations for handsets ($L \times W \geq 9 \text{ cm} \times 5 \text{ cm}$) are based on a composite test separation distance of 10 from the front, back and edges of the device containing transmitting antennas within



2.5cm of their edges, determined from general mixed use conditions for this type of devices. Since the hotspot SAR results may overlap with the body-worn accessory SAR requirements, the more conservative configurations can be considered, thus excluding some body-worn accessory SAR tests.

When the user enables the personal wireless router functions for the handset, actual operations include simultaneous transmission of both the WIFI transmitter and another licensed transmitter. Both transmitters often do not transmit at the same transmitting frequency and thus cannot be evaluated for SAR under actual use conditions due to the limitations of the SAR assessment probes. Therefore, SAR must be evaluated for each frequency transmission and mode separately and spatially summed with the WIFI transmitter according to FCC KDB Publication 447498 D01v06 publication procedures. The "Portable Hotspot" feature on the handset was NOT activated during SAR assessments, to ensure the SAR measurements were evaluated for a single transmission frequency RF signal at a time.



12. SAR Test Configuration

<GSM Mode>

A summary of these settings are illustrated below:

For GSM850 frequency band, the power control is set to 5 for GSM/GPRS mode (GSMK-CS1) and set to 8 for EDGE mode (MCS5); For GSM1900 frequency band, the power control is set to 0 for GSM/GPRS mode (GSMK-CS1) and set to 2 for EDGE mode (MCS5).

1. Per KDB 447498 D01v06, the maximum output power channel is used for SAR testing and for further SAR test reduction.
2. Per KDB 941225 D01v03r01, SAR test reduction for GSM / GPRS / EDGE modes is determined by the source-based time-averaged output power including tune-up tolerance. The mode with highest specified time-averaged output power should be tested for SAR compliance in the applicable exposure conditions. For modes with the same specified maximum output power and tolerance, the higher number time-slot configuration should be tested. Therefore, the GPRS (4Tx slots) for GSM850/GSM1900 is considered as the primary mode.
3. Other configurations of GSM / GPRS / EDGE are considered as secondary modes.

Timeslot consignations:

Remark:

1. The frame-averaged power is linearly reported the maximum burst averaged power over 8 time slots. The calculated method are shown as below:
The duty cycle "x" of different time slots as below:
1 TX slot is 1/8, 2 TX slots is 2/8, 3 TX slots is 3/8 and 4 TX slots is 4/8
Based on the calculation formula:
Frame-averaged power = Burst averaged power + 10 log (x)
So,
Frame-averaged power (1 TX slot) = Burst averaged power (1 TX slot)– 9.03
Frame-averaged power (2 TX slots) = Burst averaged power (2 TX slots)– 6.02
Frame-averaged power (3 TX slots) = Burst averaged power (3 TX slots)– 4.26
Frame-averaged power (4 TX slots) = Burst averaged power (4 TX slots) – 3.01
2. CS1 coding scheme was used in GPRS conducted power measurements and SAR testing, MCS5 coding scheme was used in EGPRS conducted power measurements and SAR testing (if necessary).

No. of Slots:	Slot 1	Slot 2	Slot 3	Slot 4
Slot Consignation:	1Up4Down	2Up3Down	3Up2Down	4Up1Down
Duty Cycle:	1:8.3	1:4.15	1:2.77	1:2.08
Correct Factor:	-9.03dB	-6.02dB	-4.26dB	-3.01dB



<WCDMA Mode>

Summary of UMTS conducted power measurement:

1. The 3G SAR test reduction procedure is applied, when the maximum output power and tune-up tolerance specified for production units in a secondary mode is $\leq \frac{1}{4}$ dB higher than the primary mode, SAR measurement is not required for the secondary mode.
2. The following tests were conducted according to the test requirements outlines in 3GPP TS 34.121 specification.
3. The procedures in KDB 941225 D01v03r01 are applied for 3GPP Rel. 6 HSPA to configure the device in the required sub-test mode(s) to determine SAR test exclusion.
4. For HSPA+ devices supporting 16 QAM in the uplink, power measurements procedure is according to the configurations in Table C.11.1.4 of 3GPP TS 34.121-1.
5. Per KDB 941225 D01v03r01, RMC 12.2kbps setting is used to evaluate SAR. The maximum output power and tune-up tolerance specified for production units in HSDPA / HSUPA / DC-HSDPA / HSPA+ is $\leq \frac{1}{4}$ dB higher than RMC 12.2Kbps or when the highest reported SAR of the RMC12.2Kbps is scaled by the ratio of specified maximum output power and tune-up tolerance of HSDPA / HSUPA / DC-HSDPA / HSPA+ to RMC12.2Kbps and the adjusted SAR is ≤ 1.2 W/kg, SAR measurement is not required for HSDPA / HSUPA / DC-HSDPA / HSPA+, and according to the following RF output power, the output power results of the secondary modes (HSDPA / HSUPA / DC-HSDPA / HSPA+) are less than $\frac{1}{4}$ dB higher than the primary modes; therefore, SAR measurement is not required for HSDPA / HSUPA / DC-HSDPA / HSPA+.
6. A fixed level power reduction is applied for WCDMA Band II when handset open Hotspot mode, the power reduction triggered.

HSDPA Setup Configuration

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	$\beta_{hr}^{(1)}$	CM (dB) ⁽²⁾
1	2/15	15/15	64	2/15	4/15	0.0
2	12/15 ⁽³⁾	15/15 ⁽³⁾	64	12/15 ⁽³⁾	24/15	1.0
3	15/15	8/15	64	15/8	30/15	1.5
4	15/15	4/15	64	15/4	30/15	1.5

Note 1: Δ_{ACK} , Δ_{NACK} and $\Delta_{CQI} = 8 \Leftrightarrow A_{hr} = \beta_{hr}/\beta_c = 30/15 \Leftrightarrow \beta_{hr} = 30/15 * \beta_c$
 Note 2: CM = 1 for $\beta_c/\beta_d = 12/15$, $\beta_{hr}/\beta_c = 24/15$.
 Note 3: For subtest 2 the β_c/β_d ratio of 12/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 11/15$ and $\beta_d = 15/15$.

HSUPA Setup Configuration

Sub-test	β_c	β_d	β_d (SF)	β_c/β_d	$\beta_{hs}^{(1)}$	β_{ec}	β_{ed}	β_{ed} (SF)	β_{ed} (codes)	CM ⁽²⁾ (dB)	MPR (dB)	AG ⁽⁴⁾ Index	E-TFCI
1	11/15 ⁽³⁾	15/15 ⁽³⁾	64	11/15 ⁽³⁾	22/15	209/225	1039/225	4	1	1.0	0.0	20	75
2	6/15	15/15	64	6/15	12/15	12/15	94/75	4	1	3.0	2.0	12	67
3	15/15	9/15	64	15/9	30/15	30/15	$\beta_{ed1}: 47/15$ $\beta_{ed2}: 47/15$	4	2	2.0	1.0	15	92
4	2/15	15/15	64	2/15	4/15	2/15	56/75	4	1	3.0	2.0	17	71
5	15/15 ⁽⁴⁾	15/15 ⁽⁴⁾	64	15/15 ⁽⁴⁾	30/15	24/15	134/15	4	1	1.0	0.0	21	81

Note 1: $\Delta_{ACK}, \Delta_{NACK}$ and $\Delta_{CQI} = 8 \Leftrightarrow A_{hs} = \beta_{hs}/\beta_c = 30/15 \Leftrightarrow \beta_{hs} = 30/15 * \beta_c$.

Note 2: CM = 1 for $\beta_c/\beta_d = 12/15, \beta_{hs}/\beta_c = 24/15$. For all other combinations of DPDCH, DPCCH, HS-DPCCH, E-DPDCH and E-DPCCH the MPR is based on the relative CM difference.

Note 3: For subtest 1 the β_c/β_d ratio of 11/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 10/15$ and $\beta_d = 15/15$.

Note 4: For subtest 5 the β_c/β_d ratio of 15/15 for the TFC during the measurement period (TF1, TF0) is achieved by setting the signaled gain factors for the reference TFC (TF1, TF1) to $\beta_c = 14/15$ and $\beta_d = 15/15$.

Note 5: Testing UE using E-DPDCH Physical Layer category 1 Sub-test 3 is not required according to TS 25.306 Table 5.1g.

Note 6: β_{ed} cannot be set directly; it is set by Absolute Grant Value.

HSPA+ 3GPP release 7 (uplink category 7) 16QAM, Setup Configuration:
Table C.11.1.4: β values for transmitter characteristics tests with HS-DPCCH and E-DCH with 16QAM

Sub-test	β_c (Note 3)	β_d	β_{hs} (Note 1)	β_{ec}	β_{ed} (2xSF2) (Note 4)	β_{ed} (2xSF4) (Note 4)	CM (dB) (Note 2)	MPR (dB) (Note 2)	AG Index (Note 4)	E-TFCI (Note 5)	E-TFCI (boost)
1	1	0	30/15	30/15	$\beta_{ed1}: 30/15$ $\beta_{ed2}: 30/15$	$\beta_{ed3}: 24/15$ $\beta_{ed4}: 24/15$	3.5	2.5	14	105	105

Note 1: $\Delta_{ACK}, \Delta_{NACK}$ and $\Delta_{CQI} = 30/15$ with $\beta_{hs} = 30/15 * \beta_c$.

Note 2: CM = 3.5 and the MPR is based on the relative CM difference, MPR = MAX(CM-1,0).

Note 3: DPDCH is not configured, therefore the β_c is set to 1 and $\beta_d = 0$ by default.

Note 4: β_{ed} can not be set directly; it is set by Absolute Grant Value.

Note 5: All the sub-tests require the UE to transmit 2SF2+2SF4 16QAM EDCH and they apply for UE using E-DPDCH category 7. E-DCH TTI is set to 2ms TTI and E-DCH table index = 2. To support these E-DCH configurations DPDCH is not allocated. The UE is signaled to use the extrapolation algorithm.

**DC-HSDPA Setup Configuration**

The following tests were completed according to procedures in section 7.3.13 of 3GPP TS34.108 v9.5.0. A summary of these settings are illustrated below:

Downlink Physical Channels are set as per 3GPP TS34.121-1 v9.0.0 E.5.

Table E.5.0: Levels for HSDPA connection setup


Parameter During Connection setup	Unit	Value
P-CPICH_Ec/Ior	dB	-10
P-CCPCH and SCH_Ec/Ior	dB	-12
PICH_Ec/Ior	dB	-15
HS-PDSCH	dB	off
HS-SCCH_1	dB	off
DPCH_Ec/Ior	dB	-5
OCNS_Ec/Ior	dB	-3.1

Call is set up as per 3GPP TS34.108 v9.5.0 sub clause 7.3.13

The configurations of the fixed reference channels for HSDPA RF tests are described in 3GPP TS 34.121, annex C for FDD and 3GPP TS 34.122.

Table C.8.1.12: Fixed Reference Channel H-Set 12

Parameter	Unit	Value
Nominal Avg. Inf. Bit Rate	kbps	60
Inter-TTI Distance	TTI's	1
Number of HARQ Processes	Processes	6
Information Bit Payload (N_{INF})	Bits	120
Number Code Blocks	Blocks	1
Binary Channel Bits Per TTI	Bits	960
Total Available SML's in UE	SML's	19200
Number of SML's per HARQ Proc.	SML's	3200
Coding Rate		0.15
Number of Physical Channel Codes	Codes	1
Modulation		QPSK
Note 1: The RMC is intended to be used for DC-HSDPA mode and both cells shall transmit with identical parameters as listed in the table. Note 2: Maximum number of transmission is limited to 1, i.e., retransmission is not allowed. The redundancy and constellation version 0 shall be used.		


Figure C.8.19: Coding rate for Fixed reference Channel H-Set 12 (QPSK)



<CDMA Mode>

1xEV-DO Rev. B

Call box setup procedure

1xEV-DO Release B

1> CMW 500 Signal Generator > 1xEV-DO Taskbar Enable

2> CMW 500 1xEV-DO Signaling Configuration Window >

3> 1xEV-DO Signaling On Window:

Under Access Network Control:

Band Class: BC0: US Cellular

RF Channel: 31

1xEV-DO Power: -70 dBm

4> 1xEV-DO Signaling Configuration Window

Under RF Frequency Band / Channel: Enter Ch. Frequency

➤ Under Carrier Configuration: RF Frequency
For Two Carriers: Low Channel (1013)

	<u>RF Channel</u>	<u>RF Channel Offset</u>
Carrier [0]	31	0
Carrier [1]	1013	982

➤ Under Carrier Configuration: RF Pilot

	<u>Carrier Sector</u>	<u>Active on AN</u>	<u>Assigned to AT</u>
Pilot [0]	C0/S0	✓	✓
	CA/S1	✓	✓

For Three Carriers: Low Channel (1013)

	<u>RF Channel</u>	<u>RF Channel Offset</u>
Carrier [0]	72	0
Carrier [1]	31	-41
Carrier [2]	1013	941

➤ Under Carrier Configuration: RF Pilot

	<u>Carrier Sector</u>	<u>Active on AN</u>	<u>Assigned to AT</u>
Pilot [0]	C0/S0	✓	✓
Pilot [1]	C1/S1	✓	✓
Pilot [2]	C2/S2	✓	✓



<LTE Mode>

LTE Target MPR level

The device implements maximum power reduction per 3GPP 36.101 requirements where the MPR target is as below table. The MPR settings are implemented configured into firmware and cannot be disabled by the end user or LTE carrier network.

Modulation	Channel bandwidth / Transmission bandwidth configuration [RB]						MPR	3GPP
	1.4	3.0	5	10	15	20	Target	MPR
	MHz	MHz	MHz	MHz	MHz	MHz	(dB)	(dB)
QPSK	> 5	> 4	> 8	> 12	> 16	> 18	1	≤ 1
16 QAM	≤ 5	≤ 4	≤ 8	≤ 12	≤ 16	≤ 18	1	≤ 1
64 QAM	> 5	> 4	> 8	> 12	> 16	> 18	2	≤ 2

Note: The measurement result showed some difference from the target MPR level, due to expected 0.5dB measurement tolerance

LTE Bands

LTE Bands	Channel bandwidth / Transmission bandwidth configuration [RB]					
	1.4	3.0	5	10	15	20
	MHz	MHz	MHz	MHz	MHz	MHz
2	✓	✓	✓	✓	✓	✓
4	✓	✓	✓	✓	✓	✓
5	✓	✓	✓	✓	N/A	N/A
7	N/A	N/A	✓	✓	✓	✓
12	✓	✓	✓	✓	N/A	N/A
13	N/A	N/A	✓	✓	N/A	N/A
14	N/A	N/A	N/A	✓	✓	N/A
17	N/A	N/A	✓	✓	N/A	N/A
25	✓	✓	✓	✓	✓	✓
26	✓	✓	✓	✓	✓	N/A
30	N/A	N/A	✓	✓	N/A	N/A
40A	N/A	N/A	✓	✓	N/A	N/A
40B	N/A	N/A	✓	✓	N/A	N/A
41	N/A	N/A	✓	✓	✓	✓
66	✓	✓	✓	✓	✓	✓
71	N/A	N/A	✓	✓	✓	✓

Note:

1. Per KDB 941225 D05v02r05, when a properly configured base station simulator is used for the SAR and power measurements, spectrum plots for each RB allocation and offset configuration is not required.
2. Per KDB 941225 D05v02r05, start with the largest channel bandwidth and measure SAR for



QPSK with 1 RB allocation, using the RB offset and required test channel combination with the highest maximum output power for RB offsets at the upper edge, middle and lower edge of each required test channel.

3. Per KDB 941225 D05v02r05, 50% RB allocation for QPSK SAR testing follows 1RB QPSK allocation procedure.
4. Per KDB 941225 D05v02r05, for QPSK with 100% RB allocation, SAR is not required when the highest maximum output power for 100 % RB allocation is less than the highest maximum output power in 50% and 1 RB allocations and the highest reported SAR for 1 RB and 50% RB allocation are ≤ 0.8 W/kg. Otherwise, SAR is measured for the highest output power channel; and if the reported SAR is > 1.45 W/kg, the remaining required test channels must also be tested.
5. Per KDB 941225 D05v02r05, 16QAM/64QAM output power for each RB allocation configuration is $>$ not $\frac{1}{2}$ dB higher than the same configuration in QPSK and the reported SAR for the QPSK configuration is ≤ 1.45 W/kg; Per KDB941225 D05v02r05, 16QAM/64QAM SAR testing is not required.
6. Per KDB 941225 D05v02r05, smaller bandwidth output power for each RB allocation configuration is $>$ not $\frac{1}{2}$ Db higher than the same configuration in the largest supported bandwidth, and the reported SAR for the largest supported band width is ≤ 1.45 W/kg; Per KDB 941225 D05v02r05, smaller bandwidth SAR testing is not required.
7. For LTE B4 / B5 / B7 / B17 the maximum bandwidth does not support three non-overlapping channels, per KDB941225 D05v02r05, when a device supports overlapping channel assignment in a channel bandwidth configuration, the middle channel of the group of overlapping channels should be selected for testing.
8. LTE band 2 / 4 / 12 SAR test was covered by Band 25 / 66 / 17; according to April 2015 TCB workshop, SAR test for overlapping LTE bands can be reduced if
 - a. The maximum output power, including tolerance, for the smaller band is \leq the larger band to qualify for the SAR test exclusion.
 - b. The channel bandwidth and other operating parameters for the smaller band are fully supported by the larger band.
9. According to 2017 TCB workshop, for 64 QAM and 16 QAM should be verified by checking the signal constellation with a call box to avoid incorrect maximum power levels due to MPR and other requirements associated with signal modulation, and the following figure is taken from the "Fundamental Measurement >> Modulation Analysis >>constellation" mode of the device connect to the CMW500 base station, therefore, the device 64QAM and 16QAMsignal modulation are correct. Identify if Maximum Power Reduction (MPR) is optional or mandatory, i.e. built-in by design: only mandatory MPR may be considered during SAR testing, when the maximum output power is permanently limited by the MPR implemented within the UE; and only for the applicable RB (resource block) configurations specified in LTE standards: b) A-MPR (additional MPR) must be disabled.



10. Per KDB 447498 D01v06, the reported SAR is the measured SAR value adjusted for maximum tune-up tolerance.
 - a. Tune-up scaling Factor = tune-up limit power (mW) / EUT RF power (mW), where tune-up limit is the maximum rated power among all production units.
 - b. For SAR testing of WLAN signal with non-100% duty cycle, the measured SAR is scaled-up by the duty cycle scaling factor which is equal to "1/(duty cycle)"
 - c. For WWAN: Reported SAR(W/kg)= Measured SAR(W/kg)*Tune-up Scaling Factor
 - d. For WLAN/Bluetooth: Reported SAR(W/kg)= Measured SAR(W/kg)* Duty Cycle scaling factor * Tune-up scaling factor
 - e. For TDD LTE SAR measurement, the duty cycle 1:1.59 (62.9 %) was used perform testing and considering the theoretical duty cycle of 63.3% for extended cyclic prefix in the uplink, and the theoretical duty cycle of 62.9% for normal cyclic prefix in uplink, a scaling factor of extended cyclic prefix $63.3\%/62.9\% = 1.006$ is applied to scale-up the measured SAR result. The Reported TDD LTE SAR = measured SAR (W/kg)* Tune-up Scaling Factor* scaling factor for extended cyclic prefix.
11. Per KDB 447498 D01v06, for each exposure position, testing of other required channels within the operating mode of a frequency band is not required when the reported 1-g or 10-g SAR for the mid-band or highest output power channel is: ≤ 0.8 W/kg or 2.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≤ 100 MHz ≤ 0.6 W/kg or 1.5 W/kg, for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz ≤ 0.4 W/kg or 1.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≥ 200 MHz
12. Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required only when the measured SAR is ≥ 0.8 W/kg.
13. Per KDB 648474 D04v01r03, when the reported SAR for a body-worn accessory measured without a headset connected to the handset is ≤ 1.2 W/kg, SAR testing with a headset connected to the handset is not required.

<WLAN 2.4GHz>

1. SAR is measured for 2.4 GHz 802.11b DSSS using either the fixed test position or, when applicable, the initial test position procedure. SAR test reduction is determined according to the following:
 - a. When the reported SAR of the highest measured maximum output power channel for the exposure configuration is ≤ 0.8 W/kg, no further SAR testing is required for 802.11b DSSS in that exposure configuration.
 - b. When the reported SAR is > 0.8 W/kg, SAR is required for that position using the next highest measured output power channel. When any reported SAR is > 1.2 W/kg, SAR is required for the third channel; i.e., all channels require testing.
2. 2.4 GHz 802.11 g/n OFDM are additionally evaluated for SAR if the highest reported SAR for 802.11b, adjusted by the ratio of the OFDM to DSSS specified maximum output power, is > 1.2 W/kg. When SAR is required for OFDM modes in 2.4 GHz band, the Initial Test



configuration Procedures should be followed.

3. For held-to-ear and hotspot operations, the initial test position procedures were applied. The test position with the highest extrapolated peak SAR will be used as the initial test position. When reported SAR for the initial test position is ≤ 0.4 W/kg, no additional testing for the remaining test positions was required. Otherwise, SAR is evaluated at the subsequent highest peak SAR positions until the reported SAR result is ≤ 0.8 W/kg or all test positions are measured.
4. Justification for test configurations for WLAN per KDB Publication 248227 D02DR02-41929 for 2.4 GHz WI-FI single transmission chain operations, the highest measured maximum output power channel for DSSS was selected for SAR measurement. SAR for OFDM modes (2.4 GHz 802.11g/n) was not required due to the maximum allowed powers and the highest reported DSSSAR.
5. A fixed level power reduction is applied for WiFi when handset operates "held to the body" condition or "held to the ear" condition, the power reduction triggered by audio receiver detection and call establish status.
6. Per KDB 248227 D01v02r02, In the 2.4 GHz band, separate SAR procedures are applied to DSSS and OFDM configurations to simplify DSSS test requirements. SAR is not required for the following 2.4 GHz OFDM conditions:
 - a. When KDB Publication 447498 SAR test exclusion applies to the OFDM configuration.
 - b. When the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is ≤ 1.2 W/kg.

<WLAN 5GHz>

A) U-NII-1 and U-NII-2A Bands

For devices that operate in only one of the U-NII-1 and U-NII-2A bands, the normally required SAR procedures for OFDM configurations are applied. For devices that operate in both U-NII bands using the same transmitter and antenna(s), SAR test reduction is determined according to the following:

1. When the same maximum output power is specified for both bands, begin SAR measurement in U-NII-2A band by applying the OFDM SAR requirements. If the highest reported SAR for a test configuration is ≤ 1.2 W/kg, SAR is not required for U-NII-1 band for that configuration (802.11 mode and exposure condition); otherwise, both bands are tested independently for SAR.
2. When different maximum output power is specified for the bands, begin SAR measurement in the band with higher specified maximum output power. The highest reported SAR for the tested configuration is adjusted by the ratio of lower to higher specified maximum output power for the two bands. When the adjusted SAR is ≤ 1.2 W/kg, SAR is not required for the band with lower maximum output power in that test configuration; otherwise, both bands are tested independently for SAR.
3. The two U-NII bands may be aggregated to support a 160 MHz channel on channel number 50.



4. Without additional testing, the maximum output power for this is limited to the lower of the maximum output power certified for the two bands. When SAR measurement is required for at least one of the bands and the highest reported SAR adjusted by the ratio of specified maximum output power of aggregated to standalone band is > 1.2 W/kg, SAR is required for the 160 MHz channel. This procedure does not apply to an aggregated band with maximum output higher than the standalone band(s); the aggregated band must be tested independently for SAR. SAR is not required when the 160 MHz channel is operating at a reduced maximum power and also qualifies for SAR test exclusion.

B) U-NII-2C and U-NII-3 Bands

The frequency range covered by these bands is 380 MHz (5.47 – 5.85 GHz), which requires a minimum of at least two SAR probe calibration frequency points to support SAR measurements. When Terminal Doppler Weather Radar (TDWR) restriction applies, all channels that operate at 5.60 – 5.65 GHz must be included to apply the SAR test reduction and measurement procedures. When the same transmitter and antenna(s) are used for U-NII-2C band and U-NII-3 band or 5.8 GHz band of §15.247, the bands may be aggregated to enable additional channels with 20, 40 or 80 MHz bandwidth to span across the band gap, as illustrated in Appendix B. The maximum output power for the additional band gap channels is limited to the lower of those certified for the bands. Unless band gap channels are permanently disabled, they must be considered for SAR testing. The frequency range covered by these bands is 380 MHz (5.47 – 5.85 GHz), which requires a minimum of at least two SAR probe calibration frequency points to support SAR measurements. To maintain SAR measurement accuracy and to facilitate test reduction, the channels in U-NII-2C band above 5.65 GHz may be grouped with the 5.8 GHz channels in U-NII-3 or §15.247 band to enable two SAR probe calibration frequency points to cover the bands, including the band gap channels. When band gap channels are supported and the bands are not aggregated for SAR testing, band gap channels must be considered independently in each band according to the normally required OFDM SAR measurement and probe calibration frequency points requirements.

C) OFDM Transmission Mode SAR Test Configuration and Channel Selection Requirements

The initial test configuration for 5 GHz OFDM transmission modes is determined by the 802.11 configuration with the highest maximum output power specified for production units, including tune-up tolerance, in each standalone and aggregated frequency band. SAR for the initial test configuration is measured using the highest maximum output power channel determined by the default power measurement procedures. When multiple configurations in a frequency band have the same specified maximum output power, the initial test configuration is determined according to the following steps applied sequentially.

1. The largest channel bandwidth configuration is selected among the multiple configurations with the same specified maximum output power.



2. If multiple configurations have the same specified maximum output power and largest channel bandwidth, the lowest order modulation among the largest channel bandwidth configurations is selected.
3. If multiple configurations have the same specified maximum output power, largest channel bandwidth and lowest order modulation, the lowest data rate configuration among these configurations is selected.
4. When multiple transmission modes (802.11a/g/n/ac) have the same specified maximum output power, largest channel bandwidth, lowest order modulation and lowest data rate, the lowest order 802.11 mode is selected; i.e., 802.11a is chosen over 802.11n then 802.11ac or 802.11g is chosen over 802.11n. After an initial test configuration is determined, if multiple test channels have the same measured maximum output power, the channel chosen for SAR measurement is determined according to the following. These channel selection procedures apply to both the initial test configuration and subsequent test configuration(s), with respect to the default power measurement procedures or additional power measurements required for further SAR test reduction. The same procedures also apply to subsequent highest output power channel(s) selection.
5. The channel closest to mid-band frequency is selected for SAR measurement.
6. For channels with equal separation from mid-band frequency; for example, high and low channels or two mid-band channels, the higher frequency (number) channel is selected for SAR measurement.

D) SAR Test Requirements for OFDM configurations


When SAR measurement is required for 802.11 a/n/ac OFDM configurations, each standalone and frequency aggregated band is considered separately for SAR test reduction. When the same transmitter and antenna(s) are used for U-NII-1 and U-NII-2A bands, additional SAR test reduction applies. When band gap channels between U-NII-2C band and 5.8 GHz U-NII-3 or §15.247 band are supported, the highest maximum output power transmission mode configuration and maximum output power channel across the bands must be used to determine SAR test reduction, according to the initial test configuration and subsequent test configuration requirements. In applying the initial test configuration and subsequent test configuration procedures, the 802.11 transmission configuration with the highest specified maximum output power and the channel within a test configuration with the highest measured maximum output power should be clearly distinguished to apply the procedures.

13. Conducted RF Output Power

Remark: The output power of GSM/WCDMA/LTE/WLAN/Bluetooth refers to the annex E of this report.

14. Hot-Spot Mode Evaluation Procedure

➤ EUT Antenna Location



➤ EUT Antenna Distance

Antenna Location	Front	Back	Left	Right	Top	Bottom
WWAN Main TX Antenna	<5mm	<5mm	<5mm	5mm	>25mm	<5mm
WLAN/BT Antenna	<5mm	<5mm	>25mm	<25mm	<5mm	>25mm



➤ **Hotspot Evaluation**


Assessment	Hotspot side for SAR Test distance: 10mm					
Antennas	Front	Back	Left	Right	Top	Bottom
WWAN Main TX Antenna	Yes	Yes	Yes	Yes	No	Yes
WLAN/BT Antenna	Yes	Yes	No	Yes	Yes	No

Note :

1. The SAR evaluation procedures for Portable Devices with Wireless Router function is according to KDB 941225 D06 Hotspot SAR v02r01.
2. Head/Body-worn/Hotspot mode SAR assessments are required.
3. Referring to KDB 941225 D06, when the overall device length and width are $\geq 9\text{cm} \times 5\text{cm}$, the test distance is 10mm. SAR must be measured for all sides and surfaces with a transmitting antenna located within 25mm from that surface or edge.

15. Block Diagram of the Tests to be Performed

15.1. Head



IEC 228/05

15.2. Body




Figure 12b – General procedure

16. Test Results List

16.1. Test Guidance

1. Per KDB 447498 D01v06, the reported SAR is the measured SAR value adjusted for maximum tune-up tolerance.
 - a. Tune-up scaling Factor = tune-up limit power (mW) / EUT RF power (mW), where tune-up limit is the maximum rated power among all production units.
 - b. For SAR testing of WLAN signal with non-100% duty cycle, the measured SAR is scaled-up by the duty cycle scaling factor which is equal to "1/(duty cycle)".
 - c. For WWAN: Reported SAR(W/kg)= Measured SAR(W/kg)*Tune-up Scaling Factor.
 - d. For WLAN/Bluetooth: Reported SAR(W/kg)= Measured SAR(W/kg)* Duty Cycle scaling factor * Tune-up scaling factor.
2. Per KDB 447498 D01v06, for each exposure position, testing of other required channels within the operating mode of a frequency band is not required when the *reported* 1-g or 10-g SAR for the mid-band or highest output power channel is:
 - a. ≤ 0.8 W/kg or 2.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≤ 100 MHz
 - b. ≤ 0.6 W/kg or 1.5 W/kg, for 1-g or 10-g respectively, when the transmission band is between 100 MHz and 200 MHz
 - c. ≤ 0.4 W/kg or 1.0 W/kg, for 1-g or 10-g respectively, when the transmission band is ≥ 200 MHz
3. Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required only when the measured SAR is ≥ 0.8 W/kg.
4. Per KDB 648474 D04v01r03, when the reported SAR for a body-worn accessory measured without a headset connected to the handset is ≤ 1.2 W/kg, SAR testing with a headset connected to the handset is not required.
5. Per KDB648474 D04v01r03, for smart phones with a display diagonal dimension > 15.0 cm or an overall diagonal dimension > 16.0 cm, when hotspot mode applies, 10-g extremity SAR is required only for the surfaces and edges with hotspot mode 1-g reported SAR > 1.2 W/kg, however, when power reduction applies to hotspot mode the measured SAR must be scaled to the maximum output power, including tolerance, allowed for tablet modes to compare with the 1.2 W/kg SAR test reduction threshold.
6. Per KDB248227 D01v02r02, a Wi-Fi device must be configured to transmit continuously at the required data rate, channel bandwidth and signal modulation, using the highest transmission duty factor supported by the test mode tools for SAR measurement. The test frequencies established using test mode must correspond to the actual channel frequencies required for operations in the U.S. When 802.11 frame gaps are accounted for in the transmission, a maximum transmission duty factor of $92 - 96\%$ is typically achievable in most test mode



configurations. A minimum transmission duty factor of 85% is required to avoid certain hardware and device implementation issues related to wide range SAR scaling. In addition, a periodic transmission duty factor is required for current generation SAR systems to measure SAR correctly. Unless it is permitted by specific KDB procedures or continuous transmission is specifically restricted by the device, the reported SAR must be scaled to 100% transmission duty factor to determine compliance at the maximum tune-up tolerance limit. When a device is not capable of sustaining continuous transmission or the output can become nonlinear, and it is limited by hardware design and unable to transmit at higher than 85% duty factor, a periodic duty factor within 15% of the maximum duty factor the device is capable of transmitting should be used. The reported SAR must be scaled to the maximum transmission duty factor to determine compliance. Descriptions of the procedures applied to establish the specific duty factor used for SAR testing are required in SAR reports to support the test results.



16.2. Head SAR Data

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1g} (W/kg)	Reported SAR _{1g} (W/kg)
	GPRS 850(2 TX slots)	Right Cheek	189	31.74	32.50	1.191	0.271	0.323
	GPRS 850(2 TX slots)	Right Tilt	189	31.74	32.50	1.191	0.192	0.229
	GPRS 850(2 TX slots)	Left Cheek	189	31.74	32.50	1.191	0.243	0.289
	GPRS 850(2 TX slots)	Left Tilt	189	31.74	32.50	1.191	0.155	0.185
1#	GPRS 850(2 TX slots)	Right Cheek	128	31.68	32.50	1.208	0.298	0.360
	GPRS 850(2 TX slots)	Right Cheek	251	31.66	32.50	1.213	0.231	0.280
	GPRS 1900(4 TX slots)	Right Cheek	661	25.24	26.00	1.191	0.080	0.095
	GPRS 1900(4 TX slots)	Right Tilt	661	25.24	26.00	1.191	0.075	0.089
	GPRS 1900(4 TX slots)	Left Cheek	661	25.24	26.00	1.191	0.064	0.076
	GPRS 1900(4 TX slots)	Left Tilt	661	25.24	26.00	1.191	0.052	0.062
2#	GPRS 1900(4 TX slots)	Right Cheek	512	25.12	26.00	1.225	0.085	0.104
	GPRS 1900(4 TX slots)	Right Cheek	810	25.20	26.00	1.202	0.082	0.099
3#	Band II/RMC 12.2Kbps	Right Cheek	9400	22.61	23.00	1.094	0.099	0.108
	Band II/RMC 12.2Kbps	Right Tilt	9400	22.61	23.00	1.094	0.081	0.089
	Band II/RMC 12.2Kbps	Left Cheek	9400	22.61	23.00	1.094	0.075	0.082
	Band II/RMC 12.2Kbps	Left Tilt	9400	22.61	23.00	1.094	0.065	0.071
	Band II/RMC 12.2Kbps	Right Cheek	9262	22.58	23.00	1.102	0.089	0.098
	Band II/RMC 12.2Kbps	Right Cheek	9538	22.54	23.00	1.112	0.082	0.091
	Band IV/RMC 12.2Kbps	Right Cheek	1413	22.87	23.50	1.156	0.117	0.135
	Band IV/RMC 12.2Kbps	Right Tilt	1413	22.87	23.50	1.156	0.057	0.066
	Band IV/RMC 12.2Kbps	Left Cheek	1413	22.87	23.50	1.156	0.035	0.040
	Band IV/RMC 12.2Kbps	Left Tilt	1413	22.87	23.50	1.156	0.027	0.031
	Band IV/RMC 12.2Kbps	Right Cheek	1312	22.86	23.50	1.159	0.116	0.134
4#	Band IV/RMC 12.2Kbps	Right Cheek	1513	22.76	23.50	1.186	0.128	0.152
5#	Band V/RMC 12.2Kbps	Right Cheek	4182	23.35	24.00	1.161	0.171	0.199
	Band V/RMC 12.2Kbps	Right Tilt	4182	23.35	24.00	1.161	0.126	0.146
	Band V/RMC 12.2Kbps	Left Cheek	4182	23.35	24.00	1.161	0.141	0.164
	Band V/RMC 12.2Kbps	Left Tilt	4182	23.35	24.00	1.161	0.092	0.107
	Band V/RMC 12.2Kbps	Right Cheek	4132	23.28	24.00	1.180	0.164	0.194
	Band V/RMC 12.2Kbps	Right Cheek	4233	23.26	24.00	1.186	0.163	0.193



Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1g} (W/kg)	Reported SAR _{1g} (W/kg)
6#	LTE Band 5/1RB#0 10M	Right Cheek	20525	23.24	24.00	1.191	0.255	0.304
	LTE Band 5/1RB#0 10M	Right Tilt	20525	23.24	24.00	1.191	0.142	0.169
	LTE Band 5/1RB#0 10M	Left Cheek	20525	23.24	24.00	1.191	0.186	0.222
	LTE Band 5/1RB#0 10M	Left Tilt	20525	23.24	24.00	1.191	0.116	0.138
	LTE Band 5/1RB#0 10M	Right Cheek	20450	23.23	24.00	1.194	0.199	0.238
	LTE Band 5/1RB#0 10M	Right Cheek	20600	23.19	24.00	1.205	0.179	0.216
	LTE Band 5/25RB#0 10M	Right Cheek	20525	22.56	23.00	1.107	0.156	0.173
	LTE Band 5/25RB#0 10M	Right Tilt	20525	22.56	23.00	1.107	0.116	0.128
	LTE Band 5/25RB#0 10M	Left Cheek	20525	22.56	23.00	1.107	0.152	0.168
	LTE Band 5/25RB#0 10M	Left Tilt	20525	22.56	23.00	1.107	0.096	0.106
	LTE Band 5/25RB#0 10M	Right Cheek	20450	22.54	23.00	1.112	0.148	0.165
	LTE Band 5/25RB#0 10M	Right Cheek	20600	22.37	23.00	1.156	0.145	0.168
7#	LTE Band 7/1RB#0 20M	Right Cheek	21100	23.55	24.00	1.109	0.088	0.098
	LTE Band 7/1RB#0 20M	Right Tilt	21100	23.55	24.00	1.109	0.074	0.082
	LTE Band 7/1RB#0 20M	Left Cheek	21100	23.55	24.00	1.109	0.075	0.083
	LTE Band 7/1RB#0 20M	Left Tilt	21100	23.55	24.00	1.109	0.066	0.073
	LTE Band 7/1RB#0 20M	Right Cheek	20850	23.54	24.00	1.112	0.073	0.081
	LTE Band 7/1RB#0 20M	Right Cheek	21350	23.47	24.00	1.130	0.082	0.093
	LTE Band 7/50RB#0 20M	Right Cheek	21100	22.57	23.00	1.104	0.073	0.081
	LTE Band 7/50RB#0 20M	Right Tilt	21100	22.57	23.00	1.104	0.064	0.071
	LTE Band 7/50RB#0 20M	Left Cheek	21100	22.57	23.00	1.104	0.055	0.061
	LTE Band 7/50RB#0 20M	Left Tilt	21100	22.57	23.00	1.104	0.042	0.046
	LTE Band 7/50RB#0 20M	Right Cheek	20850	22.50	23.00	1.122	0.070	0.079
	LTE Band 7/50RB#0 20M	Right Cheek	21350	22.54	23.00	1.112	0.068	0.076
	LTE Band 12/1RB#0 10M	Right Cheek	23095	23.29	24.00	1.178	0.166	0.195
	LTE Band 12/1RB#0 10M	Right Tilt	23095	23.29	24.00	1.178	0.116	0.137
	LTE Band 12/1RB#0 10M	Left Cheek	23095	23.29	24.00	1.178	0.152	0.179
	LTE Band 12/1RB#0 10M	Left Tilt	23095	23.29	24.00	1.178	0.085	0.100
	LTE Band 12/1RB#0 10M	Right Cheek	23060	23.13	24.00	1.222	0.161	0.197
8#	LTE Band 12/1RB#0 10M	Right Cheek	23130	23.18	24.00	1.208	0.176	0.213



Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1g} (W/kg)	Reported SAR _{1g} (W/kg)
	LTE Band 12/25RB#0 10M	Right Cheek	23095	22.66	23.00	1.081	0.152	0.164
	LTE Band 12/25RB#0 10M	Right Tilt	23095	22.66	23.00	1.081	0.097	0.105
	LTE Band 12/25RB#0 10M	Left Cheek	23095	22.66	23.00	1.081	0.139	0.150
	LTE Band 12/25RB#0 10M	Left Tilt	23095	22.66	23.00	1.081	0.069	0.075
	LTE Band 12/25RB#0 10M	Right Cheek	23060	22.56	23.00	1.107	0.155	0.172
	LTE Band 12/25RB#0 10M	Right Cheek	23130	22.57	23.00	1.104	0.158	0.174
9#	LTE Band 13/1RB#0 10M	Right Cheek	23230	23.35	24.00	1.161	0.185	0.215
	LTE Band 13/1RB#0 10M	Right Tilt	23230	23.35	24.00	1.161	0.098	0.114
	LTE Band 13/1RB#0 10M	Left Cheek	23230	23.35	24.00	1.161	0.133	0.154
	LTE Band 13/1RB#0 10M	Left Tilt	23230	23.35	24.00	1.161	0.072	0.084
	LTE Band 13/25RB#0 10M	Right Cheek	23230	22.59	23.00	1.099	0.108	0.119
	LTE Band 13/25RB#0 10M	Right Tilt	23230	22.59	23.00	1.099	0.074	0.081
	LTE Band 13/25RB#0 10M	Left Cheek	23230	22.59	23.00	1.099	0.104	0.114
	LTE Band 13/25RB#0 10M	Left Tilt	23230	22.59	23.00	1.099	0.061	0.067
10#	LTE Band 14/1RB#0 10M	Right Cheek	23330	23.23	24.00	1.194	0.171	0.204
	LTE Band 14/1RB#0 10M	Right Tilt	23330	23.23	24.00	1.194	0.053	0.063
	LTE Band 14/1RB#0 10M	Left Cheek	23330	23.23	24.00	1.194	0.080	0.096
	LTE Band 14/1RB#0 10M	Left Tilt	23330	23.23	24.00	1.194	0.045	0.054
	LTE Band 14/25RB#0 10M	Right Cheek	23330	22.58	23.00	1.102	0.155	0.171
	LTE Band 14/25RB#0 10M	Right Tilt	23330	22.58	23.00	1.102	0.040	0.044
	LTE Band 14/25RB#0 10M	Left Cheek	23330	22.58	23.00	1.102	0.055	0.061
	LTE Band 14/25RB#0 10M	Left Tilt	23330	22.58	23.00	1.102	0.031	0.034
	LTE Band 25/1RB#0 20M	Right Cheek	26365	23.28	24.00	1.180	0.153	0.181
	LTE Band 25/1RB#0 20M	Right Tilt	26365	23.28	24.00	1.180	0.144	0.170
	LTE Band 25/1RB#0 20M	Left Cheek	26365	23.28	24.00	1.180	0.077	0.091
	LTE Band 25/1RB#0 20M	Left Tilt	26365	23.28	24.00	1.180	0.061	0.072
11#	LTE Band 25/1RB#0 20M	Right Cheek	26140	23.23	24.00	1.194	0.160	0.191
	LTE Band 25/1RB#0 20M	Right Cheek	26590	23.23	24.00	1.194	0.155	0.185



Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1g} (W/kg)	Reported SAR _{1g} (W/kg)
	LTE Band 25/50RB#0 20M	Right Cheek	26365	22.54	23.00	1.112	0.142	0.158
	LTE Band 25/50RB#0 20M	Right Tilt	26365	22.54	23.00	1.112	0.133	0.148
	LTE Band 25/50RB#0 20M	Left Cheek	26365	22.54	23.00	1.112	0.061	0.068
	LTE Band 25/50RB#0 20M	Left Tilt	26365	22.54	23.00	1.112	0.047	0.052
	LTE Band 25/50RB#0 20M	Right Cheek	26140	22.48	23.00	1.127	0.144	0.162
	LTE Band 25/50RB#0 20M	Right Cheek	26590	22.46	23.00	1.132	0.140	0.159
	LTE Band 26/1RB#0 15M	Right Cheek	26865	23.25	24.00	1.189	0.152	0.181
	LTE Band 26/1RB#0 15M	Right Tilt	26865	23.25	24.00	1.189	0.122	0.145
	LTE Band 26/1RB#0 15M	Left Cheek	26865	23.25	24.00	1.189	0.142	0.169
	LTE Band 26/1RB#0 15M	Left Tilt	26865	23.25	24.00	1.189	0.087	0.103
	LTE Band 26/1RB#0 15M	Right Cheek	26765	23.21	24.00	1.199	0.127	0.152
12#	LTE Band 26/1RB#0 15M	Right Cheek	26965	23.22	24.00	1.197	0.215	0.257
	LTE Band 26/36RB#0 15M	Right Cheek	26865	22.61	23.00	1.094	0.133	0.145
	LTE Band 26/36RB#0 15M	Right Tilt	26865	22.61	23.00	1.094	0.110	0.120
	LTE Band 26/36RB#0 15M	Left Cheek	26865	22.61	23.00	1.094	0.120	0.131
	LTE Band 26/36RB#0 15M	Left Tilt	26865	22.61	23.00	1.094	0.073	0.080
	LTE Band 26/36RB#0 15M	Right Cheek	26765	22.53	23.00	1.114	0.107	0.119
	LTE Band 26/36RB#0 15M	Right Cheek	26965	22.49	23.00	1.125	0.144	0.162
13#	LTE Band 30/1RB#0 10M	Right Cheek	27710	22.83	23.50	1.167	0.044	0.051
	LTE Band 30/1RB#0 10M	Right Tilt	27710	22.83	23.50	1.167	0.033	0.039
	LTE Band 30/1RB#0 10M	Left Cheek	27710	22.83	23.50	1.167	0.036	0.042
	LTE Band 30/1RB#0 10M	Left Tilt	27710	22.83	23.50	1.167	0.025	0.029
	LTE Band 30/25RB#0 10M	Right Cheek	27710	21.79	22.50	1.178	0.032	0.038
	LTE Band 30/25RB#0 10M	Right Tilt	27710	21.79	22.50	1.178	0.024	0.028
	LTE Band 30/25RB#0 10M	Left Cheek	27710	21.79	22.50	1.178	0.028	0.033
	LTE Band 30/25RB#0 10M	Left Tilt	27710	21.79	22.50	1.178	0.015	0.018
14#	LTE Band 40A/1RB#0 10M	Right Cheek	38750	23.12	24.00	1.225	0.085	0.105
	LTE Band 40A/1RB#0 10M	Right Tilt	38750	23.12	24.00	1.225	0.074	0.091
	LTE Band 40A/1RB#0 10M	Left Cheek	38750	23.12	24.00	1.225	0.072	0.089
	LTE Band 40A/1RB#0 10M	Left Tilt	38750	23.12	24.00	1.225	0.057	0.070



Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1g} (W/kg)	Reported SAR _{1g} (W/kg)
	LTE Band 40A/25RB#0 10M	Right Cheek	38750	22.42	23.00	1.143	0.071	0.082
	LTE Band 40A/25RB#0 10M	Right Tilt	38750	22.42	23.00	1.143	0.062	0.071
	LTE Band 40A/25RB#0 10M	Left Cheek	38750	22.42	23.00	1.143	0.052	0.060
	LTE Band 40A/25RB#0 10M	Left Tilt	38750	22.42	23.00	1.143	0.044	0.051
15#	LTE Band 40B/1RB#0 10M	Right Cheek	39200	23.14	24.00	1.219	0.074	0.091
	LTE Band 40B/1RB#0 10M	Right Tilt	39200	23.14	24.00	1.219	0.062	0.076
	LTE Band 40B/1RB#0 10M	Left Cheek	39200	23.14	24.00	1.219	0.065	0.080
	LTE Band 40B/1RB#0 10M	Left Tilt	39200	23.14	24.00	1.219	0.052	0.064
	LTE Band 40B/25RB#0 10M	Right Cheek	39200	22.35	23.00	1.161	0.065	0.076
	LTE Band 40B/25RB#0 10M	Right Tilt	39200	22.35	23.00	1.161	0.041	0.048
	LTE Band 40B/25RB#0 10M	Left Cheek	39200	22.35	23.00	1.161	0.046	0.054
	LTE Band 40B/25RB#0 10M	Left Tilt	39200	22.35	23.00	1.161	0.031	0.036
	LTE Band 41/1RB#0 20M	Right Cheek	40640	23.12	24.00	1.225	0.310	0.382
	LTE Band 41/1RB#0 20M	Right Tilt	40640	23.12	24.00	1.225	0.267	0.329
	LTE Band 41/1RB#0 20M	Left Cheek	40640	23.12	24.00	1.225	0.183	0.225
	LTE Band 41/1RB#0 20M	Left Tilt	40640	23.12	24.00	1.225	0.111	0.137
	LTE Band 41/1RB#0 20M	Right Cheek	40140	23.11	24.00	1.227	0.279	0.345
	LTE Band 41/1RB#0 20M	Right Cheek	40390	23.10	24.00	1.230	0.287	0.355
	LTE Band 41/1RB#0 20M	Right Cheek	40890	23.07	24.00	1.239	0.291	0.363
16#	LTE Band 41/1RB#0 20M	Right Cheek	41140	23.09	24.00	1.233	0.339	0.421
	LTE Band 41/50RB#0 20M	Right Cheek	40640	22.43	23.00	1.140	0.286	0.328
	LTE Band 41/50RB#0 20M	Right Tilt	40640	22.43	23.00	1.140	0.213	0.244
	LTE Band 41/50RB#0 20M	Left Cheek	40640	22.43	23.00	1.140	0.134	0.154
	LTE Band 41/50RB#0 20M	Left Tilt	40640	22.43	23.00	1.140	0.092	0.106
	LTE Band 41/50RB#0 20M	Right Cheek	40140	22.22	23.00	1.197	0.251	0.302
	LTE Band 41/50RB#0 20M	Right Cheek	40390	22.42	23.00	1.143	0.249	0.286
	LTE Band 41/50RB#0 20M	Right Cheek	40890	22.41	23.00	1.146	0.255	0.294
	LTE Band 41/50RB#0 20M	Right Cheek	41140	22.36	23.00	1.159	0.256	0.298
	LTE Band 66/1RB#0 20M	Right Cheek	132322	23.41	24.00	1.146	0.160	0.183
	LTE Band 66/1RB#0 20M	Right Tilt	132322	23.41	24.00	1.146	0.145	0.166
	LTE Band 66/1RB#0 20M	Left Cheek	132322	23.41	24.00	1.146	0.029	0.033



	LTE Band 66/1RB#0 20M	Left Tilt	132322	23.41	24.00	1.146	0.023	0.026
	LTE Band 66/1RB#0 20M	Right Cheek	132072	23.30	24.00	1.175	0.168	0.197
17#	LTE Band 66/1RB#0 20M	Right Cheek	132572	23.32	24.00	1.169	0.198	0.232
	LTE Band 66/50RB#0 20M	Right Cheek	132322	22.58	23.00	1.102	0.135	0.149
	LTE Band 66/50RB#0 20M	Right Tilt	132322	22.58	23.00	1.102	0.121	0.133
	LTE Band 66/50RB#0 20M	Left Cheek	132322	22.58	23.00	1.102	0.025	0.028
	LTE Band 66/50RB#0 20M	Left Tilt	132322	22.58	23.00	1.102	0.020	0.022
	LTE Band 66/50RB#0 20M	Right Cheek	132072	22.51	23.00	1.119	0.145	0.162
	LTE Band 66/50RB#0 20M	Right Cheek	132572	22.54	23.00	1.112	0.159	0.177
	LTE Band 71/1RB#0 20M	Right Cheek	133322	23.21	24.00	1.199	0.100	0.120
	LTE Band 71/1RB#0 20M	Right Tilt	133322	23.21	24.00	1.199	0.085	0.102
	LTE Band 71/1RB#0 20M	Left Cheek	133322	23.21	24.00	1.199	0.092	0.110
	LTE Band 71/1RB#0 20M	Left Tilt	133322	23.21	24.00	1.199	0.074	0.089
18#	LTE Band 71/1RB#0 20M	Right Cheek	133222	23.14	24.00	1.219	0.117	0.143
	LTE Band 71/1RB#0 20M	Right Cheek	133372	23.18	24.00	1.208	0.098	0.118
	LTE Band 71/50RB#0 20M	Right Cheek	133322	22.47	23.00	1.130	0.090	0.102
	LTE Band 71/50RB#0 20M	Right Tilt	133322	22.47	23.00	1.130	0.074	0.084
	LTE Band 71/50RB#0 20M	Left Cheek	133322	22.47	23.00	1.130	0.082	0.093
	LTE Band 71/50RB#0 20M	Left Tilt	133322	22.47	23.00	1.130	0.061	0.069
	LTE Band 71/50RB#0 20M	Right Cheek	133222	22.25	23.00	1.189	0.091	0.108
	LTE Band 71/50RB#0 20M	Right Cheek	133372	22.33	23.00	1.167	0.081	0.095
	WLAN2.4GHz/802.11b	Right Cheek	6	15.55	16.00	1.109	0.212	0.235
	WLAN2.4GHz/802.11b	Right Tilt	6	15.55	16.00	1.109	0.186	0.206
19#	WLAN2.4GHz/802.11b	Left Cheek	6	15.55	16.00	1.109	0.923	1.024
	WLAN2.4GHz/802.11b	Left Tilt	6	15.55	16.00	1.109	0.721	0.800
	WLAN2.4GHz/802.11b	Left Cheek	1	14.95	15.50	1.135	0.724	0.822
	WLAN2.4GHz/802.11b	Left Cheek	11	15.38	16.00	1.153	0.834	0.962
	WLAN5.2GHz/802.11a	Right Cheek	48	14.84	15.50	1.164	0.143	0.172
	WLAN5.2GHz/802.11a	Right Tilt	48	14.84	15.50	1.164	0.153	0.185
20#	WLAN5.2GHz/802.11a	Left Cheek	48	14.84	15.50	1.164	0.489	0.590
	WLAN5.2GHz/802.11a	Left Tilt	48	14.84	15.50	1.164	0.338	0.408
	WLAN5.2GHz/802.11a	Left Cheek	36	14.55	15.00	1.109	0.416	0.478
	WLAN5.2GHz/802.11a	Left Cheek	44	14.62	15.00	1.091	0.500	0.565



	WLAN5.3GHz/802.11a	Right Cheek	52	14.82	15.50	1.169	0.319	0.387
	WLAN5.3GHz/802.11a	Right Tilt	52	14.82	15.50	1.169	0.347	0.420
	WLAN5.3GHz/802.11a	Left Cheek	52	14.82	15.50	1.169	0.518	0.628
	WLAN5.3GHz/802.11a	Left Tilt	52	14.82	15.50	1.169	0.452	0.548
	WLAN5.3GHz/802.11a	Left Cheek	60	14.62	15.00	1.091	0.684	0.773
21#	WLAN5.3GHz/802.11a	Left Cheek	64	14.63	15.00	1.089	0.914	1.031
	WLAN5.8GHz/802.11a	Right Cheek	149	14.29	15.00	1.178	0.052	0.064
	WLAN5.8GHz/802.11a	Right Tilt	149	14.29	15.00	1.178	0.053	0.065
22#	WLAN5.8GHz/802.11a	Left Cheek	149	14.29	15.00	1.178	0.148	0.181
	WLAN5.8GHz/802.11a	Left Tilt	149	14.29	15.00	1.178	0.095	0.116
	WLAN5.8GHz/802.11a	Left Cheek	157	13.95	14.50	1.135	0.149	0.175
	WLAN5.8GHz/802.11a	Left Cheek	165	13.90	14.50	1.148	0.140	0.167

Note:

1. Per KDB 447498 D01v06, for each exposure position, if the highest output power channel Reported SAR $\leq 0.8\text{W/kg}$, other channels SAR testing is not necessary.
2. Per KDB 865664 D01v01r04, for each frequency band, repeated SAR measurement is required when the measured SAR is $\geq 0.8\text{W/kg}$.
3. Per KDB 941225 D05v02r05, 100% RB allocation SAR measurement is not required when the highest reported SAR for 1 RB and 50% RB allocation are $\leq 0.8\text{W/kg}$.
4. Per KDB 248227 D01v02r02, for 802.11b DSSS, when the reported SAR of the highest measured maximum output power channel for the exposure configuration is $\leq 0.8\text{W/kg}$, no further SAR testing is required in that exposure configuration.
5. Per KDB 248227 D01v02r02, OFDM SAR is not required when the highest reported SAR for DSSS is adjusted by the ratio of OFDM to DSSS specified maximum output power and the adjusted SAR is $\leq 1.2\text{W/kg}$.
6. According to KDB 865664 D02v01r02, SAR plot is required for the highest measured SAR in each exposure configuration, wireless mode and frequency band combination.
7. The WLAN Reported 1g SAR (W/kg) has been calculated together with the duty cycle scaling factor 1.0 for 2.4G WLAN, 1.036 for 5GHz WLAN.



16.3. Body SAR Data

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1g} (W/kg)	Reported SAR _{1g} (W/kg)
	GPRS 850(2 TX slots)	Front Side	189	31.74	32.50	1.191	0.357	0.425
	GPRS 850(2 TX slots)	Back Side	189	31.74	32.50	1.191	0.437	0.521
	GPRS 850(2 TX slots)	Left Side	189	31.74	32.50	1.191	0.271	0.323
	GPRS 850(2 TX slots)	Right Side	189	31.74	32.50	1.191	0.359	0.428
	GPRS 850(2 TX slots)	Bottom Side	189	31.74	32.50	1.191	0.245	0.292
23#	GPRS 850(2 TX slots)	Back Side	128	31.68	32.50	1.208	0.484	0.585
	GPRS 850(2 TX slots)	Back Side	251	31.66	32.50	1.213	0.368	0.447
	GPRS 1900(4 TX slots)	Front Side	661	25.24	26.00	1.191	0.208	0.248
	GPRS 1900(4 TX slots)	Back Side	661	25.24	26.00	1.191	0.367	0.437
	GPRS 1900(4 TX slots)	Left Side	661	25.24	26.00	1.191	0.043	0.051
	GPRS 1900(4 TX slots)	Right Side	661	25.24	26.00	1.191	0.151	0.180
	GPRS 1900(4 TX slots)	Bottom Side	661	25.24	26.00	1.191	0.164	0.195
	GPRS 1900(4 TX slots)	Back Side	512	25.12	26.00	1.225	0.356	0.436
24#	GPRS 1900(4 TX slots)	Back Side	810	25.20	26.00	1.202	0.376	0.452
	Band II/RMC 12.2Kbps	Front Side	9400	22.61	23.00	1.094	0.254	0.278
	Band II/RMC 12.2Kbps	Back Side	9400	22.61	23.00	1.094	0.405	0.443
	Band II/RMC 12.2Kbps	Left Side	9400	22.61	23.00	1.094	0.050	0.054
	Band II/RMC 12.2Kbps	Right Side	9400	22.61	23.00	1.094	0.200	0.219
	Band II/RMC 12.2Kbps	Bottom Side	9400	22.61	23.00	1.094	0.186	0.203
25#	Band II/RMC 12.2Kbps	Back Side	9262	22.58	23.00	1.102	0.438	0.482
	Band II/RMC 12.2Kbps	Back Side	9538	22.54	23.00	1.112	0.375	0.417
	Band IV/RMC 12.2Kbps	Front Side	1413	22.87	23.50	1.156	0.377	0.436
	Band IV/RMC 12.2Kbps	Back Side	1413	22.87	23.50	1.156	0.709	0.820
	Band IV/RMC 12.2Kbps	Left Side	1413	22.87	23.50	1.156	0.033	0.038
	Band IV/RMC 12.2Kbps	Right Side	1413	22.87	23.50	1.156	0.263	0.304
	Band IV/RMC 12.2Kbps	Bottom Side	1413	22.87	23.50	1.156	0.611	0.706
26#	Band IV/RMC 12.2Kbps	Back Side	1312	22.86	23.50	1.159	0.797	0.924
	Band IV/RMC 12.2Kbps	Back Side	1513	22.76	23.50	1.186	0.627	0.743



Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1g} (W/kg)	Reported SAR _{1g} (W/kg)
	Band V/RMC 12.2Kbps	Front Side	4182	23.35	24.00	1.161	0.202	0.235
	Band V/RMC 12.2Kbps	Back Side	4182	23.35	24.00	1.161	0.265	0.308
	Band V/RMC 12.2Kbps	Left Side	4182	23.35	24.00	1.161	0.131	0.152
	Band V/RMC 12.2Kbps	Right Side	4182	23.35	24.00	1.161	0.190	0.221
	Band V/RMC 12.2Kbps	Bottom Side	4182	23.35	24.00	1.161	0.144	0.167
27#	Band V/RMC 12.2Kbps	Back Side	4132	23.28	24.00	1.180	0.285	0.336
	Band V/RMC 12.2Kbps	Back Side	4233	23.26	24.00	1.186	0.241	0.286
	LTE Band 5/1RB#0 10M	Front Side	20525	23.24	24.00	1.191	0.234	0.279
	LTE Band 5/1RB#0 10M	Back Side	20525	23.24	24.00	1.191	0.295	0.351
	LTE Band 5/1RB#0 10M	Left Side	20525	23.24	24.00	1.191	0.129	0.154
	LTE Band 5/1RB#0 10M	Right Side	20525	23.24	24.00	1.191	0.193	0.230
	LTE Band 5/1RB#0 10M	Bottom Side	20525	23.24	24.00	1.191	0.147	0.175
28#	LTE Band 5/1RB#0 10M	Back Side	20450	23.23	24.00	1.194	0.307	0.367
	LTE Band 5/1RB#0 10M	Back Side	20600	23.19	24.00	1.205	0.278	0.335
	LTE Band 5/25RB#0 10M	Front Side	20525	22.56	23.00	1.107	0.200	0.221
	LTE Band 5/25RB#0 10M	Back Side	20525	22.56	23.00	1.107	0.243	0.269
	LTE Band 5/25RB#0 10M	Left Side	20525	22.56	23.00	1.107	0.092	0.102
	LTE Band 5/25RB#0 10M	Right Side	20525	22.56	23.00	1.107	0.100	0.111
	LTE Band 5/25RB#0 10M	Bottom Side	20525	22.56	23.00	1.107	0.100	0.111
	LTE Band 5/25RB#0 10M	Back Side	20450	22.54	23.00	1.112	0.297	0.330
	LTE Band 5/25RB#0 10M	Back Side	20600	22.37	23.00	1.156	0.251	0.290
	LTE Band 7/1RB#0 20M	Front Side	21100	23.55	24.00	1.109	0.342	0.379
	LTE Band 7/1RB#0 20M	Back Side	21100	23.55	24.00	1.109	1.060	1.176
	LTE Band 7/1RB#0 20M	Left Side	21100	23.55	24.00	1.109	0.087	0.096
	LTE Band 7/1RB#0 20M	Right Side	21100	23.55	24.00	1.109	0.114	0.126
	LTE Band 7/1RB#0 20M	Bottom Side	21100	23.55	24.00	1.109	0.797	0.884
	LTE Band 7/1RB#0 20M	Back Side	20850	23.54	24.00	1.112	0.974	1.083
29#	LTE Band 7/1RB#0 20M	Back Side	21350	23.47	24.00	1.130	1.060	1.198
	LTE Band 7/1RB#0 20M	Bottom Side	20850	23.54	24.00	1.112	0.732	0.814
	LTE Band 7/1RB#0 20M	Bottom Side	21350	23.47	24.00	1.130	0.797	0.900



Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1g} (W/kg)	Reported SAR _{1g} (W/kg)
	LTE Band 7/50RB#0 20M	Front Side	21100	22.57	23.00	1.104	0.286	0.316
	LTE Band 7/50RB#0 20M	Back Side	21100	22.57	23.00	1.104	0.821	0.906
	LTE Band 7/50RB#0 20M	Left Side	21100	22.57	23.00	1.104	0.046	0.051
	LTE Band 7/50RB#0 20M	Right Side	21100	22.57	23.00	1.104	0.082	0.091
	LTE Band 7/50RB#0 20M	Bottom Side	21100	22.57	23.00	1.104	0.625	0.690
	LTE Band 7/50RB#0 20M	Back Side	20850	22.50	23.00	1.122	0.842	0.945
	LTE Band 7/50RB#0 20M	Back Side	21350	22.54	23.00	1.112	0.833	0.926
	LTE Band 7/100RB#0 20M	Back Side	21350	22.33	23.00	1.167	0.865	1.009
	LTE Band 12/1RB#0 10M	Front Side	23095	23.29	24.00	1.178	0.202	0.238
	LTE Band 12/1RB#0 10M	Back Side	23095	23.29	24.00	1.178	0.271	0.319
	LTE Band 12/1RB#0 10M	Left Side	23095	23.29	24.00	1.178	0.156	0.184
	LTE Band 12/1RB#0 10M	Right Side	23095	23.29	24.00	1.178	0.207	0.244
	LTE Band 12/1RB#0 10M	Bottom Side	23095	23.29	24.00	1.178	0.048	0.057
	LTE Band 12/1RB#0 10M	Back Side	23060	23.13	24.00	1.222	0.277	0.338
30#	LTE Band 12/1RB#0 10M	Back Side	23130	23.18	24.00	1.208	0.318	0.384
	LTE Band 12/25RB#0 10M	Front Side	23095	22.66	23.00	1.081	0.168	0.182
	LTE Band 12/25RB#0 10M	Back Side	23095	22.66	23.00	1.081	0.232	0.251
	LTE Band 12/25RB#0 10M	Left Side	23095	22.66	23.00	1.081	0.143	0.155
	LTE Band 12/25RB#0 10M	Right Side	23095	22.66	23.00	1.081	0.177	0.191
	LTE Band 12/25RB#0 10M	Bottom Side	23095	22.66	23.00	1.081	0.045	0.049
	LTE Band 12/25RB#0 10M	Back Side	23060	22.56	23.00	1.107	0.254	0.281
	LTE Band 12/25RB#0 10M	Back Side	23130	22.57	23.00	1.104	0.255	0.282
	LTE Band 13/1RB#0 10M	Front Side	23230	23.35	24.00	1.161	0.179	0.208
31#	LTE Band 13/1RB#0 10M	Back Side	23230	23.35	24.00	1.161	0.223	0.259
	LTE Band 13/1RB#0 10M	Left Side	23230	23.35	24.00	1.161	0.145	0.168
	LTE Band 13/1RB#0 10M	Right Side	23230	23.35	24.00	1.161	0.243	0.282
	LTE Band 13/1RB#0 10M	Bottom Side	23230	23.35	24.00	1.161	0.104	0.121
	LTE Band 13/25RB#0 10M	Front Side	23230	22.59	23.00	1.099	0.140	0.154
	LTE Band 13/25RB#0 10M	Back Side	23230	22.59	23.00	1.099	0.178	0.196
	LTE Band 13/25RB#0 10M	Left Side	23230	22.59	23.00	1.099	0.113	0.124
	LTE Band 13/25RB#0 10M	Right Side	23230	22.59	23.00	1.099	0.197	0.217
	LTE Band 13/25RB#0 10M	Bottom Side	23230	22.59	23.00	1.099	0.082	0.090



Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1g} (W/kg)	Reported SAR _{1g} (W/kg)
	LTE Band 14/1RB#0 10M	Front Side	23330	23.23	24.00	1.194	0.140	0.167
32#	LTE Band 14/1RB#0 10M	Back Side	23330	23.23	24.00	1.194	0.200	0.239
	LTE Band 14/1RB#0 10M	Left Side	23330	23.23	24.00	1.194	0.118	0.141
	LTE Band 14/1RB#0 10M	Right Side	23330	23.23	24.00	1.194	0.109	0.130
	LTE Band 14/1RB#0 10M	Bottom Side	23330	23.23	24.00	1.194	0.082	0.098
	LTE Band 14/25RB#0 10M	Front Side	23330	22.58	23.00	1.102	0.122	0.134
	LTE Band 14/25RB#0 10M	Back Side	23330	22.58	23.00	1.102	0.153	0.169
	LTE Band 14/25RB#0 10M	Left Side	23330	22.58	23.00	1.102	0.084	0.093
	LTE Band 14/25RB#0 10M	Right Side	23330	22.58	23.00	1.102	0.091	0.100
	LTE Band 14/25RB#0 10M	Bottom Side	23330	22.58	23.00	1.102	0.037	0.041
	LTE Band 25/1RB#0 20M	Front Side	26365	23.28	24.00	1.180	0.282	0.333
	LTE Band 25/1RB#0 20M	Back Side	26365	23.28	24.00	1.180	0.461	0.544
	LTE Band 25/1RB#0 20M	Left Side	26365	23.28	24.00	1.180	0.057	0.067
	LTE Band 25/1RB#0 20M	Right Side	26365	23.28	24.00	1.180	0.217	0.256
	LTE Band 25/1RB#0 20M	Bottom Side	26365	23.28	24.00	1.180	0.184	0.217
33#	LTE Band 25/1RB#0 20M	Back Side	26140	23.23	24.00	1.194	0.476	0.568
	LTE Band 25/1RB#0 20M	Back Side	26590	23.23	24.00	1.194	0.436	0.521
	LTE Band 25/50RB#0 20M	Front Side	26365	22.54	23.00	1.112	0.243	0.270
	LTE Band 25/50RB#0 20M	Back Side	26365	22.54	23.00	1.112	0.358	0.398
	LTE Band 25/50RB#0 20M	Left Side	26365	22.54	23.00	1.112	0.026	0.029
	LTE Band 25/50RB#0 20M	Right Side	26365	22.54	23.00	1.112	0.182	0.202
	LTE Band 25/50RB#0 20M	Bottom Side	26365	22.54	23.00	1.112	0.162	0.180
	LTE Band 25/50RB#0 20M	Back Side	26140	22.48	23.00	1.127	0.366	0.413
	LTE Band 25/50RB#0 20M	Back Side	26590	22.46	23.00	1.132	0.359	0.407
	LTE Band 26/1RB#0 15M	Front Side	26865	23.25	24.00	1.189	0.199	0.237
	LTE Band 26/1RB#0 15M	Back Side	26865	23.25	24.00	1.189	0.265	0.315
	LTE Band 26/1RB#0 15M	Left Side	26865	23.25	24.00	1.189	0.148	0.176
	LTE Band 26/1RB#0 15M	Right Side	26865	23.25	24.00	1.189	0.180	0.214
	LTE Band 26/1RB#0 15M	Bottom Side	26865	23.25	24.00	1.189	0.123	0.146
	LTE Band 26/1RB#0 15M	Back Side	26765	23.21	24.00	1.199	0.245	0.294
34#	LTE Band 26/1RB#0 15M	Back Side	26965	23.22	24.00	1.197	0.275	0.329



Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1q} (W/kg)	Reported SAR _{1q} (W/kg)
	LTE Band 26/36RB#0 15M	Front Side	26865	22.61	23.00	1.094	0.166	0.182
	LTE Band 26/36RB#0 15M	Back Side	26865	22.61	23.00	1.094	0.215	0.235
	LTE Band 26/36RB#0 15M	Left Side	26865	22.61	23.00	1.094	0.117	0.128
	LTE Band 26/36RB#0 15M	Right Side	26865	22.61	23.00	1.094	0.139	0.152
	LTE Band 26/36RB#0 15M	Bottom Side	26865	22.61	23.00	1.094	0.103	0.113
	LTE Band 26/36RB#0 15M	Back Side	26765	22.53	23.00	1.114	0.203	0.226
	LTE Band 26/36RB#0 15M	Back Side	26965	22.49	23.00	1.125	0.240	0.270
	LTE Band 30/1RB#0 10M	Front Side	27710	22.83	23.50	1.167	0.427	0.498
35#	LTE Band 30/1RB#0 10M	Back Side	27710	22.83	23.50	1.167	0.915	1.068
	LTE Band 30/1RB#0 10M	Left Side	27710	22.83	23.50	1.167	0.088	0.102
	LTE Band 30/1RB#0 10M	Right Side	27710	22.83	23.50	1.167	0.207	0.242
	LTE Band 30/1RB#0 10M	Bottom Side	27710	22.83	23.50	1.167	0.839	0.979
	LTE Band 30/25RB#0 10M	Front Side	27710	21.79	22.50	1.178	0.416	0.490
	LTE Band 30/25RB#0 10M	Back Side	27710	21.79	22.50	1.178	0.842	0.992
	LTE Band 30/25RB#0 10M	Left Side	27710	21.79	22.50	1.178	0.097	0.114
	LTE Band 30/25RB#0 10M	Right Side	27710	21.79	22.50	1.178	0.158	0.186
	LTE Band 30/25RB#0 10M	Bottom Side	27710	21.79	22.50	1.178	0.790	0.930
	LTE Band 30/50RB#0 10M	Back Side	27710	21.77	22.50	1.183	0.816	0.965
	LTE Band 40A/1RB#0 10M	Front Side	38750	23.12	24.00	1.225	0.198	0.244
36#	LTE Band 40A/1RB#0 10M	Back Side	38750	23.12	24.00	1.225	0.462	0.569
	LTE Band 40A/1RB#0 10M	Left Side	38750	23.12	24.00	1.225	0.045	0.055
	LTE Band 40A/1RB#0 10M	Right Side	38750	23.12	24.00	1.225	0.079	0.097
	LTE Band 40A/1RB#0 10M	Bottom Side	38750	23.12	24.00	1.225	0.375	0.462
	LTE Band 40A/25RB#0 10M	Front Side	38750	22.42	23.00	1.143	0.165	0.190
	LTE Band 40A/25RB#0 10M	Back Side	38750	22.42	23.00	1.143	0.383	0.440
	LTE Band 40A/25RB#0 10M	Left Side	38750	22.42	23.00	1.143	0.037	0.043
	LTE Band 40A/25RB#0 10M	Right Side	38750	22.42	23.00	1.143	0.064	0.074
	LTE Band 40A/25RB#0 10M	Bottom Side	38750	22.42	23.00	1.143	0.318	0.366
	LTE Band 40B/1RB#0 10M	Front Side	39200	23.14	24.00	1.219	0.172	0.211
37#	LTE Band 40B/1RB#0 10M	Back Side	39200	23.14	24.00	1.219	0.438	0.537
	LTE Band 40B/1RB#0 10M	Left Side	39200	23.14	24.00	1.219	0.042	0.052



	LTE Band 40B/1RB#0 10M	Right Side	39200	23.14	24.00	1.219	0.059	0.072
	LTE Band 40B/1RB#0 10M	Bottom Side	39200	23.14	24.00	1.219	0.350	0.429
	LTE Band 40B/25RB#0 10M	Front Side	39200	22.35	23.00	1.161	0.136	0.159
	LTE Band 40B/25RB#0 10M	Back Side	39200	22.35	23.00	1.161	0.353	0.412
	LTE Band 40B/25RB#0 10M	Left Side	39200	22.35	23.00	1.161	0.033	0.039
	LTE Band 40B/25RB#0 10M	Right Side	39200	22.35	23.00	1.161	0.046	0.054
	LTE Band 40B/25RB#0 10M	Bottom Side	39200	22.35	23.00	1.161	0.282	0.329
	LTE Band 41/1RB#0 20M	Front Side	40640	23.12	24.00	1.225	0.071	0.088
38#	LTE Band 41/1RB#0 20M	Back Side	40640	23.12	24.00	1.225	0.444	0.547
	LTE Band 41/1RB#0 20M	Left Side	40640	23.12	24.00	1.225	0.026	0.033
	LTE Band 41/1RB#0 20M	Right Side	40640	23.12	24.00	1.225	0.032	0.040
	LTE Band 41/1RB#0 20M	Bottom Side	40640	23.12	24.00	1.225	0.315	0.388
	LTE Band 41/1RB#0 20M	Back Side	40140	23.11	24.00	1.227	0.409	0.505
	LTE Band 41/1RB#0 20M	Back Side	40390	23.10	24.00	1.230	0.435	0.538
	LTE Band 41/1RB#0 20M	Back Side	40890	23.07	24.00	1.239	0.392	0.489
	TE Band 41/1RB#0 20M	Back Side	41140	23.09	24.00	1.233	0.310	0.385
	LTE Band 41/50RB#0 20M	Front Side	40640	22.43	23.00	1.140	0.057	0.066
	LTE Band 41/50RB#0 20M	Back Side	40640	22.43	23.00	1.140	0.244	0.280
	LTE Band 41/50RB#0 20M	Left Side	40640	22.43	23.00	1.140	0.016	0.018
	LTE Band 41/50RB#0 20M	Right Side	40640	22.43	23.00	1.140	0.025	0.029
	LTE Band 41/50RB#0 20M	Bottom Side	40640	22.43	23.00	1.140	0.212	0.243
	LTE Band 41/50RB#0 20M	Back Side	40140	22.22	23.00	1.197	0.222	0.267
	LTE Band 41/50RB#0 20M	Back Side	40390	22.42	23.00	1.143	0.235	0.270
	LTE Band 66/1RB#0 20M	Front Side	132322	23.41	24.00	1.146	0.446	0.511
	LTE Band 66/1RB#0 20M	Back Side	132322	23.41	24.00	1.146	0.780	0.894
	LTE Band 66/1RB#0 20M	Left Side	132322	23.41	24.00	1.146	0.039	0.045
	LTE Band 66/1RB#0 20M	Right Side	132322	23.41	24.00	1.146	0.313	0.359
	LTE Band 66/1RB#0 20M	Bottom Side	132322	23.41	24.00	1.146	0.769	0.881
	LTE Band 66/1RB#0 20M	Back Side	132070	23.30	24.00	1.175	0.751	0.882
39#	LTE Band 66/1RB#0 20M	Back Side	132572	23.32	24.00	1.169	0.814	0.952
	LTE Band 66/1RB#0 20M	Bottom Side	132070	23.30	24.00	1.175	0.733	0.861
	LTE Band 66/1RB#0 20M	Bottom Side	132572	23.32	24.00	1.169	0.796	0.931
	LTE Band 66/100RB#0 20M	Back Side	132572	22.34	23.00	1.164	0.680	0.792



	LTE Band 66/50RB#0 20M	Front Side	132322	22.58	23.00	1.102	0.259	0.285
	LTE Band 66/50RB#0 20M	Back Side	132322	22.58	23.00	1.102	0.632	0.696
	LTE Band 66/50RB#0 20M	Left Side	132322	22.58	23.00	1.102	0.026	0.029
	LTE Band 66/50RB#0 20M	Right Side	132322	22.58	23.00	1.102	0.215	0.237
	LTE Band 66/50RB#0 20M	Bottom Side	132322	22.58	23.00	1.102	0.612	0.674
	LTE Band 66/50RB#0 20M	Back Side	132070	22.51	23.00	1.119	0.622	0.696
	LTE Band 66/50RB#0 20M	Back Side	132572	22.54	23.00	1.112	0.628	0.698
	LTE Band 71/1RB#0 20M	Front Side	133322	23.21	24.00	1.199	0.330	0.396
40#	LTE Band 71/1RB#0 20M	Back Side	133322	23.21	24.00	1.199	0.453	0.543
	LTE Band 71/1RB#0 20M	Left Side	133322	23.21	24.00	1.199	0.242	0.290
	LTE Band 71/1RB#0 20M	Right Side	133322	23.21	24.00	1.199	0.392	0.470
	LTE Band 71/1RB#0 20M	Bottom Side	133322	23.21	24.00	1.199	0.121	0.145
	LTE Band 71/1RB#0 20M	Back Side	133222	23.14	24.00	1.219	0.327	0.399
	LTE Band 71/1RB#0 20M	Back Side	133372	23.18	24.00	1.208	0.276	0.333
	LTE Band 71/50RB#0 20M	Front Side	133322	22.47	23.00	1.130	0.156	0.176
	LTE Band 71/50RB#0 20M	Back Side	133322	22.47	23.00	1.130	0.193	0.218
	LTE Band 71/50RB#0 20M	Left Side	133322	22.47	23.00	1.130	0.082	0.093
	LTE Band 71/50RB#0 20M	Right Side	133322	22.47	23.00	1.130	0.120	0.136
	LTE Band 71/50RB#0 20M	Bottom Side	133322	22.47	23.00	1.130	0.092	0.104
	LTE Band 71/50RB#0 20M	Back Side	133222	22.25	23.00	1.189	0.182	0.216
	LTE Band 71/50RB#0 20M	Back Side	133372	22.33	23.00	1.167	0.189	0.221
	WLAN2.4GHz/802.11b	Front Side	6	15.55	16.00	1.109	0.181	0.201
41#	WLAN2.4GHz/802.11b	Back Side	6	15.55	16.00	1.109	0.185	0.205
	WLAN2.4GHz/802.11b	Left Side	6	15.55	16.00	1.109	0.016	0.017
	WLAN2.4GHz/802.11b	Right Side	6	15.55	16.00	1.109	0.217	0.241
	WLAN2.4GHz/802.11b	Top Side	6	15.55	16.00	1.109	0.151	0.167
	WLAN2.4GHz/802.11b	Right Side	1	14.95	15.50	1.135	0.212	0.241
42#	WLAN2.4GHz/802.11b	Right Side	11	15.38	16.00	1.153	0.221	0.255
	WLAN5.2GHz/802.11a	Front Side	48	14.84	15.50	1.164	0.226	0.273
43#	WLAN5.2GHz/802.11a	Back Side	48	14.84	15.50	1.164	0.257	0.310
	WLAN5.2GHz/802.11a	Left Side	48	14.84	15.50	1.164	0.021	0.025
44#	WLAN5.2GHz/802.11a	Right Side	48	14.84	15.50	1.164	0.326	0.393
	WLAN5.2GHz/802.11a	Top Side	48	14.84	15.50	1.164	0.262	0.316
	WLAN5.2GHz/802.11a	Right Side	36	14.55	15.00	1.109	0.269	0.309



	WLAN5.2GHz/802.11a	Right Side	44	14.62	15.00	1.091	0.307	0.347
	WLAN5.3GHz/802.11a	Front Side	52	14.82	15.50	1.169	0.147	0.178
	WLAN5.3GHz/802.11a	Back Side	52	14.82	15.50	1.169	0.195	0.236
	WLAN5.3GHz/802.11a	Back Side	60	14.62	15.00	1.091	0.222	0.251
45#	WLAN5.3GHz/802.11a	Back Side	64	14.63	15.00	1.089	0.235	0.265
	WLAN5.8GHz/802.11a	Front Side	149	14.29	15.00	1.178	0.035	0.043
	WLAN5.8GHz/802.11a	Back Side	149	14.29	15.00	1.178	0.101	0.123
	WLAN5.8GHz/802.11a	Left Side	149	14.29	15.00	1.178	0.006	0.007
	WLAN5.8GHz/802.11a	Right Side	149	14.29	15.00	1.178	0.062	0.076
	WLAN5.8GHz/802.11a	Top Side	149	14.29	15.00	1.178	0.078	0.095
	WLAN5.8GHz/802.11a	Back Side	157	13.95	14.50	1.135	0.166	0.195
46#	WLAN5.8GHz/802.11a	Back Side	165	13.90	14.50	1.148	0.165	0.196
	Bluetooth/1Mbps	Front Side	39	11.34	12.00	1.164	0.038	0.048
47#	Bluetooth/1Mbps	Back Side	39	11.34	12.00	1.164	0.044	0.055
	Bluetooth/1Mbps	Left Side	39	11.34	12.00	1.164	0.009	0.011
	Bluetooth/1Mbps	Right Side	39	11.34	12.00	1.164	0.012	0.015
	Bluetooth/1Mbps	Top Side	39	11.34	12.00	1.164	0.022	0.028
	Bluetooth/1Mbps	Back Side	0	9.63	10.00	1.089	0.041	0.048

Note:

1. The WLAN Reported 1g SAR (W/kg) has been calculated together with the duty cycle scaling factor 1.0 for 2.4G WLAN, 1.036 for 5G WLAN.
2. According to 2016 Oct. TCB workshop for Bluetooth SAR consideration and the theoretical duty cycle is 83.3%, therefore the actual duty cycle will be scaled up to the theoretical value of Bluetooth reported SAR calculation. The duty cycle of Bluetooth is 76.8%, Therefore the duty cycle scaling factor 1.085 should be used to calculating the reported SAR.



16.4. Repeated SAR Assessment

In accordance with published RF Exposure KDB procedure 865664 D01 SAR measurement 100 MHz to 6 GHz. These additional measurements are repeated after the completion of all measurements requiring the same head or body tissue-equivalent medium in a frequency band. The test device should be returned to ambient conditions (normal room temperature) with the battery fully charged before it is re-mounted on the device holder for the repeated measurement(s) to minimize any unexpected variations in the repeated results.

- 1) Repeated measurement is not required when the original highest measured SAR is < 0.80 W/kg; steps 2) through 4) do not apply.
- 2) When the original highest measured SAR is ≥ 0.80 W/kg, repeat that measurement once.
- 3) Perform a second repeated measurement only if the ratio of largest to smallest SAR for the original and first repeated measurements is > 1.20 or when the original or repeated measurement is ≥ 1.45 W/kg (~ 10% from the 1-g SAR limit).
- 4) Perform a third repeated measurement only if the original, first or second repeated measurement is ≥ 1.5 W/kg and the ratio of largest to smallest SAR for the original, first and second repeated measurements is > 1.20 .

➤ Repeated SAR

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{1g} (W/kg)	Reported SAR _{1g} (W/kg)
OR.	WLAN2.4GHz/802.11b	Left Cheek	6	15.55	16.00	1.109	0.923	1.024
1 st	WLAN2.4GHz/802.11b	Left Cheek	6	15.55	16.00	1.109	0.921	1.022
OR.	WLAN5.3GHz/802.11a	Left Cheek	64	14.63	15.00	1.089	0.914	1.031
1 st	WLAN5.3GHz/802.11a	Left Cheek	64	14.63	15.00	1.089	0.911	1.028
OR.	LTE Band 7/1RB#0 20M	Back Side	21350	23.47	24.00	1.130	1.060	1.198
1 st	LTE Band 7/1RB#0 20M	Back Side	21350	23.47	24.00	1.130	1.055	1.192
OR.	LTE Band 30/1RB#0 10M	Back Side	27710	22.83	23.50	1.167	0.915	1.068
1 st	LTE Band 30/1RB#0 10M	Back Side	27710	22.83	23.50	1.167	0.912	1.064
OR.	LTE Band 66/1RB#0 20M	Back Side	132572	23.32	24.00	1.169	0.814	0.952
1 st	LTE Band 66/1RB#0 20M	Back Side	132572	23.32	24.00	1.169	0.813	0.951

16.5. Extremity SAR Assessment

Guidance:

1. According to KDB 648747 D04v01r03 The UMPC mini-tablet procedures must also be applied to test the SAR of all surfaces and edges with an antenna located at ≤ 25 mm from that surface or edge, in direct contact with a flat phantom, for 10-g extremity SAR according to the body-equivalent tissue dielectric parameters in KDB Publication 865664 D01 to address interactive hand use exposure conditions.
2. When hotspot mode applies, 10-g extremity SAR is required only for the surfaces and edges with hotspot mode 1-g reported SAR > 1.2 W/kg.
3. According to the user manual, the EUT diagonal size is greater than 16cm, therefore the 0mm extremity SAR of WLAN 5GHz is required.
4. Test results as below:

Plot No.	Band/Mode	Test Position	CH.	Ave. Power (dBm)	Tune-up Limit (dBm)	Tune-up Scaling Factor	Meas. SAR _{10g} (W/kg)	Reported SAR _{10g} (W/kg)
	WLAN5.3GHz/802.11a	Front Side	52	14.82	15.50	1.169	0.389	0.471
	WLAN5.3GHz/802.11a	Back Side	52	14.82	15.50	1.169	0.682	0.826
	WLAN5.3GHz/802.11a	Back Side	60	14.62	15.00	1.091	0.757	0.856
48#	WLAN5.3GHz/802.11a	Back Side	64	14.63	15.00	1.089	0.778	0.878

17. Simultaneous Transmission Evaluation

17.1. Simultaneous Transmission Consideration

No.	Simultaneous Transmission Consideration	Head	Body-Worn	Hotspot
1	WWAN(2G/3G/4G)+WLAN 2.4GHz	Yes	Yes	Yes
2	WWAN(2G/3G/4G)+WLAN 5.2GHz/ WLAN 5.8GHz	Yes	Yes	Yes
3	WWAN(2G/3G/4G)+WLAN 5.3GHz	Yes	Yes	No
4	WWAN(2G/3G/4G)+Bluetooth	No	Yes	Yes

Note:

- When the user enables the personal wireless router functions for the handset, actual operations include simultaneous transmission of both the Wi-Fi transmitter and another WWAN transmitter. Both the transmitters do not transmit at the same transmitting frequency and thus cannot be evaluated for SAR under actual use conditions. The "Portable Hotspot" feature on the handset was NOT activated, to ensure the SAR measurements were evaluated for a single transmission frequency RF signal.
- The hotspot SAR result may overlap with the body-worn accessory SAR requirements, per KDB 941225 D06, the more conservative configurations can be considered, thus excluding some unnecessary body-worn accessory SAR tests.
- Simultaneous Transmission SAR evaluation is not required for BT and Wi-Fi, because the software mechanism have been incorporated to guarantee that the WLAN and Bluetooth transmitters would not simultaneously operate.
- Per KDB 447498D01v06, simultaneous transmission SAR evaluation procedures is as followed:
 - Step 1: If sum of 1 g SAR < 1.6 W/kg, Simultaneous SAR measurement is not required.
 - Step 2: If sum of 1 g SAR > 1.6 W/kg, ratio of SAR to peak separation distance for pair of transmitters calculated.
 - Step 3: If the ratio of SAR to peak separation distance is ≤ 0.04 , Simultaneous SAR measurement is not required.
 - Step 4: If the ratio of SAR to peak separation distance is > 0.04 , Simultaneous SAR measurement is required and simultaneous transmission SAR value is calculated.
(The ratio is determined by: $(SAR1 + SAR2) \wedge 1.5/Ri \leq 0.04$,
Ri is the separation distance between the peak SAR locations for the antenna pair in mm.

17.2. Simultaneous Transmission Analysis

➤ Head Simultaneous Transmission for WWAN(2/3/4G)+WLAN 2.4GHz/WLAN 5GHz

WWAN Band	Exposure Position	1	2	3	1+2 Summed 1g SAR (W/kg)	1+3 Summed 1g SAR (W/kg)
		WWAN	2.4GHz WLAN	5GHz WLAN		
		1g SAR (W/kg)	1g SAR (W/kg)	1g SAR (W/kg)		
GSM850	Right Cheek	0.360	0.235	0.387	0.595	0.747
	Right Tilt	0.229	0.206	0.420	0.435	0.649
	Left Cheek	0.289	1.024	1.031	1.313	1.320
	Left Tilt	0.185	0.800	0.548	0.985	0.733
GSM1900	Right Cheek	0.104	0.235	0.387	0.339	0.491
	Right Tilt	0.089	0.206	0.420	0.295	0.509
	Left Cheek	0.076	1.024	1.031	1.100	1.107
	Left Tilt	0.062	0.800	0.548	0.862	0.610
WCDMA Band II	Right Cheek	0.108	0.235	0.387	0.343	0.495
	Right Tilt	0.089	0.206	0.420	0.295	0.509
	Left Cheek	0.082	1.024	1.031	1.106	1.113
	Left Tilt	0.071	0.800	0.548	0.871	0.619
WCDMA Band IV	Right Cheek	0.152	0.235	0.387	0.387	0.539
	Right Tilt	0.066	0.206	0.420	0.272	0.486
	Left Cheek	0.040	1.024	1.031	1.064	1.071
	Left Tilt	0.031	0.800	0.548	0.831	0.579
WCDMA Band V	Right Cheek	0.199	0.235	0.387	0.434	0.586
	Right Tilt	0.146	0.206	0.420	0.352	0.566
	Left Cheek	0.164	1.024	1.031	1.188	1.195
	Left Tilt	0.107	0.800	0.548	0.907	0.655
LTE Band 5	Right Cheek	0.304	0.235	0.387	0.539	0.691
	Right Tilt	0.169	0.206	0.420	0.375	0.589
	Left Cheek	0.222	1.024	1.031	1.246	1.253
	Left Tilt	0.138	0.800	0.548	0.938	0.686
LTE Band 7	Right Cheek	0.098	0.235	0.387	0.333	0.485
	Right Tilt	0.082	0.206	0.420	0.288	0.502
	Left Cheek	0.083	1.024	1.031	1.107	1.114
	Left Tilt	0.073	0.800	0.548	0.873	0.621
LTE Band 12	Right Cheek	0.213	0.235	0.387	0.448	0.600
	Right Tilt	0.137	0.206	0.420	0.343	0.557



	Left Cheek	0.179	1.024	1.031	1.203	1.210
	Left Tilt	0.100	0.800	0.548	0.900	0.648
LTE Band 13	Right Cheek	0.215	0.235	0.387	0.450	0.602
	Right Tilt	0.114	0.206	0.420	0.320	0.534
	Left Cheek	0.154	1.024	1.031	1.178	1.185
	Left Tilt	0.084	0.800	0.548	0.884	0.632
LTE Band 14	Right Cheek	0.204	0.235	0.387	0.439	0.591
	Right Tilt	0.063	0.206	0.420	0.269	0.483
	Left Cheek	0.096	1.024	1.031	1.120	1.127
	Left Tilt	0.054	0.800	0.548	0.854	0.602
LTE Band 25	Right Cheek	0.191	0.235	0.387	0.426	0.578
	Right Tilt	0.170	0.206	0.420	0.376	0.590
	Left Cheek	0.091	1.024	1.031	1.115	1.122
	Left Tilt	0.072	0.800	0.548	0.872	0.620
LTE Band 26	Right Cheek	0.257	0.235	0.387	0.492	0.644
	Right Tilt	0.145	0.206	0.420	0.351	0.565
	Left Cheek	0.169	1.024	1.031	1.193	1.200
	Left Tilt	0.103	0.800	0.548	0.903	0.651
LTE Band 30	Right Cheek	0.051	0.235	0.387	0.286	0.438
	Right Tilt	0.039	0.206	0.420	0.245	0.459
	Left Cheek	0.042	1.024	1.031	1.066	1.073
	Left Tilt	0.029	0.800	0.548	0.829	0.577
LTE Band 40A	Right Cheek	0.105	0.235	0.387	0.340	0.492
	Right Tilt	0.091	0.206	0.420	0.297	0.511
	Left Cheek	0.089	1.024	1.031	1.113	1.120
	Left Tilt	0.070	0.800	0.548	0.870	0.618
LTE Band 40B	Right Cheek	0.091	0.235	0.387	0.326	0.478
	Right Tilt	0.076	0.206	0.420	0.282	0.496
	Left Cheek	0.080	1.024	1.031	1.104	1.111
	Left Tilt	0.064	0.800	0.548	0.864	0.612
LTE Band 41	Right Cheek	0.421	0.235	0.387	0.656	0.808
	Right Tilt	0.329	0.206	0.420	0.535	0.749
	Left Cheek	0.225	1.024	1.031	1.249	1.256
	Left Tilt	0.137	0.800	0.548	0.937	0.685
LTE Band 66	Right Cheek	0.232	0.235	0.387	0.467	0.619
	Right Tilt	0.166	0.206	0.420	0.372	0.586
	Left Cheek	0.033	1.024	1.031	1.057	1.064
	Left Tilt	0.026	0.800	0.548	0.826	0.574



LTE Band 71	Right Cheek	0.143	0.235	0.387	0.378	0.530
	Right Tilt	0.102	0.206	0.420	0.308	0.522
	Left Cheek	0.110	1.024	1.031	1.134	1.141
	Left Tilt	0.089	0.800	0.548	0.889	0.637

➤ **Body Simultaneous Transmission for WWAN(2/3/4G)+WLAN 2.4GHz/WLAN 5GHz/BT**

WWAN Band	Exposure Position	1	2	3	4	1+2 Summed 1g SAR (W/kg)	1+3 Summed 1g SAR (W/kg)	1+4 Summed 1g SAR (W/kg)
		WWAN 1g SAR (W/kg)	2.4GHz WLAN 1g SAR (W/kg)	5GHz WLAN 1g SAR (W/kg)	Bluetooth Estimated 1g SAR (W/kg)			
GSM850	Front	0.425	0.201	0.273	0.048	0.626	0.698	0.473
	Back	0.585	0.205	0.310	0.055	0.790	0.895	0.640
	Left side	0.323	0.017	0.025	0.011	0.340	0.348	0.334
	Right side	0.428	0.255	0.393	0.015	0.683	0.821	0.443
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.292	0.000	0.000	0.000	0.292	0.292	0.292
GSM1900	Front	0.248	0.201	0.273	0.048	0.449	0.521	0.296
	Back	0.452	0.205	0.310	0.055	0.657	0.762	0.507
	Left side	0.051	0.017	0.025	0.011	0.068	0.076	0.062
	Right side	0.180	0.255	0.393	0.015	0.435	0.573	0.195
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.195	0.000	0.000	0.000	0.195	0.195	0.195
WCDMA Band II	Front	0.278	0.201	0.273	0.048	0.479	0.551	0.326
	Back	0.482	0.205	0.310	0.055	0.687	0.792	0.537
	Left side	0.054	0.017	0.025	0.011	0.071	0.079	0.065
	Right side	0.219	0.255	0.393	0.015	0.474	0.612	0.234
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.203	0.000	0.000	0.000	0.203	0.203	0.203
WCDMA Band IV	Front	0.436	0.201	0.273	0.048	0.637	0.709	0.484
	Back	0.924	0.205	0.310	0.055	1.129	1.234	0.979
	Left side	0.038	0.017	0.025	0.011	0.055	0.063	0.049
	Right side	0.304	0.255	0.393	0.015	0.559	0.697	0.319
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.706	0.000	0.000	0.000	0.706	0.706	0.706
WCDMA Band V	Front	0.235	0.201	0.273	0.048	0.436	0.508	0.283
	Back	0.336	0.205	0.310	0.055	0.541	0.646	0.391



	Left side	0.152	0.017	0.025	0.011	0.169	0.177	0.163
	Right side	0.221	0.255	0.393	0.015	0.476	0.614	0.236
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.167	0.000	0.000	0.000	0.167	0.167	0.167
LTE Band 5	Front	0.279	0.201	0.273	0.048	0.480	0.552	0.327
	Back	0.367	0.205	0.310	0.055	0.572	0.677	0.422
	Left side	0.154	0.017	0.025	0.011	0.171	0.179	0.165
	Right side	0.230	0.255	0.393	0.015	0.485	0.623	0.245
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.175	0.000	0.000	0.000	0.175	0.175	0.175
LTE Band 7	Front	0.379	0.201	0.273	0.048	0.580	0.652	0.427
	Back	1.198	0.205	0.310	0.055	1.403	1.508	1.253
	Left side	0.096	0.017	0.025	0.011	0.113	0.121	0.107
	Right side	0.126	0.255	0.393	0.015	0.381	0.519	0.141
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.884	0.000	0.000	0.000	0.884	0.884	0.884
LTE Band 12	Front	0.238	0.201	0.273	0.048	0.439	0.511	0.286
	Back	0.384	0.205	0.310	0.055	0.589	0.694	0.439
	Left side	0.184	0.017	0.025	0.011	0.201	0.209	0.195
	Right side	0.244	0.255	0.393	0.015	0.499	0.637	0.259
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.057	0.000	0.000	0.000	0.057	0.057	0.057
LTE Band 13	Front	0.208	0.201	0.273	0.048	0.409	0.481	0.256
	Back	0.259	0.205	0.310	0.055	0.464	0.569	0.314
	Left side	0.168	0.017	0.025	0.011	0.185	0.193	0.179
	Right side	0.282	0.255	0.393	0.015	0.537	0.675	0.297
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.121	0.000	0.000	0.000	0.121	0.121	0.121
LTE Band 14	Front	0.167	0.201	0.273	0.048	0.368	0.440	0.215
	Back	0.239	0.205	0.310	0.055	0.444	0.549	0.294
	Left side	0.141	0.017	0.025	0.011	0.158	0.166	0.152
	Right side	0.130	0.255	0.393	0.015	0.385	0.523	0.145
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.098	0.000	0.000	0.000	0.098	0.098	0.098
LTE Band 25	Front	0.333	0.201	0.273	0.048	0.534	0.606	0.381
	Back	0.568	0.205	0.310	0.055	0.773	0.878	0.623
	Left side	0.067	0.017	0.025	0.011	0.084	0.092	0.078
	Right side	0.256	0.255	0.393	0.015	0.511	0.649	0.271



	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.217	0.000	0.000	0.000	0.217	0.217	0.217
LTE Band 26	Front	0.237	0.201	0.273	0.048	0.438	0.510	0.285
	Back	0.329	0.205	0.310	0.055	0.534	0.639	0.384
	Left side	0.176	0.017	0.025	0.011	0.193	0.201	0.187
	Right side	0.214	0.255	0.393	0.015	0.469	0.607	0.229
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.146	0.000	0.000	0.000	0.146	0.146	0.146
LTE Band 30	Front	0.498	0.201	0.273	0.048	0.699	0.771	0.546
	Back	1.068	0.205	0.310	0.055	1.273	1.378	1.123
	Left side	0.114	0.017	0.025	0.011	0.131	0.139	0.125
	Right side	0.242	0.255	0.393	0.015	0.497	0.635	0.257
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.979	0.000	0.000	0.000	0.979	0.979	0.979
LTE Band 40A	Front	0.244	0.201	0.273	0.048	0.445	0.517	0.292
	Back	0.569	0.205	0.310	0.055	0.774	0.879	0.624
	Left side	0.055	0.017	0.025	0.011	0.072	0.080	0.066
	Right side	0.097	0.255	0.393	0.015	0.352	0.490	0.112
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.462	0.000	0.000	0.000	0.462	0.462	0.462
LTE Band 40B	Front	0.211	0.201	0.273	0.048	0.412	0.484	0.259
	Back	0.537	0.205	0.310	0.055	0.742	0.847	0.592
	Left side	0.052	0.017	0.025	0.011	0.069	0.077	0.063
	Right side	0.072	0.255	0.393	0.015	0.327	0.465	0.087
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.429	0.000	0.000	0.000	0.429	0.429	0.429
LTE Band 41	Front	0.088	0.201	0.273	0.048	0.289	0.361	0.136
	Back	0.547	0.205	0.310	0.055	0.752	0.857	0.602
	Left side	0.033	0.017	0.025	0.011	0.050	0.058	0.044
	Right side	0.040	0.255	0.393	0.015	0.295	0.433	0.055
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.388	0.000	0.000	0.000	0.388	0.388	0.388
LTE Band 66	Front	0.511	0.201	0.273	0.048	0.712	0.784	0.559
	Back	0.952	0.205	0.310	0.055	1.157	1.262	1.007
	Left side	0.045	0.017	0.025	0.011	0.062	0.070	0.056
	Right side	0.359	0.255	0.393	0.015	0.614	0.752	0.374
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.931	0.000	0.000	0.000	0.931	0.931	0.931



LTE Band 71	Front	0.396	0.201	0.273	0.048	0.597	0.669	0.444
	Back	0.543	0.205	0.310	0.055	0.748	0.853	0.598
	Left side	0.290	0.017	0.025	0.011	0.307	0.315	0.301
	Right side	0.470	0.255	0.393	0.015	0.725	0.863	0.485
	Top side	0.000	0.167	0.316	0.028	0.167	0.316	0.028
	Bottom side	0.145	0.000	0.000	0.000	0.145	0.145	0.145

18. Uncertainty Assessment

The component of uncertainty may generally be categorized according to the methods used to evaluate them. The evaluation of uncertainty by the statistical analysis of a series of observations is termed a Type A evaluation of uncertainty. The evaluation of uncertainty by means other than the statistical analysis of a series of observation is termed a Type B evaluation of uncertainty. Each component of uncertainty, however evaluated, is represented by an estimated standard deviation, termed standard uncertainty, which is determined by the positive square root of the estimated variance.

A Type A evaluation of standard uncertainty may be based on any valid statistical method for treating data. This includes calculating the standard deviation of the mean of a series of independent observations; using the method of least squares to fit a curve to the data in order to estimate the parameter of the curve and their standard deviations; or carrying out an analysis of variance in order to identify and quantify random effects in certain kinds of measurement.

A type B evaluation of standard uncertainty is typically based on scientific judgment using all of the relevant information available. These may include previous measurement data, experience, and knowledge of the behavior and properties of relevant materials and instruments, manufacture's specification, data provided in calibration reports and uncertainties assigned to reference data taken from handbooks. Broadly speaking, the uncertainty is either obtained from an outdoor source or obtained from an assumed distribution, such as the normal distribution, rectangular or triangular distributions indicated in table below.

Uncertainty	Normal	Rectangular	Triangular	U-Shape
Multi-plying Factor ^(a)	$1/k^{(b)}$	$1/\sqrt{3}$	$1/\sqrt{6}$	$1/\sqrt{2}$

Standard Uncertainty for Assumed Distribution

(a) standard uncertainty is determined as the product of the multiplying factor and the estimated range of variations in the measured quantity

(b) κ is the coverage factor

The combined standard uncertainty of the measurement result represents the estimated standard deviation of the result. It is obtained by combining the individual standard uncertainties of both Type A and Type B evaluation using the usual "root-sum-squares" (RSS) methods of combining standard deviations by taking the positive square root of the estimated variances.

Expanded uncertainty is a measure of uncertainty that defines an interval about the measurement result within which the measured value is confidently believed to lie. It is obtained by multiplying the combined standard uncertainty by a coverage factor. Typically, the coverage factor ranges from 2 to 3. Using a coverage factor allows the true value of a measured quantity to be specified with a



defined probability within the specified uncertainty range. For purpose of this document, a coverage factor two is used, which corresponds to confidence interval of about 95 %. The DASy uncertainty Budget is shown in the following tables.

Error Description	Uncertainty Value (±%)	Probability	Divisor	(Ci) 1g	(Ci) 10g	Standard Uncertainty (1g) (±%)	Standard Uncertainty (10g) (±%)
Measurement System							
Probe Calibration	6.0	N	1	1	1	6.0	6.0
Axial Isotropy	4.7	R	1.732	0.7	0.7	1.9	1.9
Hemispherical Isotropy	9.6	R	1.732	0.7	0.7	3.9	3.9
Boundary Effects	1.0	R	1.732	1	1	0.6	0.6
Linearity	4.7	R	1.732	1	1	2.7	2.7
System Detection Limits	1.0	R	1.732	1	1	0.6	0.6
Modulation Response	3.2	R	1.732	1	1	1.8	1.8
Readout Electronics	0.3	N	1	1	1	0.3	0.3
Response Time	0.0	R	1.732	1	1	0.0	0.0
Integration Time	2.6	R	1.732	1	1	1.5	1.5
RF Ambient Noise	3.0	R	1.732	1	1	1.7	1.7
RF Ambient Reflections	3.0	R	1.732	1	1	1.7	1.7
Probe Positioner	0.4	R	1.732	1	1	0.2	0.2
Probe Positioning	2.9	R	1.732	1	1	1.7	1.7
Max. SAR Eval.	2.0	R	1.732	1	1	1.2	1.2
Test Sample Related							
Device Positioning	3.0	N	1	1	1	3.0	3.0
Device Holder	3.6	N	1	1	1	0.089	0.089
Power Drift	5.0	R	1.732	1	1	2.9	2.9
Power Scaling	0.0	R	1.732	1	1	0.0	0.0
Phantom and Setup							
Phantom Uncertainty	6.1	R	1.732	1	1	3.5	3.5
SAR correction	0.0	R	1.732	1	0.84	0.0	0.0
Liquid Conductivity Repeatability	0.2	N	1	0.78	0.71	0.1	0.1
Liquid Conductivity (target)	5.0	R	1.732	0.78	0.71	2.3	2.0
Liquid Conductivity (mea.)	2.5	R	1.732	0.78	0.71	1.1	1.0
Temp. unc. - Conductivity	3.4	R	1.732	0.78	0.71	1.5	1.4
Liquid Permittivity Repeatability	0.15	N	1	0.23	0.26	0.0	0.0
Liquid Permittivity (target)	5.0	R	1.732	0.23	0.26	0.7	0.8
Liquid Permittivity (mea.)	2.5	R	1.732	0.23	0.26	0.3	0.4
Temp. unc. - Permittivity	0.83	R	1.732	0.23	0.26	0.1	0.1
Combined Std. Uncertainty						11.4%	11.4%
Coverage Factor for 95 %						K=2	K=2
Expanded STD Uncertainty						22.9%	22.7%



Error Description	Uncertainty Value (±%)	Probability	Divisor	(Ci) 1g	(Ci) 10g	Standard Uncertainty (1g) (±%)	Standard Uncertainty (10g) (±%)
Measurement System							
Probe Calibration	6.55	N	1	1	1	6.0	6.0
Axial Isotropy	4.7	R	1.732	0.7	0.7	1.9	1.9
Hemispherical Isotropy	9.6	R	1.732	0.7	0.7	3.9	3.9
Boundary Effects	2.0	R	1.732	1	1	1.2	1.2
Linearity	4.7	R	1.732	1	1	2.7	2.7
System Detection Limits	1.0	R	1.732	1	1	0.6	0.6
Modulation Response	3.2	R	1.732	1	1	1.8	1.8
Readout Electronics	0.3	N	1	1	1	0.3	0.3
Response Time	0.0	R	1.732	1	1	0.0	0.0
Integration Time	2.6	R	1.732	1	1	1.5	1.5
RF Ambient Noise	3.0	R	1.732	1	1	1.7	1.7
RF Ambient Reflections	3.0	R	1.732	1	1	1.7	1.7
Probe Positioner	0.4	R	1.732	1	1	0.2	0.2
Probe Positioning	6.7	R	1.732	1	1	3.9	3.9
Max. SAR Eval.	4.0	R	1.732	1	1	2.3	2.3
Test Sample Related							
Device Positioning	3.0	N	1	1	1	3.0	3.0
Device Holder	3.6	N	1	1	1	0.089	0.089
Power Drift	5.0	R	1.732	1	1	2.9	2.9
Power Scaling	0.0	R	1.732	1	1	0.0	0.0
Phantom and Setup							
Phantom Uncertainty	6.1	R	1.732	1	1	3.8	3.8
SAR correction	0.0	R	1.732	1	0.84	0.0	0.0
Liquid Conductivity Repeatability	0.2	N	1	0.78	0.71	0.1	0.1
Liquid Conductivity (target)	5.0	R	1.732	0.78	0.71	2.3	2.0
Liquid Conductivity (mea.)	2.5	R	1.732	0.78	0.71	1.1	1.0
Temp. unc. - Conductivity	3.4	R	1.732	0.78	0.71	1.5	1.4
Liquid Permittivity Repeatability	0.15	N	1	0.23	0.26	0.0	0.0
Liquid Permittivity (target)	5.0	R	1.732	0.23	0.26	0.7	0.8
Liquid Permittivity (mea.)	2.5	R	1.732	0.23	0.26	0.3	0.4
Temp. unc. - Permittivity	0.83	R	1.732	0.23	0.26	0.1	0.1
Combined Std. Uncertainty						12.5%	12.5%
Coverage Factor for 95 %						K=2	K=2
Expanded STD Uncertainty						25.1 %	25.1%



Annex A General Information

1. Identification of the Responsible Testing Laboratory

Laboratory Name:	Shenzhen Morlab Communications Technology Co., Ltd.
Laboratory Address:	FL.1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block 67, BaoAn District, ShenZhen, GuangDong Province, P. R. China
Telephone:	+86 755 36698555
Facsimile:	+86 755 36698525

2. Identification of the Responsible Testing Location

Name:	Shenzhen Morlab Communications Technology Co., Ltd.
Address:	FL.1-3, Building A, FeiYang Science Park, No.8 LongChang Road, Block 67, BaoAn District, ShenZhen, GuangDong Province, P. R. China

3. Facilities and Accreditations

All measurement facilities used to collect the measurement data are located at FL.3, Building A, FeiYang Science Park, Block 67, BaoAn District, Shenzhen, 518101 P. R. China. Morlab facility is a registered (7183A) test laboratory with the site description on file with ISED.

Note:

The main report is end here and the other Annex (B,C,D,E) will be submitted separately.

***** END OF MAIN REPORT *****