

## RF Exposure evaluation

According to 447498 D04 Interim General RF Exposure Guidance v01

$$P_{th} (\text{mW}) = \begin{cases} ERP_{20\text{ cm}}(d/20\text{ cm})^x & d \leq 20\text{ cm} \\ ERP_{20\text{ cm}} & 20\text{ cm} < d \leq 40\text{ cm} \end{cases} \quad (\text{B.2})$$

where

$$x = -\log_{10} \left( \frac{60}{ERP_{20\text{ cm}}\sqrt{f}} \right)$$

$$P_{th} (\text{mW}) = ERP_{20\text{ cm}} (\text{mW}) = \begin{cases} 2040f & 0.3 \text{ GHz} \leq f < 1.5 \text{ GHz} \\ 3060 & 1.5 \text{ GHz} \leq f \leq 6 \text{ GHz} \end{cases} \quad (\text{B.1})$$

Table B.2—Example Power Thresholds (mW)

Frequency (MHz)	Distance (mm)									
	5	10	15	20	25	30	35	40	45	50
300	39	65	88	110	129	148	166	184	201	217
450	22	44	67	89	112	135	158	180	203	226
835	9	25	44	66	90	116	145	175	207	240
1900	3	12	26	44	66	92	122	157	195	236
2450	3	10	22	38	59	83	111	143	179	219
3600	2	8	18	32	49	71	96	125	158	195
5800	1	6	14	25	40	58	80	106	136	169

$$\text{eirp} = \text{pt} \times \text{gt} = (\text{Exd})^2/30$$

where:

pt = transmitter output power in watts,

gt = numeric gain of the transmitting antenna (unitless),

E = electric field strength in V/m, ---  $10^{((\text{dBuV/m})/20)}/10^6$

d = measurement distance in meters (m)---3m

$$\text{Sopt} = (\text{Exd})^2/30 \times \text{gt}$$

Ant gain = -2.0dBi so Ant numeric gain= 0.631

Field strength = 86.83dB $\mu$ V/m @3m@433.92MHz

$$\text{So Pt} = \{ [10^{(86.83/20)}/10^6 \times 3]^2 / (30 \times 0.631) \} \times 1000 \text{ mW} = 0.229 \text{ mW} < 23.1657 \text{ mW}$$

Then SAR evaluation is not required