成品尺寸：110*80mm，材质：封面180g铜板纸（表面覆哑膜）+内页128g铜版纸

VeGue

www.vegustech.com
support@vegustech.com
If you have any questions, please feel free to contact us.

MADE IN CHINA

FC CE UK CA RoHS

VeGue

INSTRUCTION MANUAL

VWGO | 2.4G Wireless Microphone

Greetings from VeGue

Thanks for choosing VWGO Lavalier Microphone. We established a robust brand with great-value products and customer-friendly service here. Our designer spares no effort to write the user manual. Hope the manual could effectively help you to know roughly our microphone and deal with any problems when using it. We hustle day and night work out with our engineer and designer on the microphone for better quality and user experience. If you have any questions, please feel free to contact us.

Have fun with our microphone!

VeGue Team

1 EN

PACKAGE LIST



2 EN

FUNCTION

1. TRANSMITTER



① Power Indicator
② USB-C Charging Port
③ Mic Jack
④ Clipper
⑤ Pair Indicator
⑥ Power Button/Pair Button
⑦ In-built Mic

2. RECEIVER



① Power Indicator
② USB-C Charging Port
③ Power Button/Pair Button
④ Headphone Output
⑤ Pair Indicator
⑥ Vol-
⑦ Vol+
⑧ Clipper

3 EN

INSTRUCTIONS

1. Indicator

Status	Power Indicator(red)	Pair Indicator(blue)
Turn on/off	Light power	Power on
Pairing status	/	In pairing
Quick flash 3 times, then off	Power off	/
Keep on and solid	Charging(on); Full Charge(off)	Complete pairing

2. Operating

1. Power
Hold down the power button for 2 seconds to turn on/off the machine.

2. Pair
Automatically pairing when power on. To pair manually, please make sure both the transmitter and receiver are turned off, then simultaneously hold down both power button and volume button of RX receiver for 3 seconds to turn it on for pairing. Then, turn on the transmitter and it will pair automatically.

3. Install
The Transmitter can be clipped to your clothes. And the Receiver can be clipped to camera/phone.

4 EN

4. Connect
The receiver is able to output the audio to your device via 3.5mm TRS cable(camera) or 3.5mm TRRS cable(phone). Please choose the correct cable according to your device.

5. Record
The Transmitter can record your voice via the built-in mic (equipped with a Furry Windshield) or the extra Lavalier Microphone.

SPECIFCATIONS

1. Transmitter

Wireless Transmission:	Digital 2.4GHz
Frequency:	2403.86MHz-2477.86MHz
Working Distance:	70m(230ft)
Latency:	12.5ms
Audio Input Electronic Level:	≤-10dBV
Output Power:	< 10mW
Power Required:	USB 5V
Battery Type:	Built-in Lithium Battery
Charging Time:	2h
Working Time:	4h

5 EN

2. Receiver

Wireless Transmission:	Digital 2.4GHz
Frequency:	2403.86MHz-2477.86MHz
Working Distance:	70m(230ft)
Latency:	12.5ms
RF Sensitive:	-95dB
Level:	4 Adjust Levels
Power Required:	USB 5V
Battery Type:	Built-in Lithium Battery
Charging Time:	1.5h
Working Time:	4h

3. Microphone



Type:	Built-in/External Lavalier Microphone
Sound Track:	Mono
Polar Pattern:	Omni-directional
Frequency Range:	50Hz-20KHz
Sensitive:	-40±3dB, 20dB (1V/Pa, at 1KHz)
Max SPL:	110dB

Warning:
Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE:
This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) This device must accept any interference received, including interference that may cause undesired operation.

FCC Statement
This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
--Reorient or relocate the receiving antenna.
--Increase the separation between the equipment and receiver.
--Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
--Consult the dealer or an experienced radio/TV technician for help.