

TEST REPORT

Report No.:	BCTC2404071906-1E					
Applicant:	Shenzhen Baseus Technology Co., Ltd.					
Product Name:	Baseus Open-Ear TWS Earbuds					
Test Model:	Baseus PM66-A					
Tested Date:	2024-04-19 to 2024-05-14					
Issued Date:	2024-05-16					
She	enzhen BCTC Testing Co., Ltd.					
No.: BCTC/RF-EMC-005	Page: 1 of 128 Edition: B,2					



FCC ID: 2A482-PM66-A

Product Name:	Baseus Open-Ear TWS Earbuds
Trademark:	baseus
Model/Type Reference:	Baseus PM66-A
Prepared For:	Shenzhen Baseus Technology Co., Ltd.
Address:	2 nd Floor, Building B, Baseus Intelligence Park, No.2008, Xuegang Rd, Gangtou Community, Bantian Street, Longgang District, Shenzhen, China
Manufacturer:	Shenzhen Baseus Technology Co., Ltd.
Address:	2 nd Floor, Building B, Baseus Intelligence Park, No.2008, Xuegang Rd, Gangtou Community, Bantian Street, Longgang District, Shenzhen, China
Prepared By:	Shenzhen BCTC Testing Co., Ltd.
Address:	1-2/F., Building B, Pengzhou Industrial Park, No.158, Fuyuan 1st Road, Zhancheng, Fuhai Subdistrict, Bao'an District, Shenzhen, Guangdong, China
Sample Received Date:	2024-04-19
Sample tested Date:	2024-04-19 to 2024-05-14
Issue Date:	2024-05-16
Report No.:	BCTC2404071906-1E
Test Standards	FCC Part15.247 ANSI C63.10-2013
Test Results	PASS
Remark:	This is Bluetooth Classic radio test report.

Tested by: Shanshan . Zhang

Shanshan. Zhang / Project Handler

Approved by:

Zero Zhou/Reviewer

The test report is effective only with both signature and specialized stamp. This result(s) shown in this report refer only to the sample(s) tested. Without written approval of Shenzhen BCTC Testing Co., Ltd, this report can't be reproduced except in full. The tested sample(s) and the sample information are provided by the client.

No.: BCTC/RF-EMC-005

Page: 2 of 128

Edition: B.2



Table Of Content

Test	Report Declaration F	Page
1.	Version	5
2.	Test Summary	6
3.	Measurement Uncertainty	7
4.	Product Information And Test Setup	8
4.1	Product Information	8
4.2	Test Setup Configuration	8
4.3	Support Equipment	9
4.4	Channel List	9
4.5	Test Mode	
4.6	Table Of Parameters Of Text Software Setting	10
5.	Test Facility And Test Instrument Used	11
5.1	Test Facility	11
5.2	Test Instrument Used	11
6.	Conducted Emissions	13
6.1	Block Diagram Of Test Setup	
6.2	Limit	
6.3	Test procedure	
6.4	EUT operating Conditions	13
6.5	Test Result	
7.	Radiated emissions	
7.1	Block Diagram Of Test Setup	
7.2	Limit	
7.3	Test procedure	
7.4	EUT operating Conditions	
7.5	Test Result	
8.	Radiated Band Emission Measurement And Restricted Bands Of Operati	
8.1	Block Diagram Of Test Setup	
8.2	Limit	24
8.3	Test procedure	
8.4	EUT operating Conditions	25
8.5	Test Result	
9.	Spurious RF Conducted Emissions	
9.1	Block Diagram Of Test Setup	
9.2	Limit Test procedure Test Result	
9.3	Test procedure	
9.4	Test Result	
10.	20 dB Bandwidth Block Diagram Of Test Setup	
10.1	Block Diagram Of Test Setup	
10.2		
10.3	Test Decult	
10.4	I est Result.	
11.	Maximum Peak Output Power	
11.1 11.2	Block Diagram Of Test Setup	ຽງ ດາ
11.2	Limit	03

Page: 3 of 128



11.3 Test procedure	83
11.4 Test Result	
12. Hopping Channel Separation	95
12.1 Block Diagram Of Test Setup	95
12.2 Limit	95
12.3 Test procedure	95
12.4 Test Result	95
13. Number Of Hopping Frequency	107
13.1 Block Diagram Of Test Setup	107
13.2 Limit	
13.3 Test procedure	107
13.4 Test Result	107
14. Dwell Time	112
14.1 Block Diagram Of Test Setup	112
14.2 Limit	112
14.3 Test procedure	112
14.4 Test Result	
15. Antenna Requirement	123
15.1 Limit	123
15.2 Test Result	123
16. EUT Photographs	124
17. EUT Test Setup Photographs	126

(Note: N/A Means Not Applicable)


Page: 4 of 128

Edition: B.2



1. Version

Report No.	Issue Date	Description	Approved
BCTC2404071906-1E	2024-05-16	Original	Valid





2. Test Summary

The Product has been tested according to the following specifications:

No.	Test Parameter	Clause No.	Results
1	Conducted emission AC power port	§15.207	PASS
2	Conducted peak output power for FHSS	§15.247(b)(1)	PASS
3	20dB Occupied bandwidth	§15.247(a)(1)	PASS
4	Hopping channel separation	§15.247(a)(1)	PASS
5	Number of hopping frequencies	§15.247(a)(1)(iii)	PASS
6	Dwell Time	§15.247(a)(1)(iii)	PASS
7	Spurious RF conducted emissions	§15.247(d)	PASS
8	Band edge	§15.247(d)	PASS
9	Spurious radiated emissions for transmitter	§15.247(d) & §15.209 & §15.205	PASS
10	Antenna Requirement	15.203	PASS

No.: BCTC/RF-EMC-005

Page: 6 of 128

Edition: B,2



3. Measurement Uncertainty

Where relevant, the following measurement uncertainty levels have been estimated for tests performed on the Product as specified in CISPR 16-4-2. This uncertainty represents an expanded uncertainty expressed at approximately the 95% confidence level using a coverage factor of k=2.

No.	Item	Uncertainty
1	3m chamber Radiated spurious emission(30MHz-1GHz)	U=4.3dB
2	3m chamber Radiated spurious emission(9KHz-30MHz)	U=3.7dB
3	3m chamber Radiated spurious emission(1GHz-18GHz)	U=4.5dB
4	3m chamber Radiated spurious emission(18GHz-40GHz)	U=3.34dB
5	Conducted Emission (150kHz-30MHz)	U=3.20dB
6	Conducted Adjacent channel power	U=1.38dB
7	Conducted output power uncertainty Above 1G	U=1.576dB
8	Conducted output power uncertainty below 1G	U=1.28dB
9	humidity uncertainty	U=5.3%
10	Temperature uncertainty	U=0.59 ℃

No.: BCTC/RF-EMC-005

Page: 7 of 128

Edition: B,2



4. Product Information And Test Setup

4.1 Product Information

Model/Type reference:	Baseus PM66-A
Model differences:	N/A
Bluetooth Version:	5.0
Hardware Version:	N/A
Software Version:	N/A
Operation Frequency:	2402-2480MHz
Type of Modulation:	GFSK, π/ 4 DQPSK, 8DPSK
Number Of Channel	79CH
Antenna installation:	Internal antenna
Antenna Gain:	 L: -0.95 dBi R: -1.92dBi Remark: The antenna gain of the product comes from the antenna report provided by the customer, and the test data is affected by the customer information. The antenna gain of the product is provided by the customer, and the test data is affected by the customer, and the test data is affected by the customer, and the test data is affected by the customer.
Ratings:	DC 5V from adapter or DC 3.7V from battery

4.2 Test Setup Configuration

See test photographs attached in *EUT TEST SETUP PHOTOGRAPHS* for the actual connections between Product and support equipment.

Conducted Emission:

				\sim , , , , , , , , , , , , , , , , , , ,
	E-1 EUT	<u>C-1</u>	E-2 Adapter	AC
Radia	ated Spurio	ous Emiss	sion	
	E-1 EUT		********	
No.:	BCTC/RF	-EMC-00	5	Page: 8 of 128 Edition: B,2



4.3 Support Equipment

No.	Device Type	Brand	Model	Series No.	Note
E-1	Baseus Open-Ear TWS Earbuds	baseus	Baseus PM66-A	N/A	EUT
E-2	N/A	N/A	N/A	N/A	Auxiliary

ltem	Shielded Type	Ferrite Core	Length	Note
C-1	N/A	N/A	0.5M	DC cable unshielded

Notes:

1. All the equipment/cables were placed in the worst-case configuration to maximize the emission during the test.

2. Grounding was established in accordance with the manufacturer's requirements and conditions for the intended use.

4.4 Channel List

СН	Frequency (MHz)	СН	Frequency (MHz)	СН	Frequency (MHz)	СН	Frequency (MHz)
0	2402	1	2403	2	2404	3	2405
4	2406	5	2407	6	2408	7	2409
8	2410	9	2411	10	2412	11	2413
12	2414	13	2415	14	2416	15	2417
16	2418	17	2419	18	2420	19	2421
20	2422	21	2423	22	2424	23	2425
24	2426	25	2427	26	2428	27	2429
28	2430	29	2431	30	2432	31	2433
32	2434	33	2435	34	2436	35	2437
36	2438	37	2439	38	2440	39	2441
40	2442	41	2443	42	2444	43	2445
44	2446	45	2447	46	2448	47	2449
48	2450	49	2451	50	2452	51	2453
52	2454	53	2455	54	2456	55	2457
56	2458	57	2459	58	2460	59	2461
60	2462	61	2463	62	2464	63	2465
64	2466	65	2467	66	2468	67	2469
68	2470	69	2471	70	2472	71	2473
72	2474	73	2475	74	2476	75	2477
76	2478	77	2479	78	2480	79	



4.5 Test Mode

To investigate the maximum EMI emission characteristics generates from EUT, the test system was pre-scanning tested base on the consideration of following EUT operation mode or test configuration mode which possible have effect on EMI emission level. Each of these EUT operation mode(s) or test configuration mode(s) mentioned above was evaluated respectively.

Test Mode	Test mode	Low channel	Low channel Middle channel			
1	Transmitting(GFSK)	2402MHz	2441MHz	2480MHz		
2	Transmitting(π/ 4 DQPSK)	2402MHz	2441MHz	2480MHz		
3	Transmitting(8DPSK)	2402MHz	2441MHz	2480MHz		
4	Charging (Conducted emission, Radiated emission)					
5.	BT Linking (Radiated emission)					

Note:

(1) The measurements are performed at the highest, middle, lowest available channels.

(2) Fully-charged battery is used during the test

4.6 Table Of Parameters Of Text Software Setting

During testing channel & power controlling software provided by the customer was used to control the operating channel as well as the output power level. The RF output power selection is for the setting of RF output power expected by the customer and is going to be fixed on the firmware of the final end product power parameters

Test software Version		BT FCC Tool V2.24	
Frequency	2402 MHz	2441 MHz	2480 MHz
Parameters	DEF	DEF	DEF



5. Test Facility And Test Instrument Used

5.1 Test Facility

All measurement facilities used to collect the measurement data are located at Shenzhen BCTC Testing Co., Ltd. Address: 1-2/F., Building B, Pengzhou Industrial Park, No.158, Fuyuan 1st Road, Zhancheng, Fuhai Subdistrict, Bao'an District, Shenzhen, Guangdong, China. The site and apparatus are constructed in conformance with the requirements of ANSI C63.4 and CISPR 16-1-1 other equivalent standards. FCC Test Firm Registration Number: 712850

A2LA certificate registration number is: CN1212

ISED Registered No.: 23583

ISED CAB identifier: CN0017

5.2 Test Instrument Used

Conducted Emissions Test							
Equipment Manufacturer Model# Serial# Last Cal.							
Receiver	R&S	ESR3	102075	May 15, 2023	May 14, 2024		
LISN	R&S	ENV216	101375	May 15, 2023	May 14, 2024		
Software	vare Frad EZ-		EMC-CON 3A1	\	\		
Pulse limiter	Schwarzbeck	VTSD9561-F	01323	Sept. 22, 2023	Sept 21, 2024		

	RF Conducted Test								
Equipment	Manufacturer	Model# Serial#		Last Cal.	Next Cal.				
Power meter	Keysight	E4419		May 15, 2023	May 14, 2024				
Power Sensor (AV)	Keysight	E9300A		May 15, 2023	May 14, 2024				
Signal Analyzer20kH z-26.5GHz	Keysight	N9020A	MY49100060	May 15, 2023	May 14, 2024				
Spectrum Analyzer9kHz- 40GHz	R&S	FSP40	100363	May 15, 2023	May 14, 2024				
Radio frequency control box	MAIWEI	MW100-RFC B	and a second						
Software	MAIWEI	MTS 8310	· · · · · · · · · · · · · · · · · · ·		\mathbf{V}				



Radiated Emissions Test (966 Chamber01)							
Equipment	Manufacturer	Model#	Serial#	Last Cal.	Next Cal.		
966 chamber	ChengYu	966 Room	966	May 15, 2023	May 14, 2026		
Receiver	R&S	ESR3	102075	May 15, 2023	May 14, 2024		
Receiver	R&S	ESRP	101154	May 15, 2023	May 14, 2024		
Amplifier	Schwarzbeck	BBV9744	9744-0037	May 15, 2023	May 14, 2024		
TRILOG Broadband Antenna	Schwarzbeck	VULB9163	942	May 29, 2023	May 28, 2024		
Loop Antenna(9KHz -30MHz)	Schwarzbeck	FMZB1519B	00014	May 31, 2023	May 30, 2024		
Amplifier	Amplifier SKET		SK202104090 1	May 15, 2023	May 14, 2024		
Horn Antenna	Schwarzbeck	BBHA9120D	1541	May 31, 2023	May 30, 2024		
Amplifier(18G Hz-40GHz)	MITEQ	TTA1840-35- HG	2034381	May 15, 2023	May 14, 2024		
Horn Antenna18GH z-40GHz)	Schwarzbeck	BBHA9170	00822	May 31, 2023	May 30, 2024		
Spectrum Analyzer9kHz- 40GHz	R&S	FSP40	100363	May 15, 2023	May 14, 2024		
Software	Frad	EZ-EMC	FA-03A2 RE	١	١		


Page: 12 of 128

Edition: B.2



6. Conducted Emissions

6.1 Block Diagram Of Test Setup



6.2 Limit

	Limit (dBuV)			
Frequency (MHz)	Quas-peak	Average		
0.15 -0.5	66 - 56 *	56 - 46 *		
0.50 -5.0	56.00	46.00		
5.0 -30.0	60.00	50.00		

Notes:

1. *Decreasing linearly with logarithm of frequency.

2. The lower limit shall apply at the transition frequencies.

6.3 Test procedure

Receiver Parameters	Setting
Attenuation	10 dB
Start Frequency	0.15 MHz
Stop Frequency	30 MHz
IF Bandwidth	9 kHz

a. The Product was placed on a nonconductive table 0.8 m above the horizontal ground reference plane, and 0.4 m from the vertical ground reference plane, and connected to the main through Line Impedance Stability Network (L.I.S.N).

b. The RBW of the receiver was set at 9 kHz in 150 kHz ~ 30MHz with Peak and AVG detector in Max Hold mode. Run the receiver's pre-scan to record the maximum disturbance generated from Product in all power lines in the full band.

c. For each frequency whose maximum record was higher or close to limit, measure its QP and AVG values and record.


6.4 EUT operating Conditions

The EUT was configured for testing in a typical fashion (as a customer would normally use it). The EUT has been programmed to continuously transmit during test. This operating condition was tested and used to collect the included data.



6.5 Test Result

Temperature:	26 ℃	Relative Humidity:	54%
Pressure:	101KPa	Phase :	L
Test Mode:	Mode 4	Test Voltage :	AC 120V/60Hz




Remark:

All readings are Quasi-Peak and Average values.
 Factor = Insertion Loss + Cable Loss.
 Measurement = Reading Level + Correct Factor
 Over = Measurement - Limit

				_				
No.	Mk.	Freq.	Reading Level	Correct Factor	Measure- ment	Limit	Over	
		MHz		dB	dBu∨	dBuV	dB	Detector
1		0.4736	11.58	19.84	31.42	56.45	-25.03	QP
2		0.4736	1.78	19.84	21.62	46.45	-24.83	AVG
3		0.9136	19.56	19.92	39.48	56.00	-16.52	QP
4	*	0.9136	10.78	19.92	30.70	46.00	-15.30	AVG
5		1.2162	11.99	19.95	31.94	56.00	-24.06	QP
6		1.2162	3.25	19.95	23.20	46.00	-22.80	AVG
7		2.1439	10.21	20.00	30.21	56.00	-25.79	QP
8		2.1439	1.36	20.00	21.36	46.00	-24.64	AVG
9		2.7502	9.73	20.22	29.95	56.00	-26.05	QP
10		2.7502	0.23	20.22	20.45	46.00	-25.55	AVG
11		4.5015	7.49	20.54	28.03	56.00	-27.97	QP
12		4.5015	-3.21	20.54	17.33	46.00	-28.67	AVG



Temperature:	26 ℃	Relative Humidity:	54%
Pressure:	101KPa	Phase :	Ν
Test Mode:	Mode 4	Test Voltage :	AC 120V/60Hz



Remark:

All readings are Quasi-Peak and Average values.
 Factor = Insertion Loss + Cable Loss.
 Measurement = Reading Level + Correct Factor

No. I	Mk. Freq.	Reading Level	Correct Factor	Measure- ment	Limit	Over	
	MHz		dB	dBuV	dBuV	dB	Detector
1	0.1500	12.59	19.73	32.32	66.00	-33.68	QP
2	0.1500	-2.55	19.73	17.18	56.00	-38.82	AVG
3	0.5055	8.71	19.84	28.55	56.00	-27.45	QP
4	0.5055	-1.54	19.84	18.30	46.00	-27.70	AVG
5	* 0.9105	15.32	19.92	35.24	56.00	-20.76	QP
6	0.9105	4.44	19.92	24.36	46.00	-21.64	AVG
7	1.2930	8.02	19.95	27.97	56.00	-28.03	QP
8	1.2930	-2.79	19.95	17.16	46.00	-28.84	AVG
9	2.3055	6.39	20.06	26.45	56.00	-29.55	QP
10	2.3055	-4.45	20.06	15.61	46.00	-30.39	AVG
11	3.0480	5.85	20.32	26.17	56.00	-29.83	QP
12	3.0480	-6.26	20.32	14.06	46.00	-31.94	AVG

No.: BCTC/RF-EMC-005

Page: 15 of 128


Edition:




7. Radiated emissions

7.1 Block Diagram Of Test Setup

(A) Radiated Emission Test-Up Frequency Below 30MHz




(B) Radiated Emission Test-Up Frequency 30MHz~1GHz





(C) Radiated Emission Test-Up Frequency Above 1GHz



7.2 Limit

20dBc in any 100 kHz bandwidth outside the operating frequency band. In case the emission fall within the restricted band specified on 15.205(a), then the 15.209(a) limit in the table below has to be followed.

Field Strength	Distance	Field Strength Lir	nit at 3m Distance
uV/m	(m)	uV/m	dBuV/m
2400/F(kHz)	300	10000 * 2400/F(kHz)	20log ^{(2400/F(kHz))} + 80
24000/F(kHz)	30	100 * 24000/F(kHz)	20log ^{(24000/F(kHz))} + 40
30	30	100 * 30	20log ⁽³⁰⁾ + 40
100	3	100	20log ⁽¹⁰⁰⁾
150	····. 3 ····.	150	20log ⁽¹⁵⁰⁾
200	3	200	20log ⁽²⁰⁰⁾
500	3	500	20log ⁽⁵⁰⁰⁾
	uV/m 2400/F(kHz) 24000/F(kHz) 30 100 150 200	uV/m (m) 2400/F(kHz) 300 24000/F(kHz) 30 30 30 100 3 150 3 200 3	uV/m(m)uV/m2400/F(kHz)30010000 * 2400/F(kHz)24000/F(kHz)30100 * 24000/F(kHz)3030100 * 30100310015031502003200

Limits Of Radiated Emission Measurement (Above 1000MHz)

Eroguopov (MHT)	Limit (dBuV/m) (at 3M)	
Frequency (MHz)	Peak	Average
Above 1000	74	54

Notes:

(1)The limit for radiated test was performed according to FCC PART 15C

(2)The tighter limit applies at the band edges.

(3) Emission level (dBuV/m)=20log Emission level (uV/m).



Frequency Range Of Radiated Measurement

(a) For an intentional radiator the spectrum shall be investigated from the lowest radio frequency signal generated in the device, without going below 9 kHz, up to at least the frequency shown in this paragraph:

(1) If the intentional radiator operates below 10 GHz: to the tenth harmonic of the highest fundamental frequency or to 40 GHz, whichever is lower.

(2) If the intentional radiator operates at or above 10 GHz and below 30 GHz: to the fifth harmonic of the highest fundamental frequency or to 100 GHz, whichever is lower.

(3) If the intentional radiator operates at or above 30 GHz: to the fifth harmonic of the highest fundamental frequency or to 200 GHz, whichever is lower, unless specified otherwise elsewhere in the rules.

(4) If the intentional radiator operates at or above 95 GHz: To the third harmonic of the highest fundamental frequency or to 750 GHz, whichever is lower, unless specified otherwise elsewhere in the rules.
(5) If the intentional radiator contains a digital device, regardless of whether this digital device controls the functions of the intentional radiator or the digital device is used for additional control or function purposes

other than to enable the operation of the intentional radiator, the frequency range shall be investigated up to the range specified in paragraphs (a) (1)through (4) of this section or the range applicable to the digital device, as shown in paragraph (b)(1) of this section, whichever is the higher frequency range of investigation.

7.3 Test procedure

Receiver Parameter	Setting
Attenuation	Auto
9kHz~150kHz	RBW 200Hz for QP
150kHz~30MHz	RBW 9kHz for QP
30MHz~1000MHz	RBW 120kHz for QP

Spectrum Parameter	Setting
1-25GHz	RBW 1 MHz /VBW 1 MHz for Peak, RBW 1 MHz / VBW 10Hz for Average

Below 1GHz test procedure as below:

a. The EUT was placed on the top of a rotating table 0.8 meters above the ground at a 3 meter semi-anechoic camber. The table was rotated 360 degrees to determine the position of the highest radiation.

b. The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.

c. The antenna height is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.

d. For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters (for the test frequency of below 30MHz, the antenna was tuned to heights 1 meter) and the rotatable table was turned from 0 degrees to 360 degrees to find the maximum reading.

e. The test-receiver system was set to Peak Detect Function and Specified Bandwidth with Maximum Hold Mode.

f. If the emission level of the EUT in peak mode was 10dB lower than the limit specified, then testing could be stopped and the peak values of the EUT would be reported. Otherwise the emissions that did not have 10dB margin would be re-tested one by one using peak, quasi-peak or average method as specified and then reported in a data sheet.



Above 1GHz test procedure as below:

a. The EUT was placed on the top of a rotating table 1.5 meters above the ground at a 3 meter camber. The table was rotated 360 degrees to determine the position of the highest radiation.

b.The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.

c.The antenna height is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.

d.For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters and the rota table was turned from 0 degrees to 360 degrees to find the maximum reading.

e.The test-receiver system was set to Peak Detect Function and Specified Bandwidth with Maximum Hold Mode.

f. If the emission level of the EUT in peak mode was 10dB lower than the limit specified, then testing could be stopped and the peak values of the EUT would be reported. Otherwise the emissions that did not have 10dB margin would be re-tested one by one using peak, quasi-peak or average method as specified and then reported in a data sheet.

g. Test the EUT in the lowest channel, the middlest channel, the Highest channel. Note:

Both horizontal and vertical antenna polarities were tested and performed pretest to three orthogonal axis. The worst case emissions were reported.

7.4 EUT operating Conditions

The EUT was configured for testing in a typical fashion (as a customer would normally use it). The EUT has been programmed to continuously transmit during test. This operating condition was tested and used to collect the included data.

7.5 Test Result

Below 30MHz

Temperature:	26 ℃	···.	Relative Humidity:	54%
Pressure:	101KPa		Test Voltage :	DC 3.7V
Test Mode:	Mode 5		Polarization :	
				NH H / / / / / / / / /

Freq.	Reading	Limit	Margin	State
(MHz)	(dBuV/m)	(dBuV/m)	(dB)	P/F
				PASS
		·····		PASS

Note:

The amplitude of spurious emissions which are attenuated by more than 20dB below the permissible value has no need to be reported.

Distance extrapolation factor =40 log (specific distance/test distance)(dB);

Limit line = specific limits(dBuv) + distance extrapolation factor.



Temperature:		Relative Humidity:	54%
Pressure:	101KPa	Phase :	Horizontal
Test Mode:	Mode 4	Test Voltage :	DC 3.7V




80.0 dBuV/	m					1						
											FCC/IC	QP
										Mar	jin -6 d	B
					1	2 And And And And And And And And And And	M Charly	A				1
40					Å	nutral weather a num			5			
								- hw	λ			6
					per la				N.		Magner	Rent Werky
Maham	Mural	Mun Within	for the starting	www.wyhaty	with more				hr hr	When		
0.0												
	40 50) 60	70 80		(MHz)		300	400	500	600	700	1000.000
Remark: . Factor = 2. Measure 3. Over = N	ment =	Reading	g Level +		Pre-amplifier Factor	•				8 8 8 8 8 8 8 8 8 8 8 8 8 8 8 8 8 8 8		
No. N	lk.	Freq.		ading evel	Correct Factor	Measu men		Limit		Ove	er	

No.	M۲	k. Freq.	Level	Factor	ment	Limit	Over	
		MHz	dBuV	dB	dBuV/m	dB/m	dB	Detector
1	İ	188.4125	55.17	-16.58	38.59	43.50	-4.91	QP
2	İ	250.3012	56.23	-14.28	41.95	46.00	-4.05	QP
3	*	314.3765	55.55	-12.73	42.82	46.00	-3.18	QP
4	İ	396.6015	52.48	-10.88	41.60	46.00	-4.40	QP
5		478.8456	44.92	-9.14	35.78	46.00	-10.22	QP
6		839.1818	32.86	-4.07	28.79	46.00	-17.21	QP



Temperature:	26 ℃	Relative Humidity:	54%
Pressure:	101KPa	Phase :	Vertical
Test Mode:	Mode 4	Test Voltage :	DC 3.7V



No.	Mk	. Freq.	Reading Level	Correct Factor	Measure- ment	Limit	Over	
		MHz	dBuV	dB	dBuV/m	dB/m	dB	Detector
1		74.3955	50.84	-18.77	32.07	40.00	-7.93	QP
2		91.1746	51.60	-17.23	34.37	43.50	-9.13	QP
3	*	158.1123	57.54	-18.83	38.71	43.50	-4.79	QP
4		184.4298	54.21	-16.88	37.33	43.50	-6.17	QP
5	İ	294.1137	54.12	-13.36	40.76	46.00	-5.24	QP
6		390.7226	44.11	-10.96	33.15	46.00	-12.85	QP



Left

Between 1GHz - 25GHz

Polar	Fre- quency	Reading Level	Correct Factor	Measure- ment	Limits	Over	Detector			
(H/V)	(MHz)	(dBuV/m)	(dB)	(dBuV/m)	(dBuV/m)	(dB)	Туре			
GFSK Low channel										
V	4804.00	73.52	-19.99	53.53	74.00	-20.47	PK			
V	4804.00	62.79	-19.99	42.80	54.00	-11.20	AV			
V	7206.00	62.96	-14.22	48.74	74.00	-25.26	PK			
V	7206.00	53.69	-14.22	39.47	54.00	-14.53	AV			
Н	4804.00	68.62	-19.99	48.63	74.00	-25.37	PK			
Н	4804.00	58.49	-19.99	38.50	54.00	-15.50	AV			
Н	7206.00	61.41	-14.22	47.19	74.00	-26.81	PK			
Н	7206.00	53.53	-14.22	39.31	54.00	-14.69	AV			
			GFSK Mid	dle channel						
V	4882.00	70.35	-19.84	50.51	74.00	-23.49	PK			
V	4882.00	64.34	-19.84	44.50	54.00	-9.50	AV			
V	7323.00	61.65	-13.90	47.75	74.00	-26.25	PK			
V	7323.00	53.05	-13.90	39.15	54.00	-14.85	AV			
Н	4882.00	67.91	-19.84	48.07	74.00	-25.93	PK			
Н	4882.00	58.79	-19.84	38.95	54.00	-15.05	AV			
Н	7323.00	59.74	-13.90	45.84	74.00	-28.16	PK			
Н	7323.00	51.00	-13.90	37.10	54.00	-16.90	AV			
			GFSK Hig	gh channel		:				
V	4960.00	71.62	-19.68	51.94	74.00	-22.06	PK			
V	4960.00	62.00	-19.68	42.32	54.00	-11.68	AV			
V	7440.00	65.52	-13.57	51.95	74.00	-22.05	PK			
V	7440.00	55.96	-13.57	42.39	54.00	-11.61	AV			
Н	4960.00	69.54	-19.68	49.86	74.00	-24.14	PK			
Н	4960.00	60.46	-19.68	40.78	54.00	-13.22	AV			
Н	7440.00	63.99	-13.57	50.42	74.00	-23.58	PK			
Н	7440.00	56.72	-13.57	43.15	54.00	-10.85	AV			

Remark:

1. Measurement = Reading Level + Correct Factor,

Correct Factor = Antenna Factor + Cable Loss - Pre-amplifier,

Over= Measurement - Limit

2.If peak below the average limit, the average emission was no test.

3. In restricted bands of operation, The spurious emissions below the permissible value more than 20dB 4. The amplitude of spurious emissions which are attenuated by more than 20dB below the permissible value has no need to be reported.

5.All the Modulation are test, the worst mode is GFSK, the data recording in the report.



Right

Between 1GHz - 25GHz

Polar	Fre- quency	Reading Level	Correct Factor	Measure- ment	Limits	Over	Detector
(H/V)	(MHz)	(dBuV/m)	(dB)	(dBuV/m)	(dBuV/m)	(dB)	Туре
			GFSK Lo	w channel			-
V	4804.00	73.20	-19.99	53.21	74.00	-20.79	PK
V	4804.00	64.57	-19.99	44.58	54.00	-9.42	AV
V	7206.00	63.35	-14.22	49.13	74.00	-24.87	PK
V	7206.00	52.82	-14.22	38.60	54.00	-15.40	AV
Н	4804.00	69.66	-19.99	49.67	74.00	-24.33	PK
Н	4804.00	60.44	-19.99	40.45	54.00	-13.55	AV
Н	7206.00	61.70	-14.22	47.48	74.00	-26.52	PK
Н	7206.00	53.79	-14.22	39.57	54.00	-14.43	AV
			GFSK Mid	dle channel			
V	4882.00	70.92	-19.84	51.08	74.00	-22.92	PK
V	4882.00	63.42	-19.84	43.58	54.00	-10.42	AV
V	7323.00	63.73	-13.90	49.83	74.00	-24.17	PK
V	7323.00	54.78	-13.90	40.88	54.00	-13.12	AV
Н	4882.00	69.31	-19.84	49.47	74.00	-24.53	PK
Н	4882.00	59.96	-19.84	40.12	54.00	-13.88	AV
Н	7323.00	61.75	-13.90	47.85	74.00	-26.15	PK
Н	7323.00	54.18	-13.90	40.28	54.00	-13.72	AV
			GFSK Hig	h channel		0 0 0	
V	4960.00	71.94	-19.68	52.26	74.00	-21.74	PK
V	4960.00	61.79	-19.68	42.11	54.00	-11.89	AV
V	7440.00	63.11	-13.57	49.54	74.00	-24.46	PK
V	7440.00	52.85	-13.57	39.28	54.00	-14.72	AV
Н	4960.00	69.49	-19.68	49.81	74.00	-24.19	PK
Н	4960.00	58.56	-19.68	38.88	54.00	-15.12	AV
Н	7440.00	60.94	-13.57	47.37	74.00	-26.63	PK
Н	7440.00	53.10	-13.57	39.53	54.00	-14.47	AV

Remark:

1. Measurement = Reading Level + Correct Factor,

Correct Factor = Antenna Factor + Cable Loss - Pre-amplifier,

Over= Measurement - Limit

2.If peak below the average limit, the average emission was no test.

In restricted bands of operation, The spurious emissions below the permissible value more than 20dB
 The amplitude of spurious emissions which are attenuated by more than 20dB below the permissible value has no need to be reported.


5.All the Modulation are test, the worst mode is GFSK, the data recording in the report.



8. Radiated Band Emission Measurement And Restricted Bands Of Operation

8.1 Block Diagram Of Test Setup

Radiated Emission Test-Up Frequency Above 1GHz



8.2 Limit

FCC Part15 C Section 15.209 and 15.205

(a) Except as shown in paragraph (d) of this section, only spurious emissions are permitted in any of the frequency bands listed below:

MHz	MHz	MHz	GHz
0.090-0.110	16.42-16.423	399.9-410	4.5-5.15
¹ 0.495-0.505	16.69475-16.69525	608-614	5.35-5.46
2.1735-2.1905	16.80425-16.80475	960-1240	7.25-7.75
4.125-4.128	25.5-25.67	1300-1427	8.025-8.5
4.17725-4.17775	37.5-38.25	1435-1626.5	9.0-9.2
4.20725-4.20775	73-74.6	1645.5-1646.5	9.3-9.5
6.215-6.218	74.8-75.2	1660-1710	10.6-12.7
6.26775-6.26825	108-121.94	1718.8-1722.2	13.25-13.4
6.31175-6.31225	123-138	2200-2300	14.47-14.5
8.291-8.294	149.9-150.05	2310-2390	15.35-16.2
8.362-8.366	156.52475-156.52525	2483.5-2500	17.7-21.4
8.37625-8.38675	156.7-156.9	2690-2900	22.01-23.12
8.41425-8.41475	162.0125-167.17	3260-3267	23.6-24.0
12.29-12.293	167.72-173.2	3332-3339	31.2-31.8
12.51975-12.52025	240-285	3345.8-3358	36.43-36.5
12.57675-12.57725	322-335.4	3600-4400	(²)
13.36-13.41			



Limits Of Radiated Emission Measurement (Above 1000MHz)

Frequency (MHz)	Limit (dBuV/m) (at 3M)			
Frequency (MHZ)	Peak	Average		
Above 1000	74	54		

Notes:

(1)The limit for radiated test was performed according to FCC PART 15C.

(2)The tighter limit applies at the band edges.

(3)Emission level (dBuV/m)=20log Emission level (uV/m).

8.3 Test procedure

Receiver Parameter	Setting
Attenuation	Auto
Start Frequency	2300MHz
Stop Frequency	2520
RB / VB (Emission In Restricted Band)	1 MHz / 1 MHz for Peak, 1 MHz / 10Hz for Average

Above 1GHz test procedure as below:

a. The EUT was placed on the top of a rotating table 1.5 meters above the ground at a 3 meter camber. The table was rotated 360 degrees to determine the position of the highest radiation.

b.The EUT was set 3 meters away from the interference-receiving antenna, which was mounted on the top of a variable-height antenna tower.

c.The antenna height is varied from one meter to four meters above the ground to determine the maximum value of the field strength. Both horizontal and vertical polarizations of the antenna are set to make the measurement.

d.For each suspected emission, the EUT was arranged to its worst case and then the antenna was tuned to heights from 1 meter to 4 meters and the rota table was turned from 0 degrees to 360 degrees to find the maximum reading.

e.The test-receiver system was set to Peak Detect Function and Specified Bandwidth with Maximum Hold Mode.

f. If the emission level of the EUT in peak mode was 10dB lower than the limit specified, then testing could be stopped and the peak values of the EUT would be reported. Otherwise the emissions that did not have 10dB margin would be re-tested one by one using peak, quasi-peak or average method as specified and then reported in a data sheet.

g. Test the EUT in the lowest channel, the middlest channel, the Highest channel.

Note:

Both horizontal and vertical antenna polarities were tested and performed pretest to three orthogonal axis. The worst case emissions were reported.

8.4 EUT operating Conditions

The EUT was configured for testing in a typical fashion (as a customer would normally use it). The EUT has been programmed to continuously transmit during test. This operating condition was tested and used to collect the included data.



8.5 Test Result

Test mode	Polar (H/V)	Fre- quency	Reading Level	Correct Factor (dB)	Measure- ment (dBuV/m)	Limits (dBuV/m)		Result			
		(MHz)	(dBuV/m)		PK Í	PK	AV	l			
			Ĺ	ow Channe	l 2402MHz						
	Н	2390.00	72.72	-25.43	47.29	74.00	54.00	PASS			
	Н	2400.00	76.75	-25.40	51.35	74.00	54.00	PASS			
	V	2390.00	72.19	-25.43	46.76	74.00	54.00	PASS			
	V	2400.00	75.31	-25.40	49.91	74.00	54.00	PASS			
GFSK	High Channel 2480MHz										
	Н	2483.50	74.90	-25.15	49.75	74.00	54.00	PASS			
	Н	2500.00	71.15	-25.10	46.05	74.00	54.00	PASS			
	V	2483.50	75.17	-25.15	50.02	74.00	54.00	PASS			
	V	2500.00	71.15	-25.10	46.05	74.00	54.00	PASS			
	Low Channel 2402MHz										
	Н	2390.00	72.00	-25.43	46.57	74.00	54.00	PASS			
	Н	2400.00	75.97	-25.40	50.57	74.00	54.00	PASS			
	V	2390.00	71.33	-25.43	45.90	74.00	54.00	PASS			
	V	2400.00	74.73	-25.40	49.33	74.00	54.00	PASS			
π/4DQPSK	High Channel 2480MHz										
	Н	2483.50	75.52	-25.15	50.37	74.00	54.00	PASS			
	Н	2500.00	71.24	-25.10	46.14	74.00	54.00	PASS			
	V	2483.50	74.62	-25.15	49.47	74.00	54.00	PASS			
	V	2500.00	70.37	-25.10	45.27	74.00	54.00	PASS			
			L	ow Channe	l 2402MHz						
	Н	2390.00	72.39	-25.43	46.96	74.00	54.00	PASS			
	Н	2400.00	75.44	-25.40	50.04	74.00	54.00	PASS			
	V	2390.00	73.34	-25.43	47.91	74.00	54.00	PASS			
	V	2400.00	76.83	-25.40	51.43	74.00	54.00	PASS			
8DPSK			1	ligh Channe	el 2480MHz						
	Н	2483.50	75.79	-25.15	50.64	74.00	54.00	PASS			
	Н	2500.00	69.58	-25.10	44.48	74.00	54.00	PASS			
	V	2483.50	76.48	-25.15	51.33	74.00	54.00	PASS			
	V	2500.00	73.79	-25.10	48.69	74.00	54.00	PASS			

1. Measurement = Reading Level + Correct Factor, Correct Factor = Antenna Factor + Cable Loss – Pre-amplifier,

Over= Measurement - Limit

2. If the PK measured levels comply with average limit, then the average level were deemed to comply with average limit.

3 In restricted bands of operation, The spurious emissions below the permissible value more than 20dB 4. The amplitude of spurious emissions which are attenuated by more than 20dB below the permissible value has no need to be reported.



Right Test mode	Polar (H/V)	Fre- quency	Reading Level	Correct Factor	Measure- ment (dBuV/m)		nits ıV/m)	Result		
	()	(MHz)	(dBuV/m)	(dB)	PK	PK	AV			
			L	ow Channe	l 2402MHz		•			
	Н	2390.00	72.75	-25.43	47.32	74.00	54.00	PASS		
	Н	2400.00	76.14	-25.40	50.74	74.00	54.00	PASS		
	V	2390.00	72.32	-25.43	46.89	74.00	54.00	PASS		
GFSK	V	2400.00	76.63	-25.40	51.23	74.00	54.00	PASS		
			F	ligh Channe	el 2480MHz					
	Н	2483.50	76.94	-25.15	51.79	74.00	54.00	PASS		
	Н	2500.00	72.00	-25.10	46.90	74.00	54.00	PASS		
	V	2483.50	76.53	-25.15	51.38	74.00	54.00	PASS		
	V	2500.00	72.37	-25.10	47.27	74.00	54.00	PASS		
	Low Channel 2402MHz									
	Н	2390.00	72.20	-25.43	46.77	74.00	54.00	PASS		
	Н	2400.00	75.22	-25.40	49.82	74.00	54.00	PASS		
	V	2390.00	72.40	-25.43	46.97	74.00	54.00	PASS		
π/4DQPSK	V	2400.00	76.38	-25.40	50.98	74.00	54.00	PASS		
	High Channel 2480MHz									
	Н	2483.50	75.94	-25.15	50.79	74.00	54.00	PASS		
	Н	2500.00	70.87	-25.10	45.77	74.00	54.00	PASS		
	V	2483.50	76.42	-25.15	51.27	74.00	54.00	PASS		
	V	2500.00	73.21	-25.10	48.11	74.00	54.00	PASS		
			L	ow Channe	l 2402MHz					
	Н	2390.00	71.22	-25.43	45.79	74.00	54.00	PASS		
	Н	2400.00	74.72	-25.40	49.32	74.00	54.00	PASS		
	V	2390.00	72.09	-25.43	46.66	74.00	54.00	PASS		
8DPSK	V	2400.00	76.17	-25.40	50.77	74.00	54.00	PASS		
OUFSK			°∼., F	ligh Channe	l 2480MHz					
	Н	2483.50	75.65	-25.15	50.50	74.00	54.00	PASS		
	Н	2500.00	68.44	-25.10	43.34	74.00	54.00	PASS		
	V	2483.50	74.23	-25.15	49.08	74.00	54.00	PASS		
	V	2500.00	69.38	-25.10	44.28	74.00	54.00	PASS		

Remark:

1. Measurement = Reading Level + Correct Factor,

Correct Factor = Antenna Factor + Cable Loss - Pre-amplifier,

Over= Measurement - Limit

2. If the PK measured levels comply with average limit, then the average level were deemed to comply with average limit.

3 In restricted bands of operation, The spurious emissions below the permissible value more than 20dB 4. The amplitude of spurious emissions which are attenuated by more than 20dB below the permissible value has no need to be reported.



9. Spurious RF Conducted Emissions

9.1 Block Diagram Of Test Setup



9.2 Limit

Regulation 15.247 (d),In any 100 kHz bandwidth outside the frequency band in which the spread spectrum or digitally modulated intentional radiator is operating, the radio frequency power that is produced by the intentional radiator shall be at least 20 dB below that in the 100 kHz bandwidth within the band that contains the highest level of the desired power, based on either an RF conducted or a radiated measurement, provided the transmitter demonstrates compliance with the peak conducted power limits. If the transmitter complies with the conducted power limits based on the use of RMS averaging over a time interval, as permitted under paragraph (b)(3) of this section, the attenuation required under this paragraph shall be 30 dB instead of 20 dB. Attenuation below the general limits specified in §15.209(a) is not required. In addition, radiated emissions which fall in the restricted bands, as defined in §15.205(a), must also comply with the radiated emission limits specified in §15.205(c))

9.3 Test procedure

1. Remove the antenna from the EUT and then connect a low RF cable from the antenna port to the spectrum;

2. Set the spectrum analyzer: RBW = 100kHz, VBW = 300kHz, Sweep = auto Detector function = peak, Trace = max hold


Page: 28 of 1

Edition: B.2



9.4 Test Result

Left






📕 Agilent Spectrum Analyzer - S	wept SA				- P
RL RF 50	Ω AC	SENSE:INT	ALIGN AUTO #Avg Ty	ne: RMS	10:31:30 PM Apr 24, 20 TRACE 1 2 3 4 5
Center Freq 2.441	PN	O:Wide ↔ Trig:Fre ain:Low #Atten:	ee Run Avg Hold	pe: RMS d: 100/100	TYPE MWWW DET P NNNN
Ref Offset 2	2.6 dB			Mkr1 2.4	40 831 10 GH
0 dB/div Ref 12.60					1.700 dBr
2.60		\			
		Multuneture			
7.40	north and a start and a start and a start a start a start a start a start a start a start a start a start a st	ANT Y N	· · · · · · · · · · · · · · · · · · ·	Why when and	
17.4	nterflord Will and			A CONTRACTOR OF THE OWNER OWNER	WWWWWWWWWWWWWW
27.4					Man Man Market
Mon					A North Starter
37.4					
47.4					
57.4					
67.4					
77.4					
enter 2.4410000 G Res BW 100 kHz	Hz	#VBW 300 kH	7	Sween 21	Span 1.500 MH 000 ms (30001 pt
SG					
	Tx. Spurio	us NVNT 1-D	H1 2441MHz	Emission	
RL RF 50	wept SA	SENSE:INT	ALIGN AUTO		10:32:01 PM Apr 24, 20
Center Freq 13.26	5000000 GHz	IO: Fast ↔→→ Trig: Fre	#Avg Ty ee Run Avg Hold		TRACE 1 2 3 4 5 TYPE MWWWW DET P N N N N
	IFC	ain:Low #Atten:	20 dB	ML	r1 2.440 5 GH
Ref Offset					-1.105 dBn
. og 2.60					
17.4					-18.30 dB
27.4					-18.30 dB
17.4 27.4 37.4 47.4		.5			-16.30 dB
17.4 27.4 47.4 57.4		<u></u> 5			-18:30.05
17.4		5			-19:30 dB
17.4					\$2 Stop 26.50 GH
17.4 37.4 47.4		#VBW 300 kF			Stop 26.50 GH 2.530 s (30001 pts)
17.4 27.4 27.4 47.4	× 2.440 5 GHz	#VBW 300 kF Y F -1.105 dBm	IZ FUNCTION WIDTH		\$2 Stop 26.50 GH
17.4 27.4 27.4 47.4 57.5 57.5	2.440 5 GHz 25.580 6 GHz 4.882 0 GHz	#VBW 300 kl -1.105 dBm -51.203 dBm -59.564 dBm			Stop 26.50 GH 2.530 s (30001 pts)
2 N 1 f	2.440 5 GHz 25.580 6 GHz	#VBW 300 kH Y F -1.105 dBm -51.203 dBm			Stop 26.50 GH 2.530 s (30001 pts)
17.4 27.4 27.4 47.4 57.4 47.4 57.4 47.4 57.4	2.440 5 GHz 25.580 6 GHz 4.882 0 GHz 7.297 8 GHz	#VBW 300 kł Y F -1.105 dBm -51.203 dBm -59.564 dBm -63.723 dBm			Stop 26.50 GH 2.530 s (30001 pts)
17.4 27.4	2.440 5 GHz 25.580 6 GHz 4.882 0 GHz 7.297 8 GHz	#VBW 300 kł Y F -1.105 dBm -51.203 dBm -59.564 dBm -63.723 dBm			Stop 26.50 GH 2.530 s (30001 pts)
17.4 37.4 37.4 47.4 57.4 58.4 58.4 10.0	2.440 5 GHz 25.580 6 GHz 4.882 0 GHz 7.297 8 GHz	#VBW 300 kł Y F -1.105 dBm -51.203 dBm -59.564 dBm -63.723 dBm			Stop 26.50 GH 2.530 s (30001 pts)


Edition: B.2






Page: 31 of 128






Edition: B.2






Edition: B.2






Edition: B.2





Edition: B.2





Edition: B.2




RL RF 50 Ω	AC	SENSE:I	NT	ALIGN AUTO		10:45:58 PM Apr 24, 2
enter Freq 2.480000	0000 GHz	O:Wide ⊶ Trig	g: Free Run ten: 20 dB	#Avg Type Avg Hold:		TRACE 1 2 3 4 TYPE MWWW DET P N N N
Ref Offset 2.61 dB/div Ref 12.61 dl					Mkr1 :	2.480 161 40 GI 2.745 dB
	ymynymy medyl	-man Mark	ur many	mr MM Mann	www.wayala	Manyara Maria
4						······································
7.4 7.4 7.4						
enter 2.4800000 GHz es BW 100 kHz		#VBW 30	0 647		Swoon	Span 1.500 M 2.000 ms (30001 p
G G G G G G G G G G G G G G G G G G G		#VB44.30	V KHZ	I STATUS	oweep	2.000 ms (3000 r p
	Tx. Spurio	us NVNT 3	-DH1 24	180MHz E	mission	
Agilent Spectrum Analyzer - Swept	CA.					
	AC 00000 GHz	SENSE:I	NT g: Free Run	ALIGN AUTO #Avg Type Avg Hold:		10:46:28 PM Apr 24, 2 TRACE 1 2 3 4
enter Freq 13.26500	AC DOOOOO GHz PH IFC	NO: Fast +++ Trig		ALIGN AUTO #Avg Type	: 10/10	10:46:28 PM Apr 24, 2 TRACE 1 2 3 4 TYPE MWWW DET P NNN
Ref Offset 2.6 0 dB/div Ref 12.61 dl	AC DOOOOO GHZ IFC	NO:Fast ↔ Trig	g: Free Run	ALIGN AUTO #Avg Type	: 10/10	10:46:28 PM Apr 24, 2 TRACE 1 2 3 4 TYPE MWWW DET P NNN
Ref Offset 2.67 Ref Offset 2.67 Ref 12.61 dl	AC DOOOOO GHZ IFC	NO:Fast ↔ Trig	g: Free Run	ALIGN AUTO #Avg Type	: 10/10	10:46:28 PM Apr 24, 2 TRACE 12 3 4 TYPE WWY DET NNN Mkr1 2,480 2 GH 2,514 dB
Ref Offset 2.67 dB/div Ref 12.61 dl 9 61 33 7.4 7.4	AC DOOOOO GHZ IFC	NO:Fast ↔ Trig	g: Free Run	ALIGN AUTO #Avg Type	: 10/10	10:46:28 PM Apr24, 2 TRACE 12:3 4 TYPE MWWY DET PMNN MKr1 2,480 2 GH 2,514 dB
Ref Offset 2.67 Ref Offset 2.67 Ref 12.61 dl 1 3 3 7.4	AC DOOOOO GHZ IFC	NO:Fast ↔ Trig	g: Free Run	ALIGN AUTO #Avg Type	: 10/10	10:46:28 PM Apr24, 2 TRACE 12:3 4 TYPE MWWY DET PMNN MKr1 2,480 2 GH 2,514 dB
Ref Offset 2.67 dB/div Ref 12.61 dl 9 1 1 1 1 1 1 1 1 1 1 1 1 1	AC ODUCIÓN GHZ PERSONAL ACONTRACIÓN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTR	IO: Fast → Trių Jain:Low #At	g: Free Run	ALIGN AUTO #Avg Type	: 10/10	10:46:28 PM Apr 24, 2 TRACE 12 3 4 TYPE WWY DET NNN Mkr1 2,480 2 GH 2,514 dB
Ref Offset 2.6' dB/div Ref 12.61 dl	AC ODUCIÓN GHZ PERSONAL ACONTRACIÓN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTRACTÍN DE CONTR	IO: Fast → Trių Jain:Low #At	g: Free Run ten: 20 dB	ALIGN AUTO #Avg Type		10:46:28 PM Apr24, 2 TRACE 02 3 4 TYPE MUNIC Mkr1 2.480 2 GF 2.514 dB -17.36
Ref Offset 2.67 dB/div Ref 12.61 dl Ref 12.61 dl art 30 MHz Res BW 100 kHz Ref 000 kHz Ref	AC DOUCOO GHz Price	VO: Fast →→ Trit Jain:Low → #At	g: Free Run ten: 20 dB	ALIGN AUTO #Avg Type	Sweep	10:46:28 PM Apr24, 2 TRACE 02 3 4 TYPE MUNIC Mkr1 2.480 2 GF 2.514 dB -17.36
Ref Offset 2.67 dB/div Ref 12.61 dl 9 4 9 4 4 4 4 4 4 4 4	AC D00000 GHz P IFC I dB Bm 4 4 4 4 4 4 4 4 4 4 4 4 4	VO: Fast →→ Triţ Jain:Low → #At	g: Free Run ten: 20 dB	ALIGN AUTO #Avg Type Avg Hold:	Sweep	10:46:28 PM Apr24, 2 10:46:28 PM Apr24, 2 TYPE WWW DET WWW Mkr1 2:480 2 GH 2.514 dB .17 20 .17 20 .10

Edition: B.2









Edition: B.2
























Edition: B.2













Band Ed	dge(Hopping) N	VNT 2-DH1 2402M	Hz Hopping
Image: Again Spectrum Analyzer - Swept SA RF SO Q AC Image: Again Spectrum Analyzer - Swept SA RF SO Q AC AC Image: Again Spectrum Analyzer - Swept SA RF SO Q AC AC AC Image: Again Spectrum Analyzer - Swept SA RF SO Q AC	GHz PNO: Wide ↔		I1:00:13 PM Apr24, 2024 ype: RMS TRACE I 2 23 45 6 Jd: 2000/2000 TVPE PMNNNN DET PMNNNN
Ref Offset 2.59 dB 10 dB/div Ref 20.00 dBm			Mkr1 2.404 832 GHz 2.014 dBm
Log			
0.00			
-10.0		manth	a Mayor Mayor
-20.0	/	/v · · · · · · · · · · · · · · · · · · ·	
-30.0			
-40.0			
-50.0	MAN I		
-50.0 -60.0 MmmmmmmmmMM	/\`\\\\\		
-70.0			
Center 2.402000 GHz			Span 8.000 MHz
#Res BW 100 kHz	#VBW 3	300 kHz	Sweep 1.000 ms (1001 pts)
Band Edge(F	Hopping) NVNT	2-DH1 2402MHz	Hopping Emission
Agilent Spectrum Analyzer - Swept SA K RF 50 Ω AC	SENS	SE:INT ALIGN AUTO	11:00:46 PM Apr 24, 2024
Mailent Spectrum Analyzer - Swept SA	GHz	SE:INT ALIGN AUTO #Avg T	
Agilent Spectrum Analyzer - Swept SA RL RF 50 Ω AC Center Freq 2.356000000 Ref Offset 2.59 dB Ref Offset 2.59 dB Ref 20.00 dBm	GHz PNO: Fast	SE:INT ALIGN AUTO #Avg T Trig: Free Run Avg Hc	11:00:46 PM Apr 24, 2024 ype: RMS TRACE 2345 6 trace 2345 6
Relient Spectrum Analyzer - Swept SA RL RF 50 Ω AC Center Freq 2.356000000 (Ref Offset 2.59 dB Ref Offset 2.59 dB Ref Offset 2.59 dB 10 dB/div Ref 20.00 dBm 10 dB/div Ref 20.00 dBm 10 dB/div	GHz PNO: Fast	SE:INT ALIGN AUTO #Avg T Trig: Free Run Avg Hc	II:00:46 PM Apr 24, 2024 Ype: RMS TRACE I 2 3 4 5 0 Jd: 2000/2000 TYPE IV RM Mkr1 2.405 0 GHz
Agilent Spectrum Analyzer - Swept SA RL	GHz PNO: Fast	SE:INT ALIGN AUTO #Avg T Trig: Free Run Avg Hc	II:00:46 PM Apr 24, 2024 Ype: RMS TRACE I 2 3 4 5 0 Jd: 2000/2000 TYPE IV RM Mkr1 2.405 0 GHz
Relient Spectrum Analyzer - Swept SA RL RF 50 Ω AC Center Freq 2.356000000 (Ref Offset 2.59 dB Ref Offset 2.59 dB Ref Offset 2.59 dB 10 dB/div Ref 20.00 dBm 0 <td>GHz PNO: Fast</td> <td>SE:INT ALIGN AUTO #Avg T Trig: Free Run Avg Hc</td> <td>II:00:46 PM Apr 24, 2024 Ype: RMS TRACE I 2 3 4 5 0 Jd: 2000/2000 TYPE IV RM Mkr1 2.405 0 GHz</td>	GHz PNO: Fast	SE:INT ALIGN AUTO #Avg T Trig: Free Run Avg Hc	II:00:46 PM Apr 24, 2024 Ype: RMS TRACE I 2 3 4 5 0 Jd: 2000/2000 TYPE IV RM Mkr1 2.405 0 GHz
Magilent Spectrum Analyzer - Swept SA M RF 50 Ω AC Center Freq 2.356000000 (Ref Offset 2.59 dB Ref Offset 2.59 dB 10 dB/div Ref 20.00 dBm Cog <	GHz PNO: Fast	SE:INT ALIGN AUTO #Avg T Trig: Free Run Avg Hc	II:00:46 PM Apr 24, 2024 Ype: RMS TRACE I 2 3 4 5 0 Jd: 2000/2000 TYPE IV RM Mkr1 2.405 0 GHz
Ref Offset 2.59 dB 10.0 Ref 20.00 dB 0.00	GHz PNO: Fast	SE:INT ALIGN AUTO #Avg T Trig: Free Run Avg Hc	11:00:46 PM Apr24, 2024 ype: RMS TRACE 12:23:43:00 DET DET Mkr1 2.405 0 GHz
Ref Offset 2.59 dB Ref Offset 2.59 dB 10 dB/div Ref 20.00 dBm	GHz PNO: Fast IFGain:Low →	SE:INT ALIGN AUTO #Avg T Trig: Free Run Avg Hc	11:00:46 PM Apr24, 2024 ype: RMS TRACE 12:23:43:00 DET DET Mkr1 2.405 0 GHz
Agilent Spectrum Analyzer - Swept SA M RL RF 50 Ω AC Center Freq 2.356000000 Ref Offset 2.59 dB 10 dB/div Ref Offset 2.59 dB 10 dB/div Ref 20.00 dBm 0 0 0 0 10 dB/div Ref 0ffset 2.59 dB 0 0 0 0 0 10 dB/div Ref 0ffset 2.59 dB 0 <td>GHz PNO: Fast IFGain:Low</td> <td>SEINT ALIGN AUTO Trig: Free Run #Avg T #Avg T #Atten: 30 dB</td> <td>уре: RMS 11:00:46 PM Apr24, 2024 уре: 2000/2000</td>	GHz PNO: Fast IFGain:Low	SEINT ALIGN AUTO Trig: Free Run #Avg T #Avg T #Atten: 30 dB	уре: RMS 11:00:46 PM Apr24, 2024 уре: 2000/2000
Agilent Spectrum Analyzer - Swept SA W RL RF S0 Ω AC Center Freq 2.356000000 Ref Offset 2.59 dB Ref Offset 2.59 dB Ref Offset 2.59 dB 10 dB/div Ref 20.00 dBm Ref 20.00 dBm Ref 20.00 dBm Ref 20.00 dBm 0.00	GHz PNO: Fast IFGain:Low #VBW	SEINT ALIGN AUTO Trig: Free Run Avg]Hc Avg]Hc Avg]Hc Avg]Hc S00 kHz EVUNCTION FUNCTION WIDTH m m m	II:00:46 PM Apr24, 2024 Ype: RMS ITRACE IR:2000/2000 IR:200/2000/2000 IR:200/20
Agilent Spectrum Analyzer - Swept SA W RL RF SO Ω AC Center Freq 2.356000000 Ref Offset 2.59 dB Ref Offset 2.59 dB Ref Offset 2.59 dB 10 dB/div Ref 20.00 dBm Context and the set of the set	GHz PNO: Fast IFGain:Low → #VBW 1 #VBW 1 05 0 GHz → 6.0.862 dB 0.862 dB	SEINT ALIGN AUTO Trig: Free Run Avg]Hc Avg]Hc Avg]Hc Avg]Hc S00 kHz EVUNCTION FUNCTION WIDTH m m m	III00:46 PM Apr 24, 2024 Ype: RMS TRACE Mkr1 2.405 0 GHz 0.862 dBm
Agilent Spectrum Analyzer - Swept SA W RL RF 50 Ω AC Center Freq 2.356000000 (Ref Offset 2.59 dB 10 dB/div Ref 20.00 dBm Log	GHz PNO: Fast IFGain:Low #VBW	SEINT ALIGN AUTO Trig: Free Run Avg]Hc Avg]Hc Avg]Hc Avg]Hc S00 kHz EVUNCTION FUNCTION WIDTH m m m	III00:46 PM Apr 24, 2024 Ype: RMS TRACE Mkr1 2.405 0 GHz 0.862 dBm
Agilent Spectrum Analyzer - Swept SA VI RL RF S0 Ω AC Center Freq 2.356000000 Ref Offset 2.59 dB Context Press Context Press <td>GHz PNO: Fast IFGain:Low #VBW</td> <td>SEINT ALIGN AUTO Trig: Free Run Avg]Hc Avg]Hc Avg]Hc Avg]Hc S00 kHz EVUNCTION FUNCTION WIDTH m m m</td> <td>11:00:46 PM Apr 24, 2024 Ype: RMS TRACE TRACE Det Mkr1 2.405 0 GHz 0.862 dBm 0.862 dBm Stop 2.40600 GHz Sweep 9.600 ms (1001 pts)</td>	GHz PNO: Fast IFGain:Low #VBW	SEINT ALIGN AUTO Trig: Free Run Avg]Hc Avg]Hc Avg]Hc Avg]Hc S00 kHz EVUNCTION FUNCTION WIDTH m m m	11:00:46 PM Apr 24, 2024 Ype: RMS TRACE TRACE Det Mkr1 2.405 0 GHz 0.862 dBm 0.862 dBm Stop 2.40600 GHz Sweep 9.600 ms (1001 pts)












Agilent Spectrum Analyzer - Swept	SA	1			z Hoppi	
RL RF 50 Ω Center Freq 2.480000		SENSE	rig: Free Run	ALIGN AUTO #Avg Type: Avg Hold: 2		11:07:10 PM Apr 24, 20 TRACE 1 2 3 4 5 TYPE MWWWW
	P		Atten: 30 dB	Avginola. A		
Ref Offset 2.61 0 dB/div Ref 20.00 dl					Mk	r1 2.479 840 GH 2.409 dBr
og						
10.0			↓ ¹			
	M.	A AN	- MM			
	m	m hi fm	white white	A		
20.0						
30.0						
40.0				<u>\</u>		
50.0					Λ	
					WWW	Maman
60.0						
70.0						
enter 2.480000 GHz						Span 8.000 MH
Res BW 100 kHz		#VBW 3	00 kHz		Sweep	1.000 ms (1001 pt
Band Ed	ae(Honnin	a) NVNT 🤉	R-DH1 24		opping E	mission
Agilent Spectrum Analyzer - Swept		ng) NVNT 3		80MHz Ho	opping E	
Agilent Spectrum Analyzer - Swept RL RF 50 Ω	AC 0000 GHz	SENSE	INT	80MHz Ho	RMS	11:07:43 PM Apr 24, 20 TRACE 2 3 4 TVPF
Agilent Spectrum Analyzer - Swept RL RF 50 Ω	AC 0000 GHz	SENSE		80MHz Ho	RMS 2000/2000	11:07:43 PM Apr 24, 20 TRACE 1 2 3 4 TYPE MWWWW DET PNNN
Agilent Spectrum Analyzer - Swept RL RF 50 Ω Center Freq 2.526000 Ref Offset 2.67	AC	SENSE NO: Fast ↔ T	ig: Free Run	80MHz Ho	RMS 2000/2000	11:07:43 PM Apr24, 20 TRACE 1 2 3 4 9 TYPE MWWW DET P NNN Mkr1 2.480 2 GH
Agilent Spectrum Analyzer - Swept RL RF 50 Ω Senter Freq 2.52600(Ref Offset 2.6/ 0 dB/div Ref 20.00 dl	AC	SENSE NO: Fast ↔ T	ig: Free Run	80MHz Ho	RMS 2000/2000	11:07:43 PM Apr24, 20 TRACE 1 2 3 4 9 TYPE MWWW DET P NNN Mkr1 2.480 2 GH
Agilent Spectrum Analyzer - Swept RL RF 50.0. center Freq 2.526000 Ref Offset 2.67 0 dB/div Ref Offset 2.67 10.0 1	AC	SENSE NO: Fast ↔ T	ig: Free Run	80MHz Ho	RMS 2000/2000	11:07:43 PM Apr 24, 20 TRACE 12 23 4 TYPE M WWW DET P NNNN Mkr1 2.480 2 GH 2.585 dBr
Agilent Spectrum Analyzer - Swept RL RF 50.0 center Freq 2.526000 Ref Offset 2.6' 0 dB/div Ref 20.00 di 0.00 1 0.00 1 0.00 1 0.00 1	AC	SENSE NO: Fast ↔ T	ig: Free Run	80MHz Ho	RMS 2000/2000	11:07:43 PM Apr 24, 20 TRACE 12 23 4 TYPE M WWW DET P NNNN Mkr1 2.480 2 GH 2.585 dBr
Rejient Spectrum Analyzer - Swept RL RF 50 Ω center Freq 2.526000 Ref Offset 2.6' Ref Offset 2.6' 0 dB/div Ref 20.00 dl Ref 20.00 dl 0 dB/div 1 0 0 0.000 1 0 0 0.000 1 0 0 0 0.00 1 0 0 0 0.00 1 0 0 0 0.00 1 0 0 0 0.00 1 0 0 0 0.00 1 0 0 0 0.00 1 0 0 0	AC	SENSE NO: Fast ↔ T	ig: Free Run	80MHz Ho	RMS 2000/2000	11:07:43 PM Apr 24, 20 TRACE 12 23 4 TYPE M WWW DET P NNNN Mkr1 2.480 2 GH 2.585 dBr
Rejient Spectrum Analyzer - Swept RL RF 50 Ω Center Freq 2.526000 Ref Offset 2.67 Ref Offset 2.67 0 dB/div Ref 20.00 df Ref 20.00 df 0 000 1 0 0 0.00 40 50 2 0.00 40 40 40 40	AC	SENSE NO: Fast ↔ T	ig: Free Run	80MHz Ho	RMS 2000/2000	11:07:43 PM Apr 24, 20 TRACE 12 23 4 TYPE M WWW DET P NNNN Mkr1 2.480 2 GH 2.585 dBr
Agilent Spectrum Analyzer - Swept RL RF 50Ω Senter Freq 2.526000 0 dB/div Ref Offset 2.6' 0 dB/div Ref 20.00 dl 0 0 1 0 0 1 0 0 1 0 0 1 0 0 1 0 0 1 0 0 1 0 0 1 0 0 1 0 0 1 0 0 1 0 0 1 0 0 1 0 0 1	AC	SENSE NO: Fast ↔ T	eint rig: Free Run ttten: 30 dB	80MHz Ho	RMS 2000/2000	11:07:43 PM Apr 24, 20 TRACE 12 34 4 TYPE MWWW DET P NNNN Mkr1 2.480 2 GH 2.585 dBr
Rejient Spectrum Analyzer - Swept RL RF 50 Ω Center Freq 2.526000 Ref Offset 2.67 O dB/div Ref 20.00 dI 0 00 1 0 0 00 40 0 0 0 00 40 50 0 22 0 00 40 <td>AC </td> <td>SENSE NO: Fast → TI Gain:Low ##</td> <td>rig: Free Run Atten: 30 dB</td> <td>80MHz Ho</td> <td>RMS 2000/2000</td> <td>11:07:43 PM Apr 24, 22 TRACE [2 3 4] TYPE M WWW DET P NNN Mkr1 2.480 2 GH 2.585 dBr .17 59 d .17 59 d</td>	AC	SENSE NO: Fast → TI Gain:Low ##	rig: Free Run Atten: 30 dB	80MHz Ho	RMS 2000/2000	11:07:43 PM Apr 24, 22 TRACE [2 3 4] TYPE M WWW DET P NNN Mkr1 2.480 2 GH 2.585 dBr .17 59 d .17 59 d
Agilent Spectrum Analyzer - Swept RL RF 50Ω center Freq 2.526000 Ref Offset 2.67 0 dB/div Ref 20.00 dI 10 0 1	SA AC D0000 GHz P I dB Bm 3 	SENSE NO: Fast ↔ T	eint rig: Free Run Atten: 30 dB	80MHz H(RMS 2000/2000	11:07:43 PM Apr 24, 20 TRACE [2 3 4 TYPE M WWWW DET P WWWW Mkr1 2.480 2 GH 2.585 dBr -17:59 dB -17:59 dB -
Rejient Spectrum Analyzer - Swept RL RF 50 Ω Center Freq 2.526000 Ref Offset 2.67 O dB/div Ref 20.00 dI 0 00 1 0 0 00 40 0 0 0 00 40 50 0 22 0 00 40 <td>SA AC D0000 GHz P I dB Bm 3 4 2.480 2 GHz 2.483 5 GHz</td> <td>SENSE NO: Fast →→ Tr Gain:Low #/</td> <td>int ig: Free Run tten: 30 dB</td> <td>80MHz Ho</td> <td>RMS 2000/2000</td> <td>11:07:43 PM Apr 24, 20 TRACE 12 3 4 4 TYPE M WWWW DET P NNNN Mkr1 2.480 2 GH 2.585 dBr </td>	SA AC D0000 GHz P I dB Bm 3 4 2.480 2 GHz 2.483 5 GHz	SENSE NO: Fast →→ Tr Gain:Low #/	int ig: Free Run tten: 30 dB	80MHz Ho	RMS 2000/2000	11:07:43 PM Apr 24, 20 TRACE 12 3 4 4 TYPE M WWWW DET P NNNN Mkr1 2.480 2 GH 2.585 dBr
Agilent Spectrum Analyzer - Swept RL RF 50 Ω center Freq 2.526000 Ref Offset 2.67 O dB/div Ref 20.00 dI 100 1 1 200 40 1 300 40 40 400 40 40 300 40 40 400 40 40 400 40 40 400 40 40 400 40 40 500 40 50 500 40 50 500 40 50 500 40 50 500 40 50 500 40 40 500 50 50 500 40 40 500 50 50 500 50 50 600 60 60 700 60 70 700 70	SA AC D0000 GHz P I dB Bm 3 4 3 4 4 4 5 4 5 4 5 5 5 5 5 5 5 5 5 5 5 5 5	SENSE NO: Fast →→ Tr Gain:Low ##	CINT rig: Free Run ttten: 30 dB	80MHz H(RMS 2000/2000	II:07:43 PM Apr 24, 20 TRACE [2 3 4 TARCE [2 3 4 TARCE [2 3 4 TARCE [2 3 4 TARCE [2 3 4 TARCE [2 3 4 TARCE [2 3 4 TARCE [2 3 4 TARCE [2 5 TARCE
Agilent Spectrum Analyzer - Swept RL RF 50 Ω center Freq 2.526000 Ref Offset 2.6/ Ref Offset 2.6/ 0 dB/div Ref 20.00 dI Ref 20.00 dI 10 0 1 1 1 20 0 1 1 1 1 10 0 1 1 1 1 1 20 0 1 <th1< th=""> <th1< th=""> <th1< th=""> <th1<< td=""><td>SA AC 00000 GHz F I dB Bm 3 2.480 2 GHz 2.483 2 GHz 2.500 0 GHz</td><td>SENSE SENSE SENSE</td><td>CINT rig: Free Run ttten: 30 dB</td><td>80MHz H(</td><td>RMS 2000/2000</td><td>11:07:43 PM Apr 24, 22 TRACE [2 3 4] TRACE [2 3 4] Mkr1 2.480 2 GH 2.585 dBt 4.77.59 dl 4.77.59 dl 5.00 2.57600 GH 9.600 ms (1001 pt</td></th1<<></th1<></th1<></th1<>	SA AC 00000 GHz F I dB Bm 3 2.480 2 GHz 2.483 2 GHz 2.500 0 GHz	SENSE SENSE	CINT rig: Free Run ttten: 30 dB	80MHz H(RMS 2000/2000	11:07:43 PM Apr 24, 22 TRACE [2 3 4] TRACE [2 3 4] Mkr1 2.480 2 GH 2.585 dBt 4.77.59 dl 4.77.59 dl 5.00 2.57600 GH 9.600 ms (1001 pt
Agilent Spectrum Analyzer - Swept RL RF 50 Ω Center Freq 2.526000 Ref Offset 2.67 Generation Ref Offset 2.67 Ref 20.00 dl Generation 0 dB/div Ref 20.00 dl Generation 10 0 1 1 1 20 0 40 40 40 40 30 0 40 40 40 40 40 0 40 40 40 40 50 0 40 40 40 40 40 40 0 40	SA AC 00000 GHz F I dB Bm 3 2.480 2 GHz 2.483 2 GHz 2.500 0 GHz	SENSE SENSE	CINT rig: Free Run ttten: 30 dB	80MHz H(RMS 2000/2000	11:07:43 PM Apr 24, 22 TRACE [2 3 4] TRACE [2 3 4] Mkr1 2.480 2 GH 2.585 dBt 4.77.59 dl 4.77.59 dl 5.00 2.57600 GH 9.600 ms (1001 pt
Agilent Spectrum Analyzer - Swept RL RF 50 Ω enter Freq 2.526000 Ref Offset 2.6' 0 dB/div Ref 20.00 dI 10 0 1 1 20 0 1 1 20 0 2 2 20 0 40 2 2 20 0 41 2 2 20 0 42 2 2 20 0 42 2 2 20 0 42 2 2 20 0 42 2 2 20 0 42 2 2 20 0 42 2 2 20 0 42 2 2 20 0 42 2 2 2 30 0 4 4 1 1 4 N 1 1 2 30 0 4 5 6 2 2 4 N 1 1 1 <th< td=""><td>SA AC 00000 GHz F I dB Bm 3 2.480 2 GHz 2.483 2 GHz 2.500 0 GHz</td><td>SENSE SENSE SENSE</td><td>CINT rig: Free Run ttten: 30 dB</td><td>80MHz H(</td><td>RMS 2000/2000</td><td>11:07:43 PM Apr 24, 20 TRACE [2 3 4 TRACE [2 3 4 TRACE [2 3 4 TRACE [2 3 4 TYPE MYNNY Mkr1 2.480 2 GH 2.585 dB1 477.59 d 477.59 d 5100 2.57600 GH 9.600 ms (1001 pt</td></th<>	SA AC 00000 GHz F I dB Bm 3 2.480 2 GHz 2.483 2 GHz 2.500 0 GHz	SENSE SENSE	CINT rig: Free Run ttten: 30 dB	80MHz H(RMS 2000/2000	11:07:43 PM Apr 24, 20 TRACE [2 3 4 TRACE [2 3 4 TRACE [2 3 4 TRACE [2 3 4 TYPE MYNNY Mkr1 2.480 2 GH 2.585 dB1 477.59 d 477.59 d 5100 2.57600 GH 9.600 ms (1001 pt















Edition: B.2



		Spurious N\	/NT 2-L	DH1 2402M	HZ	
gilent Spectrum Analyzer - Swep RL RF 50 Ω	AC	SENSE:IN	Т	ALIGN AUTO	DMC	12:54:46 PM Apr 28, 2
enter Freq 2.402000	Ph	10: Wide 🛶 Trig Gain:Low #Att	j: Free Run :en: 20 dB	#Avg Type Avg Hold:	100/100	TRACE 123 TYPE MWWW DET P N N
Ref Offset 2.59	dB				Mkr1	2.401 832 70 G
o dB/div Ref 12.59 dl	Bm					0.089 dE
2.59		♦1				
7.41	harnananan	A MANY	NA MARANA	AMAN AND AND AND AND AND AND AND AND AND A		
- AMARANNY	WAN WAAA A A A A A A A A A A A A A A A A	hlever t		t to the start	NAM THE MENT	Mr. Marine
17.4						why why why
27.4						¥Ŵ
37.4						
17.4						
57.4						
67.4						
77.4						
enter 2.4020000 GHz Res BW 100 kHz		#VBW 300	0 kHz		Sweep	Span 1.500 № 2.000 ms (30001 p
G				Ko status		
gilent Spectrum Analyzer - Swep		us NVNT 2	-DH1 24	402MHz E	mission	
RL RF 50 Ω						
enter Fred 13 2650		SENSE:IN	IT		: RMS	12:55:16 PM Apr 28, 2 TRACE 12.3 4
enter Freq 13.2650	00000 GHz P	NO: Fast 🛶 Trig	ıT g: Free Run sen: 20 dB	ALIGNAUTO #Avg Type Avg Hold:	e: RMS 10/10	12:55:16 PM Apr 28, 2 TRACE 1 2 3 4 TYPE MWWW DET P N N
Ref Offset 2.55	00000 GHz P IF0 9 dB	NO: Fast 🛶 Trig	: Free Run	#Avg Type	10/10	TRACE 1234 TYPE MWWW DET P N N N
Ref Offset 2.55 0 dB/div Ref 12.59 d	00000 GHz P IF0 9 dB	NO: Fast 🛶 Trig	: Free Run	#Avg Type	10/10	TRACE 1234 TYPE MWWW DET PNN
Ref Offset 2.55 0 dB/div Ref 12.59 d	00000 GHz P IF0 9 dB	NO: Fast 🛶 Trig	: Free Run	#Avg Type	10/10	TRACE 1234 TYPE MWWW DET P N N N
Ref Offset 2.55 0 dB/div 2 59 7.41 17.4	00000 GHz P IF0 9 dB	NO: Fast 🛶 Trig	: Free Run	#Avg Type	10/10	TRACE 1234 TYPE MWWW DET P N N N
Ref Offset 2.59 0 dB/div Ref 12.59 d 2 59 7 41 17 4 27 4	00000 GHz P IFd Bm Bm	NO: Fast 🛶 Trig	: Free Run	#Avg Type	10/10	7RACE 11.2 3 TYPE MANA DET PINN Alkr1 2.401 7 G -8.517 dE
Ref Offset 2.55 0 dB/div 2 59 7 41 17 4 27 4 47 4 47 4	00000 GHz P IF0 9 dB	NO: Fast 🛶 Trig	: Free Run	#Avg Type	10/10	7RACE 11.2 3 TYPE MANA DET PINN Alkr1 2.401 7 G -8.517 dE
Ref Offset 2.55 0 dB/div 2 59 7 41 17 4 27 4 47 4 47 4	00000 GHz P IFd Bm Bm	NO: Fast → Trig Gain:Low #Att	: Free Run	#Avg Type	10/10	7RACE 11.2 3 TYPE MANA DET PINN Alkr1 2.401 7 G -8.517 dE
Ref Offset 2.55 0 dB/div Ref 12.59 df 2 49 1 7 41 7 4 4 4 7 4 7 4 7 4 7 4 7 4 7	00000 GHz P IFd Bm Bm	NO: Fast → Trig Gain:Low #Att	: Free Run	#Avg Type	10/10	7RACE 11.2 3 TYPE MANA DET PINN Alkr1 2.401 7 G -8.517 dE
Ref Offset 2.55 0 dB/div 9 2 59 7 .41 1	00000 GHz P IFd Bm Bm	NO: Fast I Trig Sain: Low #Att	y: Free Run ten: 20 dB	#Avg Type		TRACE 12 3- TYPE MANN DET P.N.N. Akr1 2.401 7 G -8.517 dE
Ref Offset 2.55 0 dB/div 259 7.41 17.4 <tr td=""> 17.4</tr>	00000 GHz P IFd Bm Bm	NO: Fast → Trig Gain:Low #Att	y: Free Run ten: 20 dB	#Avg Type	10/10	TRACE 11 2 3 - TYPE Muno DET PINIS Akr1 2.401 7 G -8.517 dE
Ref Offset 2.55 0 dB/div Ref 12.59 dl 2.59	00000 GHz P If dB Bm 3 4 2.4017 GHz 26.100 3 GHz	N0: Fast → Trig Sain:Low #Att 5 5 */VBW 300 */VBW 300 */ */VBW 300 */ */SW 300	y: Free Run Ren: 20 dB	#Avg Typ- Avg Hold:	10/10	TRACE 12 3- TYPE Muno DET PNNT Akr1 2.401 7 G -8.517 dE
Ref Offset 2.55 od B/div Ref 12.59 di 2.59	2.401 7 GHz 2.401 7 GHz 2.401 6 GHz	N0: Fast → Trig Sain:Low #Att #Att 5 5 #VBW 300 ¥ 8.517 dBm -45.987 dBm 51.347 dBm	y: Free Run Ren: 20 dB	#Avg Typ- Avg Hold:	10/10	TRACE 12 3- TYPE Muno DET PNNT Akr1 2.401 7 G -8.517 dE
0 dB/div Ref 12.59 dl 9 dB/div Ref 12.59 dl 7 dl 7 dl 7 dl 7 dl 7 dl 7 dl 7 dl 8	2.401 7 GHz 2.401 7 GHz 2.401 3 GHz	NO: Fast Trig gain:Low #Att	y: Free Run Ren: 20 dB	#Avg Typ- Avg Hold:	10/10	TRACE 12 3- TYPE Muno DET PNNT Akr1 2.401 7 G -8.517 dE
Ref Offiset 2.55 0 dB/div Ref 12.59 dl 259 1 7.41 1 17.4 1 28.5 1 29.5 1<	2.401 7 GHz 2.401 7 GHz 2.401 6 GHz	N0: Fast → Trig Sain:Low #Att #Att 5 5 #VBW 300 ¥ 8.517 dBm -45.987 dBm 51.347 dBm	y: Free Run Ren: 20 dB	#Avg Typ- Avg Hold:	10/10	TRACE 12 3- TYPE Muno DET PNNT Akr1 2.401 7 G -8.517 dE
Ref Offset 2.55 OdB/div Ref 12.59 di 99	2.401 7 GHz 2.401 7 GHz 2.401 6 GHz	N0: Fast → Trig Sain:Low #Att #Att 5 5 #VBW 300 ¥ 8.517 dBm -45.987 dBm 51.347 dBm	y: Free Run Ren: 20 dB	#Avg Typ- Avg Hold:	10/10	TRACE 12 3- TYPE Muno DET PNNT Akr1 2.401 7 G -8.517 dE





Edition: B.2




gilent Spectrum Analyzer - Sv	wept SA			H1 2480M⊦			
RL RF 50 G enter Freq 2.4800	Ω AC	SENSE:INT		ALIGN AUTO #Avg Type:	RMS	01:00:54 PM TRACE	Apr 28, 202
	PN	0:Wide ↔ Trig: Gain:Low #Atte	Free Run n: 20 dB	AvgjHold: 1	00/100	DE	
Ref Offset 2. 0 dB/div Ref 12.61					Mkr1	2.479 819 -0.10	65 GH)4 dBr
		. 1					
2.61			with have man				
7.39	and the second and a second second second second second second second second second second second second second	Variation of the second	๛๚ๅๅ๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛๛	alaur (ill street averaged a	MANNA MUNIN	-MMusa	
17.4						- WWWWWW	
27.4							WWW WAR
and a start of the							/V *
37.4							
47.4							
57.4							
57.4							
77.4							
(.4)							
enter 2.4800000 GH	IZ					Span 1.	
Res BW 100 kHz		#VBW 300	KHZ	I STATUS	Sweep	2.000 ms (30	0001 pt
	Tx. Spurio	us NVNT 2-	DH1 24		mission		
gilent Spectrum Analyzer - Sv RL RF 50 S	wept SA						
RL RF 50 \$		OTNICE, IND				01-01-0C PM	Ame 20, 202
enter Freq 13.265	000000 GHz		Free Run	ALIGNAUTO #Avg Type: Avg Hold: 1	RMS 0/10		12345 Miatatata
Ref Offset 2	000000 GHz Ph IFG 61 dB	IO:East ⊶⊷ Trig:		#Avg Type:	0/10	TRACE TYPE DE Mkr1 2.480	
Ref Offset 2 0 dB/div Ref 12.61	000000 GHz Ph IFG 61 dB	IO: Fast ↔ Trig:	Free Run	#Avg Type:	0/10	TRACE TYPE DE Mkr1 2.480	12345 MWWW PNNNN
Ref Offset 2 0 dB/div Ref 12.61	000000 GHz Ph IFG 61 dB	IO: Fast ↔ Trig:	Free Run	#Avg Type:	0/10	TRACE TYPE DE Mkr1 2.480	12345 MWWW PNNNN
Ref Offset 2 0 dB/div Ref 12.61	000000 GHz Ph IFG 61 dB	IO: Fast ↔ Trig:	Free Run	#Avg Type:	0/10	TRACE TYPE DE Mkr1 2.480	12345 MWWW PNNNN
Ref Offset 2 0 dB/div Ref 12.61	000000 GHz Ph IFG 61 dB	IO: Fast ↔ Trig:	Free Run	#Avg Type:	0/10	TRACE TYPE DE Mkr1 2.480	2 GH
Ref Offset 2 0 dB/div Ref 12.61 9 7.39 7.4	000000 GHz Ph IFG 61 dB	IO: Fast ↔ Trig:	Free Run	#Avg Type:	0/10	TRACE TYPE DE Mkr1 2.480	2 GH
Ref Offset 2 0 dB/div Ref 12.61 9 7.39 7.7.4	000000 GHz Ph IFG 61 dB	IO: Fast ↔ Trig:	Free Run	#Avg Type:	0/10	TRACE TYPE DE Mkr1 2.480	2 GH
Ref Offset 2 0 dB/div Ref 12.61 9 7.39 17.4 7.4 7.4	000000 GHz Ph IFG 61 dB	IO: Fast ↔ Trig:	Free Run	#Avg Type:	0/10	TRACE TYPE DE Mkr1 2.480	2 GH
Ref Offset 2 0 dB/div 2.61 7.39 17.4 27.4 47.4 7.4 4	000000 GHz Ph IFG 61 dB	10: Fast + Trig: Jain:Low #Atte	Free Run n: 20 dB	#Avg Type:		TRACE TVP DE Mkr1 2.480 -4.94	.50 GH
Ref Offset 2 0 dB/div Ref 12.61 0 dJ/div 1 7.39 1 17.4 1 27.4 1 37.4 1 47.4 1 57.4 1 57.4 1 57.4 1	000000 GHz Ph IFG 61 dB	IO: Fast ↔ Trig:	Free Run n: 20 dB	#Avg Type:	0/10	TRACE TYPE DE Mkr1 2.480 -4.94	12345 MWWWW PNNNN 2 GH 2 dBr
Ref Offset 2 0 dB/div Ref 12.61 9 1 7.39 1 7.4 1 7.4 1 7.4 1 7.4 1 7.4 1 7.4 1 7.4 1 7.4 1 7.4 1	000000 GHz Photomatical States of the state	10: Fast ain:Low #Atte	Free Run n: 20 dB	#Avg Hold: 1	0/10	TRACE TWP DE Mkr1 2.480 -4.94 -4.94 Stop 26 p 2.530 s (30	12345 MWWWW PNNNN 2 GH 2 dBr
Ref Offset 2 0 B/div Ref 12.61 2.61 1 7.39 1 37.4 1	2.480 2 GHz 26.190 3 GHz 2.690 5 GHz 7.439 8 GHz	10: Fast ain:Low #Atte	Free Run n: 20 dB	#Avg Hold: 1	0/10	TRACE TWP DE Mkr1 2.480 -4.94 -4.94 Stop 26 p 2.530 s (30	12345 MWWWW PNNNN 2 GH 2 dBr
Ref Offset 2 Ref 12.61 9 1 9 1 9 1 9 1 9 1 9 1 9 1 9 1 9 1 9 1 9 1 9 1 9 1 9 1 9 1 10 1 10 1 11 1 12 1 13 1 14 1 15 1 16 1	000000 GHz Pho IFG .61 dB dBm .61 dB .61	10: Fast ain:Low	Free Run n: 20 dB	#Avg Hold: 1	0/10	TRACE TWP DE Mkr1 2.480 -4.94 -4.94 Stop 26 p 2.530 s (30	.50 GH
Ref Offset 2 Ref 12.61 9 1 7.39 1 7.4 1 27.4 1 37.4 1 47.4 1 57.4 1	2.480 2 GHz 26.190 3 GHz 2.690 5 GHz 7.439 8 GHz	10: Fast ain:Low #Atte	Free Run n: 20 dB	#Avg Hold: 1	0/10	TRACE TWP DE Mkr1 2.480 -4.94 -4.94 Stop 26 p 2.530 s (30	.50 GH
Ref Offset 2 0 dB/div Ref 12.61 9 2 61 7 39 7 4 7 4 7 4 7 4 7 4 7 4 7 4 7 4	2.480 2 GHz 26.190 3 GHz 2.690 5 GHz 7.439 8 GHz	10: Fast ain:Low #Atte	Free Run n: 20 dB	#Avg Hold: 1	0/10	TRACE TWP DE Mkr1 2.480 -4.94 -4.94 Stop 26 p 2.530 s (30	12345 MWWWW PNNNN 2 GH 2 dBr





Edition: B.2































Edition: B.2




































Page: 70 of 128