

# GOODaaa PN-W22 Plus 说明书 36800mAh 尺寸: 90 \*120mm 折页



**Important Safety Instructions**

**Warning:** When using this product, basic precautions should always be followed, including the following:

- Carefully read the User Manual before using the power bank.
- Close supervision is needed when power bank is used near children.
- Do not strike, hit or insert any foreign objects into the power bank or any of its ports.
- Do not expose the power bank to heavy rain/snow to avoid malfunction.
- Do not immerse the power bank into water to avoid malfunction.
- Do not disassemble or reassemble the power bank without authorization from manufacturer.
- Do not use the power bank if it has been damaged or modified. If you see bulging, swelling, leakage or other abnormality from the power bank, stop using it immediately.

**Special Attention**

- The suggested working/storage temperature is between -4°F and +140°F (-20°C ~ +60°C).
- Do not expose a power bank to fire or extreme high temperature. Exposure to fire or temperature above 176°F/80°C may cause battery swelling up or explosion.
- Do not leave the power bank on the car dashboard without supervision. Under hot weather, the temperature inside a parked car can reach above 176°F/80°C may cause battery swell up or explode.
- Do not leave the power bank on the flat surface of concrete, metal and wooden floor to have the battery being solar charged. Under strong sunlight, the surface temperature of concrete, metal and wooden floor may reach above 170°F/80°C, where the battery may swell up or explode.
- For solar panel charging, we recommend that you hang the power bank in a ventilated environment for solar charging to a void swell up of the battery due to extremely high temperature.

**Legal and the Regulatory Compliance**

All GOODaaa power bank have undergone extensive tests and the strict quality control procedure. Both our factory and products are tested and certified.

- ISO 9001: Quality management system that demonstration our ability to consistently provide products and service that meet customer and applicable statutory and regulatory requirements.
- UN38.3 Test Certificate: This ensures that the battery cell used in the power bank adheres to safety standards for things like maximum continuous charge voltage, cut off voltage, cell number, nominal voltage, discharge etc.
- MSDS Certificate: This is the Material Safety Data Sheet, all our power banks come with MSDS sheets, these sheets outline the hazardousness material with batteries, handling procedures, precaution etc.
- UL 2056 Test Certificate: A safety standards proves that the products has been gone through a series of in-depth evaluations by UL expert engineers.
- CE Certificate: All our power banks are certified with CE certificates to ensure they comply with regulations for sale in Europe Market.



**Product Parameters**

OUT1: Lightning Output Cable	DC 5V/1A
OUT2: USB-C Output Cable	DC 5V/3A
OUT3: Micro USB Output Cable	DC 5V/3A
OUT4: USB Output Port	DC 5V/3A (MAX)
USB-C Input/Output Port	DC 5V/3A
IN1: USB Input Cable	DC 5V/3A
IN2: Micro USB Input Port	DC 5V/2.1A
Solar Charging Input	DC 5V/0.26A*5 with 25000LUX light intensity
Capacity	36800mAh/3.7V (=136Wh)
Power of LED Light	1W

**Package Include**

GOODaaa solar power bank x1  
 USB-C to USB-C Charging Cable x1  
 Carabiner x1  
 User Manual x1  
 Thankyou Card x1

**Product Features**

- Exclusive appearance design, stylish and beautiful.
- Made of original A-grade polymer battery, safe, stable, and durable.
- Advanced wireless charging, compatible with all Qi standard mobile phones.
- High capacity portable power bank, supports charging multiple devices at the same time.
- With multiple input ports and five solar panels charging input, frees your worries of power-off.
- Equipped with dual LED flashlights, convenient for outdoor use.

**Instructions**

**(1) Turn on/off the power bank**

Press the power switch to turn on the power bank, the LED power indicators light up. Without the device connected, the power bank will automatically shut down after 30 seconds.

**(2) Charge electronic devices**

- Use wireless charging**

This wireless power bank is compatible with all Qi-enabled devices. Gently press the power switch to turn on the power bank, the LED power indicators light up, and put the phone on the correct wireless charging area.

If you use the wireless charger to charge your phone, the phone case must not contain metal and the thickness of the case must not exceed 4mm.

- Use built-in output cables**

Gently press the power switch to turn on the power bank, the LED power indicators light up, take the cable out, and plug it into the corresponding device to charge the device.

- Use built-in output ports**

Gently press the power switch to turn on the power bank, the LED power indicators light up, plug the charging cable in the charging ports and your devices. This power bank supports charging multiple devices simultaneously.

**(3) Recharge the power bank**

- Power charging**

1. Use the built-in input cable  
 Gently press the power switch to turn on the power bank, the LED power indicators light up, take the cable out, plug it into a USB adapter to recharge the product. The blue LED power indicators flash when charging, and four power indicators all light up when fully charged.

2. Use the built-in input ports  
 Gently press the power switch to turn on the power bank, the LED power indicators light up, plug the charging cable in the charging ports and adapters to recharge the product. The blue LED power indicators flash when charging, and four power indicators all light up when fully.

- Solar charging**

Place the solar panels facing upward in the direct sunlight, the sunlight will be converted into electricity to charge the power bank. The solar charging performance will be more effective under strong light. When solar panel works, the green indicator is on. When the temperature is high in summer, please do not place the power bank on the concrete floor, car, and other places where heat gathers. When the power bank temperature exceeds 50 degrees, please stop using solar energy to charge the power bank.

**(4) LED flashlights**

Press and hold the power button for 3 seconds to turn on the LED flashlights. When you don't need to use the flashlights, please turn them off to save power.

**FCC Statement**

Changes or modifications not expressly approved by the party responsible for compliance could void the user authority to operate the product. NOTE: This equipment has been tested and found to comply with the limits for a wireless power charger, pursuant to Part 18 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment on and on, the user is encouraged to try to correct the interference by one or more of the following measures:  
 -Reorient or relocate the receiving antenna.  
 -Increase the separation between the equipment and receiver.  
 -Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.  
 -Consult the dealer or an experienced radio/TV technician for help.

**Product Maintenance**

To ensure the best efficiency of this product, please pay attention to the following reminders.

- Keep away from moisture and corrosive substances.
- Do not use chemicals to clean the product.
- Charge the power bank once every six months when the it is not used.

**Other Important Notes**

- This product is suitable for charging equipment within the specifications of DC 5V/3A, if use the charging equipment beyond this specification may cause damage to the product.
- Please do not disassemble or modify this product.
- Please pay attention to fire and moisture, to prevent malfunction.
- Do not use this product in the high-temperature environment (≥45°C).
- Please connect the equipment that meets the output specification of this product.
- If the battery expands, leaks, or emits a strange smell, please stop using it immediately.

**Troubleshooting**

- Only one blue LED power indicator flashes when pressing the power switch  
 -- Battery is about to run out, please charge the power bank immediately
- Unable to recharge the power bank  
 -- Change the charging adapter and charging cable to charge the power bank again
- Cannot charge phones or other devices  
 -- Please unplug and plug the phones/devices bank to the power bank.
- The power bank cannot be fully charged.  
 -- Please use the charging cable and adapter that supports 5V/2.1A or above output.  
 -- The current of Lightning charging is low, resulting in a long charging time, it is recommended to charge the power bank through Micro USB or USB-C input.
- Other common treatment methods:  
 -- Check if the button is flexible  
 -- Check if the charging indicators are on when charging  
 -- Check if the USB input cable is good and there is any abnormality after connecting to the power bank

-- Check if the USB output cable is good and there is any abnormality when connecting to the device that needs to be charged  
 -- Check if there is any abnormal noise or odor in the product  
 -- Please do not disassemble the power bank, the warranty does not cover human-made damage

(6) If the problems cannot be solved after the above methods, please message us via Amazon or contact our after-sales service for help. (Email address: [juanying\\_us@126.com](mailto:juanying_us@126.com))

**Warranty and Customer Service:**

- All GOODaaa products come with warranty of 12 months and life-time technical support.
- Within 30 days from the date of purchase, products in good packaging and without damage can be returned and fully refunded.
- A free exchange for a products that has quality problems within 12 months.
- If you are not 100% satisfied with our products, please feel free to message us via Amazon or contact our customer service via email: [juanying\\_us@126.com](mailto:juanying_us@126.com). We attach great importance for customer feedback and we will get back to you within 24 hours (including weekends).