

SPECS:

Combination property:

dynamic range: >90dB

armonic distortion: <0.5%

frequency of response: 40Hz~18kHz

AUDIO OUTPUT: stand alone type : 0~±400mV

Hybrid: 0~±200mV

Temperature range: -10~50°C

Opereation specification: Radius 50m

Receiving Distance: >20 米

3V microphone (launch)

modulation system: FM

Maximum percentage modulation: ±30kHz

Ultraharmonics: Below the main wave reference 60dB more than

Power voltage: 2*1.5V battery

Battery life: 2-3 hours

DASH RECEIVER:

Power voltage: DC+5.8-8V/40mA

Consumed power: 0.3W

SNR: >73dB

Image Interference Ratio : >80dB

ACIR: >80dB

Receive sensitivity: >12dBu (S/N=20dB)

Product accessories list:

3V microphone tube 1pc size: long 240CM

RX-199receiver board 1pc

antenna:1*300MM

FCC Caution:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement.

The device can be used in portable exposure condition without restriction.