

蓝牙连接手机

1.将手机固定在手机支架上,长按拍照键3秒至绿灯闪烁开启蓝牙

2.打开手机蓝牙设置,搜索并连接 "SEAJIC MT2",成功后绿灯长

3.按下自拍杆的拍照键进行拍照,再次长按拍照键3秒,则关闭 自拍支架电源,同时关闭蓝牙配对模式。

注意:自拍支架默认连接已配对成功的手机,如您需要更换连接手

新设备。

机设备 , 请先在已连接的手机上取消蓝牙配对 , 再连接配对

SEAJIC MT2

然后进入回连/广播闪烁状态;

直接自动连接; 休眠唤醒后自动配对:休眠唤醒后,如上一次已配对手机蓝牙是

手机删除连接:自拍器与手机处于连接状态时.在手机里面取消自

距离过远断开:自拍器与手机处于连接状态时.自拍器或手机距离 连接时关闭手机蓝牙:自拍器与手机处于连接状态时,关闭手机

的蓝牙,自拍器直接进入休眠, 连接后无操作时间: 手机与自拍器连接后, 不拍照5分钟后, 自动

低电指示:1.电量低于2.6V每次开机,无配对时配对或回连,配对

遥控器功能说明

开机方式:长按拍照键2秒开机绿色指示灯长亮3秒进入回连状态, 同连不成功讲入广播状态指示灯绿色闪烁 3分钟后讲入休眠 关机方式:开机及休眠状态下,长按拍照键3秒绿灯闪3次关机,休

〒15分钟后绿灯闪三次自动关机 已配对连接状态:绿色指示灯长亮5秒后熄灭 无配对连接状态:绿色指示灯闪烁 休眠唤醒:休眠状态下,短接一下拍照键,拍照指示灯亮一下

开机自动配对:开机后,如上一次已配对手机蓝牙是打开状态,

打开状态,直接自动连接; 拍照:短按拍照键/摄像,绿灯亮一下

拍器配对, 自拍器直接进入休眠 过远断开后,自拍器直接进入休眠

进入休眠,休眠15分钟后绿灯闪三次自动关机

遥控器功能说明

成功后绿灯常亮5s后红灯闪烁5次,频率为1s/次,然后熄灭 2 工作状态时 每次操作纤灯亭起基件绿灯操作反馈: 功耗要求:静态电流小于1UA

蓝牙名称: SEAJIC/客户订制 电池容量: CR1632/110mAh

按键个数:1个 指示灯个数:2个

伸缩杆过度旋转造成损坏.

产品介绍

拍照/开关键

- 分离式遥控器

- 三脚支架

冷靴口

----铝合金

____**手**板套简

← 柱 元 1 公

← 手机支架拉手


蓝牙版本: 4.2以上版本

距离要求: 10M内有效

冷靴口扩展安装: 旋转打开顶盖,将适配的补光灯等设备 安装到冷靴口.

提示:旋转顶盖时,请握住手机夹,避免

打开/合拢支架




手机固定支架

将手机横向倾斜45度,放入手机支架上,轻轻用力往上推,手机即 可固定在支架上。




本产品采用专利滑轨式手机支架,预留前后倾,左右旋转空间,不 取手机也可以横竖屏白中切换。





更换遥控器电池

用卡针或适当工具插入遥控器底部针孔,取下电池盖,更换电池 然后装回电池盖



4.仅可使用生产厂商指定的附件/配件

湿或受潮、无法正常运转、设备跌落损坏等,请联系官方客服 咨询相关事宜。

产品名称: 三脚架自拍杆 产品型是· AR226-PT 整机尺寸: 336*48*39mm

> 产品重量: 420a 连接方式: 蓝牙 遥控距离: 10m 支持系统· Android/IOS 产品材料: ABS+PC/铝 电池类型: 锂锰纽扣电池 电池型号: CR1632

重要安全信息

1.使用前请仔细阅读所有安全和操作说明,并妥善保管用户手册, 以备日后查阅:

- 2.请注意设备上和用户手册中所有注意事项
- 3 清谱从所有操作和使用说明
- 5.本设备须由官方维修人员进行维修操作;
- 6.如果本设备损坏,例如支架体损坏、液体渗入、设备遭雨水淋

产品有毒有害物质的名称和含量

部件名称 Pb Hg Cd Cr(VI) PBBs PBDEs 铅 汞 镉 六价铬 多溴联苯 多溴联苯醚

○:表示该有毒有害物质在该部件所有均质材料中的含量均在

X:表示该有毒有害物质至少在该部件的某一均质材料中的含

量超出GB/T26572标准规定的限量要求。为保护人类环境

: 本产品报废后请将其与生活垃圾分开,消费者有责任将其

: 关于本产品回收处理的详细信息,请咨询当地政府、废品

: 同收中心将通过活当的方法同收再利用产品中的材料

白拍支迦

包装配件(

和 人 迷健康

送至有资质的同收点

处理中心或经销商。

本表依据SJ/T11364的规定编制。

GB/T26572标准规定的限量要求以下。

- 请勿将设备暴露于雨水或潮湿环境中。
- 请勿将任何明火火源(如点燃的蜡烛)放置在设备上或靠近设
- 请勿将设备放置在热源附近,例如烤箱、散热器、火炉等其它
- 请勿将设备暴露于沸水环境中;
- 请勿将设备放置在装有液体的物品中,如花瓶等;
- 请勿将设备放置于高温灼热的环境中
- 使用时注意用力适度,避免暴力拉扯或者用力过猛造成产品的
- 请勿擅自拆开设备后盖,使用者不可自行维修内部零件,以防 触电或损坏设备。

为避免造成设备损坏,请注意:

- - - 用户信息
 - 联系电话:
 - 购买日期: 购买平台及店铺名:

SEAJIC产品后妥善保管保修卡和有效购买凭证

SEAJIC产品售后服务

SEAJIC售后服务承诺: 所有SEAJIC官方渠道及官方授权渠道出售的

商品 SFA IIC将严格根据《中华人民共和国消费者权益保护法》及

现行有效的法律法规,对于执行特殊三包条约的地区,SEAJIC承诺

遵守当地的相关规定提供售后服务。为了保障您的权益,请您在购买

SEAJIC产品保修卡

订单号:____ 产品信息


产品型号:_

服务热线: 0755-84827936 * 本说明书中的图片及文字解释权归欧森隆(中国





本产品的环保使用期限为10年。(仅在用户手册所述要求下使 用本产品,上述"环保使用期限"才有效)



2. Enter Bluetooth settings of mobile phone, to search and connect " SEAJIC MT2"; the green indicator will be normally on after successful connection:

press and hold the camera button for 3s to power off the product and disable Bluetooth pairing mode.



Attention: The product will connect the successfully paired mobile phone by default. To connect a new mobile phone. you need to unpair the former mobile phone before pairing a new one.

Capture Indicator Light:

Press and hold the Capture button for 2 seconds to power on The green indicator light stays on for 3 seconds to enter broadcast mode, and the green indicator flashes during broadcast mode

> In both powered-on and sleep modes, press and hold the Capture button for 3 seconds to turn off, and the capture indicator light will go off

Unpaired and not connected status: The green indicator light

Wake from Sleep: In sleep mode, short press the Capture button, the capture

indicator light will briefly flash, then it will enter broadcast flashing mode Auto Pairing on Power On:


Low Battery Indicator: When the battery is low (≤ 3.4V), the red indicator light will begin to flash automatically

The capture indicator light is displayed in green

Photo taking: Short press the photo button/camera button Mobile phone disconnection: When the selfie camera is connected to the phone, unpair the selfie camera in the phone and the selfie camera will enter sleep mode directly

Battery capacity: CR1632/110mAh Bluetooth version: Version 4.2 or higher


Distance requirement: Effective within 10M



Power consumption requirement: Static current less than 1UA Bluetooth name: SEAJIC MT2/Customer tailored

Number of indicator lights: 2





First of all, pull the handle of the mobile phone holder out along upward direction and drop it vertically from a height of about 10cm from the ground; then the tripod of selfie stick will bounce automatically.



magnetic stand, and gently force towards it Stick, the mobile phone can be fixed on the magnetic stand.




holder, reserved for front and back tilt,Rotate the left and right space, and you can switch horizontally and vertically without taking the phone.



b: The battery model is CR1632. Please purchase a genuine, compatible battery from a reputable brand.

Insert a pin or an appropriate tool into the hole at the bottom of the remote control to remove the battery cover. replace the battery, and then reattach the battery cover



Battery Model: CR1632

5. The product must be maintained by professionals; a: When installing the battery, ensure the positive pole of the

Product Name: Tripod Selfie Stick Model: AB226-PT Overall Dimensions: 336*48*39mm Weight: 420g

Connection Method: Bluetooth Remote Control Range: 10m Supported Systems: Android/iOS Material: ABS+PC/Aluminum Battery Type: Lithium Manganese Button Battery

1. Please read all safety and operation instructions carefully before using the product. Keep the manual properly for

2. Please pay attention to all precautions on the product and in the Manual;

3. Please follow all operation and use instructions: 4. Use the accessories/attachments designated by the manufacturer only;

the official after-sales service specialist to receive the

designated maintenance service.

6. For any damage of the product, such as holder damage. liquid penetration, affection by rainwater or moisture. nctioning failure or damage due to falling, please contact

O: It means that the content of the toxic and hazardous

substance in all the homogeneous materials of the component

protect the environment and human health:

materials properly;
3. For details of scrapping the product, please consult the local

To avoid damaging the product, please Do not expose the product to rain or a wet environment Do not put open flames (such as lighted candle) on or near

scrapped products to the designated recycling center:

2. The recycling center should recycle the product's useful

- Do not place the product near heat sources, such as oven,
- - Do not open the product's back cover by force, or repair its. nternal parts without permission to avoid electric shock or damage.

approved by the party responsible for compliance could void the user's authority to operate this equipment. This device complies with Part 15 of the ECC Rules. Operation

is subject to the following two conditions:
(1) This device may not cause harmful interference, and (2) this device must accept any interference received

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency

energy and, if not installed and used in accordance with the may cause harmful interference to radio communications However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the followingmeasures:
-- Reorient or relocate the receiving antenna.


-- Increase the separation between the equipment and received -- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician f

FCC Radiation Exposure Statement:

The equipment complies with FCC Radiation exposure limit set forth for uncontrolled environment. The device shall be operated and installed without restriction.


three-warranty services for all products which are sold through the official channel or authorized channel of SEAJIC in strict accordance with Law of the People's Republic of China on Protection of Consumer Rights and Interests. For regions where special three-warranty regulations are executed, SEAJIC hereby undertakes to abide by the local regulations. Please keep the varranty card and effective purchase voucher properly in order

Date of purchase: ___





conditions mentioned in the Manual.



Fix the mobile phone onto the holder, press and hold the camera button for 3s until the green lamp flickers, to enter the Bluetooth pairing mode;

3. Press the camera button on the product to take photos:





Power Off:

Paired and connected status: The green indicator light stays on

After powering on, if no connection is available, the device will automatically enter sleep mode after 10 minutes, and the capture indicator light will turn off and no longer flash. The device will automatically turn off after 30 minutes of sleep

After powering on, if the phone's Bluetooth was previously paired and turned on, it will automatically connect

Automatic pairing after sleep wake-up: After wake-up, if the Bluetooth of the previously paired phone is turned on, it will automatically connect directly:

Note: When rotating the top cover, please hold the phone clamp to avoid excessive rotation of the extension pole, which may cause damage.



While folding the product, hold the middle position of tripod and push back the pull rod back to the handle sleeve section

Place the mobile phone horizontally on the mobile phone



This product adopts patented magnetic mobile phone






a: 安装电池时请注意电池正极朝外。

品牌的话配电池。

b: 电池型号为 CR1632 请自行购买正规



battery is facing outward.

his table was prepared according to SJ/T11364

X: It means that the content of the toxic and harmful substance in at least one homogeneous material of the component exceeds the limit requirements specified by GB/T 26572.To . Once scrapped, the product should be separated from the

government, waste disposal center or dealer:

cooler, stove or other heating devices;

• Do not expose the product to boiled water . Do not put the product in articles containing liquids, such

Do not place the product in hot places; Do not pull the product by force;

FCC Caution: Any changes or modifications not expressly After-sales service commitment of SEAJIC: We provide

to safeguard your legal rights.

User Information Name: _____ Contact phone:

Purchase platform and shop name:

Order No.:____

Product information Model:



The product's environmentally friendly service life, which is 10 years, is determined by the enterprise according to its design characteristics. The product's environmentally friendly service life is effective only when the product is used under the normal





SEAJIC Cool Mount for Mobile Photography Hercules [Cold Shoe Version] Revolutionary Patent, Automatically Pops Open whenPlaced on the Ground