



Appendix B

RF Test Data for BT LE (Conducted Measurement)

Product Name: Bluetooth Sports Headphones

Test Model: B51S Pro

Environmental Conditions

Temperature:	23.8 ° C
Relative Humidity:	52.1%
ATM Pressure:	100.0 kPa
Test Engineer:	Paddi Chen
Supervised by:	Ling Zhu





B.1 -6dB Bandwidth


Condition	Mode	Frequency (MHz)	Antenna	-6 dB Bandwidth (MHz)	Limit -6 dB Bandwidth (MHz)	Verdict
NVNT	BLE 1M	2402	Ant1	0.654	0.5	Pass
NVNT	BLE 1M	2440	Ant1	0.675	0.5	Pass
NVNT	BLE 1M	2480	Ant1	0.659	0.5	Pass
NVNT	BLE 2M	2402	Ant1	1.247	0.5	Pass
NVNT	BLE 2M	2440	Ant1	1.158	0.5	Pass
NVNT	BLE 2M	2480	Ant1	1.127	0.5	Pass






Test Graphs

-6dB Bandwidth NVNT BLE 1M 2402MHz Ant1




-6dB Bandwidth NVNT BLE 1M 2440MHz Ant1






-6dB Bandwidth NVNT BLE 1M 2480MHz Ant1




-6dB Bandwidth NVNT BLE 2M 2402MHz Ant1






-6dB Bandwidth NVNT BLE 2M 2440MHz Ant1



-6dB Bandwidth NVNT BLE 2M 2480MHz Ant1





B.2 Maximum Conducted Output Power

Condition	Mode	Frequency (MHz)	Antenna	Total Power (dBm)	Limit (dBm)	Verdict
NVNT	BLE 1M	2402	Ant1	-2.69	30	Pass
NVNT	BLE 1M	2440	Ant1	-3.12	30	Pass
NVNT	BLE 1M	2480	Ant1	-4.13	30	Pass
NVNT	BLE 2M	2402	Ant1	-2.15	30	Pass
NVNT	BLE 2M	2440	Ant1	-2.38	30	Pass
NVNT	BLE 2M	2480	Ant1	-3.20	30	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity






Test Graphs



Power NVNT BLE 1M 2402MHz Ant1



Power NVNT BLE 1M 2440MHz Ant1











B.3 Maximum Power Spectral Density Level

Condition	Mode	Frequency (MHz)	Antenna	Total PSD (dBm/3kHz)	Limit (dBm/3kHz)	Verdict
NVNT	BLE 1M	2402	Ant1	-18.6	8	Pass
NVNT	BLE 1M	2440	Ant1	-19.09	8	Pass
NVNT	BLE 1M	2480	Ant1	-20.12	8	Pass
NVNT	BLE 2M	2402	Ant1	-20.36	8	Pass
NVNT	BLE 2M	2440	Ant1	-21.07	8	Pass
NVNT	BLE 2M	2480	Ant1	-21.77	8	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity








PSD NVNT BLE 1M 2480MHz Ant1



PSD NVNT BLE 2M 2402MHz Ant1







B.4 Band Edge

Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE 1M	2402	Ant1	-53.39	-20	Pass
NVNT	BLE 1M	2480	Ant1	-54.11	-20	Pass
NVNT	BLE 2M	2402	Ant1	-35.01	-20	Pass
NVNT	BLE 2M	2480	Ant1	-46.47	-20	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity






Test Graphs

Band Edge NVNT BLE 1M 2402MHz Ant1 Ref




Band Edge NVNT BLE 1M 2402MHz Ant1 Emission








Band Edge NVNT BLE 2M 2402MHz Ant1 Ref




Band Edge NVNT BLE 2M 2402MHz Ant1 Emission






Band Edge NVNT BLE 2M 2480MHz Ant1 Ref



Band Edge NVNT BLE 2M 2480MHz Ant1 Emission





B.5 Conducted RF Spurious Emission

Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE 1M	2402	Ant1	-43.46	-20	Pass
NVNT	BLE 1M	2440	Ant1	-42.24	-20	Pass
NVNT	BLE 1M	2480	Ant1	-42.18	-20	Pass
NVNT	BLE 2M	2402	Ant1	-40.44	-20	Pass
NVNT	BLE 2M	2440	Ant1	-36.32	-20	Pass
NVNT	BLE 2M	2480	Ant1	-38.14	-20	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity




Test Graphs

Tx. Spurious NVNT BLE 1M 2402MHz Ant1 Ref




Tx. Spurious NVNT BLE 1M 2402MHz Ant1 Emission






Tx. Spurious NVNT BLE 1M 2440MHz Ant1 Ref




Tx. Spurious NVNT BLE 1M 2440MHz Ant1 Emission






Tx. Spurious NVNT BLE 1M 2480MHz Ant1 Ref




Tx. Spurious NVNT BLE 1M 2480MHz Ant1 Emission






Tx. Spurious NVNT BLE 2M 2402MHz Ant1 Ref




Tx. Spurious NVNT BLE 2M 2402MHz Ant1 Emission






Tx. Spurious NVNT BLE 2M 2440MHz Ant1 Ref




Tx. Spurious NVNT BLE 2M 2440MHz Ant1 Emission






Tx. Spurious NVNT BLE 2M 2480MHz Ant1 Ref



Tx. Spurious NVNT BLE 2M 2480MHz Ant1 Emission





B.6 Duty Cycle

Condition	Mode	Frequency (MHz)	Antenna	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)
NVNT	BLE 1M	2402	Ant1	85.38	0.69	0.47
NVNT	BLE 1M	2440	Ant1	85.4	0.69	0.47
NVNT	BLE 1M	2480	Ant1	85.4	0.69	0.47
NVNT	BLE 2M	2402	Ant1	43.3	3.64	0.92
NVNT	BLE 2M	2440	Ant1	43.32	3.63	0.92
NVNT	BLE 2M	2480	Ant1	43.3	3.64	0.92




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity






Test Graphs



Duty Cycle NVNT BLE 1M 2402MHz Ant1



Duty Cycle NVNT BLE 1M 2440MHz Ant1









B.7 Restrict Band

Condition	Mode	Frequency (MHz)	Antenna	Spur Freq (MHz)	Power (dBm)	Gain (dBi)	E (dBuV/m)	Detector	Limit (dBuV/m)	Verdict
NVNT	BLE 1M	2402	Ant1	2310	-51.89	2	45.37	Peak	74	Pass
NVNT	BLE 1M	2402	Ant1	2310	-61.73	2	35.53	Average	54	Pass
NVNT	BLE 1M	2402	Ant1	2355.504	-47.84	2	49.42	Peak	74	Pass
NVNT	BLE 1M	2402	Ant1	2353.968	-59.68	2	37.58	Average	54	Pass
NVNT	BLE 1M	2402	Ant1	2390	-52.02	2	45.24	Peak	74	Pass
NVNT	BLE 1M	2402	Ant1	2390	-60.74	2	36.52	Average	54	Pass
NVNT	BLE 1M	2480	Ant1	2483.5	-51.05	2	46.21	Peak	74	Pass
NVNT	BLE 1M	2480	Ant1	2483.5	-60.59	2	36.67	Average	54	Pass
NVNT	BLE 1M	2480	Ant1	2487.592	-47.93	2	49.33	Peak	74	Pass
NVNT	BLE 1M	2480	Ant1	2498.056	-60.56	2	36.7	Average	54	Pass
NVNT	BLE 1M	2480	Ant1	2500	-49.67	2	47.59	Peak	74	Pass
NVNT	BLE 1M	2480	Ant1	2500	-60.78	2	36.48	Average	54	Pass
NVNT	BLE 2M	2402	Ant1	2310	-53.26	2	44	Peak	74	Pass
NVNT	BLE 2M	2402	Ant1	2310	-61.38	2	35.88	Average	54	Pass
NVNT	BLE 2M	2402	Ant1	2353.872	-48.67	2	48.59	Peak	74	Pass
NVNT	BLE 2M	2402	Ant1	2354.352	-59.75	2	37.51	Average	54	Pass
NVNT	BLE 2M	2402	Ant1	2390	-51.6	2	45.66	Peak	74	Pass
NVNT	BLE 2M	2402	Ant1	2390	-60.69	2	36.57	Average	54	Pass
NVNT	BLE 2M	2480	Ant1	2483.5	-50.17	2	47.09	Peak	74	Pass
NVNT	BLE 2M	2480	Ant1	2483.5	-58.14	2	39.12	Average	54	Pass
NVNT	BLE 2M	2480	Ant1	2485.696	-40.07	2	57.19	Peak	74	Pass
NVNT	BLE 2M	2480	Ant1	2483.512	-58.14	2	39.12	Average	54	Pass
NVNT	BLE 2M	2480	Ant1	2500	-52.2	2	45.06	Peak	74	Pass
NVNT	BLE 2M	2480	Ant1	2500	-60.45	2	36.81	Average	54	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
 Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
 Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
 Scan code to check authenticity



Test Graphs

Restrict Band NVNT BLE 1M 2402MHz Ant1 Peak



Restrict Band NVNT BLE 1M 2402MHz Ant1 Average

